



Compatibility Matrix for Cisco Content Security Management Appliances

Published: March 28, 2013

Revised: August 10, 2018

Contents

- [General Compatibility Information, page 1](#)
- [Compatibility with Email Security Appliances, page 2](#)
- [Compatibility with Web Security Appliances, page 4](#)
- [Additional Information, page 18](#)

General Compatibility Information

Each release of the Cisco Content Security Management Appliance (SMA) is compatible with several releases of the Email Security appliance (ESA) and several releases of the Web Security appliance (WSA).

A feature is supported on the Security Management appliance only when it is supported on the associated Email Security appliance or Web Security appliance. However, see [Support for Cloud Web Security Connector, page 17](#).

If an older Security Management appliance release manages supported newer Email or Web Security appliance releases, it generally does not support the new features that are available on those newer-release managed appliances.

The compatibility tables below assume that you have the latest build for each version. For example, if 7.9.0-201 is the latest build for version 7.9.0, you should have build 201, not build 107. This applies to Security Management appliances and associated Email and Web Security releases.



Compatibility With Virtual Appliances

The management appliance does not distinguish between managed appliances that run on physical (hardware) and those that are virtual appliances.

Compatibility with Email Security Appliances

Release	ESA 7.1.x	ESA 7.3.x	ESA 7.5.x	ESA 7.6.x	ESA 8.0.x	ESA 8.5.x	ESA 9.x	ESA 10.x	ESA 11.x
Releases earlier than 7.9.1: See the Release Notes for your version.									
SMA 7.9.1	ESA 7.1.5	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	—	—	—	—	
SMA 8.0	ESA 7.1.5	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	—	—	—	—	
SMA 8.1.x	—	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1 ESA 8.0.2	—	—	—	
SMA 8.2	—	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1	—	—	—	
SMA 8.3.0	—	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1 ESA 8.0.2	ESA 8.5.0	—	—	
SMA 8.3.5	—	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1	ESA 8.5.0 ESA 8.5.5	—	—	
SMA 8.3.6	—	ESA 7.3.1 ESA 7.3.2	ESA 7.5.1 ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1 ESA 8.0.2	ESA 8.5.0 ESA 8.5.5 ESA 8.5.6	—	—	
SMA 8.3.7	—	—	ESA 7.5.2	ESA 7.6.1 ESA 7.6.2 ESA 7.6.3	ESA 8.0.0 ESA 8.0.1	ESA 8.5.0 ESA 8.5.5 ESA 8.5.6 ESA 8.5.7	—	—	
SMA 8.4	This release supports only Web Security appliances.								
SMA 9.0	—	—	—	—	ESA 8.0.0 ESA 8.0.1	ESA 8.5.x	ESA 9.0	—	

Release	ESA 7.1.x	ESA 7.3.x	ESA 7.5.x	ESA 7.6.x	ESA 8.0.x	ESA 8.5.x	ESA 9.x	ESA 10.x	ESA 11.x
SMA 9.1.x (SMA 9.1.2 is for x60 hardware only)	—	—	—	—	ESA 8.0.0	ESA 8.5.x	ESA 9.0.0 ESA 9.1.x (except ESA 9.1.2)	—	
SMA 9.5-053	—	—	—	—	ESA 8.0.1	ESA 8.5.6 ESA 8.5.7	ESA 9.0.0 ESA 9.1.x (except ESA 9.1.2) ESA 9.5.0	—	
SMA 9.5-125	—	—	—	—	ESA 8.0.1	ESA 8.5.6 ESA 8.5.7	ESA 9.6.0 ESA 9.5.0 ESA 9.1.x (except ESA 9.1.2) ESA 9.0.0	—	
SMA 9.5.1	—	—	—	—	ESA 8.0.1	ESA 8.5.7 ESA 8.5.6	ESA 9.6.0 ESA 9.5.0 ESA 9.1.x (except ESA 9.1.2) ESA 9.0.0	—	
SMA 9.5.2	—	—	—	—	—	ESA 8.5.7	ESA 9.6.0 ESA 9.5.0 ESA 9.1.x ESA 9.7.x	—	
SMA 9.6 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	—	—	—	ESA 8.5.7	ESA 9.8.x ¹ ESA 9.7.0 ESA 9.6.0 ESA 9.1.x (except ESA 9.1.2)	—	
SMA 9.6.1	—	—	—	—	—	ESA 8.5.7	ESA 9.7.x ESA 9.6.0 ESA 9.5.0 ESA 9.1.x	—	

Release	ESA 7.1.x	ESA 7.3.x	ESA 7.5.x	ESA 7.6.x	ESA 8.0.x	ESA 8.5.x	ESA 9.x	ESA 10.x	ESA 11.x
SMA 10.0	—	—	—	—	—	ESA 8.5.7	ESA 9.7.x ESA 9.6.0 ESA 9.5.0 ESA 9.1.x	ESA 10.0.0	
SMA 10.1	—	—	—	—	—	ESA 8.5.7	ESA 9.8.x ESA 9.7.x ESA 9.6.0 ESA 9.5.0 ESA 9.1.x	ESA 10.0.0 ESA 10.0.1 ESA 10.0.2 ESA 10.0.3	
SMA 11.0	—	—	—	—	—		ESA 9.8.0 ESA 9.7.x ESA 9.6.0 ESA 9.5.0 ESA 9.1.x	ESA 10.0.0 ESA 10.0.1 ESA 10.0.2 ESA 10.0.3	ESA 11.0.0 ESA 11.0.1 ESA 11.0.2
SMA 11.4 (Cloud Email Security)	—	—	—	—	—	—	—	—	ESA 11.1.0
SMA 11.5	—	—	—	—	—		ESA 9.8.0 ESA 9.7.x ESA 9.6.0 ESA 9.5.0 ESA 9.1.x	ESA 10.0.0 ESA 10.0.1 ESA 10.0.2 ESA 10.0.3	ESA 11.0.0 ESA 11.0.1 ESA 11.0.2 ESA 11.1.0 ESA 11.1.1

1. You can connect AsyncOS 9.8 to a Security Management appliance only if the AsyncOS version of the Security Management appliance is 9.6.0-077.

Compatibility with Web Security Appliances

- [Centralized Web Reporting and Tracking, page 5](#)
- [Centralized Configuration Management, page 8](#)
- [Support for Cloud Web Security Connector, page 17](#)

Centralized Web Reporting and Tracking

Release	WSA 7.1	WSA 7.5	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.5 and WSA 8.6	WSA 8.7 and WSA 8.8	WSA 9.0.x and WSA 9.1.x	WSA 10.x	WSA 11.x
Releases earlier than 7.9.1: See the Release Notes for your version.										
SMA 7.9.1	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	—	—	—	—	—	—	—	—
SMA 8.0	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	—	—	—	—	—	—	—
SMA 8.1.x	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	—	—	—	—	—	—	—
SMA 8.2	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0	—	—	—	—	—	—
SMA 8.3.0	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0	—	—	—	—	—	—
SMA 8.3.5	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5	—	—	—	—	—	—
SMA 8.3.6	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7	—	—	—	—	—	—
SMA 8.3.7	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7	WSA 8.1	—	—	—	—	—
SMA 8.4	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7	WSA 8.1	WSA 8.5 WSA 8.6	—	—	—	—
SMA 9.0	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5	—	—	—	—

Release	WSA 7.1	WSA 7.5	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.5 and WSA 8.6	WSA 8.7 and WSA 8.8	WSA 9.0.x and WSA 9.1.x	WSA 10.x	WSA 11.x
SMA 9.1.0	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7 WSA 8.0.8	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5	WSA 8.7	—	—	—
SMA 9.1.1	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7 WSA 8.0.8	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.2	WSA 8.7	—	—	—
SMA 9.1.2 (For x60 hardware only)	WSA 7.1.3 WSA 7.1.4	WSA 7.5.0 WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7 WSA 8.0.8	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.7	—	—	—
SMA 9.5-053	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	WSA 8.1	WSA 8.6 WSA 8.5.1 WSA 8.5.0	WSA 8.7	—	—	—
SMA 9.5-125	—	—	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.6 WSA 8.5.2 WSA 8.5.1 WSA 8.5.0	WSA 8.8 WSA 8.7	—	—	—
SMA 9.5.1	—	—	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.6 WSA 8.5.2 WSA 8.5.1 WSA 8.5.0	WSA 8.8 WSA 8.7	WSA 9.0.x	—	—
SMA 9.5.2	—	—	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.6 WSA 8.5.2 WSA 8.5.1 WSA 8.5.0	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	—	—
SMA 9.6 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7	WSA 8.1	WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.0.0	—	—

Release	WSA 7.1	WSA 7.5	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.5 and WSA 8.6	WSA 8.7 and WSA 8.8	WSA 9.0.x and WSA 9.1.x	WSA 10.x	WSA 11.x
SMA 9.6.1 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	—	—
SMA 9.6.1-019 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.1 WSA 9.1.0 WSA 9.0.x	—	—
SMA 9.6.1-027 SMA 9.5.2-038	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.2 WSA 9.1.1 WSA 9.1.0 WSA 9.0.x	—	—
SMA 10.0	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x	—
SMA 10.1	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x WSA 10.1.x	—
SMA 11.0.0	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x WSA 10.1.0 WSA 10.5.x	WSA 11.0.x
SMA 11.0.0-128 SMA 11.0.0-132 SMA 11.0.0-133	—	—	WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x WSA 10.1.x WSA 10.5.x	WSA 11.0.x

Release	WSA 7.1	WSA 7.5	WSA 7.7.x	WSA 8.0.x	WSA 8.1	WSA 8.5 and WSA 8.6	WSA 8.7 and WSA 8.8	WSA 9.0.x and WSA 9.1.x	WSA 10.x	WSA 11.x
SMA 11.5.0-065			WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x WSA 10.1.x WSA 10.5.x	WSA 11.0.x
SMA 11.5.0-110			WSA 7.7.x	WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	WSA 8.1	WSA 8.6 WSA 8.5.4 WSA 8.5.3 WSA 8.5.2	WSA 8.8 WSA 8.7	WSA 9.1.x WSA 9.0.x	WSA 10.0.x WSA 10.1.x WSA 10.5.x	WSA 11.0.x WSA 11.5

Centralized Configuration Management

- [Advanced File Publishing, page 8](#)
- [Configuration Masters, page 8](#)

Advanced File Publishing

For Advanced File Publishing, the file to be published must be saved from a Web Security appliance running the identical version as the target Web Security appliance, including build number. For example, you can use Advanced File Publishing to publish a WSA 7.1.4-999 configuration file to a WSA running 7.1.4-999.

Configuration Masters

You can import configuration files from Web Security appliances into Configuration Masters on the Security Management appliance and publish Configuration Masters to Web Security appliances as follows:

	Configuration Master												
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
Releases earlier than 7.9.1: See the Release Notes for your version.													
SMA 7.9.1	WSA 7.1.4	WSA 7.5.1	—	—	—	—	—	—	—	—	—	—	—
SMA 8.0.0-404	WSA 7.1.4	WSA 7.5.1	WSA 7.7.x except 7.7.0-753	—	—	—	—	—	—	—	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 8.0.0-407	WSA 7.1.4	WSA 7.5.1	WSA 7.7.0-753	—	—	—	—	—	—	—	—	—	—
SMA 8.1.0	WSA 7.1.4	WSA 7.5.1	WSA 7.7.x except WSA 7.7.0-753	—	—	—	—	—	—	—	—	—	—
SMA 8.1.1-013	WSA 7.1.4	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x except WSA 7.7.0-753	—	—	—	—	—	—	—	—	—	—
SMA 8.1.1-031	WSA 7.1.4	WSA 7.5.1 WSA 7.5.2-304	WSA 7.7.0-753 WSA 7.7.0-725	—	—	—	—	—	—	—	—	—	—
SMA 8.2	—	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0	—	—	—	—	—	—	—	—	—
SMA 8.3.0	—	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0	—	—	—	—	—	—	—	—	—
SMA 8.3.5	—	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5	—	—	—	—	—	—	—	—	—
SMA 8.3.6	—	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	WSA 8.0.0 WSA 8.0.5 WSA 8.0.6 WSA 8.0.7	—	—	—	—	—	—	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 8.3.7	—	WSA 7.5.1 WSA 7.5.2	WSA 7.7.x	—	WSA 8.1 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	—	—	—	—	—	—	—	—
SMA 8.4	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	WSA 8.6 WSA 8.5.0	—	—	—	—	—	—	—
SMA 9.0	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	WSA 8.6 WSA 8.5.0	—	—	—	—	—	—	—
SMA 9.1.0	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	—	WSA 8.7 WSA 8.6 WSA 8.5.1	—	—	—	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 9.1.1	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	—	WSA 8.7 WSA 8.6 WSA 8.5.2	—	—	—	—	—	—
SMA 9.1.2 (For x60 hardware only)	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	—	WSA 8.7 WSA 8.6 WSA 8.5.3 WSA 8.5.2	—	—	—	—	—	—
SMA 9.5-053	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7 WSA 8.0.6 WSA 8.0.5 WSA 8.0.0	—	— WSA 8.7 WSA 8.6 WSA 8.5.1 WSA 8.5.0	—	—	—	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 9.5-125	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.x	—	—	WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.2 WSA 8.5.1 WSA 8.5.0	—	—	—	—	—
SMA 9.5.1	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.x	—	—	—	WSA 9.0.x WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.x	—	—	—	—
SMA 9.5.2	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.x	—	—	—	—	WSA 9.1.x WSA 9.0.x WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.x	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 9.6 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7	—	—	—	WSA 9.0.0 WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.3 WSA 8.5.2	—	—	—	—
SMA 9.6.1 (For x60 hardware, use SMA 9.1.2 instead.)	—	—	WSA 7.7.x	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7	—	—	—	WSA 9.1.x WSA 9.0.x WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.3 WSA 8.5.2	—	—	—	—
SMA 10.0.0-055	—	—	—	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7	—	—	—	—	WSA 9.1.x WSA 9.0.x WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.3 WSA 8.5.2	—	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 10.0.0-096	—	—	—	—	WSA 8.1 WSA 8.0.8 WSA 8.0.7	—	—	—	—	WSA 9.1.x WSA 9.0.x WSA 8.8 WSA 8.7 WSA 8.6 WSA 8.5.3 WSA 8.5.2	WSA 10.0.x	—	—
SMA 10.1.0-037	—	—	—	—	WSA 8.1.x WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	—	—	—	—	WSA 9.1.2 WSA 9.1.x WSA 9.0.x WSA 8.8.x WSA 8.7.x WSA 8.6.x WSA 8.5.3 WSA 8.5.2	WSA 10.0.x WSA 10.1.x	—	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 10.1.0-052	—	—	—	—	WSA 8.1.x WSA 8.0.8 WSA 8.0.7 WSA 8.0.6	—	—	—	—	WSA 9.1.2 WSA 9.1.x WSA 9.0.x WSA 8.8.x WSA 8.7.x WSA 8.6.x WSA 8.5.3 WSA 8.5.2	WSA 10.0.x WSA 10.1.x WSA 10.5.x ¹	—	—
SMA 11.0.0	—	—	—	—	—	—	—	—	—	WSA 9.1.x WSA 9.1.2 WSA 9.0.x WSA 8.8.x WSA 8.7.x WSA 8.6.x WSA 8.5.3 WSA 8.5.2	WSA 10.5.x	WSA 11.0.x WSA 10.1.x WSA 10.0.x	—

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 11.0.0-128										WSA 9.1.x		WSA 10.5.x	WSA 11.0.x
SMA 11.0.0-132										WSA 9.1.2			WSA 10.1.x
SMA 11.0.0-133										WSA 9.0.x			WSA 10.0.x
										WSA 8.8.x			
										WSA 8.7.x			
										WSA 8.6.x			
										WSA 8.5.3			
										WSA 8.5.2			

Configuration Master													
SMA Release	CM 7.1	CM 7.5	CM 7.7	CM 8.0	CM 8.1	CM 8.5	CM 8.7	CM 8.8	CM 9.0	CM 9.1	CM 10.0	CM 10.5	CM 11.0
SMA 11.5.0-065										WSA 9.1.x		WSA 10.5.x	WSA 11.0.x
										WSA 9.1.2			WSA 10.1.x
										WSA 9.0.x			WSA 10.0.x
										WSA 8.8.x			
										WSA 8.7.x			
										WSA 8.6.x			
										WSA 8.5.3			
										WSA 8.5.2			
SMA 11.5.0-110										WSA 9.1.x		WSA 10.5.x	WSA 11.5
										WSA 9.1.2			WSA 11.0.x
										WSA 9.0.x			WSA 10.1.x
										WSA 8.8.x			WSA 10.0.x
										WSA 8.7.x			
										WSA 8.6.x			
										WSA 8.5.3			
										WSA 8.5.2			

1. Advanced publishing of a 10.1 XML file to a WSA running AsyncOS 10.5 is not supported.

Support for Cloud Web Security Connector

Security Management appliances do not support Web Security appliances running in Cloud Web Security Connector mode.

Additional Information

For additional information about your release of AsyncOS for Cisco Content Security Management, see the Release Notes at

<http://www.cisco.com/c/en/us/support/security/content-security-management-appliance/products-release-notes-list.html>.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2018 Cisco Systems, Inc. All rights reserved.