



AP3500i

RF Tx Power Levels

Software Release 7.0



CCDE, CCENT, CCSI, Cisco Eos, Cisco HealthPresence, Cisco IronPort, the Cisco logo, Cisco Nurse Connect, Cisco Pulse, Cisco SensorBase, Cisco StackPower, Cisco StadiumVision, Cisco TelePresence, Cisco Unified Computing System, Cisco WebEx, DCE, Flip Channels, Flip for Good, Flip Mino, Flipshare (Design), Flip Ultra, Flip Video, Flip Video (Design), Instant Broadband, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn, Cisco Capital, Cisco Capital (Design), Cisco:Financed (Stylized), Cisco Store, Flip Gift Card, and One Million Acts of Green are service marks; and Access Registrar, Aironet, AllTouch, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Lumin, Cisco Nexus, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, Continuum, EtherFast, EtherSwitch, Event Center, Explorer, Follow Me Browsing, GainMaker, iLYNX, IOS, iPhone, IronPort, the IronPort logo, Laser Link, LightStream, Linksys, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, PCNow, PIX, PowerKEY, PowerPanels, PowerTV, PowerTV (Design), PowerVu, Prisma, ProConnect, ROSA, SenderBase, SMARTnet, Spectrum Expert, StackWise, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries. All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0910R) © 2010 Cisco Systems, Inc. All rights reserved.

AP3500i 2.4 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -A - Antenna Gain: 4 dBi

Software Release 7.0		CCK Tx Diversity Single Ant 1 to 11 Mb/s			CCK Dual Ants 1 to 11 Mb/s			Non HT20 Single Ant 6 to 54 Mb/s			Non HT20 Dual Ants 6 to 54 Mb/s			Non HT20 Beam Form Dual Ants 6 to 54 Mb/s			Non HT40 Duplicate Single Ant 6 to 54 Mb/s			Non HT40 Duplicate Dual Ants 6 to 54 Mb/s			HT20 Single Ant M0 to M7			HT20 Dual Ants M0 to M15			HT40 Single Ant M0 to M7			HT40 Dual Ants M0 to M15					
		BW	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr			
20 MHz	2412	1	20	off	20	18	18	21	17	off	17	16	16	19	13	13	16	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2417	2	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2422	3	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2427	4	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2432	5	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2437	6	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2442	7	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2447	8	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2452	9	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2457	10	20	off	20	20	20	23	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
	2462	11	20	off	20	18	18	21	17	off	17	14	14	17	11	11	14	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-		
40 MHz	2412 & 2432	1, 5U or 5, 1L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	14	off	14	12	12	15
	2417 & 2437	2, 6U or 6, 2L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	
	2422 & 2442	3, 7U or 7, 3L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	14	off	14	12	12	15	
	2427 & 2447	4, 8U or 8, 4L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	
	2432 & 2452	5, 9U or 9, 5L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	14	off	14	12	12	15	
	2437 & 2457	6, 10U or 10, 6L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	
	2442 & 2462	7, 11U or 11, 7L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	14	off	14	12	12	15	



AP3500i 2.4 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -E - Antenna Gain: 4 dBi

Software Release 7.0			CCK Tx Diversity Single Ant 1 to 11 Mb/s			CCK Dual Ants 1 to 11 Mb/s			Non HT20 Single Ant 6 to 54 Mb/s			Non HT20 Dual Ants 6 to 54 Mb/s			Non HT20 Beam Form Dual Ants 6 to 54 Mb/s			Non HT40 Duplicate Single Ant 6 to 54 Mb/s			Non HT40 Duplicate Dual Ants 6 to 54 Mb/s			HT20 Single Ant M0 to M7			HT20 Dual Ants M0 to M15			HT40 Single Ant M0 to M7			HT40 Dual Ants M0 to M15				
			BW	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr		
20 MHz	2412	1	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2417	2	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2422	3	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2427	4	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2432	5	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2437	6	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2442	7	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2447	8	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2452	9	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2457	10	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2462	11	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2467	12	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	2472	13	16	off	16	13	13	16	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
40 MHz	2412 & 2432	1, 5U or 5, 1L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16
	2417 & 2437	2, 6U or 6, 2L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	-	16	off	16	13	13	16	
	2422 & 2442	3, 7U or 7, 3L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
	2427 & 2447	4, 8U or 8, 4L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
	2432 & 2452	5, 9U or 9, 5L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
	2437 & 2457	6, 10U or 10, 6L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
	2442 & 2462	7, 11U or 11, 7L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
	2447 & 2467	8, 12U or 12, 8L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16		
2452 & 2472	9, 13U or 13, 9L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-	-	16	off	16	13	13	16			



AP3500i 2.4 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -Q - Antenna Gain: 4 dBi

Software Release 7.0			CCK Tx Diversity Single Ant 1 to 11 Mb/s			CCK Dual Ants 1 to 11 Mb/s			Non HT20 Single Ant 6 to 54 Mb/s			Non HT20 Dual Ants 6 to 54 Mb/s			Non HT20 Beam Form Dual Ants 6 to 54 Mb/s			Non HT40 Duplicate Single Ant 6 to 54 Mb/s			Non HT40 Duplicate Dual Ants 6 to 54 Mb/s			HT20 Single Ant M0 to M7			HT20 Dual Ants M0 to M15			HT40 Single Ant M0 to M7			HT40 Dual Ants M0 to M15				
BW	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr					
20 MHz	2412	1	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2417	2	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2422	3	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2427	4	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2432	5	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2437	6	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2442	7	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2447	8	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2452	9	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2457	10	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2462	11	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2467	12	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
	2472	13	15	off	15	12	12	15	17	off	17	15	15	18	12	12	15	-	-	-	-	-	-	17	off	17	15	15	18	-	-	-	-	-	-		
40 MHz	2412 & 2432	1, 5U or 5, 1L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	-	-	17	off	17	14	14	17
	2417 & 2437	2, 6U or 6, 2L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	-	17	off	17	14	14	17	
	2422 & 2442	3, 7U or 7, 3L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	2427 & 2447	4, 8U or 8, 4L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	2432 & 2452	5, 9U or 9, 5L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	2437 & 2457	6, 10U or 10, 6L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	2442 & 2462	7, 11U or 11, 7L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	2447 & 2467	8, 12U or 12, 8L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
2452 & 2472	9, 13U or 13, 9L	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	16	off	16	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17			

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -A - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>			
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	
20 MHz	UNII-1	5180	36	15	off	15	11	11	14	8	8	11	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-	-
		5200	40	15	off	15	11	11	14	8	8	11	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-	-
		5220	44	15	off	15	11	11	14	8	8	11	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-	-
		5240	48	15	off	15	11	11	14	8	8	11	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-	-
	UNII-2	5260	52	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5280	56	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5300	60	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5320	64	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
	UNII-2 Ext	5500	100	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5520	104	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5540	108	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5560	112	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5580	116	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
		5600	120	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported						
		5620	124	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported									
		5640	128	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported									
	5660	132	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
	5680	136	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
	5700	140	17	off	17	17	17	20	15	15	18	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
	UNII-3	5745	149	17	off	17	17	17	20	17	17	20	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-
5765		153	17	off	17	17	17	20	17	17	20	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
5785		157	17	off	17	17	17	20	17	17	20	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
5805		161	17	off	17	17	17	20	17	17	20	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
5.8 ISM	5825	165	17	off	17	17	17	20	17	17	20	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	13	off	13	12	12	15	-	-	-	-	-	-	14	off	14	13	13	16	
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	17	off	17	12	12	15	
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	17	off	17	17	17	20	
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	-	15	off	15	14	14	17	-	-	-	-	-	17	off	17	15	15	18
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	15	off	15	13	13	16	-	-	-	-	-	-	16	off	16	15	15	18
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	17	off	17	17	17	20
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	17	off	17	17	17	20	
	UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20
5785 & 5805		157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	17	off	17	17	17	20	

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -C - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20			Non HT20			Non HT20 Beam Form			Non HT40 Duplicate			Non HT40 Duplicate			HT20			HT20			HT40			HT40						
				Single Ant 6 to 54 Mb/s			Dual Ants 6 to 54 Mb/s			Dual Ants 6 to 54 Mb/s			Single Ant 6 to 54 Mb/s			Dual Ants 6 to 54 Mb/s			Single Ant M0 to M7			Dual Ants M0 to M15			Single Ant M0 to M7			Dual Ants M0 to M15						
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr				
20 MHz	UNII-1	5180	36																															
		5200	40																															
		5220	44																															
		5240	48																															
	UNII-2	5260	52																															
		5280	56																															
		5300	60																															
		5320	64																															
	UNII-2 Ext	5500	100																															
		5520	104	Not Supported																														
		5540	108	Not Supported																														
		5560	112	Not Supported																														
		5580	116	Not Supported																														
		5600	120	Not Supported																														
		5620	124	Not Supported																														
		5640	128	Not Supported																														
	UNII-3	5745	149		17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
		5765	153		17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
		5785	157		17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
		5805	161		17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-	
5.8 ISM	5825	165	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	-			
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-																						
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-																					
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-																						
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-																					
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-																						
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-																						
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-																						
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-																						
UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-																							
	5785 & 5805	157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-																							

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -E - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>			
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	
20 MHz	UNII-1	5180	36	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5200	40	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5220	44	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5240	48	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
	UNII-2	5260	52	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5280	56	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5300	60	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
		5320	64	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	
	UNII-2 Ext	5500	100	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	
		5520	104	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	
		5540	108	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	
		5560	112	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	
		5580	116	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	
		5600	120	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported						
		5620	124	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported									
		5640	128	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported									
	5660	132	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-		
	5680	136	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-		
	5700	140	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-		
	UNII-3	5745	149	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported									
5765		153	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported										
5785		157	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported										
5805		161	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported										
5.8 ISM	5825	165	Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported			Not Supported										
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			Not Supported			Not Supported								
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			Not Supported			Not Supported								
	5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	
	UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			Not Supported			Not Supported								
5785 & 5805		157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			Not Supported			Not Supported									

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -I - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>			
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	
20 MHz	UNII-1	5180	36	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5200	40	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5220	44	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5240	48	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
	UNII-2	5260	52	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5280	56	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5300	60	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
		5320	64	17	<i>off</i>	17	16	16	19	13	13	16	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	-
	UNII-2 Ext	5500	100	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5520	104	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5540	108	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5560	112	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5580	116	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5600	120	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5620	124	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5640	128	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
	UNII-3	5660	132	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5680	136	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5700	140	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5745	149	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
UNII-3	5765	153	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
	5785	157	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
	5805	161	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
	5.8 ISM	5825	165	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-		
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-		
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-		
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-		
UNII-3	5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
UNII-3	5785 & 5805	157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -K - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>			
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	
20 MHz	UNII-1	5180	36	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5200	40	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5220	44	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5240	48	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
	UNII-2	5260	52	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5280	56	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5300	60	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5320	64	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
	UNII-2 Ext	5500	100	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5520	104	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5540	108	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5560	112	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5580	116	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5600	120	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5620	124	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5640	128	Not Supported			Not Supported			Not Supported			-			-			Not Supported			Not Supported			-			-			
		5660	132	Not Supported			Not Supported			Not Supported			-			-			Not Supported			Not Supported			-			-			
		5680	136	Not Supported			Not Supported			Not Supported			-			-			Not Supported			Not Supported			-			-			
	5700	140	Not Supported			Not Supported			Not Supported			-			-			Not Supported			Not Supported			-			-				
	UNII-3	5745	149	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
5765		153	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-	
5785		157	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-	
5805		161	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-	
5.8 ISM	5825	165	Not Supported			Not Supported			Not Supported			-			-			Not Supported			Not Supported			-			-				
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19	-	-	-	-	-	-	17	<i>off</i>	17	16	16	19
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			Not Supported			Not Supported					
		5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			Not Supported			Not Supported					
	UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
5785 & 5805		157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -N - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>				
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr		
20 MHz	UNII-1	5180	36	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-	
		5200	40	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
		5220	44	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
		5240	48	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
	UNII-2	5260	52	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
		5280	56	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
		5300	60	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
		5320	64	15	off	15	11	11	14	8	8	11	-	-	-	-	-	-	-	15	off	15	11	11	14	-	-	-	-	-	-	-
	UNII-2 Ext	5500	100	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5520	104	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5540	108	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5560	112	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5580	116	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5600	120	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5620	124	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
		5640	128	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
	UNII-3	5745	149	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	
		5765	153	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-
		5785	157	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-
		5805	161	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-
5.8 ISM	5825	165	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	-	
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	13	off	13	12	12	15	-	-	-	-	-	-	14	off	14	13	13	16		
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17	
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20	
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	15	off	15	14	14	17	-	-	-	-	-	-	17	off	17	15	15	18	
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			
UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20		
	5785 & 5805	157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20		

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -Q - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20 <small>Single Ant 6 to 54 Mb/s</small>			Non HT20 <small>Dual Ants 6 to 54 Mb/s</small>			Non HT20 <small>Beam Form Dual Ants 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Single Ant 6 to 54 Mb/s</small>			Non HT40 <small>Duplicate Dual Ants 6 to 54 Mb/s</small>			HT20 <small>Single Ant M0 to M7</small>			HT20 <small>Dual Ants M0 to M15</small>			HT40 <small>Single Ant M0 to M7</small>			HT40 <small>Dual Ants M0 to M15</small>			
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	
20 MHz	UNII-1	5180	36	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5200	40	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5220	44	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
		5240	48	16	<i>off</i>	16	13	13	16	10	10	13	-	-	-	-	-	-	16	<i>off</i>	16	13	13	16	-	-	-	-	-	-	-
	UNII-2	5260	52	11	<i>off</i>	11	8	8	11	5	5	8	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	-
		5280	56	11	<i>off</i>	11	8	8	11	5	5	8	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	-
		5300	60	11	<i>off</i>	11	8	8	11	5	5	8	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	-
		5320	64	11	<i>off</i>	11	8	8	11	5	5	8	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	-
	UNII-2 Ext	5500	100	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5520	104	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5540	108	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5560	112	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5580	116	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5600	120	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5620	124	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5640	128	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5660	132	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
		5680	136	17	<i>off</i>	17	17	17	20	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	-
	UNII-3	5745	149	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
		5765	153	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-			
5785		157	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
5805		161	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
5.8 ISM	5825	165	Not Supported			Not Supported			Not Supported			-			-			-			-			-			-				
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	14	<i>off</i>	14	11	11	14	-	-	-	-	-	-	14	<i>off</i>	14	11	11	14	
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	14	<i>off</i>	14	11	11	14	-	-	-	-	-	-	14	<i>off</i>	14	11	11	14
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11	-	-	-	-	-	-	11	<i>off</i>	11	8	8	11
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
		5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20	-	-	-	-	-	-	17	<i>off</i>	17	17	17	20
	UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-		
5785 & 5805		157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-			-			-			-			

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -S - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20			Non HT20			Non HT20			Non HT40			Non HT40			HT20			HT20			HT40			HT40					
				Single Ant 6 to 54 Mb/s			Dual Ants 6 to 54 Mb/s			Beam Form Dual Ants 6 to 54 Mb/s			Duplicate Single Ant 6 to 54 Mb/s			Duplicate Dual Ants 6 to 54 Mb/s			Single Ant M0 to M7			Dual Ants M0 to M15			Single Ant M0 to M7			Dual Ants M0 to M15					
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr			
20 MHz	UNII-1	5180	36	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-			
		5200	40	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
		5220	44	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
		5240	48	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	UNII-2	5260	52	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
		5280	56	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
		5300	60	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
		5320	64	16	off	16	13	13	16	10	10	13	-	-	-	-	-	-	-	16	off	16	13	13	16	-	-	-	-	-	-		
	UNII-2 Ext	5500	100	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	-	
		5520	104	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	
		5540	108	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	
		5560	112	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
		5580	116	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
		5600	120	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
		5620	124	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
		5640	128	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
	5660	132	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	
	5680	136	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	
	5700	140	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	
	UNII-3	5745	149	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-		
5765		153	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-			
5785		157	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-			
5805		161	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-			
5.8 ISM	5825	165	17	off	17	17	17	20	17	17	20	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-			
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17			
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	-	17	off	17	14	14	17	-	-	-	-	-	-	17	off	17	14	14	17		
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported				
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported				
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported				
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported				
5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported						
UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20			
	5785 & 5805	157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	-	17	off	17	17	17	20	-	-	-	-	-	-	17	off	17	17	17	20			

AP3500i 5 GHz Max Tx Power Over Frequency (in dBm)

Regulatory Domain: -T - Antenna Gain: 3 dBi

SW Release 7.0 <i>DFS Channels Are In Italics</i>				Non HT20			Non HT20			Non HT20			Non HT40			Non HT40			HT20			HT20			HT40			HT40		
				Single Ant 6 to 54 Mb/s			Dual Ants 6 to 54 Mb/s			Beam Form Dual Ants 6 to 54 Mb/s			Duplicate Single Ant 6 to 54 Mb/s			Duplicate Dual Ants 6 to 54 Mb/s			Single Ant M0 to M7			Dual Ants M0 to M15			Single Ant M0 to M7			Dual Ants M0 to M15		
BW	Band	Freq (MHz)	Ch ID	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr	Tx 1	Tx 2	Total Pwr
20 MHz	UNII-1	5180	36	Not Supported			Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-
		5200	40										-	-	-	-	-	-							-	-	-	-	-	-
		5220	44										-	-	-	-	-	-							-	-	-	-	-	-
		5240	48										-	-	-	-	-	-							-	-	-	-	-	-
	UNII-2	5260	52	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		5280	56	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	<i>8</i>	<i>8</i>	11	-	-	-	-	-	-	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	-	-	-	-	-	-
		5300	60	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	<i>8</i>	<i>8</i>	11	-	-	-	-	-	-	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	-	-	-	-	-	-
	UNII-2 Ext	5320	64	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	<i>8</i>	<i>8</i>	11	-	-	-	-	-	-	<i>15</i>	<i>off</i>	15	<i>11</i>	<i>11</i>	14	-	-	-	-	-	-
		5500	100	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5520	104	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5540	108	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5560	112	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5580	116	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5600	120	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5620	124	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5640	128	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
		5660	132	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
	5680	136	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
	5700	140	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>15</i>	<i>15</i>	18	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
	UNII-3	5745	149	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-
5765		153	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
5785		157	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
5805		161	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
5.8 ISM	5825	165	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	
40 MHz	UNII-1	5180 & 5200	36, 40U & 36L, 40	-	-	-	-	-	-	-	-	-	Not Supported			Not Supported			-	-	-	-	-	-	Not Supported			Not Supported		
		5220 & 5240	44, 48U & 44L, 48	-	-	-	-	-	-	-	-	-							-	-	-									
	UNII-2	5260 & 5280	52, 56U & 52L, 56	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		5300 & 5320	60, 64U & 60L, 64	-	-	-	-	-	-	-	-	-	<i>15</i>	<i>off</i>	15	<i>14</i>	<i>14</i>	17	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>15</i>	<i>15</i>	18
	UNII-2 Ext	5500 & 5520	100, 104U & 100L, 104	-	-	-	-	-	-	-	-	-	<i>15</i>	<i>off</i>	15	<i>13</i>	<i>13</i>	16	-	-	-	-	-	-	<i>16</i>	<i>off</i>	16	<i>15</i>	<i>15</i>	18
		5540 & 5560	108, 112U & 108L, 112	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20
		5580 & 5600	116, 120U & 116L, 120	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20
		5620 & 5640	124, 128U & 124L, 128	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20
		5660 & 5680	132, 136U & 132L, 136	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20
	UNII-3	5745 & 5765	149, 153U & 149L, 153	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20
5785 & 5805		157, 161U & 157L, 161	-	-	-	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	-	-	-	-	-	-	<i>17</i>	<i>off</i>	17	<i>17</i>	<i>17</i>	20	