

# Contents

[Introduction](#)

[Background Information](#)

[Procedure](#)

## Introduction

This document describes how to overcome the issue of netflow data which is not displayed for the individual site but for the unassigned devices.

## Background Information

If rules are not declared properly at **Services > Application Visibility & control > Endpoint Association** then you face this issue.

After declaring the same we are able to see traffic classified into corresponding site.

For Netflow data not shown for sites.

[http://www.cisco.com/c/en/us/td/docs/net\\_mgmt/prime/infrastructure/3-0/administrator/guide/PIAdminBook/metrics.html](http://www.cisco.com/c/en/us/td/docs/net_mgmt/prime/infrastructure/3-0/administrator/guide/PIAdminBook/metrics.html)

## Procedure

Follow the procedure as shown in the image:

**Step 1** Create a site structure for your organization and assign your principal routers to the appropriate sites:

- a. Choose **Maps > Site Maps**.
- b. Add one or more campuses, buildings, and floors (for details, see "Working With Maps").

**Step 2** Associate your sites with authorized data sources:

- a. Choose **Services > Application Visibility & Control > Data Deduplication**.
- b. Click **Enable Data Deduplication**, then click **Apply**. You can then assign authoritative sources for ART, Traffic Analysis and Voice/Video data (see "Enabling Data Deduplication").

**Step 3** Associate your sites with endpoint subnets:

- a. Choose **Services > Application Visibility & Control > Endpoint Association**.
- b. Associate subnets with your sites (see "Associating Endpoints With Sites").

If you fail to do this, by default the data collected for these endpoints will have their sites set to **Unassigned**.

**Step 4** Configure your compatible routers for Cisco Medianet Performance Monitor (see "Configuring Mediatrace on Routers and Switches").

**Step 5** Configure your routers for Mediatrace and WSMA (see "Using Mediatrace").

---