

Tidal Enterprise Orchestrator: Windows Event Trigger Does Not Register

Document ID: 112179

Contents

Introduction

Prerequisites

- Components Used

- Conventions

Problem

Solution

- Windows 2008

- Windows 2003

Related Information

Introduction

When attempting to monitor a Windows event on another Windows server, the event trigger does not register.

Prerequisites

Components Used

- Tidal Enterprise Orchestrator (TEO) 2.1 or later
- Windows Trigger

Conventions

Refer to Cisco Technical Tips Conventions for more information on document conventions.

Problem

The Windows event trigger does not register with the TEO Server. This error message may be seen:

```
The RPC server is unavailable.  
(Exception from HRESULT: 0x800706BA)
```

Solution

Three WMI firewall rules must be enabled to allow passage through the firewall. This configuration should be performed on the TEO server.

Windows 2008

Perform these steps for Windows 2008:

1. Click **Start > Server Manager**.
2. Go to **Configuration > Windows Firewall > Inbound Rules**.

3. In order to allow inbound of these components, right-click on them and allow enable of rule:

- ◆ WMI (Async-In)
- ◆ WMI (DCOM-In)
- ◆ WMI (WMI-In)

Windows 2003

Perform these steps for Windows 2003:

1. Click **Start > Control Panel > Windows Firewall**.
2. Click the **Exceptions** tab, choose the **WMI** check box, and click **OK**.

Related Information

- [Technical Support & Documentation – Cisco Systems](#)
-

[Contacts & Feedback](#) | [Help](#) | [Site Map](#)

© 2014 – 2015 Cisco Systems, Inc. All rights reserved. [Terms & Conditions](#) | [Privacy Statement](#) | [Cookie Policy](#) | [Trademarks of Cisco Systems, Inc.](#)

Updated: Mar 01, 2011

Document ID: 112179
