

Changing the IP Address for Cisco Unified CallManager / Unified Communications Manager

[TAC Notice: What's Changing on TAC Web](#)

Contents

[Introduction](#)

[Prerequisites](#)

[Requirements](#)

[Components Used](#)

[Conventions](#)

[Changing the Cisco Unified Communications Manager 5.x and 6.x IP Address](#)

[Changing the CallManager 3.x and 4.x IP Address](#)

[NetPro Discussion Forums - Featured Conversations](#)

[Related Information](#)

Help us help you.



Please rate this document.

- Excellent
- Good
- Average
- Fair
- Poor



This document solved my problem.

- Yes
- No
- Just browsing



Suggestions for improvement:

(256 character limit)



Introduction

This document describes how to change the IP address on a Cisco CallManager server. The Cisco CallManager IP address is changed for a variety of reasons. It includes moving the server from one segment to another or resolving a duplicate IP address problem.

Prerequisites

Requirements

There are no specific requirements for this document.

Components Used

This document is not restricted to specific software and hardware versions.

Conventions

Refer to the [Cisco Technical Tips Conventions](#) for more information on document conventions.

Changing the Cisco Unified Communications Manager 5.x and 6.x IP Address

For information on how to change the IP address or host name in Cisco Unified Communications Manager 5.X or 6.X, refer to [Changing the IP Address and Host Name for Cisco Unified Communications Manager 5.x and 6.x Servers](#).

Changing the CallManager 3.x and 4.x IP Address

Complete these steps in order to change the IP address for a Cisco CallManager server.

1. Choose **Start > Settings > Control Panel**.
2. Double-click **Network and Dial-up Connections**.
3. Double-click **Local Area Connection**.
4. In the Local Area Connection Status window, click **Properties**.
5. In the list on the Local Area Connection Properties window, double-click the **Internet Protocol (TCP/IP)**.
6. In the Internet Protocol (TCP/IP) Properties window, click the **Use the following IP address** button and type an IP address.
7. Click **OK**.
8. In the Local Area Connection Properties window, click **OK**.
9. In the Local Area Connection Status window, click **Close**.
10. Restart the server when prompted.

The procedure to change the IP address for the server is complete. The next step is to change the IP address in Cisco CallManager Administration.

11. Choose **Start > Programs > Cisco CallManager 3.0 > CallManager Administration**. Each system has a different version number like 3.1 or 3.2, 3.3, or 4.0.

12. Choose **System > Server**.
13. On the Server Configuration window, click on the appropriate Cisco CallManager server in the list.
14. In the DNS or IP Address field, type the new IP address.

Note: IP phones require WINS in order to resolve CallManager NetBios names and DNS in order to resolve Domain Names. If there is any chance of having a problem with DNS or WINS resolution, it is always good to use the IP address. You might face issues with the SRST configuration where DNS servers are at a remote location and cannot be contacted when the WAN link fails.

15. Click **Update**.
16. Reboot all servers in the Cisco CallManager cluster.

System Route Plan Service Feature Device User Application Help

Cisco CallManager Administration
For Cisco IP Telephony Solutions

CISCO SYSTEMS

Server Configuration

[Add a New Server](#)
[Configure Cisco CallManager \(CM_PUB333\)](#)
[Back to Find/List Servers](#)
[Dependency Records](#)

Current Server: 172.16.17.175
Status: Ready

Update Delete

Host Name/IP Address*

MAC Address

Description

Note: You must update the DNS server when a DNS name is used.

Both the server and the Cisco CallManager system have new IP addresses now. Repeat these steps as necessary for each server PC and Cisco CallManager system.

Note: Additional IP address changes are needed within Cisco CallManager. The changes are also needed in applications that reference Cisco CallManager such as Cisco Customer Response Applications (CRA). This list is an example of sections that might or might not need changes.

- In CRA, change the IP address under Engine configuration.
- In CRA, change the IP address under Java Telephony API (JTAPI).

- In CRA, change the IP address in the Directory configuration.
- In CRA, change the IP address in the Repository configuration.
- Stop the DC Directory service on the server. Choose **Control Panel > Administrative Tools > Services**.
- Change the IP address in the hoteling profile in the DC Directory on your CallManager server. Choose **Start > Programs > DC Directory Administration**. Click **System Profile > hoteling**.
- In Cisco CallManager, change the IP address in the URLs under **System > Enterprise Parameters**.
- In Cisco CallManager, change the IP address in the URLs under **Features > IP Phone Services**.
- Change the LMHOST and HOSTS files on all servers.
- Change DHCP option 150 to a new IP address.
- Open SQL Enterprise Manager and change the IP addresses in the URLs in the PlugIn table.
- Open the stiBackup configuration and change the server IP addresses under all appropriate tabs.
- Change the IP address in C:\TAPS\TAPSCCM.txt.
- If you have integrated Cisco CallManager and Cisco Unity, update the TSP on the Cisco Unity server to point to the new Cisco CallManager IP address. On the Cisco Unity server, go to the Windows **Start** menu, and choose **Programs > Cisco Unity > Manage Integrations**.

If you connect to a Cisco CallManager cluster, Cisco recommends that you enter the IP address (or DNS name) of a subscriber Cisco CallManager server.

Note: *If* you have Subscribers, when you change the IP address of the Publisher, you need to edit the LMHOST files in the Subscribers to the new IP address.

NetPro Discussion Forums - Featured Conversations

Networking Professionals Connection is a forum for networking professionals to share questions, suggestions, and information about networking solutions, products, and technologies. The featured links are some of the most recent conversations available in this technology.

NetPro Discussion Forums - Featured Conversations for Voice

Service Providers: Voice over IP

[re-INVITE SIP-H323 GW](#) - Jun 17, 2008

[AS5400 and SIP/H323 Voice calls.....????????????????](#) - Jun 17, 2008

[PGW reboot for machine and services????????????????](#) - Jun 17, 2008

[change username and password for PGW2200 ??????????](#) - Jun 17, 2008

[How to agregate some BRI up to 3 on ASS400](#) - Jun 16, 2008

Voice & Video: Voice over IP

[multicast video over wirelss problems!!!](#) - Jun 15, 2008

[SIP Trunking](#) - Jun 14, 2008

[Transcription server](#) - Jun 13, 2008

[voicemail broadcast](#) - Jun 13, 2008

[Does a need a CCM for a System 3500 Videocoferencing system or similar ?](#) - Jun 13, 2008

Voice & Video: IP Telephony

[sip server through site to site VPN](#) - Jun 17, 2008

[Dialing 0 from Metting Place Express](#) - Jun 17, 2008

[Callmanager 5 Option Under IP phones network settings??](#) - Jun 17, 2008

[Upgrade CCM 4.13 to 6.1](#) - Jun 17, 2008

[H323 gateway reoder tone](#) - Jun 17, 2008

Voice & Video: IP Phone Services for End Users

[7971 touch screen wont respond to touch](#) - Jun 17, 2008

["Requesting" displayed on IPMA phones](#) - Jun 17, 2008

[Loading Disk 3](#) - Jun 16, 2008

[Cisco 7921G can not associate with any Access Points](#) - Jun 16, 2008

[Can i connect cisco ip phone 7940 series with normal telephone line](#) - Jun 16, 2008

Voice & Video: Unified Communications

[CCM Trace Config issue](#) - Jun 17, 2008

[Meeting place error on Oultook client - "Action cancelled"](#) - Jun 17, 2008

[ADSchemaSetup.log error](#) - Jun 17, 2008

[CUSM doesnt detect phones from CUCM](#) - Jun 17, 2008

[CCM 4.2.\(1\)sr1 question](#) - Jun 17, 2008

Voice & Video: IP Phone Services for Developers

[How to change Agent state remot in IPCC](#) - Jun 17, 2008

[CCM can send spontaneous trap to a manager?](#) - Jun 17, 2008

[Custom text on "Your current options"](#) - Jun 17, 2008

[AddH323Gateway AXL Example.](#) - Jun 16, 2008

[AXL 6 does not properly encode responses.](#) - Jun 16, 2008

Voice & Video: General

[CUCM6-BE](#) - Jun 17, 2008


[voice-vlan problem in DID](#) - Jun 17, 2008

[ATA186-Problem with second DN](#) - Jun 17, 2008

[UC Mobility, genuine ICLID transmission](#) - Jun 17, 2008

[CUMC, operational questions](#) - Jun 17, 2008

Related Information

- [Troubleshooting Guide for Cisco Unified CallManager, Release 4.x](#)
 - [Voice Technology Support](#)
 - [Voice and Unified Communications Product Support](#)
 - **Recommended Reading:** [Troubleshooting Cisco IP Telephony](#) 
 - [Technical Support & Documentation - Cisco Systems](#)
-

[Home](#)

[How to Buy](#)

[Login](#)

[Profile](#)

[Feedback](#)

[Site Map](#)

[Help](#)

[Contacts & Feedback](#) | [Help](#) | [Site Map](#)

© 2007 - 2008 Cisco Systems, Inc. All rights reserved. [Terms & Conditions](#) | [Privacy Statement](#) | [Cookie Policy](#) |

[Trademarks of Cisco Systems, Inc.](#)