



APPENDIX **A**

Cisco Service Control MIBs

Revised: February 15, 2011, OL-19896-07

Introduction

The SCE platform originally supported the standard MIB-II and a proprietary Service Control Enterprise MIB. The proprietary *pcube* MIB enabled the external management system to perform configuration, performance, troubleshooting and alerting operations specific to the SCE platform that were not provided by the standard MIB.

The proprietary *pcube* MIBs has been replaced by a combination of standard and Cisco MIBs and new Cisco Service Control MIBs. The new MIB structure was designed to keep backward compatibility and provide the same information as provided in the past as much as possible.

This appendix explains how to map the proprietary *pcube* MIB supported in previous releases to the new MIB structure. It points out backward compatible issues and provides mapping guidelines from old MIB or OID group to a new MIB.



Note

These MIB updates are supported on the SCE8000 platform only. The *pcube* MIB is backward compatible to 3.1.6 for the SCE 1000 and SCE 2000 platforms.

The list of supported MIBs is described at the following URL under the Cisco Service Routing Products section. Select the desired product and then the desired release.

<http://www.cisco.com/public/sw-center/netmgmt/ctk/mibs.shtml>

All Cisco MIBs and some of the common standard MIBs can be obtained at the following URL:

<http://tools.cisco.com/Support/SNMP/do/BrowseMIB.do?local=en&step=2>

MIB Files

The pcube MIB was grouped into several MIBs, each of which represented a certain aspect or functionality in the SCE platform (see the tables in the [pcube to Cisco MIB Mapping: Detailed OID Mappings](#), page A-5 section for more details).

The pcube MIB files have been replaced by MIBs from three sources:

- standard MIBs
- existing Cisco MIBs
- new Cisco Service Control MIBs

[Table A-1](#), [Table A-2](#), and [Table A-3](#) describe the former pcube MIB files and the MIB files that replace the pcube MIB.

Table A-1 *pcube MIBs*

MIB	Description
PCUBE-SMI.my	Defines P-cube enterprise tree structure
PCUBE-PRODUCTS-MIB.my	Defines OIDs of Cisco Service Control products
PCUBE-CONFIG-COPY-MIB.my	Contains a subset of the Cisco Config-Copy-MIB ported to the pcube enterprise subtree
CISCO-SCAS-BB-MIB.my	Contains SCA BB information handlers
PCUBE-SE-MIB.my	Contains information about the SCE platform

Table A-2 *Newly added CISCO-SERVICE_CONTROL MIBs that replace pcube MIBs*

MIB	Description
CISCO-SERVICE-CONTROL-LINK-MIB.my	Provides information about the status and configuration of links used by service control entities.
CISCO-SERVICE-CONTROL-RDR-MIB.my	Defines objects describing statistics and configuration relating to the Raw Data Record Formatter running on a service control entity.
CISCO-SERVICE-CONTROL-SUBSCRIBERS-MIB.my	Provides global and specific information on subscribers managed by a service control entity
CISCO-SERVICE-CONTROL-TP-STATS-MIB.my	Provides information and statistics on the traffic processor(s) of a service control entity.
CISCO-SERVICE-CONTROL-ATTACK-MIB.my	Provides information related to different types of attacks detected on the network entities and corresponding actions taken in the monitored network
CISCO-SERVICE-CONTROLLER-MIB.my	Provides information about service control traffic controllers.

Table A-3 Standard and Cisco MIBs used to replace pcube MIBs

MIBs	Description
CISCO-SMI.my	Defines Cisco enterprise tree structure
CISCO-TC.my	Contains Textual Conventions needed in some MIBs
CISCO-CONFIG-COPY-MIB.my	Facilitates writing of configuration files
CISCO-ENTITY-ALARM-MIB.my	Defines the managed objects that support the monitoring of alarms generated by physical entities contained by the system
CISCO-ENTITY-FRU-CONTROL-MIB.my	Monitor s and configures operational status of Field Replaceable Units
CISCO-ENTITY-REDUNDANCY-MIB.my	Supports configuration, control and monitoring of redundancy protection for various kinds of components on Cisco managed devices.
CISCO-ENTITY-REDUNDANCY-TC-MIB.my	Defines the textual conventions used within Cisco Entity Redundancy MIBs
CISCO-ENTITY-SENSOR-MIB.my	Monitors the values of sensors in the Entity-MIB
CISCO-PROCESS-MIB.my	Provides overall information about the CPU load.
CISCO-QUEUE-MIB.my	Manages interface queuing in Cisco devices.
CISCO-SECURE-SHELL-MIB.my	Displays and configures accounting and Secure Shell (SSH) related features in a device.
CISCO-SYSLOG-EXT-MIB.my	Extends the Cisco Syslog MIB and provides network management support to handle and process Syslog messages as device events
CISCO-SYSLOG-EVENT-EXT-MIB.my	Extends the Cisco Syslog.MIB and provides network management support to handle and process Syslog messages as device events
CISCO-SYSLOG-MIB.my	Describes and stores the system messages generated by the IOS and any other OS which supports syslogs.
CISCO-TELNET-SERVER-MIB.my	Displays and configures Telnet related features in a device.
ENTITY-MIB.my	Represents multiple logical entities supported by a single SNMP agent
ENTITY-STATE-MIB.my	Defines a state extension to the Entity MIB
ENTITY-STATE-TC-MIB.my	Defines state textual conventions.
HOST-RESOURCES-MIB.my	Manages host systems.

**Note**

Only OIDs that are mapped to former pcube MIB OIDs are in use in the standard and Cisco MIBs as listed in this table.

Loading MIBs

It is important to load the MIBs in the proper order.

Before loading any new CISCO-SERVICE-CONTROL MIB, load the following MIBs in this order:

1. SNMPv2-SMI.my
2. SNMPv2-CONF.my
3. SNMPv2-TC.my
4. SNMP-FRAMEWORK-MIB.my
5. ENTITY-MIB.my
6. INET-ADDRESS-MIB.my
7. CISCO-SMI.my
8. CISCO-TC.my

Loading procedure for standard MIBs and other legacy Cisco MIBs is explained here:

<http://tools.cisco.com/Support/SNMP/do/BrowseMIB.do?local=en&step=2>

pcube to Cisco MIB Mapping

This section is an overview of how the former pcube MIB maps to the current Cisco MIBs. Two P-cube MIBs are mapped; PcubeSeMIB and PcubeEngageMIB (CISCO-SCABB-MIB). [Table A-4](#) lists the objects related to the overall tree structure and [Table A-5](#) lists the PcubeSeMIB group names and objects.

Table A-4 Overall tree structure: related objects

Pcube Object Name	New MIB Object Name/MIB Name
pcube	CISCO-SERVICE-CONTROL or cServiceControl
pcubeProducts	ciscoMgmt
pcubeModules	Removed
pcubeSeMIB	See Table A-5 on page A-4
pcubeEngageMIB	See pcube Engage MIB (CISCO-SCAS-BB-MIB) , page A-5

Table A-5 PcubeSeMIB

PcubeSEMIB Group Name	New MIB Object Name/MIB Name
pcubeSeMIBpcubeModuleGroup	cServiceControlMIB
pcubeSeConformance	cServiceControlNotifs
pcubeSeGroups	cServiceControlObjects
pcubeSystemGroup	ENTITY and ENTITY-EXTENTION MIBs
pcubeChassisGroup	ENTITY and ENTITY-EXTENTION MIBs
pcuebModuleGroup	ENTITY and ENTITY-EXTENTION MIBs

Table A-5 *PcubeSeMIB (continued)*

PcubeSEMIB Group Name	New MIB Object Name/MIB Name
pcubeLinkGroup	CISCO-SERVICE-CONTROL-LINK-MIB
pcubeDiskGroup	HOST-RESOURCES-MIB
pcubeRdrFormatterGroup	CISCO-SERVICE-CONTROL-RDR-MIB
pcubeLoggerGroup	clogHistoryTable from CISCO-SYSLOG-MIB
pcubeSubscribersGroup	CISCO-SERVICE-CONTROL-SUBSCRIBERS-MIB
pcubeTrafficProcessorGroup	CISCO-SERVICE-CONTROL-TP-STATS-MIB
pcubePortGroup	ENTITY-MIB, many objects in the group are no longer necessary
pcubeTxQueuesGroup	CISCO-QUEUE-MIB with a few modifications.
pcubeGlobalControllersGroup	CISCO-SERVICE-CONTROLLER-MIB
pcubeTrafficCountersGroup	CISCO-SERVICE-CONTROL-TP-STATS-MIB
pcubeAttackGroup	CISCO-SERVICE-CONTROL-ATTACK-MIB
pcubeTrapObjectsGroup	Notifications have been mapped to the relevant MIBs

pcube Engage MIB (CISCO-SCAS-BB-MIB)

The information in the pcubeEngageMIB is available from various RDRs and from tables of the Collection Manager database. Therefore this MIB has not been replaced by a new Cisco Service Control MIB.

For information regarding the mapping of the MIB objects to RDRs and the Collection Manager database, see [Table A-21 on page A-23](#).

pcube to Cisco MIB Mapping: Detailed OID Mappings

The following tables provide the detailed mappings for specific pcubeSeMIB (1.3.6.1.4.1.5655.4.1/0) OIDs to the current standard and Cisco MIBs.

Table A-6 *systemGrp (1.3.6.1.4.1.5655.4.1.1)*

pcube Object Name	OID	New MIB	New Object Name	OID
sysOperationalStatus	1.3.6.1.4.1.5655.4.1.1.1	ENTITY-STATE-MIB	entStateTable.entStateOper entStateTable.entStateAlarm	1.3.6.1.2.1.131.1.1.1.3 1.3.6.1.2.1.131.1.1.1.5
other(1)			entStateTable.entStateOper = unknown (1) entStateTable.entStateAlarm = indeterminate (2).	
boot(2)			entStateTable.entStateOper = testing (4) entStateTable.entStateAlarm = unknown (0x80)	
operational(3)			entStateTable.entStateOper = enabled (3) entStateTable.entStateAlarm = unknown(0x80)	
warning(4)			entStateTable.entStateOper = enabled (3) entStateTable.entStateAlarm = warning (5)	
failure(5)			entStateTable.entStateOper = disabled (2) entStateTable.entStateAlarm = critical(2) or major(3)	
sysFailureRecovery	1.3.6.1.4.1.5655.4.1.1.2	CISCO-ENTITY-EXT-MIB	not mapped	
sysVersion	1.3.6.1.4.1.5655.4.1.1.2.1	ENTITY-MIB	entPhysicalDescr	1.3.6.1.2.1.47.1.1.1.1.2

Table A-7 *pchassisGrp (1.3.6.1.4.1.5655.4.1.2)*

pcube Object Name	OID	New MIB	New Object Name	OID
pchassisSysType	1.3.6.1.4.1.5655.4.1.2.1		Not mapped. Derived from entPhysicalDescr and entPhysicalClass chassis(3)	
pchassisPowerSupply Alarm	1.3.6.1.4.1.5655.4.1.2.2	CISCO-ENTITY-FRU-CONTROL-MIB	Trap is sent Current status available using the show environment CLI command	

Table A-7 *pchassisGrp (1.3.6.1.4.1.5655.4.1.2 (continued))*

pcube Object Name	OID	New MIB	New Object Name	OID
pchassisFansAlarm	1.3.6.1.4.1.5655.4.1.2.3	CISCO-ENTITY-FRU-CONTROL-MIB	Trap is sent Current status available using the show environment CLI command	
pchassisTempAlarm	1.3.6.1.4.1.5655.4.1.2.4	CISCO-ENTITY-SENSOR-MIB	Trap is sent Current status available using the show environment CLI command	
pchassisVoltageAlarm	1.3.6.1.4.1.5655.4.1.2.5	CISCO-ENTITY-SENSOR-MIB	Trap is sent Current status available using the show environment CLI command	
pchassisNumSlots	1.3.6.1.4.1.5655.4.1.2.6	ENTITY-MIB	The entity MIB shows the number of slots. According to the Entity MIB mapping and container relationship	
pchassisSlotConfig	1.3.6.1.4.1.5655.4.1.2.7	ENTITY-MIB	The Entity MIB indicates which slots in the chassis have modules inserted.	
pchassisPsuType	1.3.6.1.4.1.5655.4.1.2.8	ENTITY-MIB	entity physical name shows the Name	
pchassisLineFeedAlarm	1.3.6.1.4.1.5655.4.1.2.10	ENTITY-MIB	Trap is sent Current status available using the show environment CLI command	

Table A-8 *pmoduleGrp (1.3.6.1.4.1.5655.4.1.3)*

pcube Object Name	OID	New MIB	New Object Name	OID
pmoduleTable	1.3.6.1.4.1.5655.4.1.3.1	ENTITY-MIB	entPhysicalTable	1.3.6.1.2.1.47.1.1.1
pmoduleEntry	1.3.6.1.4.1.5655.4.1.3.1.1	ENTITY-MIB	entPhysicalEntry	1.3.6.1.2.1.47.1.1.1.1
pmoduleIndex	1.3.6.1.4.1.5655.4.1.3.1.1.1	ENTITY-MIB	entPhysicalIndex	1.3.6.1.2.1.47.1.1.1.1.1
pmoduleType	1.3.6.1.4.1.5655.4.1.3.1.1.2	ENTITY-MIB	entPhysicalName entPhysicalClass	1.3.6.1.2.1.47.1.1.1.1.7 1.3.6.1.2.1.47.1.1.1.1.5
pmoduleNumTrafficProcessors	1.3.6.1.4.1.5655.4.1.3.1.1.3	CISCO-PROCESS-MIB	cpmCPUTotalTable.cpmCPUTotalPhysicalIndex	1.3.6.1.4.1.9.9.109.1.1.1.1.2

Table A-8 pmoduleGrp (1.3.6.1.4.1.5655.4.1.3) (continued)

pcube Object Name	OID	New MIB	New Object Name	OID
pmoduleSlotNum	1.3.6.1.4.1.5655.4.1.3.1.1.4	ENTITY-MIB	entPhysicalContainedIn	1.3.6.1.2.1.47.1.1.1.1.4
pmoduleHwVersion	1.3.6.1.4.1.5655.4.1.3.1.1.5	ENTITY-MIB	entPhysicalHardwareRev	1.3.6.1.2.1.47.1.1.1.1.8
pmoduleNumPorts	1.3.6.1.4.1.5655.4.1.3.1.1.6	ENTITY-MIB	The number of entries in ENTITY-MIB with entPhysicalClass = port	
pmoduleNumLinks	1.3.6.1.4.1.5655.4.1.3.1.1.7	ENTITY-MIB	The number of entries in ENTITY-MIB with entPhysicalClass = other	
pmoduleConnection Mode	1.3.6.1.4.1.5655.4.1.3.1.1.8	Not mapped	Use CLI command: show interface linecard connection-mode	
pmoduleSerialNumber	1.3.6.1.4.1.5655.4.1.3.1.1.9	ENTITY-MIB	entPhysicalSerialNum	1.3.6.1.2.1.47.1.1.1.1.11
pmoduleUpStream AttackFilteringTime	1.3.6.1.4.1.5655.4.1.3.1.1.10	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaInfoUpStream AttackFilteringTime	1.3.6.1.4.1.9.9.693.1.3.1.1
pmoduleUpStreamLastAttackFilteringTime	1.3.6.1.4.1.5655.4.1.3.1.1.11	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaInfoUpStreamLast AttackFilteringTime	1.3.6.1.4.1.9.9.693.1.3.1.2
pmoduleDownStream AttackFilteringTime	1.3.6.1.4.1.5655.4.1.3.1.1.12	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaInfoDownStream AttackFilteringTime	1.3.6.1.4.1.9.9.693.1.3.1.3
pmoduleDownStreamLastAttack FilteringTime	1.3.6.1.4.1.5655.4.1.3.1.1.13	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaInfoDownStreamLast AttackFilteringTime	1.3.6.1.4.1.9.9.693.1.3.1.4
pmoduleAttack ObjectsClearTime	1.3.6.1.4.1.5655.4.1.3.1.1.14		Not mapped	
pmoduleAdminStatus	1.3.6.1.4.1.5655.4.1.3.1.1.15	ENTITY-MIB	entStateAdmin	1.3.6.1.2.1.131.1.1.1.2
pmoduleOperStatus	1.3.6.1.4.1.5655.4.1.3.1.1.16	ENTITY-MIB	entStateOper entStateStandby	1.3.6.1.2.1.131.1.1.1.3 1.3.6.1.2.1.131.1.1.1.6

Table A-9 *linkGrp (1.3.6.1.4.1.5655.4.1.4): all mapped objects mapped to CISCO-SERVICE-CONTROL-LINK-MIB*

pcube Object Name	OID	New Object Name	OID
linkTable	1.3.6.1.4.1.5655.4.1.4.1	cscLinkStatusTable	1.3.6.1.4.1.9.9.631.1.2
linkEntry	1.3.6.1.4.1.5655.4.1.4.1.1	cscLinkStatusEntry	1.3.6.1.4.1.9.9.631.1.2.1
linkModuleIndex	1.3.6.1.4.1.5655.4.1.4.1.1.1	Not mapped. Not needed in the new structure - Information provided by ENTITY-MIB	
linkIndex	1.3.6.1.4.1.5655.4.1.4.1.1.2	entPhysicalIndex	1.3.6.1.2.1.47.1.1.1.1.1
linkAdminModeOnActive	1.3.6.1.4.1.5655.4.1.4.1.1.3	cscLinkStatusAdminModeOnActive	1.3.6.1.4.1.9.9.631.1.2.1.1
linkAdminModeOnFailure	1.3.6.1.4.1.5655.4.1.4.1.1.4	cscLinkStatusAdminModeOnFailure	1.3.6.1.4.1.9.9.631.1.2.1.2
linkOperMode	1.3.6.1.4.1.5655.4.1.4.1.1.5	cscLinkStatusOperMode	1.3.6.1.4.1.9.9.631.1.2.1.3
linkStatusReflectionEnable	1.3.6.1.4.1.5655.4.1.4.1.1.6	cscLinkStatusStatusReflectionEnable	1.3.6.1.4.1.9.9.631.1.2.1.4
linkSubscriberSidePortIndex	1.3.6.1.4.1.5655.4.1.4.1.1.7	cscLinkStatusSubscriberSidePortIndex	1.3.6.1.4.1.9.9.631.1.2.1.5
linkNetworkSidePortIndex	1.3.6.1.4.1.5655.4.1.4.1.1.8	cscLinkStatusNetworkSidePortIndex	1.3.6.1.4.1.9.9.631.1.2.1.6
		New objects: cscLinkStatusStatusReflectionState = noLinkReflection(1) reflectingFailureToNetwork (2) reflectingFailureToSubscriber(3)	1.3.6.1.4.1.9.9.631.1.2.1.7

Table A-10 *diskGrp (1.3.6.1.4.1.5655.4.1.5): all objects mapped to HOST-RESOURCE-MIB*

pcube Object Name	OID	New Object Name	OID
diskNumUsedBytes	1.3.6.1.4.1.5655.4.1.5.1	hrStorageTable.hrStorageUsed	1.3.6.1.2.1.25.2.3.1.6
diskNumFreeBytes	1.3.6.1.4.1.5655.4.1.5.2	hrStorageTable.hrStorageUsed hrStorageTable.hrStorageSize	1.3.6.1.2.1.25.2.3.1.6 1.3.6.1.2.1.25.2.3.1.5

Table A-11 *rdrFormatterGrp (1.3.6.1.4.1.5655.4.1.6): all mapped objects mapped to CISCO-SERVICE-CONTROL-RDR-MIB*

pcube Object Name	OID	New Object Name	OID
rdrFormatterEnable	1.3.6.1.4.1.5655.4.1.6.1	cServiceControlRDRFormatterEnable	1.3.6.1.4.1.9.9.637.1.1.1.1
rdrFormatterDestTable	1.3.6.1.4.1.5655.4.1.6.2	cServiceControlRDRFormatterDestTable	1.3.6.1.4.1.9.9.637.1.2

Table A-11 *rdrFormatterGrp (1.3.6.1.4.1.5655.4.1.6): all mapped objects mapped to CISCO-SERVICE-CONTROL-RDR-MIB (continued)*

pcube Object Name	OID	New Object Name	OID
rdRFormatterDestEntry	1.3.6.1.4.1.5655.4.1.6.2.1	cServiceControlRDRFormatterDestEntry	1.3.6.1.4.1.9.9.637.1.2.1
rdRFormatterDestIPAddr	1.3.6.1.4.1.5655.4.1.6.2.1.1	cServiceControlRDRFormatterDestIPAddr	1.3.6.1.4.1.9.9.637.1.2.1.3
rdRFormatterDestPort	1.3.6.1.4.1.5655.4.1.6.2.1.2	cServiceControlRDRFormatterDestPort	1.3.6.1.4.1.9.9.637.1.2.1.4
rdRFormatterDestPriority	1.3.6.1.4.1.5655.4.1.6.2.1.3	cServiceControlRDRFormatterDestPriority	1.3.6.1.4.1.9.9.637.1.2.1.5
rdRFormatterDestStatus	1.3.6.1.4.1.5655.4.1.6.2.1.4	cServiceControlRDRFormatterDestStatus	1.3.6.1.4.1.9.9.637.1.2.1.6
rdRFormatterDestConnectionStatus	1.3.6.1.4.1.5655.4.1.6.2.1.5	cServiceControlRDRFormatterDestConnectionStatus	1.3.6.1.4.1.9.9.637.1.2.1.7
rdRFormatterDestNumReportsSent	1.3.6.1.4.1.5655.4.1.6.2.1.6	cServiceControlRDRFormatterDestNumReportsSent	1.3.6.1.4.1.9.9.637.1.2.1.8
rdRFormatterDestNumReportsDiscarded	1.3.6.1.4.1.5655.4.1.6.2.1.7	cServiceControlRDRFormatterDestNumReportsDiscarded	1.3.6.1.4.1.9.9.637.1.2.1.9
rdRFormatterDestReportRate	1.3.6.1.4.1.5655.4.1.6.2.1.8	cServiceControlRDRFormatterDestReportRate	1.3.6.1.4.1.9.9.637.1.2.1.10
rdRFormatterDestReportRatePeak	1.3.6.1.4.1.5655.4.1.6.2.1.9	Not mapped	
rdRFormatterDestReportRatePeakTime	1.3.6.1.4.1.5655.4.1.6.2.1.10	Not mapped	
rdRFormatterNumReportsSent	1.3.6.1.4.1.5655.4.1.6.3	cServiceControlRDRFormatterNumReportsSent	1.3.6.1.4.1.9.9.637.1.1.1.2
rdRFormatterNumReportsDiscarded	1.3.6.1.4.1.5655.4.1.6.4	cServiceControlRDRFormatterNumReportsDiscarded	1.3.6.1.4.1.9.9.637.1.1.1.3
rdRFormatterClearCountersTime	1.3.6.1.4.1.5655.4.1.6.5	Not mapped	
rdRFormatterReportRate	1.3.6.1.4.1.5655.4.1.6.6	cServiceControlRDRFormatterReportRate	1.3.6.1.4.1.9.9.637.1.1.1.4
rdRFormatterReportRatePeak	1.3.6.1.4.1.5655.4.1.6.7	cscRdrFormatterReportRatePeak	1.3.6.1.4.1.9.9.637.1.1.1.5
rdRFormatterReportRatePeakTime	1.3.6.1.4.1.5655.4.1.6.8	cscRdrFormatterReportRatePeakTime	1.3.6.1.4.1.9.9.637.1.1.1.6
rdRFormatterProtocol	1.3.6.1.4.1.5655.4.1.6.9	cServiceControlRDRFormatterProtocol	1.3.6.1.4.1.9.9.637.1.1.1.7
rdRFormatterForwardingMode	1.3.6.1.4.1.5655.4.1.6.10	cServiceControlRDRFormatterForwardingMode	1.3.6.1.4.1.9.9.637.1.1.1.8

Table A-11 *rdrFormatterGrp (1.3.6.1.4.1.5655.4.1.6): all mapped objects mapped to CISCO-SERVICE-CONTROL-RDR-MIB (continued)*

pcube Object Name	OID	New Object Name	OID
rdrFormatterCategory Table	1.3.6.1.4.1.5655.4.1.6.11	Available through the CLI.	
rdrFormatterCategory Entry	1.3.6.1.4.1.5655.4.1.6.11.1	Available through the CLI.	
rdrFormatterCategory Index	1.3.6.1.4.1.5655.4.1.6.11.1.1	Available through the CLI.	
rdrFormatterCategory Name	1.3.6.1.4.1.5655.4.1.6.11.1.2	Available through the CLI.	
rdrFormatterCategory NumReportsSent	1.3.6.1.4.1.5655.4.1.6.11.1.3	Available through the CLI.	
rdrFormatterCategory NumReportsDiscarded	1.3.6.1.4.1.5655.4.1.6.11.1.4	Available through the CLI.	
rdrFormatterCategory ReportRate	1.3.6.1.4.1.5655.4.1.6.11.1.5	Available through the CLI.	
rdrFormatterCategory ReportRatePeak	1.3.6.1.4.1.5655.4.1.6.11.1.6	Not mapped	
rdrFormatterCategory ReportRatePeakTime	1.3.6.1.4.1.5655.4.1.6.11.1.7	Not mapped	
rdrFormatterCategory NumReportsQueued	1.3.6.1.4.1.5655.4.1.6.11.1.8	Available through the CLI.	
rdrFormatterCategory DestTable	1.3.6.1.4.1.5655.4.1.6.12	Available through the CLI.	
rdrFormatterCategory DestEntry	1.3.6.1.4.1.5655.4.1.6.12.1	Available through the CLI.	
rdrFormatterCategory DestPriority	1.3.6.1.4.1.5655.4.1.6.12.1.1	Available through the CLI.	
rdrFormatterCategory DestStatus	1.3.6.1.4.1.5655.4.1.6.12.1.2	Available through the CLI.	

Table A-12 *loggerGrp (1.3.6.1.4.1.5655.4.1.7): all mapped objects mapped to CISCO-SYSLOG-EVENT-EXT-MIB*

pcube Object Name	OID	New Object Name	OID
loggerUserLogEnable	1.3.6.1.4.1.5655.4.1.7.1	Not mapped	
loggerUserLogNumInfo	1.3.6.1.4.1.5655.4.1.7.2	cslogEventDispositionTable	1.3.6.1.4.1.9.9.270.1.1.5.1.3
loggerUserLogNumWarning	1.3.6.1.4.1.5655.4.1.7.3	cslogEventDispositionTable	1.3.6.1.4.1.9.9.270.1.1.5.1.4
loggerUserLogNumError	1.3.6.1.4.1.5655.4.1.7.4	cslogEventDispositionTable	1.3.6.1.4.1.9.9.270.1.1.5.1.5
loggerUserLogNumFatal	1.3.6.1.4.1.5655.4.1.7.5	cslogEventDispositionTable	1.3.6.1.4.1.9.9.270.1.1.5.1.6
loggerUserLogClearCountersTime	1.3.6.1.4.1.5655.4.1.7.6	Not mapped	

Table A-13 *subscribersGrp (1.3.6.1.4.1.5655.4.1.8): all mapped objects mapped to CISCO-SERVICE-CONTROL-SUBSCRIBERS-MIB*

pcube Object Name	OID	New Object Name	OID
subscribersInfoTable	1.3.6.1.4.1.5655.4.1.8.1.1	cServiceControlSubscribersInfoTable	1.3.6.1.4.1.9.9.628.1.2
subscribersInfoEntry	1.3.6.1.4.1.5655.4.1.8.1.1.1	cServiceControlSubscribersInfoEntry	1.3.6.1.4.1.9.9.628.1.2.1
subscribersNumIntroduced	1.3.6.1.4.1.5655.4.1.8.1.11.1	cServiceControlSubscribersNumIntroduced	1.3.6.1.4.1.9.9.628.1.2.1.1
subscribersNumFree	1.3.6.1.4.1.5655.4.1.8.1.1.2	cServiceControlSubscribersNumFree	1.3.6.1.4.1.9.9.628.1.2.1.2
subscribersNumIpAddrMappings	1.3.6.1.4.1.5655.4.1.8.1.1.3	cServiceControlSubscribersNumIpAddrMappings	1.3.6.1.4.1.9.9.628.1.2.1.3
subscribersNumIpAddrMappingsFree	1.3.6.1.4.1.5655.4.1.8.1.1.4	cServiceControlSubscribersNumIpAddrMappingsFree	1.3.6.1.4.1.9.9.628.1.2.1.4
subscribersNumIpRangeMappings	1.3.6.1.4.1.5655.4.1.8.1.1.5	cServiceControlSubscribersNumIpRangeMappings	1.3.6.1.4.1.9.9.628.1.2.1.5
subscribersNumIpRangeMappingsFree	1.3.6.1.4.1.5655.4.1.8.1.1.6	cServiceControlSubscribersNumIpRangeMappingsFree	1.3.6.1.4.1.9.9.628.1.2.1.6
subscribersNumVlanMappings	1.3.6.1.4.1.5655.4.1.8.1.1.7	cServiceControlSubscribersNumVlanMappings	1.3.6.1.4.1.9.9.628.1.2.1.7
subscribersNumVlanMappingsFree	1.3.6.1.4.1.5655.4.1.8.1.1.8	cServiceControlSubscribersNumVlanMappingsFree	1.3.6.1.4.1.9.9.628.1.2.1.8
subscribersNumActive	1.3.6.1.4.1.5655.4.1.8.1.1.9	cServiceControlSubscribersNumActive	1.3.6.1.4.1.9.9.628.1.2.1.9
subscribersNumActivePeak	1.3.6.1.4.1.5655.4.1.8.1.1.10	Not mapped	
subscribersNumActivePeakTime	1.3.6.1.4.1.5655.4.1.8.1.1.11	Not mapped	
subscribersNumUpdates	1.3.6.1.4.1.5655.4.1.8.1.1.12	cServiceControlSubscribersNumUpdates	1.3.6.1.4.1.9.9.628.1.2.1.10
subscribersCountersClearTime	1.3.6.1.4.1.5655.4.1.8.1.1.13	Not mapped	

Table A-13 subscribersGrp (1.3.6.1.4.1.5655.4.1.8): all mapped objects mapped to CISCO-SERVICE-CONTROL-SUBSCRIBERS-MIB (continued)

pcube Object Name	OID	New Object Name	OID
subscribersNumTpIpRange Mappings	1.3.6.1.4.1.5655.4.1.8.1.1.14	cServiceControlSubscribersNumTpIpRangeMappings	1.3.6.1.4.1.9.9.628.1.2.1.11
subscribersNumTpIpRange MappingsFree	1.3.6.1.4.1.5655.4.1.8.1.1.15	cServiceControlSubscribersNumTpIpRange MappingsFree	1.3.6.1.4.1.9.9.628.1.2.1.12
subscribersNumAnonymous	1.3.6.1.4.1.5655.4.1.8.1.1.16	cServiceControlSubscribersNumAnonymous	1.3.6.1.4.1.9.9.628.1.2.1.13
subscribersNumWithSessions	1.3.6.1.4.1.5655.4.1.8.1.1.17	cServiceControlSubscribersNumWithSessions	1.3.6.1.4.1.9.9.628.1.2.1.14
subscribersPropertiesTable	1.3.6.1.4.1.5655.4.1.8.2	Not mapped.	
subscribersPropertiesEntry	1.3.6.1.4.1.5655.4.1.8.2.1	Not mapped.	
spIndex	1.3.6.1.4.1.5655.4.1.8.2.1.1	Not mapped.	
spName	1.3.6.1.4.1.5655.4.1.8.2.1.2	Not mapped.	
spType	1.3.6.1.4.1.5655.4.1.8.2.1.3	Not mapped.	
subscribersPropertiesValueTable	1.3.6.1.4.1.5655.4.1.8.3	Not mapped.	
subscribersPropertiesValueEntry	1.3.6.1.4.1.5655.4.1.8.3.1	Not mapped.	
spvIndex	1.3.6.1.4.1.5655.4.1.8.3.1.1	Not mapped.	
spvSubName	1.3.6.1.4.1.5655.4.1.8.3.1.2	Not mapped.	
spvPropertyName	1.3.6.1.4.1.5655.4.1.8.3.1.3	Not mapped.	
spvRowStatus	1.3.6.1.4.1.5655.4.1.8.3.1.4	Not mapped.	
spvPropertyStringValue	1.3.6.1.4.1.5655.4.1.8.3.1.5	Not mapped.	
spvPropertyUintValue	1.3.6.1.4.1.5655.4.1.8.3.1.6	Not mapped.	
spvPropertyCounter64Value	1.3.6.1.4.1.5655.4.1.8.3.1.7	Not mapped.	
New MIB Objects			
		cServiceControlSubscriberMappingFailedReason	1.3.6.1.4.1.9.9.628.1.2.1.15
		cServiceControlSubscribersMaxSupported	1.3.6.1.4.1.9.9.628.1.2.1.16
		cServiceControlSubscribersRowStatus	1.3.6.1.4.1.9.9.628.1.1.1.4
		cServiceControlSubscribersPackageIndex	1.3.6.1.4.1.9.9.628.1.1.1.5
		cServiceControlSubscribersRealTimeMonitor	1.3.6.1.4.1.9.9.628.1.1.1.6

Table A-14 trafficProcessorGrp (1.3.6.1.4.1.5655.4.1.9)

pcube Object Name	OID	New MIB	New Object Name	OID
tpInfoTable	1.3.6.1.4.1.5655.4.1.9.1	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpTable	1.3.6.1.4.1.9.9.634.1.1
tpInfoEntry	1.3.6.1.4.1.5655.4.1.9.1.1	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpEntry	1.3.6.1.4.1.9.9.634.1.1.1
tpModuleIndex	1.3.6.1.4.1.5655.4.1.9.1.1.1	CISCO-SERVICE-CONTROL-TP-STATS-MIB	entPhysicalIndex	1.3.6.1.2.1.47.1.1.1.1.1
tpIndex	1.3.6.1.4.1.5655.4.1.9.1.1.2	CISCO-SERVICE-CONTROL-TP-STATS-MIB	entPhysicalIndex	1.3.6.1.2.1.47.1.1.1.1.1
tpTotalNumHandledPackets	1.3.6.1.4.1.5655.4.1.9.1.1.3	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpTotalHandledPackets	1.3.6.1.4.1.9.9.634.1.1.1.1
tpTotalNumHandledFlows	1.3.6.1.4.1.5655.4.1.9.1.1.4	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpTotalHandledFlows	1.3.6.1.4.1.9.9.634.1.1.1.2
tpNumActiveFlows	1.3.6.1.4.1.5655.4.1.9.1.1.5	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpActiveFlows	1.3.6.1.4.1.9.9.634.1.1.1.3
tpNumActiveFlowsPeak	1.3.6.1.4.1.5655.4.1.9.1.1.6		Not mapped.	
tpNumActiveFlowsPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.7		Not mapped.	
tpNumTcpActiveFlows	1.3.6.1.4.1.5655.4.1.9.1.1.8	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpTcpActiveFlows	1.3.6.1.4.1.9.9.634.1.1.1.4
TpNumTcpActiveFlowsPeak	1.3.6.1.4.1.5655.4.1.9.1.1.9		Not mapped.	
tpNumTcpActiveFlowsPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.10		Not mapped.	
tpNumUdpActiveFlows	1.3.6.1.4.1.5655.4.1.9.1.1.11	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpUdpActiveFlows	1.3.6.1.4.1.9.9.634.1.1.1.5
tpNumUdpActiveFlowsPeak	1.3.6.1.4.1.5655.4.1.9.1.1.12		Not mapped.	
tpNumUdpActiveFlowsPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.13		Not mapped.	
tpNumNonTcpUdpActiveFlows	1.3.6.1.4.1.5655.4.1.9.1.1.14	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpUdpActiveFlows	1.3.6.1.4.1.9.9.634.1.1.1.5
tpNumNonTcpUdpActiveFlowsPeak	1.3.6.1.4.1.5655.4.1.9.1.1.15		Not mapped.	

Table A-14 trafficProcessorGrp (1.3.6.1.4.1.5655.4.1.9) (continued)

pcube Object Name	OID	New MIB	New Object Name	OID
tpNumNonTcpUdp ActiveFlowsPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.16		Not mapped.	
tpTotalNum BlockedPackets	1.3.6.1.4.1.5655.4.1.9.1.1.17	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalBlockedPackets	1.3.6.1.4.1.9.9.634.1.1.1.6
tpTotalNum BlockedFlows	1.3.6.1.4.1.5655.4.1.9.1.1.18	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalBlockedFlows	1.3.6.1.4.1.9.9.634.1.1.1.7
tpTotalNumDiscarded PacketsDueToBwLimit	1.3.6.1.4.1.5655.4.1.9.1.1.19	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalBandwidth DiscardedPackets	1.3.6.1.4.1.9.9.634.1.1.1.8
tpTotalNumWred DiscardedPackets	1.3.6.1.4.1.5655.4.1.9.1.1.20	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalWred DiscardedPackets	1.3.6.1.4.1.9.9.634.1.1.1.9
tpTotalNumFragments	1.3.6.1.4.1.5655.4.1.9.1.1.21	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalFragments	1.3.6.1.4.1.9.9.634.1.1.1.10
tpTotalNum NonIpPackets	1.3.6.1.4.1.5655.4.1.9.1.1.22	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalNonIpPackets	1.3.6.1.4.1.9.9.634.1.1.1.11
tpTotalNumIp CrcErrPackets	1.3.6.1.4.1.5655.4.1.9.1.1.23	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalIpChecksum ErrPackets	1.3.6.1.4.1.9.9.634.1.1.1.12
tpTotalNumIpLength ErrPackets	1.3.6.1.4.1.5655.4.1.9.1.1.24	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalIpLengt ErrPackets	1.3.6.1.4.1.9.9.634.1.1.1.13
tpTotalNumIp BroadcastPackets	1.3.6.1.4.1.5655.4.1.9.1.1.25	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalIp BroadcastPackets	1.3.6.1.4.1.9.9.634.1.1.1.14
tpTotalNum TtlErrPackets	1.3.6.1.4.1.5655.4.1.9.1.1.26	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalTTLErrPackets	1.3.6.1.4.1.9.9.634.1.1.1.15
tpTotalNumTcpUdp CrcErrPackets	1.3.6.1.4.1.5655.4.1.9.1.1.27	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpTotalTcpUdp ChksumErrPackets	1.3.6.1.4.1.9.9.634.1.1.1.16
tpClearCountersTimed	1.3.6.1.4.1.5655.4.1.9.1.1.28		Not mapped.	
tpHandledPacketsRate	1.3.6.1.4.1.5655.4.1.9.1.1.29	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpHandledPacketsRate	1.3.6.1.4.1.9.9.634.1.1.1.17
tpHandledPackets RatePeak	1.3.6.1.4.1.5655.4.1.9.1.1.30		Not mapped.	
tpHandledPackets RatePeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.31		Not mapped.	
tpHandledFlowsRate	1.3.6.1.4.1.5655.4.1.9.1.1.32	CISCO-SERVICE-CONTROL- TP-STATS-MIB	cscTpHandledFlowsRate	1.3.6.1.4.1.9.9.634.1.1.1.18

Table A-14 *trafficProcessorGrp (1.3.6.1.4.1.5655.4.1.9) (continued)*

pcube Object Name	OID	New MIB	New Object Name	OID
tpHandledFlowsRatePeak	1.3.6.1.4.1.5655.4.1.9.1.1.33		Not mapped	
tpHandledFlowsRatePeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.34		Not mapped	
tpCpuUtilization	1.3.6.1.4.1.5655.4.1.9.1.1.35	CISCO-PROCESS-MIB	cpmCPUTotal1minRev cpmCPUTotal5minRev	1.3.6.1.4.1.9.9.109.1.1.1.1.7 1.3.6.1.4.1.9.9.109.1.1.1.1.8
tpCpuUtilizationPeak	1.3.6.1.4.1.5655.4.1.9.1.1.36		Not mapped	
tpCpuUtilizationPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.37		Not mapped	
tpFlowsCapacityUtilization	1.3.6.1.4.1.5655.4.1.9.1.1.38	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpFlowsCapacityUtilization	1.3.6.1.4.1.9.9.634.1.1.1.19
tpFlowsCapacityUtilizationPeak	1.3.6.1.4.1.5655.4.1.9.1.1.39		Not mapped	
tpFlowsCapacityUtilizationPeakTime	1.3.6.1.4.1.5655.4.1.9.1.1.40		Not mapped	
tpServiceLoss	1.3.6.1.4.1.5655.4.1.9.1.1.41	CISCO-SERVICE-CONTROL-TP-STATS-MIB	cscTpServiceLoss	1.3.6.1.4.1.9.9.634.1.1.1.20

Table A-15 *pportGrp (1.3.6.1.4.1.5655.4.1.10)*

pcube Object Name	OID	New MIB	New Object Name	OID
pportTable	1.3.6.1.4.1.5655.4.1.10.1	Not mapped	Information provided by ENTITY-MIB	
pportEntry	1.3.6.1.4.1.5655.4.1.10.1.1	Not mapped	Information provided by ENTITY-MIB	
pportModuleIndex	1.3.6.1.4.1.5655.4.1.10.1.1.1	ENTITY-MIB	entPhysicalContainedIn	1.3.6.1.2.1.47.1.1.1.1.4
pportIndex	1.3.6.1.4.1.5655.4.1.10.1.1.2	ENTITY-MIB	Each port is uniquely defined. Index is implied by entPhysicalIndex or ifIndex	1.3.6.1.2.1.47.1.1.1.1.1
pportType	1.3.6.1.4.1.5655.4.1.10.1.1.3	RFC1213-MIB	ifType and cevPort Also entPhysicalVendorType can be queried for this value.	1.3.6.1.2.1.2.2.1.3
pportNumTxQueues	1.3.6.1.4.1.5655.4.1.10.1.1.4		Not mapped Information provided by CISCO-QUEUE-MIB cQIfSubqueues	

Table A-15 *pportGrp (1.3.6.1.4.1.5655.4.1.10) (continued)*

pcube Object Name	OID	New MIB	New Object Name	OID
pportIfIndex	1.3.6.1.4.1.5655.4.1.10.1.1.5		Not mapped ifIndex mapping information provided by entAliasMappingTable.	
pportAdminSpeed	1.3.6.1.4.1.5655.4.1.10.1.1.6		Not mapped	
pportAdminDuplex	1.3.6.1.4.1.5655.4.1.10.1.1.7		Not mapped	
pportOperDuplex	1.3.6.1.4.1.5655.4.1.10.1.1.8		Not mapped	
pportLinkIndex	1.3.6.1.4.1.5655.4.1.10.1.1.9	ENTITY-MIB	entPhysicalIndex Available from ENTITY-MIB container/contained relationship: Chassis contains Slot contains Link contains Port	1.3.6.1.2.1.47.1.1.1.1.1
pportOperStatus	1.3.6.1.4.1.5655.4.1.10.1.1.10	ENTITY-MIB	entPhysicalIndex Defined in ENTITY-STATE-MIB.	1.3.6.1.2.1.47.1.1.1.1.1

Table A-16 *txQueuesGrp (1.3.6.1.4.1.5655.4.1.11)*

pcube Object Name	OID	New MIB	New Object Name	OID
txQueuesTable	1.3.6.1.4.1.5655.4.1.11.1	CISCO-QUEUE-MIB	cQIfTable and cQStatsTable	1.3.6.1.4.1.9.9.37.1.2
txQueuesEntry	1.3.6.1.4.1.5655.4.1.11.1.1	CISCO-QUEUE-MIB	cQStatsEntry	1.3.6.1.4.1.9.9.37.1.2.1
txQueuesModuleIndex	1.3.6.1.4.1.5655.4.1.11.1.1.1		Not mapped	
txQueuesPortIndex	1.3.6.1.4.1.5655.4.1.11.1.1.2	RFC1213-MIB	ifIndex The entry is indexed by ifIndex of IF-MIB	1.3.6.1.2.1.2.2.1.1
txQueuesQueueIndex	1.3.6.1.4.1.5655.4.1.11.1.1.3	CISCO-QUEUE-MIB	cQStatsQNumber	1.3.6.1.4.1.9.9.37.1.2.1.1
txQueuesDescription	1.3.6.1.4.1.5655.4.1.11.1.1.4	CISCO-QUEUE-MIB	cQIfTable.cQifQType	1.3.6.1.4.1.9.9.37.1.1.1.1
txQueuesBandwidth	1.3.6.1.4.1.5655.4.1.11.1.1.5	CISCO-QUEUE-MIB	cQStatsBandwidth	1.3.6.1.4.1.9.9.37.1.2.1.5
txQueuesUtilization	1.3.6.1.4.1.5655.4.1.11.1.1.6		Not mapped	
txQueuesUtilizationPeak	1.3.6.1.4.1.5655.4.1.11.1.1.7		Not mapped	
txQueuesUtilizationPeak Time	1.3.6.1.4.1.5655.4.1.11.1.1.8		Not mapped	

Table A-16 *txQueuesGrp (1.3.6.1.4.1.5655.4.1.11) (continued)*

pcube Object Name	OID	New MIB	New Object Name	OID
txQueuesClearCountersTime	1.3.6.1.4.1.5655.4.1.11.1.9		Not mapped	
txQueuesDroppedBytes	1.3.6.1.4.1.5655.4.1.11.1.10	CISCO-QUEUE-MIB	cQStatsDiscards This object counts bytes	1.3.6.1.4.1.9.9.37.1.2.1.4

Table A-17 *globalControllersGrp (1.3.6.1.4.1.5655.4.1.12): all mapped objects mapped to CISCO-SERVICE-CONTROLLER-MIB*

pcube Object Name	OID	New Object Name	OID
globalControllersTable	1.3.6.1.4.1.5655.4.1.12.1	cscGlobalControllersTable	1.3.6.1.4.1.9.9.667.0.1
globalControllersEntry	1.3.6.1.4.1.5655.4.1.12.1.1	cscGlobalControllersEntry	1.3.6.1.4.1.9.9.667.0.1.1
globalControllersModuleIndex	1.3.6.1.4.1.5655.4.1.12.1.1.1	Not mapped Provided by entPhysicalIndex	
globalControllersPortIndex	1.3.6.1.4.1.5655.4.1.12.1.1.2	Not mapped Provided by entityPhyIndex	
globalControllersIndex	1.3.6.1.4.1.5655.4.1.12.1.1.3	cscGlobalControllersId	1.3.6.1.4.1.9.9.667.0.1.1.2
globalControllersDescription	1.3.6.1.4.1.5655.4.1.12.1.1.4	cscGlobalControllersDescription	1.3.6.1.4.1.9.9.667.0.1.1.3
globalControllersBandwidth	1.3.6.1.4.1.5655.4.1.12.1.1.5	cscGlobalControllersBandwidth	1.3.6.1.4.1.9.9.667.0.1.1.5
globalControllersUtilization	1.3.6.1.4.1.5655.4.1.12.1.1.6	cscGlobalControllersUtilization	1.3.6.1.4.1.9.9.667.0.1.1.6
globalControllersUtilizationPeak	1.3.6.1.4.1.5655.4.1.12.1.1.7	Not mapped	
globalControllersUtilizationPeakTime	1.3.6.1.4.1.5655.4.1.12.1.1.8	Not mapped	
globalControllersClearCountersTime	1.3.6.1.4.1.5655.4.1.12.1.1.9	Not mapped	
globalControllersDroppedBytes	1.3.6.1.4.1.5655.4.1.12.1.1.10	Not mapped	

Table A-18 *trafficCountersGrp (1.3.6.1.4.1.5655.4.1.14): all objects mapped to CISCO-SERVICE-CONTROL-TP-STATS-MIB*

pcube Object Name	OID	New Object Name	OID
trafficCountersTable	1.3.6.1.4.1.5655.4.1.14.1	cscTpStatsTrafficCountersTable	1.3.6.1.4.1.9.9.634.1.2
trafficCountersEntry	1.3.6.1.4.1.5655.4.1.14.1.1	cscTpStatsTrafficCountersEntry	1.3.6.1.4.1.9.9.634.1.2.1
trafficCounterIndex	1.3.6.1.4.1.5655.4.1.14.1.1.1	cscTpStatsTrafficCounterIndex	1.3.6.1.4.1.9.9.634.1.2.1.1
trafficCounterValue	1.3.6.1.4.1.5655.4.1.14.1.1.2	cscTpStatsTrafficCounterValue	1.3.6.1.4.1.9.9.634.1.2.1.2
trafficCounterName	1.3.6.1.4.1.5655.4.1.14.1.1.3	cscTpStatsTrafficCounterName	1.3.6.1.4.1.9.9.634.1.2.1.3
trafficCounterType	1.3.6.1.4.1.5655.4.1.14.1.1.4	cscTpStatsTrafficCounterType	1.3.6.1.4.1.9.9.634.1.2.1.4

Table A-19 *attackGrp (1.3.6.1.4.1.5655.4.1.15): all objects mapped to CISCO-SERVICE-CONTROL-ATTACK-MIB*

pcube Object Name	OID	New Object Name	OID
attackTypeTable	1.3.6.1.4.1.5655.4.1.15.1	cscaTypeTable	1.3.6.1.4.1.9.9.693.1.2
attackTypeEntry	1.3.6.1.4.1.5655.4.1.15.1.1	cscaTypeEntry	1.3.6.1.4.1.9.9.693.1.2.1
attackTypeIndex	1.3.6.1.4.1.5655.4.1.15.1.1.1	cscaTypeIndex	1.3.6.1.4.1.9.9.693.1.2.1.1
attackTypeName	1.3.6.1.4.1.5655.4.1.15.1.1.2	not mapped	
attackTypeCurrentNumAttacks	1.3.6.1.4.1.5655.4.1.15.1.1.3	cscaTypeCurrentNumAttacks	1.3.6.1.4.1.9.9.693.1.2.1.2
attackTypeTotalNumAttacks	1.3.6.1.4.1.5655.4.1.15.1.1.4	cscaTypeTotalNumAttacks	1.3.6.1.4.1.9.9.693.1.2.1.3
attackTypeTotalNumFlows	1.3.6.1.4.1.5655.4.1.15.1.1.5	cscaTypeTotalNumFlows	1.3.6.1.4.1.9.9.693.1.2.1.4
attackTypeTotalNumSeconds	1.3.6.1.4.1.5655.4.1.15.1.1.6	cscaTypeTotalNumSeconds	1.3.6.1.4.1.9.9.693.1.2.1.5

New Objects at this MIB - Used For TRAPS

		cscaType	1.3.6.1.4.1.9.9.693.1.1.1
		cscaSourceAddressType	1.3.6.1.4.1.9.9.693.1.1.2
		cscaSourceAddress	1.3.6.1.4.1.9.9.693.1.1.3
		cscaDestinationAddressType	1.3.6.1.4.1.9.9.693.1.1.4
		cscaDestinationAddress	1.3.6.1.4.1.9.9.693.1.1.5
		cscaDestinationPort	1.3.6.1.4.1.9.9.693.1.1.6
		cscaFilterStatus	1.3.6.1.4.1.9.9.693.1.1.7

Table A-20 PCUBE SeEvents (1.3.6.1.4.1.5655.4.0)

pcube Object Name	OID	New MIB	New Object Name	OID
operationalStatus OperationalTrap	1.3.6.1.4.1.5655.4.0.1	CISCO-ENTITY-FRU-CONTROL-MIB	cefcModuleOperStatus = oper_ok	1.3.6.1.4.1.9.9.117.2.0.1
operationalStatus WarningTrap	1.3.6.1.4.1.5655.4.0.2	CISCO-ENTITY-FRU-CONTROL-MIB	cefcModuleOperStatus = ok_but_diag_failed	1.3.6.1.4.1.9.9.117.2.0.1
operationalStatusFailure Trap	1.3.6.1.4.1.5655.4.0.3	CISCO-ENTITY-FRU-CONTROL-MIB	cefcModuleOperStatus = failed	1.3.6.1.4.1.9.9.117.2.0.1
systemResetTrap	1.3.6.1.4.1.5655.4.0.4	CISCO-ENTITY-FRU-CONTROL-MIB	cefcPowerStatusChange cefcFRUPowerOperStatus =off_env_other(1) cefcFRUPowerAdminStatus =power_on(1)	1.3.6.1.4.1.9.9.117.2.0.2
chassisTempAlarmOn Trap	1.3.6.1.4.1.5655.4.0.5	CISCO-ENTITY-SENSOR-MIB	entSensorThresholdNotification entSensorThresholdValue =1 entSensorValue =1	1.3.6.1.4.1.9.9.91.2.0.1
chassisTempAlarmOff Trap	1.3.6.1.4.1.5655.4.0.6	CISCO-ENTITY-SENSOR-MIB	entSensorThresholdNotification entSensorThresholdValue =0 entSensorValue =0	1.3.6.1.4.1.9.9.91.2.0.1
chassisVoltageAlarmOn Trap	1.3.6.1.4.1.5655.4.0.7	CISCO-ENTITY-SENSOR-MIB	entSensorThresholdNotification entSensorThresholdValue =1 entSensorValue =1	1.3.6.1.4.1.9.9.91.2.0.1
chassisFansAlarmOn Trap	1.3.6.1.4.1.5655.4.0.8	CISCO-ENTITY-FRU-CONTROL-MIB	cefcFanTrayStatusChange	1.3.6.1.4.1.9.9.117.2.0.6
chassisPowerSupply AlarmOnTrap	1.3.6.1.4.1.5655.4.0.9	CISCO-ENTITY-FRU-CONTROL-MIB	cefcPowerSupplyOutputChange Trap functions as follows: <ul style="list-style-type: none"> • Unplug power cord from SCE platform— trap sent • Plug power cord into SCE platform—trap not sent • Remove a PSU—trap not sent • Insert a PSU— trap sent 	1.3.6.1.4.1.9.9.117.2.0.7
rdrActiveConnection Trap	1.3.6.1.4.1.5655.4.0.10	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrActiveConnectionTrap	1.3.6.1.4.1.9.9.637.0.5

Table A-20 PCUBE SeEvents (1.3.6.1.4.1.5655.4.0) (continued)

pcube Object Name	OID	New MIB	New Object Name	OID
rdrNoActiveConnection Trap	1.3.6.1.4.1.5655.4.0.11	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrNoActiveConnection Trap	1.3.6.1.4.1.9.9.637.0.3
rdrConnectionUpTrap	1.3.6.1.4.1.5655.4.0.12	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrConnectionStatus UpTrap	1.3.6.1.4.1.9.9.637.0.6
rdrConnectionDown Trap	1.3.6.1.4.1.5655.4.0.13	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrConnectionStatusDownTrap	1.3.6.1.4.1.9.9.637.0.4
telnetSessionStartedTrap	1.3.6.1.4.1.5655.4.0.14	CISCO-TELNET-SERVER-MIB	ctsSessionStarted	1.3.6.1.4.1.9.9.630.0.2
telnetSessionEndedTrap	1.3.6.1.4.1.5655.4.0.15	CISCO-TELNET-SERVER-MIB	ctsSessionEnded	1.3.6.1.4.1.9.9.630.0.1
telnetSessionDenied AccessTrap	1.3.6.1.4.1.5655.4.0.16	CISCO-TELNET-SERVER-MIB	ctsSessionDenied	1.3.6.1.4.1.9.9.630.0.3
telnetSessionBadLogin Trap	1.3.6.1.4.1.5655.4.0.17	CISCO-TELNET-SERVER-MIB	ctsSessionLoginFailure	1.3.6.1.4.1.9.9.630.0.4
loggerUserLogIsFull Trap	1.3.6.1.4.1.5655.4.0.18	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2
sntpClockDriftWarnTrap	1.3.6.1.4.1.5655.4.0.19	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2
linkModeBypassTrap	1.3.6.1.4.1.5655.4.0.20	CISCO-SERVICE-CONTROL-LINK-MIB	cServiceControlLinkModeChangeTrap	1.3.6.1.4.1.9.9.631.0.1
linkModeForwarding Trap	1.3.6.1.4.1.5655.4.0.21	CISCO-SERVICE-CONTROL-LINK-MIB	cServiceControlLinkModeChangeTrap	1.3.6.1.4.1.9.9.631.0.1
linkModeCutoffTrap	1.3.6.1.4.1.5655.4.0.22	CISCO-SERVICE-CONTROL-LINK-MIB	cServiceControlLinkModeChangeTrap	1.3.6.1.4.1.9.9.631.0.1
moduleAttackFilter ActivatedTrap	1.3.6.1.4.1.5655.4.0.25	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaFilterChange	1.3.6.1.4.1.9.9.693.0.1
moduleAttackFilter DeactivatedTrap	1.3.6.1.4.1.5655.4.0.26	CISCO-SERVICE-CONTROL-ATTACK-MIB	cscaFilterChange	1.3.6.1.4.1.9.9.693.0.1
moduleEmAgentGeneric Trap	1.3.6.1.4.1.5655.4.0.27		Not mapped	
linkModeSniffingTrap	1.3.6.1.4.1.5655.4.0.28	CISCO-SERVICE-CONTROL-LINK-MIB	cServiceControlLinkModeChangeTrap	1.3.6.1.4.1.9.9.631.0.1

Table A-20 PCUBE SeEvents (1.3.6.1.4.1.5655.4.0) (continued)

pcube Object Name	OID	New MIB	New Object Name	OID
moduleRedundancy ReadyTrap	1.3.6.1.4.1.5655.4.0.29	CISCO-ENTITY-REDUNDANCY-MIB	ceRedunProtectStatusChange ceRedunMbrStatusCurrent=protection_provided(0x10)	1.3.6.1.4.1.9.9.498.0.2
moduleRedundant ConfigurationMismatch Trap	1.3.6.1.4.1.5655.4.0.30	CISCO-ENTITY-REDUNDANCY-MIB	ceRedunProtectStatusChange ceRedunMbrStatusCurrent=failure(0x40)	1.3.6.1.4.1.9.9.498.0.2
moduleLostRedundancy Trap	1.3.6.1.4.1.5655.4.0.31	CISCO-ENTITY-REDUNDANCY-MIB	ceRedunProtectStatusChange ceRedunMbrStatusCurrent=protection_lock_out(0x0)	1.3.6.1.4.1.9.9.498.0.2
moduleSmConnection DownTrap	1.3.6.1.4.1.5655.4.0.32	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2
moduleSmConnection UpTrap	1.3.6.1.4.1.5655.4.0.33	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2
moduleOperStatus ChangeTrap	1.3.6.1.4.1.5655.4.0.34	CISCO-ENTITY-FRU-CONTROL-MIB	Not mapped	1.3.6.1.4.1.9.9.117.2.0.1
portOperStatusChange Trap	1.3.6.1.4.1.5655.4.0.35	CISCO-ENTITY-FRU-CONTROL-MIB	entStateOperEnabled or entStateOperDisabled	1.3.6.1.4.1.9.9.117.2.0.1
chassisLineFeedAlarm OnTrap	1.3.6.1.4.1.5655.4.0.36	CISCO-ENTITY-FRU-CONTROL-MIB	cefcPowerStatusChange cefcFRUPowerOperStatus =off_env_power(5) cefcFRUPowerAdminStatus =power_on(1)	1.3.6.1.4.1.9.9.117.2.0.2
rdrFormatterCategory DiscardingReportsTrap	1.3.6.1.4.1.5655.4.0.37	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrCategoryDiscarding ReportsTrap	1.3.6.1.4.1.9.9.637.0.2
rdrFormatterCategory StoppedDiscarding ReportsTrap	1.3.6.1.4.1.5655.4.0.38	CISCO-SERVICE-CONTROL-RDR-MIB	cServiceControlRdrCategoryStopped DiscardingReportsTrap	1.3.6.1.4.1.9.9.637.0.1
sessionStartedTrap	1.3.6.1.4.1.5655.4.0.39	CISCO-SECURE-SHELL-MIB	cssSessionStartedTrap	1.3.6.1.4.1.9.9.339.0.3
sessionEndedTrap	1.3.6.1.4.1.5655.4.0.40	CISCO-SECURE-SHELL-MIB	cssSessionEndedTrap	1.3.6.1.4.1.9.9.339.0.1
sessionDeniedAccess Trap	1.3.6.1.4.1.5655.4.0.41	CISCO-SECURE-SHELL-MIB	cssSessionDeniedTrap	1.3.6.1.4.1.9.9.339.0.2

Table A-20 *PCUBE SeEvents (1.3.6.1.4.1.5655.4.0) (continued)*

pcube Object Name	OID	New MIB	New Object Name	OID
sessionBadLoginTrap	1.3.6.1.4.1.5655.4.0.42	CISCO-SECURE-SHELL-MIB	cssSessionDeniedTrap cssSessionDeniedReason	1.3.6.1.4.1.9.9.339.0.2 1.3.6.1.4.1.9.9.339.1.3.2.1.4
illegalSubscriberMappingTrap	1.3.6.1.4.1.5655.4.0.43	CISCO-SERVICE-CONTROL-SUBSCRIBER-MIB	cServiceControlSubscriberMappingTrap	1.3.6.1.4.1.9.9.628.0.1
loggerLineAttackLogFullTrap	1.3.6.1.4.1.5655.4.0.44	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2
pullRequestNumber	1.3.6.1.4.1.5655.4.0.46		Not mapped	
pullRequestRetryFailedTrap	1.3.6.1.4.1.5655.4.0.47	Not mapped	For SM connection issues the following notification can be used: ceAlarmAsserted ceAlarmCleared	For SM connection issues the following OIDs can be used: 1.3.6.1.4.1.9.9.138.2.0.1 1.3.6.1.4.1.9.9.138.2.0.2
mplsVpnTotalHWMappingsThresholdExceededTrap	1.3.6.1.4.1.5655.4.0.48	CISCO-ENTITY-ALARM-MIB	ceAlarmAsserted/ ceAlarmCleared	1.3.6.1.4.1.9.9.138.2.0.1/ 1.3.6.1.4.1.9.9.138.2.0.2



Note applicationGrp (1.3.6.1.4.1.5655.4.1.13) is not mapped to a current MIB.

Table A-21 *pcubeEnageMIB 1.3.6.1.4.1.5655.4.2*

pcube Object Name	OID	Corresponding RDR	Objects not mapped	OID
linkGrp	1.3.6.1.4.1.5655.4.2.2	Link Usage RDRs or the RPT_LUR DB table	linkServiceUpDroppedPackets linkServiceDownDroppedPackets linkServiceUpDroppedBytes	1.3.6.1.4.1.5655.4.2.2
packageGrp	1.3.6.1.4.1.5655.4.2.3	Package Usage RDRs or the RPT_PUR DB table	packageServiceUpDroppedPackets packageServiceDownDroppedPackets packageServiceUpDroppedBytes	1.3.6.1.4.1.5655.4.2.3
subscriberGrp	1.3.6.1.4.1.5655.4.2.4	Subscriber Usage RDRs	none	1.3.6.1.4.1.5655.4.2.4
serviceCounterGrp	1.3.6.1.4.1.5655.4.2.5	Service Configuration API or the INI_VALUES DB table	none	1.3.6.1.4.1.5655.4.2.5

SCE Platform-Specific MIB Information

This section contains definitions that are specific to the SCE platforms for certain standard and Cisco MIB objects.

CISCO-ENTITY-ALARM-MIB

ceAlarmDescrSeverity (integer)

ceAlarmDescrSeverity.1.1—3

ceAlarmDescrSeverity.1.2—3

ceAlarmDescrSeverity.1.3—2

ceAlarmDescrSeverity.1.4—4

ceAlarmDescrSeverity.1.5—3

ceAlarmDescrSeverity.1.6—3

ceAlarmDescrSeverity.1.7—3

ceAlarmDescrText (octet string)

ceAlarmDescrText.1.1—Logger user log is full

ceAlarmDescrText.1.2—Sntp clock drift warn

ceAlarmDescrText.1.3—Module sm connection down

ceAlarmDescrText.1.4—Module sm connection up

ceAlarmDescrText.1.5—Logger line attack log full

ceAlarmDescrText.1.6—External bypass device isn't connected

ceAlarmDescrText.1.7—External bypass device is connected

MIB Updates

The definitions of the following MIB objects have been updated, but the updated definitions may not yet appear in the online MIB.

CISCO-SERVICE-CONTROL-TP-STATS-MIB

cscTpServiceLoss

The average service loss **per second in the last minute** (or since the last time the TP counters were cleared) in a traffic Processor, in units of 0.001%.

The service loss is computed as the relative amount of traffic which was bypassed by the SCE from one side to another without being serviced due to lack of resources (either CPU or memory).

In previous versions, it indicated the service loss **since last reboot** or last time the counters were cleared.