



Logging in and Managing the Cisco Nexus Data Broker

This chapter has details about logging in and managing the Cisco NDB and overview of the new GUI.

- [Configuring High Availability Clusters](#) , on page 1
- [Logging in to Cisco Nexus Data Broker GUI](#), on page 3
- [Changing Controller Access](#), on page 3
- [Cisco Nexus Data Broker GUI Overview](#), on page 4

Configuring High Availability Clusters

Cisco Nexus Data Broker supports high availability clustering in active/active mode with up to five controllers. To use high availability clustering with Cisco Nexus Data Broker, you must edit the `config.ini` file for each instance of Cisco Nexus Data Broker.



Note IPv6 is supported in centralized NDB mode only, it is not supported in Embedded mode.



Note Cisco NDB supports only 2 node configuration or odd number node configuration. If you configure even number of nodes, the last node is not included in the cluster formation, ensuring odd number of nodes in a setup.

Table 1: Cluster Operation Status

| Cluster Indicator | Cluster Status | Recommendation |
|-------------------|---|---|
| Green | Operational | |
| Yellow | Some of the cluster nodes are not available | Do not make any changes or add to the existing NDB configuration. |

| Cluster Indicator | Cluster Status | Recommendation |
|-------------------|--|---|
| Red | The node is isolated from the cluster. | Do not make any changes or add to the existing NDB configuration. Note: For two node cluster, you need to override in any one of the cluster node only, to ensure regular operation. |

Before you begin

- All IP addresses must be reachable and capable of communicating with each other.
- All switches in the cluster must connect to all of the controllers.
- All controllers must have the same HA clustering configuration information in the `config.ini` files.
- All controllers must have the same information in the `xnc/configuration/startup` directory.
- If using cluster passwords, all controllers must have the same password configured in the `xncjgroups.xml` file.

Step 1 Open a command window on one of the instances in the cluster.

Step 2 Navigate to the `xnc/configuration` directory that was created when you installed the software.

Step 3 Use any text editor to open the `config.ini` file.

Step 4 Locate the following text:

```
# HA Clustering configuration (semi-colon-separated IP addresses of all controllers that are part of
the cluster.)
# supernodes=<ip1>;<ip2>;<ip3>;<ipn>
```

Step 5 **Example:**

IPv4 example.

```
# HA Clustering configuration (semi-colon-separated IP addresses of all controllers that are part of
the cluster.)
supernodes=10.1.1.1;10.2.1.1;10.3.1.1;10.4.1.1;10.5.1.1
```

Example:

IPv6 example.

```
# HA Clustering configuration (semi-colon-separated IP addresses of all controllers that are part of
the cluster.)
supernodes=2001:22:11::1;2001:33::44::1;2001:55:66::1
```

Step 6 Save the file and exit the editor.

Password Protecting High Availability Clusters

Step 1 Open a command window on one of the instances in the cluster.

Step 2 Navigate to the `xnc/configuration` directory.

Step 3 Use any text editor to open the `xncjgroups.xml` file.

Step 4 Locate the following text:

```
<!-- <AUTH auth_class="org.jgroups.auth.MD5Token" auth_value="ciscoXNC" token_hash="MD5"></AUTH> -->
```

Step 5 Remove the comments from the AUTH line.

Example:

```
<AUTH auth_class="org.jgroups.auth.MD5Token" auth_value="ciscoXNC" token_hash="MD5"></AUTH>
```

Step 6 (Optional) Change the password in the `auth_value` attribute.

By default, the cluster is protected with the password "ciscoXNC". You can change this password to whatever value you want, you need make the similar changes on all machines in the cluster.

Step 7 Save the file and exit the editor.

Logging in to Cisco Nexus Data Broker GUI

You can login to the Cisco Nexus Data Broher GUI using HTTPS. The default HTTPS web link for the Cisco NDB GUI is `https://Nexus_Data_Broker_IP:8443/monitor`.



Note You must manually specify the `https://` protocol in your web browser. The controller must also be configured for HTTPS.

Step 1 In your web browser, enter the Cisco NDB web link.

Step 2 On the launch page, do the following:

- a) Enter your username and password.

The default username and password is `admin/admin`.

- b) Click **LOGIN**.

Changing Controller Access

An unencrypted (HTTP) access to the GUI and the API to the controller access is disabled by default. You cannot access the controller with the URL `http://<host>:8080`.

To change the controller access to HTTP, complete the following steps:

Before you begin

Cisco Nexus Data Broker is shipped with a certificate for the HTTPS connection between the Cisco Nexus Data Broker and a browser. You can change to a different certificate.

The script **generateWebUICertificate.sh** is available in the **ndb/configuration** folder. If you execute this script, it moves the shipped certificate to **old_keystore** and the new certificate is generated in **keystore**. On the next Cisco Nexus Data Broker restart, this new certificate is used.

Step 1 Remove the comment character from the connector for port 8080 in the `tomcat-server.xml` files in the configuration directory as displayed in the following example:

```
<Service name="Catalina">
<!--
<Connector port="8080" protocol="HTTP/1.1"
connectionTimeout="20000"
redirectPort="8443" server="Cisco NDB" enableLookups="false" />
-->
<Connector port="8443" protocol="HTTP/1.1" SSLEnabled="true"
scheme="https" secure="true"
clientAuth="false" sslProtocol="TLS"
keystoreFile="configuration/keystore"
keystorePass="ciscondb" server="Cisco NDB"
connectionTimeout="60000" enableLookups="false" />
```

Step 2 Restart the controller.

Cisco Nexus Data Broker GUI Overview

The Cisco Nexus Data Broker GUI contains the following tabs and each of these tabs are discussed in detail (as separate chapters) in the subsequent pages of this guide.

- [Dashboard](#)
- [Topology](#)
- [Devices](#)
- [Connections](#)
- [Components](#)
- [Sessions](#)
- [Statistics](#)
- [Troubleshooting](#)
- [Administration](#)

For details about the header icons, see [Header](#).

Components of a screen of the Cisco Nexus Data Broker

When you click a tab/ sub-tab, the current information of the tab is displayed in a table.

A typical screen representing one of the tabs of the Release 3.10 Cisco NDB GUI is displayed here:





The screenshot displays the Cisco Nexus Data Broker interface. At the top, the header includes the Cisco logo, the text 'Nexus Data Broker', and a 'Stand-alone Slice' dropdown menu set to 'default'. To the right of the header are several utility icons: a refresh icon (3), a column customization icon (4), and an 'Actions' button (5). The main content area is titled 'Filters' (1) and contains a table with the following columns: 'In Use', 'Default', 'Filter Name', 'Bidirectional', 'EtherType', 'Protocol', 'AdvancedFilter(s)', 'Created By', and 'Last Modified By'. Above the table is a 'Filter by attributes' bar (2). The table lists several filters, including 'Default-Match-all', 'Default-Match-ARP', 'Default-Match-ICMP', 'Default-Match-ICM...', and 'Default-Match-IP'. At the bottom left, there is a 'Rows' dropdown menu (6) set to 5. At the bottom right, there is a 'Page 1 of 7' indicator and navigation arrows.


- 1—Name of the tab/sub-tab.
- 2—Use the *Filter by attributes* bar to filter the displayed table which has the details of the selected tab. Choose the attribute, operator and filter-value.
You can also filter the displayed table based on the *filter* icon that appears when you hover over an element of the table.
- 3—Use the *Refresh* icon to refresh the displayed details and get the latest information about the tab/sub-tab.
- 4—Use the *Column Customization* icon to select the columns you want to see in the displayed table.
- 5—Click the **Actions** button to see the available actions for the screen.
- 6—From the **Rows** drop-down list, select the number of rows to be displayed in the table.

Header

This section provides an overview of the Cisco Nexus Data Broker GUI Header (upper right corner) icons:

Table 2: Cisco Nexus Data Broker Header Icons

| Icon | Description |
|---|--|
| Cluster | Displays the role of the current NDB controller instance—either Primary (P) or Member (M). The IP addresses of the primary and member(s) are displayed; the IP address of the primary cluster is denoted with an (*). If NDB controller is not in a cluster, <code>Stand-alone</code> is displayed. |
| Slice | Displays the slice name the user is currently logged in to. From the drop-down list, select another slice to change the network view. |
| Figure 1: Create  | Provides quick navigation to often-used configuration and administration procedures. |
| Figure 2: Alarm  | Displays the number of inconsistent NDB devices. Click the Alarm icon; you are directed to the Flow Management tab for details. |
| Figure 3: Help Menu-Bar  | Displays the following options: <ul style="list-style-type: none"> • What's New—Displays new features for the latest release. • Help—Displays online help content. |
| Figure 4: System Tools Menu-Bar  | Provides the following options: <ul style="list-style-type: none"> • Download Log—Enables you to download log files to your local machine. • Northbound API—takes you to the Swagger UI for details about NDB REST APIs. • Session Timeout—Enables you to set the session timeout value. • About Nexus Data Broker—Displays NDB details such as, build and version. |

| Icon | Description |
|---|---|
| <p data-bbox="386 289 665 317"><i>Figure 5: User Profile Menu-Bar</i></p>  | <p data-bbox="938 296 1273 323">Provides the following options:</p> <ul data-bbox="976 342 1523 537" style="list-style-type: none"><li data-bbox="976 342 1523 401">• Welcome <i>User</i>—Displays the current user of the GUI.<li data-bbox="976 426 1523 485">• Change Password—Enables you to change the password of the current user.<li data-bbox="976 510 1523 537">• Logout—Enables you to logout of the GUI. |

