

Cisco Nexus 9000 Series NX-OS Verified Scalability Guide, Release 10.1(2)

Introduction

This document describes the Cisco NX-OS configuration limits for Cisco Nexus 9000 Series switches.

The values provided in this guide should not be interpreted as theoretical system limits for Cisco Nexus 9000 Series hardware or Cisco NX-OS software. These limits refer to values that have been validated by Cisco. They can increase over time as more testing and validation is done.

Verified Scalability Limits - Unidimensional

The tables in this section list the verified scalability limits for the Cisco Nexus 9000 Series switches for Cisco NX-OS Release 10.1(2).

These limits are validated with a unidimensional configuration. The values are provided in these tables focus on the scalability of one particular feature at a time.

Each number is the absolute maximum that is currently supported by this Cisco NX-OS release for the corresponding feature. If the hardware is capable of a higher scale, future software releases could increase this verified maximum limit. Results might differ from the values that are listed in this guide when you try to achieve maximum scalability with multiple features enabled.



- Note**
1. If only one number is provided, the verified limit applies to all supported platforms and line cards.
 2. Verified limits are provided only for supported platforms.
 3. If a feature is not supported for a particular platform, the verified limit is not provided.

Table 1: Cisco Nexus 2000 Series Fabric Extenders (FEX) Straight Through Mode Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Fabric Extenders ¹ and Fabric Extender server interfaces	Nexus 9300-EX/FX/FX2/FX3 switches	16 and 768
VLANs across all Fabric Extenders	Nexus 9300-EX/FX/FX2/FX3 switches	562
VLANs per Fabric Extender server interface ²	Nexus 9300-EX/FX/FX2/FX3 switches	75
Port channels	Nexus 9300-EX/FX/FX2/FX3 switches + FEX	511

¹ When FEX configured using "AA" mode, then the maximum number of 6 FEX on the NFE base ToR and 16 FEX for the LSE base ToR are supported.

² For FEX HIF port channels, Cisco recommends that you enable STP port type edge using the **spanning tree port type edge [trunk]** command.

Table 2: ePBR Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Maximum services per switch	Nexus 9300 and 9500 switches	150 ³
Endpoints per service	Nexus 9300 and 9500 switches	32
ePBR policies per switch	Nexus 9300 and 9500 switches	150
Policies per VRF	Nexus 9300 and 9500 switches	16
Services per chain	Nexus 9300 and 9500 switches	6
Match per policy.	Nexus 9300 and 9500 switches	16
Aces per match	Nexus 9300 and 9500 switches	256

³ Only 62 unique ACLs can be configured per slice of ASIC. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62. In order to achieve 150 services per switch with the limitation of 62 ACLs per slice, the ingress interfaces should be spread across multiple slices of ASIC.



- Note**
1. For a list of platforms on which ePBR is supported, see the [Cisco Nexus 9000 Series NX-OS ePBR Configuration Guide](#).
 2. For the ACL limitations, see the [Cisco Nexus 9000 Series NX-OS Security Configuration Guide](#).

Table 3: FC and FCoE Switch Level Configuration Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
FLOGI per port	Nexus 93180YC-FX and 93360YC-FX2 switches	256
FLOGI per switch	Nexus 93180YC-FX and 93360YC-FX2 switches	1000
Port channels	Nexus 93180YC-FX and 93360YC-FX2 switches	8 ⁴
Maximum number of member ports in a port channel	Nexus 93180YC-FX and 93360YC-FX2 switches	16
NPV switches per NPIV core switch	Nexus 93180YC-FX and 93360YC-FX2 switches	8 ⁵
Maximum number of FC ports supported	Nexus 93180YC-FX switches	48
	Nexus 93360YC-FX2 switches	96
VFCs	Nexus 93180YC-FX and 93360YC-FX2 switches	512 ⁶
VSANs	Nexus 93180YC-FX and 93360YC-FX2 switches	32

- ⁴ The number of SAN port channels and virtual FC port channels, together, can be only 8 on the Cisco Nexus 9000 Series switch.
- ⁵ Tested with FC NPV.
- ⁶ This is applicable only for the NPV mode and tested in the Nexus 93180YC-FX switch.

Table 4: FC and FCoE Fabric Level Configuration Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Zones	Nexus 93180YC-FX and 93360YC-FX2 switches	8000
Zone members	Nexus 93180YC-FX and 93360YC-FX2 switches	16000
Zone sets	Nexus 93180YC-FX and 93360YC-FX2 switches	32
Zone database size	Nexus 93180YC-FX and 93360YC-FX2 switches	2 MB
FCNS entries in the fabric	Nexus 93180YC-FX and 93360YC-FX2 switches	10000
Device Alias	Nexus 93180YC-FX and 93360YC-FX2 switches	8000
Switch hops from server to storage	Nexus 93180YC-FX and 93360YC-FX2 switches	7

Table 5: Intelligent Traffic Director Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Nodes per device group	Nexus 9300-FX switches	64
	N9K-X96136YC-R, N9K-X9636Q-R, N9K-X9636C-R, and N9K-X9636C-RX line cards	16
ITD services per switch	Nexus 9300-FX switches	150 ⁷
Buckets per ITD service	N9K-X96136YC-R, N9K-X9636Q-R, N9K-X9636C-R, and N9K-X9636C-RX line cards	64
	Nexus 9300-FX switches	256

⁷ Only 62 unique ACLs can be configured per slice of ASIC. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62. In order to achieve 150 ITD services per switch with the limitation of 62 ACLs per slice, the ingress interfaces should be spread across multiple slices of ASIC.



- Note**
1. For a list of platforms on which ITD is supported, see the *Cisco Nexus 9000 Series NX-OS Intelligent Traffic Director Configuration Guide*.
 2. For the ACL limitations, see the *Cisco Nexus 9000 Series NX-OS Security Configuration Guide*.

Table 6: Interfaces Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
DHCP clients per switch	Nexus 9300-EX/FX/FX2/FX3 switches	10 (IPv4) + 10 (IPv6)
	N9K-X9716D-GX and Nexus 9700-EX line cards	
Flex link	Nexus 9300-EX/FX/FX2, and 9364C switches	One pair consists of one each of active and backup interface. The active and backup interface can be either a physical port or port channel.
IP DHCP relay addresses (helper addresses) per L3 interface	Nexus 9300-EX/FX/FX2/FX3 switches	32 (IPv4) + 32 (IPv6)
	N9K-X9716D-GX and Nexus 9700-EX line cards	
Generic routing encapsulation (GRE) tunnels	Nexus 9300-EX/FX/FX2 switches	16
	N9K-X9716D-GX and Nexus 9700-EX line cards	
LACP rate fast support during system switchover	Nexus 9700-EX line cards	606 ports
Port channel links	Nexus 9300-EX/FX/FX2/FX3 switches and the Nexus 9600-R, 9600-RX, and 9700-EX line cards	32
SVIs	Nexus 9300-EX/FX/FX2 switches, and the N9K-X9716D-GX line cards	1000 (with HSRP) 1000 HSRP groups
	Nexus 9300-FX3 switches	510
	Nexus 9300-GX	1000
	Nexus 9700-EX line cards	1000 (with HSRP), 1500 (without HSRP)
	Nexus 9600-R and 9600-RX line cards	3967
Selective Q-in-Q with Multiprovider tag	Nexus 9300-EX/FX/FX2/FX3 switches and the Nexus 9600-R/RX line cards	Per port limits: 4000 mappings, 10 provider VLANs
		Total switch limits: 48,000 mappings, 512 Provider VLANs
SVI Unnumbered	Nexus 9300-EX/FX/FX2 switches	Primary (50); Secondary (450), 1 primary SVI can have a maximum of 50 secondary SVIs
	N9K-X9716D-GX and Nexus 9700-EX line cards	

Feature	Supported Platforms	Verified Limits
vPCs	Nexus 9300-FX/FX2/FX3 switches	80
	Nexus 9300-EX switches	48
	Nexus 9700-EX line cards	300
	Nexus 9600-R, 9600-RX, and 9700-EX line cards	255
Static Network Address Translation (NAT)	Nexus 9300-EX/FX/FX2/FX3/GX switches	1023
Dynamic Network Address Translation (NAT)	Nexus 9300-EX/FX/FX2/FX3/GX switches	1023
Static twice Network Address Translation (NAT)	Nexus 9300-EX/FX/FX2/FX3/GX switches	768
Dynamic twice Network Address Translation (NAT)	Nexus 9300-EX/FX/FX2/FX3/GX switches	1023

Table 7: Label Switching Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Forwarding Equivalence Classes (FECs) (Node/Prefix/Adj/Binding SID)	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	MPLS Heavy Template: 4096; Default: 1024
	Nexus 9600-R and 9600-RX line cards	1000
Equal-cost multipaths (ECMPs)	Nexus 9300-EX/FX switches, and the Nexus 9700-EX/FX line cards	32
	Nexus 9600-R and 9600-RX line cards	8 - way

Feature	Supported Platforms	Verified Limits
Equal-cost multipaths Groups (ECMPs)	Nexus 9300-EX/FX2, and 9364C switches	MPLS Heavy Template: 7166 (with 4-way ECMP) and 4096 (with 8-way ECMP) Default: 1024 Note After the ECMP objects are exhausted, there is a fallback to the adjacency for all further routes.
	Nexus 9300-FX/GX switches	MPLS Heavy Template and Default Routing Mode: 7166 (with a 4-way ECMP) and 4096 (with 8-way ECMP) Note After the ECMP objects are exhausted, there is a fallback to the adjacency for all further routes.
	Nexus 9600-RX line cards	24000 ECMP Groups 2 paths per ECMP Note Supported only on Cisco NX-OS Release 9.2(4).
FECs * ECMPs	Nexus 9600-R and 9600-RX line cards	8000
Flex counters for segment-routing in ingress direction	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	Total ingress label stats: 4000; VRF ingress label stats: 1,000; (MPLS Heavy Template)
Flex counters for segment-routing in Egress direction	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	Total ingress label stats: 48000 (MPLS Heavy Template)
Egress Peer Engineering	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	64
IAS option B labels	Nexus 9600-R and 9600-RX line cards	450000
Label-switched paths (LSPs) for label stack imposition ⁸	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	256 (with 32 - way ECMP and 5 label stack push)
Layer 3 VPN routes	Nexus 9600-R and 9600-RX line cards	450000
Layer 3 EVPN Labels	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	1000 (With MPLS Heavy Template)
LDP session	Nexus 9600-R and 9600-RX line cards ⁹	200
Node Sid/Prefix SID	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	4,000

Feature	Supported Platforms	Verified Limits
Adjacency SID	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	112
Binding SID	Nexus 9300-EX/FX switches and the Nexus 9700-EX/FX line cards	1000
SRTE Policy		
SRTE policy with PBR	Nexus 9300-FX/FX2/FX3/GX and 9364C switches	512 per slice with 4 way ECMP/1024 per slice with 2 way ECMP
Number of route-maps with SRTE policy (IPv4/IPv6)	Nexus 9300-FX/FX2/FX3/GX and 9364C switches	256 (IPv4) + 256 (IPv6) per slice with 4 way ECMP
Private VLANs (PVLANS)		
Primary VLANs ¹⁰	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	16
	Nexus 9300-EX/FX/FX2/FX3 switches	400
Secondary VLANs ¹¹	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	20
	Nexus 9300-EX/FX/FX2/FX3 switches	400
Ports in Community host mode	Nexus 9300-EX/FX/FX2/FX3	40
	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	
Ports in isolated host mode	Nexus 9300-EX/FX/FX2/FX3 switches	40
	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	40
Ports in isolated trunk host mode	Nexus 9300-EX/FX/FX2/FX3 switches	40
	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	
Ports in promiscuous mode	Nexus 9300-EX/FX switches	10
	Nexus 9300-FX2/FX3 switches, Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	5
Ports in promiscuous trunk mode	Nexus 9300-EX/FX switches	10
	Nexus 9300-FX2/FX3 switches, Nexus N9K-X9716D-GX, and the Nexus 9700-EX/FX line cards	5

Feature	Supported Platforms	Verified Limits
PVLANS allowed on a PVLAN port ¹²	Nexus N9K-X9716D-GX and Nexus 9700-EX/FX line cards	16
	Nexus 9300-EX/FX/FX2/FX3 switches	400

⁸ For Cisco Nexus 9300 and 9500 Series switches, LSPs *ECMP* label stack push cannot exceed 1500.

⁹ N9K-X9636C-RX, N9K-X9636C-R, N9K-X9636Q-R, and N9K-96136YC-R

¹⁰ The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port

¹¹ The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port

¹² The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port



Note For network scalability, Cisco recommends using a hierarchical routing design with multi-hop BGP for advertising the attached prefixes from a top-of-rack (ToR) or border leaf switch.

Table 8: Layer 2 Switching Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
MAC addresses	Nexus 9300-EX/FX/FX2/FX3 switches, Nexus N9K-X9716D-GX and the Nexus 9700-EX/FX line cards	92000
	Nexus 9300-GX switches	92000 (default system routing mode) 200000 ¹³
	Nexus 9364C switches	90000 (default system routing mode without system routing layer 3 scale) 32000 (default system routing mode with system routing layer 3 scale)
	Nexus 9600-R and 9600-RX line cards	192000
	N9K-C9264PQ and 9300-EX switches	200000 ¹⁴
MST instances	Nexus 9300-EX/FX/FX2/FX3 switches and the Nexus 9600-R, 9600-RX, N9K-X9716D-GX, and 9700-EX/FX line cards	64
MST PV count with single instances 0	Nexus 9300-FX/FX2/FX3 switches	190000
MST virtual ports with more than 1 MST instance	Nexus 9300-EX/FX/FX2/FX3 switches	48000
	Nexus N9K-X9716D-GX and 9700-EX/FX line cards	85000
	Nexus 9600-R and 9600-RX line cards	236000

Feature	Supported Platforms	Verified Limits
RPVST virtual ports (physical ports * vlans)	Nexus 9300-EX/FX/FX2/FX3 switches	12,000
	Nexus N9K-X9716D-GX and 9700-EX/FX line cards	22,000
	Nexus 9600-R and 9600-RX line cards	13750
RPVST logical ports (logical ports * vlans)	Nexus 9300-EX/FX/FX2/FX3 switches	12,000
	Nexus N9K-X9716D-GX and 9700-EX/FX line cards	22,000
	Nexus 9600-R and 9600-RX line cards	13750
VLANs	Nexus 9300-EX/FX/FX2/FX3 switches and the Nexus N9K-X9716D-GX, 9600-R, 9600-RX, and 9700-EX/FX line cards	3967 (the remaining 127 VLANs are reserved)
	Nexus 92348GC-X switches	4096
VLANs in RPVST mode	Nexus 9300-EX/FX/FX2/FX3/GX switches	3967
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	3967 ¹⁵
	Nexus 9600-R and 9600-RX line cards	250
Total number of VLANs × ports with switch port isolated (3967 VLANs x 48 ports)	Nexus 9300-EX/FX/FX2/FX3 switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	190,000
Private VLANs (PVLANS)		
Primary VLANs	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	16
Secondary VLANs	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	20
Ports in Community host mode	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	40
Ports in isolated host mode	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	40
Ports in isolated trunk host mode	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	40
Ports in promiscuous mode	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	5
Ports in promiscuous trunk mode	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	5
PVLANS allowed on a PVLAN port	Nexus 9300-EX/FX/FX2 switches, Nexus 9700-EX and N9K-X9716D-GX line cards	16

- ¹³ Layer 2 unidimensional scale only. SVI, Layer 3 interface, and VXLAN VLANs are not supported. 200K MAC is enabled only when " system routing template-l2-heavy" is configured and the system is reloaded.
- ¹⁴ Layer 2 unidimensional scale only. SVI, Layer 3 interface, and VXLAN VLANs are not supported. 200K MAC is enabled only when " system routing template-l2-heavy" is configured and the system is reloaded.
- ¹⁵ On EOR, support is for 12000 PV count with 3967 vlans and RPVST with default timers. If 22000 PV count is needed with 3968 vlans and RPVST, recommended hello timer value is 4 or higher. It is also recommended to tune forward delay and max age accordingly



Note

- The number of supported VLANs per vPC should be within the MST or RPVST virtual port count that is specified in this table, depending on the topology.
- The number of supported STP VLAN port instances, for Fabric Extender host interface ports, should be less than 13000.

Table 9: Multicast Routing Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Egress NAT	Nexus 9300-EX/FX/FX2 switches	2000
Ingress NAT	Nexus 9300-EX/FX/FX2 switches	2000
Egress and Ingress NAT	Nexus 9300-EX/FX/FX2 switches	2000

Feature	Supported Platforms	Verified Limits
Note The limits are for a combination of IPv4 and IPv6 multicast routes. Layer 2 multicast entries are a part of the total 120K limits. For example, 110K IPv4 + 2K IPv6 multicast routes + 8K Layer 2 multicast entries.	Nexus 9348GC-FXP switches	8192 (Layer 2 + Layer 3)
	Nexus 9300-EX switches and the Nexus 9700-EX line cards	8192 (Layer 2 + Layer 3); 32768 (layer 2 + Layer 3 with system routing template - multicast -heavy mode); 8192 (with system routing template - lpm - heavy mode)
	Nexus 9332C and 9364C switches	16384 (Layer 2 + Layer 3) with the default template and the system routing layer 3 scale configuration.
	Nexus 9300-FX2 switches	8192 (Layer 2 + Layer 3); 32768 (Layer 2 + Layer 3 with system routing template -multicast -heavy mode); 131072 (with system routing template -multicast - ext - heavy mode)
	Nexus 9300-FX3 switches	128000 (64000 *, G + 64000 S,G)
	Nexus 9700-FX line cards	8192 (Layer 2 + Layer 3); 32768 (layer 2 + Layer 3 with system routing template - multicast -heavy mode); 131072 (with system routing template - multicast - ext - heavy mode) ¹⁶
	Nexus 9300-FX/GX switches	32,768 (layer 2 + Layer 3 with system routing template - default, multicast -heavy mode); 131,072 (with system routing template - multicast - ext - heavy mode)
	Nexus 9600-R and 9600-line cards	32768 (Layer 3)
	Nexus N9K-X9716D-GX line card	131072 (65536 *,G + 65536 S,G)
IPv6 multicast routes	Nexus 92160YC-X, 9300-EX/FX, and 9500 switches	8192 (Layer 3 with system routing template - default, multicast - heavy, multicast - ext - heavy and multicast - heavy, multicast - ext - heavy, dual - stack - multicast)
	Nexus 9300-FX2 and 9364C switches	8192 (Layer 3 with system routing template -multicast -heavy mode)
	Nexus 9300-FX3 switches and N9K-X9716D-GX line card	8192 (4096 - *, G + 4096 - S,G)
	Nexus 9332C and 9364C switches	8192 (Layer 2 + Layer 3 with system routing template -multicast -heavy mode)
	Nexus 9348GC-FXP switches	8192 (layer 2 + Layer 3 with system routing template - multicast -heavy -multicast - ext - heavy mode)
	Nexus 9300-GX switches	8192

Feature	Supported Platforms	Verified Limits
MLD snooping groups	Nexus 9300-EX/FX/FX2 switches and the Nexus 9700-EX/FX line cards	8192
Multicast FPV	Nexus 9300-GX switches	IPv4 32000 (Layer 2 + Layer 3) multicast routes
Outgoing interfaces (OIFs)	Nexus 9300-EX/FX/FX2/FX3 switches, N9K-X9716D-GX and the Nexus 9700-EX/FX line cards	40 (SVI + physical layer 3) or 256 (physical layer 3)
	Nexus 9600-R and 9600-RX line cards	16 OIFs for 32K mroutes or 287 OIFs for 1000 mroutes
IGMP snooping groups	Nexus 9300-EX switches and the Nexus 9700-EX line cards	8000
	Nexus 9300-FX2 switches and Nexus 9700-FX line cards	8000 (with system routing template - default), 16000 (with system routing template - multicast-heavy - multicast - ext - heavy mode)
	Nexus 9300-FX/FX3/GX switches and N9K-X9716D-GX line card	16000
PIM neighbors	Nexus 9300-EX/FX/FX2/FX3 switches	250
	Nexus 9600-R, 9600-RX and 9700-EX/FX line cards	500
MVPN- unidimensional		
Multicast VRFs	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	300
Default MDT groups	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	300
MVPN Peers (PIM neighbors) per device	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	900
Maximum number of PEs per VRF	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	200 PEs per VRF with up to 3 VRFs (600 PIM neighbors)
Maximum number of Data MDT groups per VRF on a PE	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	1000
Maximum number of Data MDT groups across all VRFs on a PE	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	10000
Maximum number of MDT groups across all VRFs on PE	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	10300 (10000 Data + 300 default DMT)

Feature	Supported Platforms	Verified Limits
Maximum number of Multicast routes on a PE node	Nexus 9600-R and 9600-RX line cards (except the N9K-X96136YC-R line card)	32000

¹⁶ All line cards must have the FX type.



Note

- The IPv4 multicast routes and the IPv4/IPv6 host routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
- High availability (graceful restart and stateful switchover) is not supported when unicast or multicast aggressive timers are configured at any scale.

Table 10: IP Fabric for Media Solution Verified Scalability Limits (Unidimensional)

Feature	Verified Limits
Number of nodes	35 (2 spines and 33 leafs)
No of routes	32000
Host Policy	
Sender	8000
Receiver	8000
PIM	512
FlowPolicy	2000
ASM group-range	20
NBM Static Flows	
Per switch maximum (receiver leaf where the static OIF will be programmed) mroutes	1500
Per fabric maximum mroutes	8000
VRFs	16
PMN NAT	
Egress-NAT	1000 with ing-nbm team 512
Ingress-NAT	1000 with ing-nbm team 512
Ingress/Egress NAT	1500 with ing-nbm 512
Ingress/Egress NAT	2000 with ing-nbm 0

Feature	Verified Limits
RTP Flow Monitoring with ACL	
ACL	128 IPv4 ACL entries or 64 IPv6 ACL entries (total 128 TCAM spaces) Note With combined IPv4 and IPv6 ACL entries, the scale limit cannot exceed 128 TCAM spaces.

Table 11: IP Fabric for Media Solution Policer Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
IPFM		
NBM Flow Policers (Slice/System)	Nexus 9300-EX switches	1536/3072
	Nexus 9300-FX/FX3 switches	1536/1536
	Nexus 9300-FX2 switches	1536/3072
	Nexus 9300-GX/GX2B switches	1536/6144
	Nexus 9300-GX2A switches	1536/12288
	Nexus N9K-X9636C-R Line Card	2048/12288
	Nexus N9K-X9636Q-R Line Card	2048/6144
	Nexus N9K-X9636C-RX Line Card	2048/8192
	Nexus N9K-X9624D-R2 Line Card	2048/8192
	Nexus N9K-X9836DM-A Line Card	350/3150



Note When storm control is enabled on Nexus 9300-FX3/GX/GX2 Platform Series switches, the maximum supported scale for NBM flow policers is limited to 1534.

For a list of supported platforms, see [Cisco Nexus 9000 Series NX-OS IP Fabric for Media Solution Guide](#).

Table 12: Programmability Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
gNMI		
VRF - Default	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	16 concurrent subscriptions
VRF - Management	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	16 concurrent subscriptions

Feature	Supported Platforms	Verified Limits
VRF - Default and Management	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	32 concurrent subscriptions
Paths	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	48 paths in a single subscription
Message size	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	Less than 12 MB
Aggregate MO's	Nexus 9300-EX/FX/FX2/GX switches and the Nexus 9700-FX line cards	150,000

Table 13: QoS Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Class maps per policy map	Nexus 9300-GX switches	128
AFD	Nexus 9300-GX switches	30 profiles
WRED	Nexus 9300-GX switches	30 profiles
Ingress 1R2C	Nexus 9300-GX switches	1280
Egress 1R2C	Nexus 9300-GX switches	256
Ingress 2R3C	Nexus 9300-GX switches	766
Total policy maps	Nexus 9300-GX switches	4000

Table 14: Security Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Egress ACLs	Nexus 9600-R line cards	20000
System ACLs	Nexus 9600-R line cards	4000 TCAM entries in internal TCAM 64000 TCAM entries in external TCAM
ACLs	Nexus 9300-FX3	Ingress - 3584 IPv4, 1792 IPv6
RACL Labels (maximum)	Nexus 9504 and 9508 switches	4,000
DHCP snooping bindings	Nexus 9300-EX/FX/FX2/FX3 switches, N9K-X9716D-GX and Nexus 9700-EX line cards	2048

Feature	Supported Platforms	Verified Limits
IPv4 ingress access control entries (ACEs)	Nexus 9600-R and 9600-RX line cards	<ul style="list-style-type: none"> • RACL on LC N9K-X9636C-RX: 100,000 • PACL on LC N9K-X9636C-RX: 12,000 • RACL-2048, PACL-1024 (without TCAM Carving) IPv4 52640 ACEs per system • PACL IPv4: 1024 TCAM entries in internal TCAM • PACL MAC: 2048 TCAM entries in internal TCAM • RACL IPv4: 2048 TCAM entries in internal TCAM
IPv6 ingress access control entries (ACEs)	Nexus 9600-R and 9600-RX line cards	<ul style="list-style-type: none"> • RACL-1024, PACL-1024 (without TCAM Carving) IPv6 25200 ACEs per system • PACL IPv6: 1024 TCAM entries in internal TCAM • RACL IPv6: 1024 TCAM entries in internal TCAM
IPv4 ingress TCAM entries	Nexus 9300-EX/FX/FX2/FX3 switches, N9K-X9716D-GX and Nexus 9700-EX/FX line cards	3582 (per slice of the forwarding engine)
	Nexus 9300-GX switches	4608
IPv4 egress TCAM entries	Nexus 9300-EX/FX/FX2/FX3/GX switches, N9K-X9716D-GX and Nexus 9700-EX/FX line cards	1792 (per slice of the forwarding engine)
	Nexus 92348GC-X switches	Ingress - 3072 IPv4, 1792 IPv6
IPv6 ingress TCAM entries	Nexus 9300-EX/FX/FX2/FX3 switches, N9K-X9716D-GX and Nexus 9700-EX/FX line cards	1792 (per slice of the forwarding engine)
	Nexus 9300-GX switches	2302 (per slice of the forwarding engine)
IPv6 egress TCAM entries	Nexus 9300-EX/FX/FX2/FX3/GX switches, N9K-X9716D-GX and Nexus 9700-EX/FX line cards	896 (per slice of the forwarding engine)
	Nexus 92348GC-X switches	Ingress - 3072 IPv4, 1792 IPv6

**Note**

- The TCAM entries scalability limits also apply to policy-based TCAM entries (PBACLs).
- Only 62 unique ACLs can be configured. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62.

Table 15: SRv6 Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
ARP	Nexus 9300-GX switches	48000
Host and LPM IPv4 routes	Nexus 9300-GX switches	470000
Host and LPM IPv6 routes	Nexus 9300-GX switches	256000
Leaf	Nexus 9300-GX switches	256
SID DB	Nexus 9300-GX switches	2,000
SRv6 and VXLAN Peer	Nexus 9300-GX switches	256
VRF	Nexus 9300-GX switches	1000
ND	Nexus 9300-GX switches	24000
SRv6 Traffic Engineering policies	Nexus 9300-GX switches	1000
Number of prefixes (IPv4 and IPv6) that use SRv6 Traffic Engineering policies	Nexus 9300-GX switches	50,000
Maximum number of preferences per policy	Nexus 9300-GX switches	3
Maximum number of segment lists	Nexus 9300-GX switches	3000

Table 16: System Management Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
PTP		

Feature	Supported Platforms	Verified Limits
PTP ports	Nexus 9300-EX/FX/FX2 switches	64 per system Note The verified limit for Nexus 9336C-FX2 switch is 144 per system.
	N9K-C93180YC-FX3 and N9K-C93180YC-FX3S switches	20 per system
	N9K-C93108TC-FX3P switches	25 per system
	Nexus 9300-GX switches	64 per system
	Nexus 9500 switches with Nexus 9700-EX line cards	1305 per chassis The per line card limit is based on the maximum physical ports supported. Note PTP Offload is supported on 9700-EX line cards.
	Nexus 9508 switches with -R line cards	64 per line card 300 per chassis Note PTP Offload is supported on 9508-R line cards.
	Nexus 9500 switches with Nexus 9600-RX line cards	128 per line card 512 per chassis
	Nexus 9508 switches with -R2 line cards	173 per chassis
PTP clients per port	Nexus 9300-EX/FX/FX2/FX3/GX switches and Nexus 9500 switches with 9700-EX, 9508-R and 9600-RX line cards	2
sFlow		
sFlow ports	Nexus 9300-EX/FX/FX2/GX switches	64
	Nexus 9300-FX3 switches	30
	Nexus 9700-EX line cards	256
	Nexus N9K-X9716D-GX line card	16
SPAN and ERSPAN		
Configurable SPAN or ERSPAN sessions	Nexus 9300-EX/FX/FX2/FX3 switches, the Nexus 9600-R, 9600-RX, and N9K-X9716D-GX line cards	32

Feature	Supported Platforms	Verified Limits
Active SPAN or ERSPAN sessions ¹⁷	Nexus 9300-EX/FX/FX2/FX3/GX switches, and Nexus 9600-R, 9600-RX, and 9700-EX line cards	4 sessions (per chassis/ToR or based on the number of the line cards in the EoR). ¹⁸
Active localized SPAN or ERSPAN sessions per line card ¹⁹	Nexus 9300-EX/FX/FX2/FX3 switches, and Nexus 9700-EX line cards	4
	Nexus 9600-R and 9600-RX line cards	32 sessions across ports on single-line card
Active localized SPAN or ERSPAN session (Rx and Tx, Rx, or Tx)	Nexus 9600-R and 9600-RX line cards	32 sessions, 128 sources, and 1 destination
Source interfaces per SPAN or ERSPAN session (Rx and Tx, Rx, or Tx)	Nexus 9300-EX/FX/FX2/FX3 switches, and Nexus 9700-EX and N9K-X9716D-GX line cards	48
Destination interfaces per SPAN session	Nexus 9300-EX/FX/FX2/FX3 switches, and Nexus 9600-R, 9600-RX, N9K-X9716D-GX, and 9700-EX line cards	1 (physical/PO interface) Note Destination as PO interface is not supported for N9K-X9716D-GX line card.
Source VLANs per SPAN or ERSPAN session	Nexus 9300-EX/FX/FX2/FX3 switches, and Nexus 9600-R, 9600-RX, N9K-X9716D-GX, and 9700-EX line cards	32
Tap Aggregation		
Redirect interfaces in the redirect port list	Nexus 9300-EX/FX/FX2/GX, and Nexus 9500-CloudScale platform switches	32
	Nexus 9300, 9300-FX3 and 9500 Merchant Silicon platform switches	12
	Nexus N9K-X9716D-GX line card	12
Redirect port lists (or fan outs) per system	Nexus 9300-FX3 switches	100
	Nexus N9K-X9716D-GX line card	12
NetFlow		

Feature	Supported Platforms	Verified Limits
Flow monitors	Nexus 9300-EX switches and Nexus 9500 switches with 9700-EX and FM-E fabric line cards	<p>2 flow monitors per type (2 IPv4 flow monitors and 2 IPv6 flow monitors).</p> <p>1 flow monitor for CE flows</p> <p>2 exporters for each flow monitor. Hence, a total of 4 different exporters can be configured.</p>
	Nexus 9300-FX/FX2/GX switches and 9500 with FX LC cards	<p>30 IPv4 flow monitor and each flow monitor with two exporters</p> <p>28 IPv6 flow monitor and each flow monitor with two exporters</p> <p>32 Layer2 Flow monitor and each flow monitor with two exporters</p> <p>Maximum number of exporters supported per flow monitor is 2</p>
Layer 3 interfaces (Layer 3 ports, port channels, and SVIs) to which IPv4 flow monitors can be applied	Nexus 9300-EX switches	<p>1024 (with members on just one ASIC slice): 922 for IPv4/IPv6 flow monitors, while 32 are reserved for the Layer 2 flow monitors.</p> <p>Maximum number of SVIs supported:</p> <ul style="list-style-type: none"> • 492 with IPv4 flow monitors only • 246 with IPv6 flow monitors only • 165 with both IPv4 flow monitor and IPv6 flow monitors attached <p>Number of Layer 3 interfaces (Layer 3 ports, port channels, and SVIs) to which IPv4 flow monitors can be applied. You can use the show interface hardware-mappings command to check if the interface belongs to ASIC slice 0 or slice 1.</p>
Layer 3 interfaces (Layer 3 ports, port channels, and SVIs) to which IPv6 flow monitors can be applied	Nexus 9300-EX switches	<p>252 (with members on just one ASIC slice) or 126 (with members on both ASIC slices). You can use the show interface hardware-mappings command to check if the interface belongs to ASIC slice 0 or slice 1.</p>

Feature	Supported Platforms	Verified Limits
Maximum number of flows in the software table (IPv4 or IPv6 or CE flows)	Nexus 9000 switches	100,000 flows using the show flow cache command on 9500 modular chassis per line card 1,000,000 flows (1 Million) using the show flow cache command on 9300 switches
Maximum number of concurrent flows supported (IPv4 or IPv6 or CE flows)	Nexus 9300-EX/FX/FX2 switches	6000 traffic flows. By increasing LCPU-PG-SIZE using the following command one can achieve Max 18000 concurrent flows, after modifying LCPU-PG-SIZE, the switch needs reboot after saving configuration <pre>switch(config)# hardware qos lcpu-pg-size ? <200-10000> Pool Group size</pre> <pre>switch(config)# hard qos lcpu-pg-size 5000</pre> Warning:Reload required for configured PG size to take effect. Save configuration and reload the system. <pre>switch(config)# copy running-config startup-config</pre> In Cisco Nexus Release 9.3(3), the hardware qos command is not supported.

- ¹⁷ A single forwarding engine instance supports four SPAN or ERSPAN sessions. For Cisco Nexus 9300 Series switches, if the first three sessions have bidirectional sources, the fourth session has hardware resources only for Rx sources. This limitation might also apply to Cisco Nexus 9500 Series switches, depending on the SPAN or ERSPAN source's forwarding engine instance mappings.
- ¹⁸ If the source interface configured for a monitor session is on the same line card, the maximum supported active SPAN sessions are 4. Based on the number of line cards in the EoR, the total number of active SPAN sessions are 4 x n, where n is the number of line cards on EoR, provided the source and destination interface are on the same line module.
- ¹⁹ The number of SPAN or ERSPAN sessions per line card reduces to two if the same interface is configured as the bidirectional source in more than one session.

Table 17: NetFlow Scalability Support (Flows)

Feature	Platform	Port Speed	Scale Limit (Flows)	Export Interval (seconds)	Packets / Flow
Layer 2 Flow monitor	Nexus 9300-EX switches	10G	3,800	60	89,000
		40G	3,800	60	3,56,000
		100G	3,800	60	8,85,000
	Nexus 9300-FX/FX2/FX3 switches	10G	6,000	60	89,000
		40G	6,000	60	3,56,000
		100G	6,000	60	8,85,000
	Nexus 9300-GX switches	10G	6,000	60	89,000
		40G	6,000	60	3,56,000
		100G	6,000	60	8,85,000
Layer 3 Flow monitor (IPv4)	Nexus 9300-EX	10G	27,000	60	12,000
		40G	27,000	60	54,000
		100G	27,000	60	160,000
	Nexus 9300-FX/FX2/FX3	10G	24,000	60	12,000
		40G	24,000	60	54,000
		100G	24,000	60	160,000
	Nexus 9300-GX switches	10G	24,000	60	12,000
		40G	24,000	60	54,000
		100G	24,000	60	1,60,000

Feature	Platform	Port Speed	Scale Limit (Flows)	Export Interval (seconds)	Packets / Flow
Layer 3 Flow monitor (IPv6)	Nexus 9300-EX	10G	15,000	60	12,000
		40G	15,000	60	54,000
		100G	15,000	60	160,000
	Nexus 9300-FX/FX2/FX3	10G	11,000	60	12,000
		40G	11,000	60	54,000
		100G	11,000	60	160,000
	Nexus 9300-GX	10G	11,000	60	12,000
		40G	11,000	60	54,000
		100G	11,000	60	160,000

Table 18: NetFlow Scalability Support (Flows) for Cisco Nexus 9500 Family Switches

Feature	Platform	Scale Limit (Flows)
IP flow monitor	Nexus 9500-EX Line cards	2
IPv6 flow monitor		2
Layer 2 Flow monitor		1
Maximum number of exporters per each flow monitor		2
Flow Scale		24,000 per ASIC slice
IP flow monitor	Nexus 9500-FX Line cards	30
IPv6 flow monitor		28
Layer 2 Flow monitor		1
Maximum number of exporters per each flow monitor		2
Flow Scale		24,000 per ASIC slice

Table 19: NetFlow SVI Verified Scalability Limits (Unidimensional)

Platform (VLAN Ports)	SVI			VLAN			SVI + VLAN		
	IPv4	IPv6	IPv4 + IPv6	IPv4	IPv6	IPv4 + IPv6	IPv4	IPv6	IPv4 + IPv6
Member ports from Cisco Nexus 9300-EX switches	474	118	94	474	118	94	237	61	38
Member ports from Cisco Nexus 9300-FX switches	Total interfaces supported in the system								
Member ports from Cisco Nexus 9300-EX and Nexus 9300-FX switches (EOR chassis)	474	118	94	474	118	94	237	61	38



Note The scale numbers are based on the TCAM space available on the Cisco Nexus 9300-EX and Nexus 9300-FX switches. A IPv4 flow monitor uses 2 and 4 TCAM space for the Cisco Nexus 9300-EX and Nexus 9300-FX switches respectively. Similarly, a IPv6 flow monitor uses 8 and 2 TCAM space for the Cisco Nexus 9300-EX and Cisco Nexus 9300-FX switches respectively.

For port channels, SVIs, and VLANs that have port from both 9300-EX and 9300-FX switches, the lower common denominator limit of the 9300-EX and 9300-FX switches is applied.

Table 20: Unicast Routing Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Unicast Routing		

Feature	Supported Platforms	Verified Limits
BFD sessions (echo mode)	Nexus 9364C, and 9300-EX/FX/FX2/GX switches	128 when the BFD intervals are set to default, which is 50 ms 1024 when the BFD intervals are relaxed to 300 ms Note Cisco Nexus 9300 (EX, FX, FX2, and 9364C) platform switches support up to 512 BFD sessions, when the BFD intervals are relaxed to 300 ms.
	Nexus 9300-FX3 switches	512
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	512 ²⁰ when the BFD intervals are set to default, which is 50 ms 1024 when the BFD intervals are relaxed to 300 ms
	Nexus 9600-R and 9600-RX line cards	288
BGP neighbors	Nexus 92348GC-X switches	141
	Nexus 364C, and 9300-EX/FX/FX2/FX3/GX switches	1024
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	2000
	Nexus 9600-R and 9600-RX line cards	960
EIGRP routes	Nexus 9364C, 9300-EX/FX/FX2/FX3/GX switches, and Nexus 9700-EX/FX and N9K-X9716D-GX line cards	20,000
EIGRP neighbors	Nexus 9364C, 9300-EX/FX/FX2/FX3/GX switches	256
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	512
HSRP groups	Nexus 9600-R/RX switches and N9K-X9716D-GX line card	490
	Nexus 9300-EX/FX/FX2/GX switches	1000 ²¹
	Nexus 9700-EX/FX switches and N9K-X9716D-GX line cards	1,000 (virtual MAC address support) ²²
	Nexus 9600-R and 9600-RX line cards	16 (Maximum 16 groups because 16 is the unique virtual MAC address limit)

Feature	Supported Platforms	Verified Limits
IPv4 ARP	Nexus 9364C switches	32000
	Nexus 9600-R, 9600-RX, and 9700-EX/FX line cards	48000
	Nexus 9300-EX/FX2 switches	48000 (without URPF) 32000 (with URPF enabled)
	Nexus 9300-FX/GX switches	98000 (Hash Table: Shared between IPv6 ND, IPv4 ARP))
	Nexus 9300-FX3 switches	98000
	Nexus N9K-X9716D-GX line card	98304
IPv4 host routes ²³	Nexus 9364C switches	96000 (default system routing mode without system routing layer 3 scale) 128000 (default system routing mode with system routing layer 3 scale)
	Nexus 9300-EX switches	458000 (default); 786000 / 720000 (with system routing template - lpm - heavy mode)
	Nexus 9300-FX2 switches	524,000 / 471,000 (without / with urpf enabled) (default); 786000 / 734000 (without / with urpf enabled) (with system routing template - lpm -heavy mode)
	Nexus 9300-FX/GX switches	1153000(default); 786000 / 734000 (with out / with urpf enabled) (with system routing template - lpm -heavy mode)
	Nexus 9300-FX3 switches	1119000
	Nexus 9700-EX and N9K-X9716D-GX line cards	1000000 (default); 786000 (with system routing template - lpm -heavy mode) 589000 (default); 786000 (with system routing template - lpm -heavy mode)
	Nexus 9600-R/RX line cards	1000000 (default routing template)

Feature	Supported Platforms	Verified Limits
IPv6 host routes 24	Nexus 9364C switches	48000 (default system routing mode without system routing layer 3 scale) 64000 (default system routing mode with system routing layer 3 scale)
	Nexus 9300-EX switches	24000 / 16000 (with out/with urpf enabled)
	Nexus 9300-FX2 switches	265000 (default), 442000 / 412000 (without / with urpf enabled) (with system routing template -lpm - heavy mode)
	Nexus 9300-FX/GX switches	628,000 (default), 442,000 / 412000 (without / with urpf enabled) (with system routing template -lpm - heavy mode)
	Nexus 9300-FX3 switches	600000 442000 (LPM heavy mode)
	Nexus 9700-EX/FX line cards	FM-E: 32000 FM-E2: 235000 FM-G: 235000
	Nexus 9600-RX line cards	256000 (default routing template)
	Nexus N9K-X9716D-GX line card	235000
IPv6 ND	Nexus 9364C, and 9300-EX/FX2 switches	32000 (default), 16000 (lpm heavy)
	Nexus 9300-FX/GX switches	98000 (in default routing mode, Hash Table: Shared between IPv6 ND, IPv4 ARP)
	Nexus 9300-FX3 switches	98000 (default), 16000 (lpm heavy) (Hash Table: Shared between IPv6 ND, IPv4 ARP)
	Nexus 9600-R, 9600-RX, and 9700-EX/FX line cards	32000

Feature	Supported Platforms	Verified Limits
IPv4 unicast routes (LPM)*	Nexus 9364C switches	Default system routing mode without system routing layer 3 scale: <ul style="list-style-type: none"> • Default values: 8000 (IPv4), 1900 (IPv6), and 2000 (multicast) • With hardware profile multicast max-limit lpm-entries 0 configured: 10000 (IPv4), 1900 (IPv6), and 0 (multicast) • With hardware profile ipv6 lpm-entries maximum 0 configured: 14000 (IPv4), 0 (IPv6), and 2000 (multicast) • With hardware profile ipv6 lpm-entries maximum 4096 and hardware profile multicast max - limit lpm - entries 0 configured: 4000 (IPv4), 4096 (IPv6), and 0 (multicast) • When you allocate the entire table for IPv4 or IPv6 LPM unicast routes, the other address family cannot be used. 128000 (default system routing mode with system routing layer 3 scale)
	Nexus 9300-EX switches	458000 (default)
	Nexus 9300-FX switches	1153000 / 996000 (without / with urpf enabled) (default), 786000 / 734000 (without / with urpf enabled) (with system routing template - lpm - heavy - mode)
	Nexus 9300-FX2 switches	524,000 / 471000 (default); 786000 / 734000 (without / with urpf enabled) (with system routing template - lpm -heavy mode)
	Nexus 9300-GX switches	1153000 (default), 786000 / 734000 (without / with urpf enabled) (with system routing template - lpm - heavy mode)
	Nexus 9300-FX3 switches	1119000
	Nexus 9300 switches	128000 (default system routing mode); 16,000 (max-host routing mode)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	589000 (default)

Feature	Supported Platforms	Verified Limits
	Nexus 9600-R line cards	192000 (Default system routing template)
	Nexus 9600-RX line cards	1000000 (Default system routing template)

Feature	Supported Platforms	Verified Limits
IPv6 unicast routes (LPM)*	Nexus 9364C switches	Default system routing mode without system routing layer 3 scale <ul style="list-style-type: none"> • Default values: 8000 (IPv4), 1900 (IPv6), and 2000 (multicast) • With hardware profile multicast max-limit lpm-entries 0 configured: 10000 (IPv4), 1900 (IPv6), and 0 (multicast) • With hardware profile ipv6 lpm-entries maximum 0 configured: 14,000 (IPv4), 0 (IPv6), and 2000 (multicast) • With hardware profile ipv6 lpm-entries maximum 4096 and hardware profile multicast max - limit lpm - entries 0 configured: 4000 (IPv4), 4096 (IPv6), and 0 (multicast) • When you allocate the entire table for IPv4 or IPv6 LPM unicast routes, the other address family cannot be used 64000 (default system routing mode with system routing layer 3 scale)
	Nexus 9300-EX switches	206000 (/64 prefix length); 1900 (non /64 prefix length)
	Nexus 9300-FX switches	628000 / 560000 (without / with urpf enabled) (default) ; 442000 / 412000 (without / with urpf enabled) (with system routing template - lpm - heavy mode)
	Nexus 9300-FX2 switches	294000 / 265000 (without / with urpf enabled) (default) ; 442000 / 412000 (with out / with urpf enabled) (with system routing template - lpm - heavy mode)
	Nexus 9300-GX switches	628000 / 628000 (without/with urpf enabled) (default) ; 442000 / 412000 (without / with urpf enabled) (with system routing template - lpm - heavy mode)
	Nexus 9300-FX3 switches	600000
	Nexus 9500 switches	

Feature	Supported Platforms	Verified Limits
		20000 (default system routing mode) 4000 (max-host routing mode) 80000 with no IPv4 routes (64-bit ALPM routing mode)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	FM-E: 176000 (/64 prefix length); 3900 (non /64 prefix length) FM-E2: 235000 (any prefix length) FM-G: 235000
	Nexus 9600-R line cards	62000 (Default system routing template)
	Nexus 9600-RX line cards	256000 (Default system routing template)
IPv4 host routes (LPM heavy mode)	Nexus 9236C, 9272Q, and 92304QC switches	262000
	Nexus 92160YC-X switches	650000
	Nexus 9364C switches	262000
	Nexus 9300-EX switches	786000 / 720000 (with out/with urpf enabled)
	Nexus 9300-FX switches	786000 / 734000 (with out/with urpf enabled)
	Nexus 9300-FX2/FX3/GX switches	786000 / 734000 (with out/with urpf enabled)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	786,000
IPv6 host routes (LPM heavy mode)	Nexus 9364 switches	131000
	Nexus 9300-EX switches	24000 / 16000 (with out/with urpf enabled) (protocol learned host)
	Nexus 9300-FX/FX2/FX3/GX switches	442000 / 412000 (with out/with urpf enabled) (protocol learned host)
	Nexus 9700-EX/FX line cards	FM-E: 32000 (shared between IPv6 ND and protocol learned host) FM-E2: 235000 FM-G: 235000
	Nexus N9K-X9716D-GX line card	235000

Feature	Supported Platforms	Verified Limits
IPv4 LPM routes (LPM heavy mode)	Nexus 9236C, 9272Q, and 92304QC switches	262000
	Nexus 92160YC-X switches	650000
	Nexus 9364C switches	262000
	Nexus 9300-EX switches	786000 / 720000 (with out/with urpf enabled)
	Nexus 9300-FX switches	786000 / 734000 (with out/with urpf enabled)
	Nexus 9300-FX2/GX switches	786000 / 734000 (with out/with urpf enabled)
	Nexus 9300-FX3 switches	786000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	786000
IPv6 LPM routes (LPM heavy mode)	Nexus 9236C, 9272Q, and 92304QC switches	131000 (/64 prefix length); 1900 (non /64 LPM scale)
	Nexus 92160YC-X switches	294000 (/64 prefix length); 1900 (non /64 LPM scale)
	Nexus 9364C switches	131000
	Nexus 9300-EX switches	353000 / 324000 (with out/with urpf enabled) (/64 prefix length); 1900 (non /64 prefix length)
	Nexus 9300-FX/FX2/GX switches	442000 / 412000 (with out/with urpf enabled)
	Nexus 9300-FX3 switches	442000 / 412000 (without / with urpf enabled) (protocol learned host)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	FM-E: 235000 (/64 prefix length); 3900 (non /64 prefix length) FM-E2: 235000 (any prefix len) FM-G: 235000
IPv4 host routes (dual-host mode)	Nexus 9364C switches	163000
	Nexus 9300-EX/FX/FX2/FX3/GX switches	262000
IPv6 host routes (dual-host mode)	Nexus 9364C switches	81000
	Nexus 9300-EX/FX/FX2/FX3/GX switches	131000

Feature	Supported Platforms	Verified Limits
IPv4 LPM routes (dual-host mode)	Nexus 9300-EX switches	6000
	Nexus 9300-FX and 9364C switches	8000
	Nexus 9300-FX2/GX switches	10,000
	Nexus 9300-FX3 switches	7000
IPv6 LPM routes (dual-host mode)	Nexus 9300-EX/FX/FX3, and 9364C switches	1900
	Nexus 9300-FX2/GX switches	3900
IPv4 LPM routes (l3-heavy mode)	Nexus 9600-RX line cards	1,800,000
IPv6 LPM routes (l3-heavy mode)	Nexus 9600-RX line cards	750,000
IPv4 ARP (dual-host mode)	Nexus 9364C and 9300-EX switches	64000
	Nexus 9300-FX/FX2/FX3/GX switches	98000
IPv6 ND (dual-host mode)	Nexus 9364C and 9300-EX switches	64000
	Nexus 9300-FX/FX2/FX3/GX switches	98000
Note The combined IPv4 and IPv6 route prefixes of internet-peer which was working in the internet-peering routing mode may not work forever because the global internet tables are growing. This occurs as hardware resource to accommodate IPv4 and IPv6 route prefixes do not change once the hardware/software is shipped.	Nexus 9300-EX/FX2 switches	1 Million (protocol learned host)
	Nexus 9300-FX/FX3/GX switches	1256000 (protocol learnt host)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1 Million (protocol learned host)

Feature	Supported Platforms	Verified Limits
IPv6 host routes (internet-peering mode) Note The combined IPv4 and IPv6 route prefixes of internet-peer which was working in the internet-peering routing mode may not work forever because the global internet tables are growing. This occurs as hardware resource to accommodate IPv4 and IPv6 route prefixes do not change once the hardware/software is shipped.	Nexus 9300-EX switches	16000 (Hash Table: Shared between IPv6 ND and protocol learned IPv6 host)
	Nexus 9300-EX/FX2 switches	500,000 (protocol learned host)
	Nexus 9300-FX/FX3/GX switches	628000 (Protocol learnt host)
	Nexus 9700-EX line cards	16000 (Hash Table: Shared between IPv6 ND and protocol learned IPv6 host)
	Nexus 9700-FX line cards	500,000 (protocol learned)
IPv4 LPM routes (internet-peering mode) Note The combined IPv4 and IPv6 route prefixes of internet-peer which was working in the internet-peering routing mode may not work forever because the global internet tables are growing. This occurs as hardware resource to accommodate IPv4 and IPv6 route prefixes do not change once the hardware/software is shipped.	Nexus 9300-EX/FX2 switches	1 Million (protocol learned)
	Nexus 9300-FX/FX3/GX switches	1256000 (protocol learnt)
	Nexus 9700-EX/FX line cards	1 Million (protocol learned)
IPv6 LPM routes (internet-peering mode) Note The combined IPv4 and IPv6 route prefixes of internet-peer which was working in the internet-peering routing mode may not work forever because the global internet tables are growing. This occurs as hardware resource to accommodate IPv4 and IPv6 route prefixes do not change once the hardware/software is shipped.	Nexus 9300-EX switches	500,000 (Prefix length 0-83) protocol learnt 1900 (Prefix length /84-127)
	Nexus 9300-FX2 switches	500,000 (protocol learnt)
	Nexus 9300-FX/FX3/GX switches	628224
	Nexus 9700-EX line cards	500,000 (Prefix length 48-83) protocol learnt 1900 (Prefix length /84-127)
	Nexus 9700-FX line cards	500,000 (Prefix length 48-128) protocol learnt
	Nexus 9500 switches with the FM-E2 fabric line cards	176,000 (Prefix length 0–47) protocol learnt host
	Nexus 9500 switches with the FM-G fabric line cards	500000
Routes (internet-peering mode)	Nexus 9600-R and 9600-RX line cards	1 Million ²⁵

Feature	Supported Platforms	Verified Limits
IPv4 routes (internet-peering mode)	Nexus 9600-R and 9600-RX line cards	852000 ²⁶
IPv6 routes (internet-peering mode)	Nexus 9600-R line cards	175000 ²⁷
Routes (internet-peering mode)	Nexus 9600-R line cards	852000
IPv4 routes (internet-peering mode)	Nexus 9600-R line cards	781000
IPv6 routes (internet-peering mode)	Nexus 9600-R line cards	71000
IPv4 ARP (internet peering mode)	Nexus 9300-EX switches and the Nexus 9700-EX/FX line cards	32000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host)
	Nexus 9300-FX/FX2/GX switches	32000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16000 over a SVI/VLAN (as the upper limit of the dynamic learnt MAC address in the "internet Peering" mode is 16000
	Nexus 9300-FX/FX3/GX switches	32000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16000 over a SVI/VLAN (as the upper limit of the dynamic learnt MAC address in the "internet Peering" mode is 16000
IPv6 ND (internet-peering mode)	Nexus 9300-EX switches and the Nexus 9700-EX/FX line cards	16000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host)
	Nexus 9300-FX2 switches	16000 (Hash Table: Shared between IPv6 ND, IPv4 ARP)
	Nexus 9300-FX3 switches and N9K-X9716D-GX line card	32000 over an L3 interface and 16384 over an SVI / VLAN (as the upper limit of the dynamically learnt MAC address upper limit in "Internet Peering" mode is 16384)
IS-ISv4 adjacencies (either L1, L2, or sum of L1 and L2 with default timers)	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and Nexus 9700-EX/FX and N9K-X9716D-GX line cards	255
IS-ISv4 BFD sessions (with default timers)	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and Nexus 9700-EX/FX and N9K-X9716D-GX line cards	255

Feature	Supported Platforms	Verified Limits
IS-ISv4 routes	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and Nexus 9700-EX/FX and N9K-X9716D-GX line cards	10000
IS-ISv4 network type	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX line cards	Point to point, broadcast
Groups with default timers (3s/10s) and multiple group optimizations. [There are 2 primary, one for IPv4 and the other for IPv6, and 7926 secondary]	X9636C-R/RX and X9636Q-R line cards	7928
Groups with aggressive timers (1s/3s) and multiple groups optimization. [There are 2 primary, one for IPv4 and the other for IPv6, and 7926 secondary] ²⁸	X9636C-R/RX and X9636Q-R line cards	7928
Groups per interface or I/ module	X9636C-R/RX and X9636Q-R line cards	Maximum 16 (Because 16 is the unique virtual MAC address limit)
OSPF/OSPFv3 LSA/LSDB size	Nexus 9600-R and 9600-RX line cards	250000
	Nexus 9300-FX3 switches	100000
OSPF/OSPFv3 areas	Nexus 9600-R and 9600-RX line cards	15
	Nexus 9300-FX3 switches and N9K-X9716D-GX line card	100
OSPFv2 neighbors	Nexus 9600-R, 9600-RX, N9K-X9716D-GX, and 9700-EX/FX line cards	1000
	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches	256
OSPFv3 neighbors	Nexus 9600-R, 9600-RX, N9K-X9716D-GX, and 9700-EX/FX line cards	1000
	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches	256
OSPF/OSPFv3 LSA/LSDB size	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	100000

Feature	Supported Platforms	Verified Limits
OSPF/OSPFv3 areas	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	100
Static routes	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	8000
VRFs	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
	Nexus 9600-R and 9600-RX line cards	3967
VRRP groups per interface or I/O module	Nexus 9364C, and 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	250
Policy-based routing (PBR)		
Configured sequences per policy	Nexus 9300-EX/FX/FX2/FX3 switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	128
Next-hop addresses per policy	Nexus 9300-EX/FX/FX2/FX3 switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	32
IPv4 ACEs (unidimensional)	Nexus 9300-EX/FX/FX2/FX3 switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	3582 (per network forwarding engine)
IPv6 ACEs (unidimensional)	Nexus 9300-EX/FX/FX2 switches	1792 (per network forwarding engine)
IPv4 and IPv6 ACEs	Nexus 9300-EX/FX/FX2 switches	1024 IPv4 + 128 IPv6
	Nexus 9700-EX/FX line cards	1024 IPv4
Interfaces with PBR policy	Nexus 9300-EX/FX/FX2/FX3 switches and the Nexus 9700-EX/FX line cards	512
	Nexus N9K-X9716D-GX line card	256
VRRPv3		
VRRPv3 groups per interface	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX /FX line cards	255
	Nexus N9K-X9716D-GX line card	250

Feature	Supported Platforms	Verified Limits
VRRPv3 groups with default timers (1 s)	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	490
	Nexus N9K-X9716D-GX line card	250
VRRPv3 groups with relaxed timers (3 s)	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	490
Pathways with one VRRPv3 group with default timer (1 s)	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	489
VRRPv3 groups and pathways combined	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	490
	Nexus N9K-X9716D-GX line card	250
ECMP		
ECMP Paths	Nexus 9300-EX/FX/FX2/FX3/FPX/GX switches and Nexus 9504/9508 switches with -R/RX line cards	64

²⁰ The limit of supported BFD sessions for each EoR line card is 128.

²¹ If you have more than 490 groups, then only one group per SVI. SVIs cannot have a user defined MAC or any VRRP group with it.

²² If you have more than 490 groups, then only one group per SVI. SVIs cannot have a user defined MAC or any VRRP group with it.

²³ The hash table is subject to collisions. Depending on the host route pattern, collisions might occur.

²⁴ The hash table is subject to collisions. Depending on the host route pattern, collisions might occur.

²⁵ Contains internet peering profile with additional IPv4 and IPv6 routes.

²⁶ Internet profile with additional IPv4 routes (total of 914K routes consisting of IPv4 and 62K of IPv6)

²⁷ Internet profile with additional IPv6 routes (total of 871K routes consisting of IPv6 and 696K of IPv4)

²⁸ If the user has Multi-protocol configuration, user should configure appropriate CoPP policies to avoid any control plane traffic drops.

The maximum number of PBR next-hops based on 4 FM-E supported is 192 per slice of the forwarding engine



Note

- The IPv4/IPv6 host routes and the IPv4 multicast routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
- The IPv4 and IPv6 unicast routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
- High availability (graceful restart and stateful switchover) is not supported when unicast or multicast aggressive timers are configured at any scale.

Guidelines and Limitations for OSPF Verified Scalability Limits

- To achieve the highest scale, we recommend that you use a single OSPF instance instead of multiple instances.

- Each OSPFv2 and OSPFv3 scale value might vary when combined with other parameters.
- The graceful restart timeout value might be increased in multidimensional scenarios.

Table 21: PVLAN VXLAN Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
Primary VLANs	Nexus 9300-EX/FX/FX2/FX3 switches	16
Secondary VLANs	Nexus 9300-EX/FX/FX2/FX3 switches	20
Ports in community host mode	Nexus 9300-EX/FX/FX2/FX3 switches	40
Port in Isolated host mode	Nexus 9300-EX/FX/FX2/FX3 switches	40
Ports in isolated trunk mode	Nexus 9300-EX/FX/FX2/FX3 switches	40
Ports in promiscuous mode	Nexus 9300-EX/FX/FX2/FX3 switches	5
PVLANs allowed on a PVLAN port	Nexus 9300-EX/FX/FX2/FX3 switches	16

Table 22: VXLAN Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limits
IGMP snooping over VXLAN		
VXLAN VLANs	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
VTEP Peers ²⁹	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus Nexus 9600-R, 9600-RX, 9700-EX/FX, and N9K-X9716D-GX line cards	512
Underlay multicast groups	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	128
Multi-Site 30		
Asymmetric VNIs per peer	Nexus 9332C, 9364C, 9300-EX/FX/FX2/FXP switches and Nexus 9700-EX/FX line cards	4000
Number of Tunnel Encryption sessions	Nexus 9300, N9336C-FX2, N93240YC-FX2, N93360YC-FX2, N93216TC-FX2	128 ³¹
Number of BGWs per site for Secure VXLAN EVPN Multi-Site using CloudSec	N9336C-FX2, N93240YC-FX2, N93360YC-FX2, N93216TC-FX2 switches	6 per 10 sites

Feature	Supported Platforms	Verified Limits
Number of sites	Nexus 9300-EX/FX/FX2/FX3/GX, 9332C, 9364C, 9500 switches and the Nexus 9700-EX/FX line cards	25
Number of sites for Secure VXLAN EVPN Multi-Site using CloudSec	Nexus 9300-FX2 switches	10
Number of sites for TRM	Nexus 9300-EX/FX/FX2/FX3/GX, 9332C, 9364C, switches and the Nexus 9700-EX/FX line cards	15 sites
Number of BGWs per site ³²	Nexus 9332C and 9364C switches and the Nexus 9700-EX/FX line cards	2 (Anycast), 2(vPC)
	Nexus 9300-EX/FX/FX2/FX3/GX switches	6 (Anycast), 2 (vPC)
Number of BGWs per site with TRM enabled ³³	Nexus 9332C, 9364C, 9500 switches and the Nexus 9700-EX/FX line cards	2 (Anycast), 2 (vPC)
	Nexus 9300-EX/FX/FX2/FX3/GX switches	6 (Anycast), 2 (vPC)
Number of BGWs for TRM	Nexus 9300-EX/FX/FX2/FX3/GX, 9332C, 9364C, switches and the Nexus 9700-EX/FX line cards	06 BGW
Number of Secure VXLAN EVPN Multi-Site using CloudSec sessions	Nexus 9300-FX2 switches	128 ³⁴
Multisite-PIP ECMP	Nexus 9300-FX2 switches	1000 ³⁵
VTEPs per Site	Nexus 9300-EX/FX/FX2/FX3, switches and the Nexus 9700-EX/FX line cards	256
Tenant Route Multicast Layer 3 Mode with VXLAN BGP eVPN		
VXLAN Layer 2 VNI	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	1000
VXLAN Layer 3 VNI/VRFs	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	250
VTEP Peers	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	256
Underlay Multicast Group (PIM ASM Underlay)	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	128 ³⁶
Overlay Multicast Group (PIM ASM & PIM SSM)	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9700-EX/FX line cards	7200 ³⁷
VXLAN Flood and Learn		

Feature	Supported Platforms	Verified Limits
Virtual network identifiers (VNIs) or VXLAN-mapped VLANs	Nexus 9300-EX/FX/FX2/FX3 switches	2000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Underlay multicast groups	Nexus 9300-EX/FX/FX2/FX3 switches	128
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
Overlay MAC addresses	Nexus 9300-EX/FX switches	90000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
	Nexus 9300-FX2/FX3 switches	60000
Remote VXLAN tunnel endpoints (VTEPs Multicast)	Nexus 9300-EX/FX/FX2/FX3, 9364C-EX switches	512
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
Ingress replication peers 38	Nexus 9300-EX/FX/FX2/FX3 switches	512
	Nexus N9K-X9716D-GX line card	
Ingress replication Layer 2 VNIs	Nexus 9300-EX/FX/FX2/FX3 switches	1000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
MAC addresses for ingress replication	Nexus 9300-EX/FX/FX2/FX3 switches	90000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Port VLAN translations under an interface	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	100
	Nexus 9300-EX/FX/FX2/FX3 switches	3967
Port VLAN translations in a switch	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	2000
	Nexus 9300-EX/FX/FX2/FX3 switches	24,000
Static MAC addresses pointing to a remote VTEP	Nexus 9300-EX/FX/FX2/FX3 switches	1000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	

Feature	Supported Platforms	Verified Limits
VXLAN VLANs per FEX port (host interface)	Nexus 9300-FX3 switches	75
	Nexus 93180YC-EX	75 ³⁹
Layer 2 routed VNIs for vPC-centralized gateway	Nexus 9300-EX/FX/FX2/FX3 switches	450
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
IGMP groups	Nexus 9300-EX/FX/FX2/FX3 switches	8192
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	
Port Multi-VLAN Mapping ⁴⁰	Nexus 9300-FX2	510 ⁴¹
	Nexus 9300-EX/FX	368 ⁴²
VXLAN BGP eVPN		
Layer 2 VNIs	Nexus 9300-GX switches and the Nexus 9600-R and 9600-RX line cards	2000
	Nexus 9300-EX/FX/FX2/FX3 switches	2000, 4000 (with no Layer 3 VNIs)
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Xconnect VLANs	Nexus 9332C, 9300-EX/FX/FX2/FX3/GX switches	40
SVI with Distributed Anycast Gateway; Layer 2 VNI extended	Nexus 9300-EX switches	2000 ⁴³
	Nexus 9300-FX/FX2/FX3/GX switches	2000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Layer 3 VNIs / VRFs ⁴⁴	Nexus 9300-EX/FX/FX2/FX3/GX switches and the Nexus 9600-R and 9600-RX line cards	900
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	750
Underlay multicast groups	Nexus 9300-EX/FX/FX2/FX3/GX, switches and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	128
VTEPs	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9600-R, 9600-RX, and 9700-EX/FX and N9K-X9716D-GX line cards	512

Feature	Supported Platforms	Verified Limits
MAC addresses	Nexus 9300-EX/FX/FX2/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	90000
	Nexus 9300-FX3 switches	90000
	Nexus 92348GC-X switches	97000
Port VLAN translations under an interface	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	100
	Nexus 9300-EX/FX/FX2/FX3/GX switches	3967
Port VLAN translations in a switch	Nexus 9300-GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	2000
	Nexus 9300-EX/FX/FX2/FX3/GX switches	24,000
IPv4 host routes	Nexus 92348GC-X switches	16000
	Nexus 9300-EX switches	458000
	Nexus 9300-FX/FX2/FX3/GX switches	471000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	656000
	Nexus 9600-R and 9600-RX line cards	128000
IPv6 host routes	Nexus 9300-EX switches	24000
	Nexus 9300-FX/FX2/FX3/GX switches	265000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	34000
	Nexus 9600-R and 9600-RX line cards	32000
Overlay IPv4 LPM routes	Nexus 9300-EX switches	458000
	Nexus 9300-FX/FX2/FX3/GX switches	471000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	656000
Overlay IPv6 LPM routes	Nexus 9300-EX switches	206000 ⁴⁵
	Nexus 9300-FX/FX2/FX3/GX switches	265000 ⁴⁶
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	174000 ⁴⁷

Feature	Supported Platforms	Verified Limits
VXLAN VLANs per FEX port (host interface)	Nexus 9300-FX3 switches	75
IGMP groups	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	8192
VXLAN BGP eVPN Ingress Replication		
Layer 2 VNIs	Nexus 9300-EX/FX/FX2/FX3/GX switches	2000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Xconnect VLANs	Nexus 9300-EX/FX/FX2/FX3/GX switches	40
Selective Qinq with multiprovider tag	Nexus 93180YC-EX, 93180YC-FX, 9336C-FX2, and 9300-FX3 switches	4000 mappings, 10 provider VLANs; System wide: 48,000 mappings, 512 Provider VLANs
SVI with Distributed Anycast Gateway; Layer 2 VNI extended	Nexus 9300-EX switches	2000 ⁴⁸
	Nexus 9300-FX/FX2/FX3/GX switches	2000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	1000
Layer 3 VNIs / VRFs ⁴⁹	Nexus 9300-EX/FX/FX2/FX3/GX switches	900
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	750
VTEPs	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	512
MAC addresses	Nexus 9300-EX/FX/FX2/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	90000
	Nexus 9300-FX3 switches	90000
IPv4 host routes	Nexus 9300-EX switches	458000
	Nexus 9300-FX/FX2/FX3/GX switches	471000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	656000

Feature	Supported Platforms	Verified Limits
IPv6 host routes	Nexus 9300-EX switches	24000
	Nexus 9300-FX/FX2/GX switches	265000
	Nexus 9300-FX3 switches	500000
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	34000
Overlay IPv4 LPM routes	Nexus 9300-EX switches	458000
	Nexus 9300-FX/FX2/FX3/GX switches	471500
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	656000
Overlay IPv6 LPM routes	Nexus 9300-EX switches	206000 ⁵⁰
	Nexus 9300-FX/FX2/FX3/GX switches	265000 ⁵¹
	Nexus 9700-EX/FX and N9K-X9716D-GX line cards	174,000 ⁵²
VXLAN VLANs per FEX port (host interface)	Nexus 9300-FX3 switches	75
IGMP groups	Nexus 9300-EX/FX/FX2/FX3/GX switches, and the Nexus 9700-EX/FX and N9K-X9716D-GX line cards	8192
VXLAN and IP-in-IP Tunneling		
IP-in-IP tunnels	Nexus 9300-FX2 switches	16
VXLAN Static Tunnels		
VNIs	Nexus 9300-EX/FX/FX2/FX3/GX, and 9364C switches	100
VRFs	Nexus 9300-EX/FX/FX2/FX3, and 9364C switches	100
VTEP peers	Nexus 9300-EX/FX/FX2/FX3, and 9364C switches	256
V4 routes	Nexus 9300-EX/FX/FX2/FX3/GX, and 9364C switches	10000

²⁹ In case of IR, each VNI can have a max of 64 peers.

³⁰ All the other BGW numbers (number of supported L2VNIs, L3VNIs, MAC addresses, IP addresses, and so on) match the values supported on a generic VXLAN EVPN VTEP node.

³¹ Total number of Cloudsec Security Associations in hardware = 128 (M * N * L) where (M = no. of Cloudsec peers, N = no. of uplinks on each Cloudsec endpoint, L is number of border gateway nodes)

- 32 Multi-Site enabled with TRM supported number of L2VNIs –1000 and L3VNIs –100. Maximum supported multicast underlay and overlay route is 8000.
- 33 Multi-Site enabled with TRM supported number of L2VNIs –1000 and L3VNIs –100. Maximum supported multicast underlay and overlay route is 8000.
- 34 Total number of Cloudsec Security Associations in hardware = 128 (M *N*L) where (M = no. of Cloudsec peers, N = no. of uplinks on each Cloudsec endpoint, L is number of border gateway nodes)
- 35 Number of vrfs * number of sites = 1000
- 36 VXLAN underlay and overlay multicast routes shares the same hardware table. Maximum Multicast routes is 8000 in the default mode. If you want more overlay route scale, reduce the underlay multicast control group.
- 37 VXLAN underlay and overlay multicast routes shares the same hardware table. Maximum Multicast routes is 8000 in the default mode. If you want more overlay route scale, reduce the underlay multicast control group.
- 38 In case of IR, each VNI can have a maximum number of 64 peers; 512 peers supported on 100 VNIs only.
- 39 This is the limit for the Cisco Nexus 93180YC-EX and other fiber based switches. All copper based 9300-EX switches are not applicable.
- 40 Only one provider VLAN is supported.
- 41 The maximum number of Layer-2 subinterfaces is based on the available entries allocated for ing-pacl-sb team region.
- 42 Since Nexus 9300-EX and 9300-FX have only one slice, the maximum number of Layer-2 subinterfaces that can be created is lower than the limit for NEXus 9300-FX2.
- 43 Only 1900 SVI are supported if dual stack is used/IPv6 is used.
- 44 ECMP objects are not shared across multiple VRFs.
- 45 All /64 routes + 4000 for non /64 routes.
- 46 All /64 routes + 4000 for non /64 routes.
- 47 All /64 routes + 4000 for non /64 routes.
- 48 Only 1900 SVI are supported if dual stack is used/IPv6 is used.
- 49 ECMP objects are not shared across multiple VRFs.
- 50 All /64 routes + 4000 for non /64 routes.
- 51 All /64 routes + 4000 for non /64 routes.
- 52 All /64 routes + 4000 for non /64 routes.

Table 23: Tetration Verified Scalability Limits (Unidimensional)

Feature	Supported Platforms	Verified Limit
TCAM size	Nexus 92160YC-X, 9300-EX/FX switches	1024 entries
	Nexus 92160YC-X switches	IPv4 –4 entries per rule (TCP, UDP, ICMP, and IP)
	Nexus 9300-EX/FX switches	IPv4 –2 entries per rule (ICMP and IP)
	Nexus 92160YC-X switches	IPv6 –8 entries per rule (4 entries per ICMP and IPv6 for a total of 8 entries)
	Nexus 9300-EX/FX switches	IPv6 –8 entries per rule (4 entries per ICMP and IPv6 for a total of 8 entries)
	Nexus 92160YC-X, 9300-EX/FX switches	24 entries out of 1000 is consumed for default.
TCAM	Nexus 92160YC-X switches	250 (IPv4) or 62 (IPv6)
	Nexus 9300-EX/FX switches	500 (IPv4) or 125 (IPv6)

The entire Cisco Tetration Analytics documentation set is available at the following URL:
<https://www.cisco.com/c/en/us/support/data-center-analytics/tetration-analytics/tsd-products-support-series-home.html>

Verified Scalability Limits - Multidimensional

The tables in this section list the verified scalability limits for the Cisco Nexus 9000 Series platform switches. These limits are validated with a multidimensional configuration. The values provided in these tables focus on the scalability of all listed features at the same time.

For each corresponding feature, the number given is the absolute maximum currently supported in this release. If the hardware is capable of a higher scale, future software releases might increase this verified maximum limit. Results might differ from the values listed here when trying to achieve maximum scalability with multiple features enabled.



Note These numbers are not the maximum verified values if each feature is viewed in isolation. For these numbers, see the corresponding "Verified Scalability Limits" section.

Table 24: eBGP/IS-IS Profile Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
Number of 100G ports	288
ECMP	16-way (Upstream)
BGP neighbors	960
BGP IPv4 /32 unicast routes	30,000
BGP IPv4 VLSM unicast routes	18,000
BGP IPv6 /128 unicast routes	16,000
BGP IPv6 VLSM unicast routes	1000
IS-IS v2 neighbors	255
IS-IS v3 neighbors	255
IS-IS Layer 2 adjacency	16
IS-IS IPv4 /32 unicast routes	20,000
IS-IS IPv4 VLSM unicast routes	1000
IS-IS IPv6 /128 unicast routes	20,000
IS-IS IPv6 VLSM unicast routes	1000
BFD sessions	272
PIM neighbors	256

Feature	Verified Limits
ACL ACEs	15,000 500
Sub-interfaces	712
SPAN sessions	1 local SPAN session
Multicast SSM	20,000

Table 25: iBGP/OSPF Profile Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
Number of 100G ports	180
Number of 40G ports	108
ECMP	8-way (Upstream)
BGP neighbors	8
BGP IPv4 VLSM unicast routes	40,000
BGP IPv6 VLSM unicast routes	10,000
OSPFv2 neighbors	108
OSPFv3 neighbors	30
OSPF IPv4 /32 unicast routes	100,000
OSPF IPv4 VLSM unicast routes	155,000
OSPFv3 IPv6 /128 unicast routes	1000
OSPFv3 IPv6 VLSM unicast routes	9000
BFD sessions	108
VRF	250
PIM neighbors	108
IPv4 (*,G) multicast routes	2000
IPv4 (S,G) multicast routes	10,000
ACL ACEs	500 (IPv4) 500 (IPv6)
SPAN sessions	1 local SPAN session

Table 26: iBGP/EIGRP Profile Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
Number of 100G ports	180
Number of 40G ports	108
ECMP	16-way (Upstream)
BGP neighbors	8
BGP IPv4 VLSM unicast routes	40,000
BGP IPv6 VLSM unicast routes	10,000
EIGRP v4 neighbors	276
EIGRP v6 neighbors	276
EIGRP IPv4 /32 unicast routes	30,000
EIGRP IPv4 VLSM unicast routes	1000
EIGRP IPv6 /128 unicast routes	30,000
EIGRP IPv6 VLSM unicast routes	1000
BFD sessions	276
VRF	250
PIM neighbors	276
IPv4 (*,G) multicast routes	6000
IPv4 (S,G) multicast routes	16,000
ACL ACEs	500 (IPv4) 500 (IPv6)
SPAN sessions	1 local SPAN session

Table 27: MPLS Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
MPLS L3VPN	3967
VPE	3967
PE nodes	3
PE routes	20,000
X9636C-RX line card: ACL scale-IPv4	95,000

Feature	Verified Limits
X9636C-RX line card: ACL scale-IPv6	20,000
HSRP, HSRP VIP	3967 each for v4 and v6
vPC uRPF	3967
Strict uRPF	Yes
VRF	3967
SVI	3967
Layer 3 VPN routes IP ECMP	2000
MPLS LSR ECMP	2000
VPNv4 routes	400,000
VPNv6 routes	90,000
EBGP neighbors	750

Table 28: Layer 2/Layer 3 Boundary Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
MAC addresses	19,000
Number of sub-interfaces	500
vPC Port channels	46
ECMP	16-way (Upstream)
OSPFv2 neighbors	47
OSPFv3 neighbors	47
OSPF IPv4 /32 unicast routes	45,000
OSPF IPv4 VLSM unicast routes	1000
OSPF IPv6 /128 unicast routes	20,000
OSPF IPv6 VLSM unicast routes	1000
BFD sessions	49
VRF	250
VLAN	3750
SVI	3750

Feature	Verified Limits
VRRP v4 groups	1996 VRRS / 4 VRRPv3
VRRP v6 groups	1996 VRRS / 4 VRRPv3
HSRP IPv4	1743 Secondary groups / 7 Primary groups
HSRP IPv6	1743 Secondary groups / 7 Primary groups
PIM neighbors	396
IPv4 (*,G) multicast routes	3080
IPv4 (S,G) multicast routes	26,600
IGMP snooping database entries	6400
sFlow enabled interfaces	83
UDLD enabled interfaces	93
SPAN sessions	1 local SPAN session

Table 29: Segment Routing Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
VLAN	100
SVI	100
MAC entries	10,000
ARP entries	70
HSRPv4 VIPs	100
HSRpv6 VIPs	100
LACP	11
LACP members	4
eBGP IPv6 neighbors	9
eBGP IPv4 LU neighbors	9
IPv4 (LU) routes	6888
IPv4 (LU) paths	17580
IPv6 routes	6663
IPv4 (LU) routes	17,338

Feature	Verified Limits
SR ECMP	18 (dual-homed)
MPLS HW entries	11,957

Table 30: VXLAN Profile Verified Scalability Limits (Multidimensional)

Feature	Verified Limits
Ports	16
ECMP	8-way (Upstream)
BGP neighbors	200
BGP EVPN Layer 2 VPN host routes	64,000
BGP IPv4 VLSM unicast routes or OSPF	10,000
BGP IPv6 VLSM unicast routes or OSPF	6000
BFD sessions	20
PIM neighbors	20
IPv4 (*, G) multicast routes (co-existing)	4000
IPv4 (S,G) multicast routes (co-existing)	2000
Layer 3 VNI	900
Layer 2 VNI	2000
Local VTEP	1
Remote VTEPs	256
VLAN	3600
SVI	900
MAC	90,000

Deployment Case Studies

This section provides sample topologies for some common deployments. For each topology, the scalability numbers are the limits with all of the listed features enabled at the same time.



Attention These numbers are not the maximum verified values if each feature is viewed in isolation. For these numbers, see the "Verified Scalability Limits" section.

VXLAN BGP/eVPN iBGP Centric Topology

This VXLAN BGP/eVPN iBGP centric topology consists of Cisco Nexus 9300 and 9500 Platform switches acting as VXLAN vPC tunnel endpoints (VTEPs) and VXLAN non-vPC VTEPs. VXLAN VTEPs establish iBGP sessions to a Cisco Nexus 9508 switch (route reflector) acting as a spine node. VXLAN-distributed anycast gateway SVIs are configured for dual stack, and the traffic is dual stack.

The focus of this topology is to test VXLAN overlay network scale and underlay Layer 2 switching and other routing, multicast, and Layer 4 through Layer 7 features for management and operations. Underlay PIM neighbors and IS-IS adjacency were tested with the default timer and Bidirectional Forwarding Detection (BFD) enabled on all links.

In the following table, the Verified Limit column lists the verified scaling capabilities with all listed features enabled at the same time. These numbers are not the maximum verified values if each feature is viewed in isolation.

Table 31: VXLAN BGP/eVPN iBGP Centric Topology

Feature	Supported Platform	Verified Limit
System Routing Template	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	default
	Nexus 9364C switches	Not applicable
VXLAN VTEPs	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	128
VXLAN Layer 2 VNIs	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	2000
VXLAN Layer 3 VNIs/VRFs	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	500
VXLAN multicast groups	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	128
VXLAN overlay MAC addresses	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	64,000
VXLAN overlay IPv4 host routes	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	60,000
VXLAN overlay IPv6 host routes	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	16,000
	Nexus 9364C switches	Not applicable

Feature	Supported Platform	Verified Limit
VXLAN overlay IGMP Snooping groups	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C and 9500 switches and the X9700-EX/FX line cards	1000
VXLAN IPv4 LPM routes	Nexus 9200, 9300-EX, 9300-FX, and 9364C switches and the X9700-EX/FX line cards	5120
VXLAN IPv6 LPM routes	Nexus 9200, 9300-EX, and 9300-FX switches and the X9700-EX/FX line cards	1500
	Nexus 9364C switches	Not applicable
VXLAN VLAN logical port VP count	Nexus 9364C switches	Not applicable
VLANs on VTEP node	Nexus 9200, 9300, 9300-EX, 9300-FX, 9364C, and 9500 switches and the X9700-EX/FX line cards	1700 (total VLANs) 1500 (VXLAN VLANs) 200 (non-VXLAN VLANs)
MST instances	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	20
	Nexus 9364C switches	Not applicable
STP logical ports	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	3500
	Nexus 9364C switches	Not applicable
vPC port channels	Nexus 9200, 9300, 9300-EX, and 9300-FX switches and the X9700-EX/FX line cards	40
	Nexus 9364C switches	Not applicable
Underlay IS-IS neighbors	Nexus 9200, 9300, 9300-EX, and 9300-FX switches and the X9700-EX/FX line cards	32
	Nexus 9364C switches	Not applicable
Underlay PIM neighbors	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	12
	Nexus 9364C switches	Not applicable
Underlay HSRP groups for regular VLANs	Nexus 9364C switches	Not applicable

Feature	Supported Platform	Verified Limit
Underlay vPC SVIs	Nexus 9200, 9300, 9300-EX, 9300-FX, and 9500 switches and the X9700-EX/FX line cards	200
	Nexus 9364C switches	Not applicable

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS REFERENCED IN THIS DOCUMENTATION ARE SUBJECT TO CHANGE WITHOUT NOTICE. EXCEPT AS MAY OTHERWISE BE AGREED BY CISCO IN WRITING, ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS DOCUMENTATION ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED.

The Cisco End User License Agreement and any supplemental license terms govern your use of any Cisco software, including this product documentation, and are located at: <http://www.cisco.com/go/softwareterms>. Cisco product warranty information is available at <http://www.cisco.com/go/warranty>. US Federal Communications Commission Notices are found here <http://www.cisco.com/c/en/us/products/us-fcc-notice.html>.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any products and features described herein as in development or available at a future date remain in varying stages of development and will be offered on a when-and if-available basis. Any such product or feature roadmaps are subject to change at the sole discretion of Cisco and Cisco will have no liability for delay in the delivery or failure to deliver any products or feature roadmap items that may be set forth in this document.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com go trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2021 Cisco Systems, Inc. All rights reserved.