



R Commands

- radius-server deadtime, on page 6
- radius-server directed-request, on page 7
- radius-server host key 0 6 7, on page 8
- radius-server host test, on page 10
- radius-server key 0 6 7, on page 11
- radius-server retransmit, on page 12
- radius-server test, on page 13
- radius-server timeout, on page 14
- random-detect, on page 15
- random-detect2 minimum-threshold2 maximum-threshold2, on page 17
- random-detect2 non-ecn minimum-threshold2 maximum-threshold2 drop, on page 18
- random-detect, on page 19
- random-detect cos-based, on page 21
- rate-limit, on page 23
- rate-limit cpu direction input output both pps action log, on page 24
- rate-limit cpu direction input output both pps action log, on page 25
- rate-limit packet_in burst, on page 26
- rate-limit packet_in burst, on page 27
- rd, on page 28
- rd auto, on page 29
- rd auto, on page 30
- rd dual, on page 31
- read-only, on page 32
- read-only, on page 33
- receiver, on page 34
- receiver, on page 35
- reconnect-interval, on page 36
- record, on page 37
- record, on page 38
- record, on page 39
- record, on page 40
- record, on page 41
- record, on page 42

- record, on page 43
- record, on page 44
- record netflow-original, on page 45
- record netflow, on page 46
- record netflow, on page 47
- record netflow, on page 48
- record netflow protocol-port, on page 49
- redistribute filter route-map, on page 50
- redistribute filter route-map, on page 51
- redistribute maximum-prefix, on page 52
- redistribute maximum-prefix, on page 53
- redistribute maximum-prefix, on page 54
- redistribute maximum-prefix, on page 55
- redistribute maximum-prefix, on page 56
- redistribute route-map, on page 57
- redundancy-group, on page 58
- reference-bandwidth, on page 59
- reference-bandwidth, on page 60
- region, on page 61
- register-database-mapping, on page 62
- register-route-notifications, on page 63
- reload, on page 64
- reload cancel, on page 65
- reload in, on page 66
- reload module, on page 67
- reload module force-dnld, on page 68
- reload non-interruptive, on page 69
- reload sync-adjacency, on page 70
- reload timer, on page 71
- reload vdc, on page 72
- reload vdc, on page 73
- remark, on page 74
- remark, on page 75
- remark, on page 76
- remote-as, on page 77
- remote-span, on page 78
- remove-private-as, on page 79
- replay-protection, on page 80
- report, on page 81
- report, on page 82
- report, on page 83
- report, on page 84
- report, on page 85
- report, on page 86
- report, on page 87
- request-data-size, on page 88

- request-data-size, on page 89
- request-data-size, on page 90
- resequence access, on page 91
- reset, on page 92
- reset, on page 93
- reset, on page 94
- reset, on page 95
- reset, on page 96
- reset, on page 97
- reset, on page 98
- restart amt, on page 99
- restart bgp, on page 100
- restart eigrp, on page 101
- restart fabric_mcast, on page 102
- restart fabricpath domain, on page 103
- restart igmp, on page 104
- restart isis, on page 105
- restart mld, on page 106
- restart msdp, on page 107
- restart ospf, on page 108
- restart ospfv3, on page 109
- restart otv-isis, on page 110
- restart pim, on page 111
- restart pim6, on page 112
- restart rip, on page 113
- resync-database, on page 114
- retain route-target all, on page 115
- retain route-target all, on page 116
- retransmit-interval, on page 117
- retransmit-interval, on page 118
- retransmit-interval, on page 119
- reverse, on page 120
- reverse, on page 121
- revision, on page 122
- revocation-check, on page 123
- rewrite-evpn-rt-asn, on page 124
- rewrite-rt-asn, on page 125
- rfc1583compatibility, on page 126
- rib verification-report, on page 127
- rip shutdown, on page 128
- rmdir, on page 129
- rmon alarm absolute rising-threshold falling-threshold, on page 130
- rmon event, on page 131
- rmon hcalarm absolute startupalarm rising-threshold falling-threshold owner, on page 132
- roaming-eid-prefix, on page 133
- role feature-group name, on page 134

- [role name](#), on page 135
- [role priority](#), on page 136
- [rollback configuration to](#), on page 137
- [rollback running-config checkpoint](#), on page 138
- [root-priority](#), on page 139
- [route-map](#), on page 140
- [route-map](#), on page 141
- [route-map](#), on page 142
- [route-map](#), on page 143
- [route-map out](#), on page 144
- [route-map pbr-statistics](#), on page 145
- [route-reflector-client](#), on page 146
- [route-reflector-client](#), on page 147
- [route-target both](#), on page 148
- [route-target both auto](#), on page 149
- [route-target both auto](#), on page 150
- [route-target export](#), on page 151
- [route-target export](#), on page 152
- [route-target export auto](#), on page 153
- [route-target import](#), on page 154
- [route-target import](#), on page 155
- [route-target import auto](#), on page 156
- [route](#), on page 157
- [router-guard ip multicast](#), on page 159
- [router-guard ip multicast switchports](#), on page 160
- [router-guard ipv6 multicast](#), on page 161
- [router-guard ipv6 multicast switchports](#), on page 162
- [router-id](#), on page 163
- [router-id](#), on page 164
- [router-id](#), on page 165
- [router-id](#), on page 166
- [router-id](#), on page 167
- [router-id](#), on page 168
- [router-preference maximum](#), on page 169
- [router bgp](#), on page 170
- [router eigrp](#), on page 171
- [router isis](#), on page 172
- [router ospf](#), on page 173
- [router ospfv3](#), on page 174
- [router rip](#), on page 175
- [routing-context vrf](#), on page 176
- [rsakeypair](#), on page 177
- [rtr etr eid](#), on page 178
- [rule](#), on page 179
- [rule command](#), on page 180
- [rule oid](#), on page 181

- [run-script](#), on page 182
- [run2 guestshell](#), on page 183
- [run bash](#), on page 184
- [run cid](#), on page 185

radius-server deadtime

[no] radius-server deadtime <i0>

Syntax Description

no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
deadtime	duration for which non-reachable server is skipped
<i>i0</i>	Length of time, in minutes

Command Mode

- /exec/configure

radius-server directed-request

[no] radius-server directed-request

Syntax Description

no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
directed-request	enable direct authentication requests to server

Command Mode

- /exec/configure

radius-server host key 0 6 7

```
{ { [ no ] radius-server host <hostipname> { { key { 0 <s0> | 6 <s6> | 7 <s1> | <s2> } [ pac ] { [ auth-port
<i0> ] [ acct-port <i1> ] } } | { [ auth-port1 <i2> ] [ acct-port1 <i3> ] } } { [ authentication [ accounting [
timeout <i4> ] [ retransmit <i5> ] ] } | { [ accounting1 [ timeout1 <i6> ] [ retransmit1 <i7> ] ] } } | no
radius-server host <hostipname> key } }
```

Syntax Description

<i>key</i>	0
no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
host	RADIUS server's DNS name or its IP address
<i>hostipname</i>	IPV4/IPV6 address or DNS name
key	RADIUS shared secret
pac	(Optional) Secure Radius Enable
0	RADIUS shared secret(clear text)
<i>s0</i>	RADIUS shared secret(clear text)
accounting	(Optional) Use for accounting
retransmit	(Optional) RADIUS server retransmit count
<i>i5</i>	(Optional) RADIUS server retransmit count
timeout	(Optional) RADIUS server timeout period in seconds
<i>i4</i>	(Optional) RADIUS server timeout period in seconds
retransmit1	(Optional) RADIUS server retransmit count
<i>i7</i>	(Optional) RADIUS server retransmit count
auth-port	(Optional) RADIUS server's port for authentication
<i>i0</i>	(Optional) port number
timeout1	(Optional) RADIUS server timeout period in seconds
<i>i6</i>	(Optional) RADIUS server timeout period in seconds
acct-port	(Optional) RADIUS server's port for accounting
<i>i1</i>	(Optional) port number
accounting1	(Optional) Use for accounting

authentication	(Optional) Use for authentication
6	Radius shared secret(type-6 encrypted)
<i>s6</i>	Tadius shared secret(encrypted)
7	RADIUS shared secret(encrypted)
<i>s1</i>	RADIUS shared secret(encrypted)
auth-port1	(Optional) RADIUS server's port for authentication
<i>i2</i>	(Optional) port number
<i>s2</i>	RADIUS shared secret(clear text)
acct-port1	(Optional) RADIUS server's port for accounting
<i>i3</i>	(Optional) port number

Command Mode

- /exec/configure

radius-server host test

```
[no] radius-server host { <hostipname> } test { { username <s0> { [ password { <s1> | 0 <s2> | 7 <s7> } [
idle-time <i1> ] ] | [ idle-time <i1> ] } } | { password { <s1> | 0 <s2> | 7 <s7> } [ idle-time <i1> ] } | { idle-time
<i1> } } }
```

Syntax Description

<i>username</i>	<s0>
no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
host	RADIUS server's DNS name or its IP address
<i>hostipname</i>	IPV4/IPV6 address or DNS name
test	Parameters to send test packets
<i>s0</i>	user name
password	(Optional) user password in test packets
<i>s1</i>	(Optional) user password
0	(Optional) RADIUS shared secret(clear text)
<i>s2</i>	(Optional) RADIUS shared secret(clear text)
7	(Optional) RADIUS shared secret(encrypted)
<i>s7</i>	(Optional) RADIUS shared secret(encrypted)
idle-time	(Optional) time interval for monitoring the server
<i>i1</i>	(Optional) time period in minutes

Command Mode

- /exec/configure

radius-server key 0 6 7

```
{ { [ no ] radius-server key { 0 <s0> | 6 <s6> | 7 <s1> | <s2> } } | { no radius-server key } }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
key	Global RADIUS server shared secret
0	default RADIUS shared secret(clear text)
<i>s0</i>	default RADIUS shared secret(clear text)
6	default RADIUS shared secret(type-6 encrypted)
<i>s6</i>	default RADIUS shared secret(type-6 encrypted)
7	default RADIUS shared secret(encrypted)
<i>s1</i>	default RADIUS shared secret(encrypted)
<i>s2</i>	default RADIUS shared secret(clear text)

Command Mode

- /exec/configure

radius-server retransmit

[no] radius-server retransmit <i0>

Syntax Description

no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
retransmit	Global RADIUS server retransmit count
<i>i0</i>	Global RADIUS server retransmit count

Command Mode

- /exec/configure

radius-server test

```
[no] radius-server test { { username <s0> { [ password { <s1> | 0 <s2> | 7 <s7> } [ idle-time <i1> ] ] | [ idle-time <i1> ] } } | { password { <s1> | 0 <s2> | 7 <s7> } [ idle-time <i1> ] } | { idle-time <i1> } }
```

Syntax Description

<i>username</i>	<s0>
no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
test	Parameters to send test packets
<i>s0</i>	user name
password	(Optional) user password in test packets
<i>s1</i>	(Optional) user password
0	(Optional) RADIUS shared secret(clear text)
<i>s2</i>	(Optional) RADIUS shared secret(clear text)
7	(Optional) RADIUS shared secret(encrypted)
<i>s7</i>	(Optional) RADIUS shared secret(encrypted)
idle-time	(Optional) time interval for monitoring the server
<i>i1</i>	(Optional) time period in minutes

Command Mode

- /exec/configure

radius-server timeout

[no] radius-server timeout <i0>

Syntax Description

no	(Optional) Negate a command or set its defaults
radius-server	Configure RADIUS related parameters
timeout	Global RADIUS server timeout period in seconds
<i>i0</i>	RADIUS server timeout period in seconds

Command Mode

- /exec/configure

random-detect

```
[no] random-detect { cos <cos-list> [ minimum-threshold ] { <min-thresh> [ packets | bytes | kbytes | mbytes
| ms | us ] | percent <min-percent-of-qsize> } [ maximum-threshold ] { <max-thresh> [ packets1 | bytes1 |
kbytes1 | mbytes1 | ms1 | us1 ] | percent1 <max-percent-of-qsize> } }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
random-detect	Configure WRED parameters
cos	Parameters for each cos value
<i>cos-list</i>	List of class-of-service values
minimum-threshold	(Optional) Specify minimum threshold for WRED
maximum-threshold	(Optional) Specify maximum threshold for WRED
<i>max-thresh</i>	Maximum threshold value
percent	Specify thresholds in percent
percent1	Specify thresholds in percent
<i>min-percent-of-qsize</i>	Minimum threshold percent of queue size
<i>max-percent-of-qsize</i>	Maximum threshold percent of queue size
packets	(Optional) Packets
bytes	(Optional) Bytes
kbytes	(Optional) Kilo bytes
mbytes	(Optional) Mega bytes
ms	(Optional) Milli second(s)
us	(Optional) Micro second(s)
packets1	(Optional) Packets
bytes1	(Optional) Bytes
kbytes1	(Optional) Kilo Bytes
mbytes1	(Optional) Mega Bytes
ms1	(Optional) Milli second(s)
us1	(Optional) Micro second(s)

Command Mode

- /exec/configure/policy-map/type/queuing/class

random-detect2 minimum-threshold2 maximum-threshold2

```
[no] random-detect2 minimum-threshold2 <min-thresh2> { packets2 | bytes2 | kbytes2 | mbytes2 }
maximum-threshold2 <max-thresh2> { packets3 | bytes3 | kbytes3 | mbytes3 } [ drop-probability2 <drop-prob2>
weight2 <weight2> [ cap-average2 ] ]
```

Syntax Description

no	(Optional) Negate a command or set its defaults
random-detect2	Configure WRED parameters
minimum-threshold2	Specify minimum threshold for WRED
maximum-threshold2	Specify maximum threshold for WRED
packets2	Packets
bytes2	Bytes
kbytes2	Kilo Bytes
mbytes2	Mega Bytes
packets3	Packets
bytes3	Bytes
kbytes3	Kilo Bytes
mbytes3	Mega Bytes
drop-probability2	(Optional) Drop Probability at Maximum Threshold
<i>drop-prob2</i>	(Optional) Drop Probability Value
weight2	(Optional) Queue length weight
<i>weight2</i>	(Optional) Queue length weight
cap-average2	(Optional) If average queue length is more, replace average queue length with current queue length

Command Mode

- /exec/configure/policy-map/type/queuing/class

random-detect2 non-ecn minimum-threshold2 maximum-threshold2 drop

```
[no] random-detect2 non-ecn minimum-threshold2 <min-thresh2> { packets2 | bytes2 | kbytes2 | mbytes2 }
maximum-threshold2 <max-thresh2> { packets3 | bytes3 | kbytes3 | mbytes3 } { drop-probability2 <drop-prob2>
}
```

Syntax Description

no	(Optional) Negate a command or set its defaults
random-detect2	Configure WRED parameters
non-ecn	Configure WRED parameters for non-ecn
minimum-threshold2	Specify minimum threshold for WRED
maximum-threshold2	Specify maximum threshold for WRED
packets2	Packets
bytes2	Bytes
kbytes2	Kilo Bytes
mbytes2	Mega Bytes
packets3	Packets
bytes3	Bytes
kbytes3	Kilo Bytes
mbytes3	Mega Bytes
drop-probability2	Drop Probability at Maximum Threshold
<i>drop-prob2</i>	Drop Probability Value

Command Mode

- /exec/configure/policy-map/type/queuing/class

random-detect

```
[no] random-detect [ { minimum-threshold <min-thresh> { packets | bytes | kbytes | mbytes }
maximum-threshold <max-thresh> { packets1 | bytes1 | kbytes1 | mbytes1 } drop-probability <drop-prob>
weight <weight> [ cap-average ] } | threshold { burst-optimized | mesh-optimized } ] [ ecn ]
```

Syntax Description

no	(Optional) Negate a command or set its defaults
random-detect	Configure WRED parameters
threshold	(Optional) Threshold
burst-optimized	(Optional) Threshold optimized for bursty traffic
mesh-optimized	(Optional) Threshold optimized for mesh traffic
minimum-threshold	(Optional) Specify minimum threshold for WRED
maximum-threshold	(Optional) Specify maximum threshold for WRED
<i>max-thresh</i>	(Optional) Maximum threshold value
packets	(Optional) Packets
bytes	(Optional) Bytes
kbytes	(Optional) Kilo bytes
mbytes	(Optional) Mega bytes
packets1	(Optional) Packets
bytes1	(Optional) Bytes
kbytes1	(Optional) Kilo Bytes
mbytes1	(Optional) Mega Bytes
drop-probability	(Optional) Drop Probability at Maximum Threshold
<i>drop-prob</i>	(Optional) Drop Probability Value
weight	(Optional) Queue length weight
<i>weight</i>	(Optional) Queue length weight
cap-average	(Optional) If average queue length is more, replace average queue length with current queue length
ecn	(Optional) ECN

Command Mode

- /exec/configure/policy-map/type/queuing/class

random-detect cos-based

[no] random-detect cos-based [aggregate [minimum-threshold] { <min-thresh> [packets | bytes | kbytes | mbytes | ms | us] | percent <min-percent-of-qsize> } [maximum-threshold] { <max-thresh> [packets1 | bytes1 | kbytes1 | mbytes1 | ms1 | us1] | percent1 <max-percent-of-qsize> }]

Syntax Description

no	(Optional) Negate a command or set its defaults
random-detect	Configure WRED parameters
cos-based	Configure WRED parameters for cos-based mode
aggregate	(Optional) Configure WRED parameters to same value for all sub-classes
minimum-threshold	(Optional) Specify minimum threshold for WRED
maximum-threshold	(Optional) Specify maximum threshold for WRED
<i>max-thresh</i>	(Optional) Maximum threshold value
percent	(Optional) Specify thresholds in percent
percent1	(Optional) Specify thresholds in percent
<i>min-percent-of-qsize</i>	(Optional) Minimum threshold percent of queue size
<i>max-percent-of-qsize</i>	(Optional) Maximum threshold percent of queue size
packets	(Optional) Packets
bytes	(Optional) Bytes
kbytes	(Optional) Kilo bytes
mbytes	(Optional) Mega bytes
ms	(Optional) Milli second(s)
us	(Optional) Micro second(s)
packets1	(Optional) Packets
bytes1	(Optional) Bytes
kbytes1	(Optional) Kilo Bytes
mbytes1	(Optional) Mega Bytes
ms1	(Optional) Milli second(s)
us1	(Optional) Micro second(s)

Command Mode

- /exec/configure/policy-map/type/queuing/class

rate-limit

rate-limit { auto | <rate_value> } | no rate-limit

Syntax Description

no	Negate a command or set its defaults
rate-limit	Set the Rate limit for SPAN packets
auto	Set the Rate limit using auto value
<i>rate_value</i>	Enter the percentage of the maximum rate for SPAN packets

Command Mode

- /exec/configure/monitor-local-src /exec/configure/config-monitor
/exec/configure/config-monitor-erspan-src

rate-limit cpu direction input output both pps action log

```
{ rate-limit cpu direction { input | output | both } pps <pps-val> action log } | { no rate-limit cpu direction [
{ input | output | both } pps <pps-val> action log ] }
```

Syntax Description

no	Negate a command or set its defaults
rate-limit	set packet per second rate limit
cpu	Supervisor CPU limits
direction	input/output direction
input	set max input packet rate
output	set max output packet rate
both	set max input and output packet rate
pps	packet per second
<i>pps-val</i>	pps value
action	log action
log	write a syslog message if PPS hits rate-limit

Command Mode

- /exec/configure/if-eth-base /exec/configure/if-eth-any /exec/configure/if-mgmt-config

rate-limit cpu direction input output both pps action log

```
{ rate-limit cpu direction { input | output | both } pps <pps-val> action log } | { no rate-limit cpu direction [
{ input | output | both } pps <pps-val> action log ] }
```

Syntax Description

no	Negate a command or set its defaults
rate-limit	set packet per second rate limit
cpu	Supervisor CPU limits
direction	input/output direction
input	set max input packet rate
output	set max output packet rate
both	set max input and output packet rate
pps	packet per second
<i>pps-val</i>	pps value
action	log action
log	write a syslog message if PPS hits rate-limit

Command Mode

- /exec/configure

rate-limit packet_in burst

rate-limit packet_in <packetin-val> burst <burst-val> | no rate-limit

Syntax Description

no	Negate a command or set its defaults
rate-limit	OpenFlow rate limit to controller
packet_in	packet in rate (pps)
<i>packetin-val</i>	packets per second
burst	Maximum number of packets to controller (pps)
<i>burst-val</i>	packets per second

Command Mode

- /exec/configure/openflow/switch

rate-limit packet_in burst

rate-limit packet_in <packetin-val> burst <burst-val> | no rate-limit

Syntax Description

no	Negate a command or set its defaults
rate-limit	OpenFlow rate limit to controller
packet_in	packet in rate (pps)
<i>packetin-val</i>	packets per second
burst	Maximum number of packets to controller (pps)
<i>burst-val</i>	packets per second

Command Mode

- /exec/configure/openflow/switch/sub-switch

rd

```
{ rd { <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } } | { no rd [ { <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } ] }
```

Syntax Description

no	Negate a command or set its defaults
rd	VPN Route Distinguisher
<i>ext-comm-rd-aa4nn2</i>	VPN route distinguisher in aa4:nn or ip:nn format
<i>ext-comm-rd-aa2nn4</i>	VPN route distinguisher in aa:nn format

Command Mode

- /exec/configure/evpn/evi-sr

rd auto

```
{ rd { auto | <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } } | { no rd [ { auto | <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } ] }
```

Syntax Description

no	Negate a command or set its defaults
rd	VPN Route Distinguisher
auto	Generate RD automatically
<i>ext-comm-rd-aa4nn2</i>	VPN route distinguisher in aa4:nn or ip:nn format
<i>ext-comm-rd-aa2nn4</i>	VPN route distinguisher in aa:nn format

Command Mode

- /exec/configure/vrf

rd auto

```
{ rd { auto | <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } } | { no rd [ { auto | <ext-comm-rd-aa2nn4> | <ext-comm-rd-aa4nn2> } ] }
```

Syntax Description

no	Negate a command or set its defaults
rd	VPN Route Distinguisher
auto	Generate RD automatically
<i>ext-comm-rd-aa4nn2</i>	VPN route distinguisher in aa4:nn or ip:nn format
<i>ext-comm-rd-aa2nn4</i>	VPN route distinguisher in aa:nn format

Command Mode

- /exec/configure/evpn/evi

rd dual

[no] rd dual [id <value>]

Syntax Description

no	(Optional) Negate a command or set its defaults
rd	Secondary Route Distinguisher for vxlan multisite border gateway
dual	Generate Secondary RD for all VRFs and L2VNIs (Default is SITE-ID:VNI)
id	(Optional) Generate Secondary RD with ID:VNI format
<i>value</i>	(Optional) Specify 2 byte value for ID

Command Mode

- /exec/configure/router-bgp

read-only

[no] read-only

Syntax Description

no	(Optional) Negate a command or set its defaults
read-only	Make default-zone read-only

Command Mode

- /exec/configure/default-zone/attribute-group

read-only

[no] read-only

Syntax Description

no	(Optional) Negate a command or set its defaults
read-only	Make the zone read-only

Command Mode

- /exec/configure/attribute-group

receiver

[no] receiver

Syntax Description

no	(Optional) Negate a command or set its defaults
receiver	Policies for a Local Receiver

Command Mode

- /exec/configure/nbm-host-policy

receiver

[no] receiver

Syntax Description

no	(Optional) Negate a command or set its defaults
receiver	Policies for a Local Receiver

Command Mode

- /exec/configure/nbm-vrf/nbm-host-policy

reconnect-interval

reconnect-interval <interval> | no reconnect-interval [<interval>]

Syntax Description

no	Negate a command or set its defaults
reconnect-interval	Configure connection reconnect interval
<i>interval</i>	Interval in seconds

Command Mode

- /exec/configure/router-bgp/vrf-cmds

record

[no] record <recordname>

Syntax Description

record	Add a record
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/config-int-clone-md-source-monitor

record

[no] record <recordname>

Syntax Description

record	Specify INT Record to use
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/config-int-monitor

record

[no] record <recordname>

Syntax Description

record	Specify FTE Record to use
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/config-fte-monitor

record

[no] record <recordname>

Syntax Description

record	Specify Flow Record to use
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/nfm-monitor

record

[no] record <recordname>

Syntax Description

record	Add a record
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/config-buffer-latency-monitor

record

[no] record <recordname>

Syntax Description

record	Record to be monitored
<i>recordname</i>	Record name to be configured

Command Mode

- /exec/configure/config-ssx-monitor

record

[no] record <recordname>

Syntax Description

record	Specify Flow Record to use
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/nfm-monitor

record

[no] record <recordname>

Syntax Description

record	Add a record
<i>recordname</i>	Name of record

Command Mode

- /exec/configure/config-int-clone-md-sink-monitor

record netflow-original

[no] record netflow-original

Syntax Description

record	Specify Flow Record to use
netflow-original	Traditional IPv4 input NetFlow with origin ASs

Command Mode

- /exec/configure/nfm-monitor

record netflow

```
[no] record netflow { ipv6 { original-input } }
```

Syntax Description

record	Specify Flow Record to use
netflow	Traditional NetFlow collection schemes
ipv6	IPv6 collection schemes
original-input	Input NetFlow

Command Mode

- /exec/configure/nfm-monitor

record netflow

```
[no] record netflow { ipv4 { original-input } }
```

Syntax Description

record	Specify Flow Record to use
netflow	Traditional NetFlow collection schemes
ipv4	Traditional IPv4 NetFlow collection schemes
original-input	Traditional IPv4 input NetFlow

Command Mode

- /exec/configure/nfm-monitor

record netflow

```
[no] record netflow { layer2-switched { input } }
```

Syntax Description

record	Specify Flow Record to use
netflow	Traditional NetFlow collection schemes
layer2-switched	Traditional L2 NetFlow collection schemes
input	Input NetFlow

Command Mode

- /exec/configure/nfm-monitor

record netflow protocol-port

[no] record netflow protocol-port

Syntax Description

record	Specify Flow Record to use
netflow	Traditional NetFlow collection schemes
protocol-port	Protocol and Ports aggregation scheme

Command Mode

- /exec/configure/nfm-monitor

redistribute filter route-map

[no] redistribute filter route-map { <map-name> | <rtr_pol_name> }

Syntax Description

no	(Optional) Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
filter	Filter redistributed routes
route-map	Route-map to constrain redistribution
<i>map-name</i>	A 'routing-rules' route-map name
<i>rtr_pol_name</i>	An existing routing-rules policy

Command Mode

- /exec/configure/otv-isis/otv-isis-vrf-common

redistribute filter route-map

[no] redistribute filter route-map { <map-name> | <rtr_pol_name> }

Syntax Description

no	(Optional) Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
filter	Filter redistributed routes
route-map	Route-map to constrain redistribution
<i>map-name</i>	A 'routing-rules' route-map name
<i>rtr_pol_name</i>	An existing routing-rules policy

Command Mode

- /exec/configure/l2mp-isis/l2mp-isis-vrf-common

redistribute maximum-prefix

```
redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] | no redistribute maximum-prefix [ <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] ]
```

Syntax Description

no	Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
maximum-prefix	Max number of prefixes redistributed
<i>maximum</i>	max number
<i>threshold</i>	(Optional) Threshold in %, at which message is generated
warning-only	(Optional) Warning msg is logged when max is reached
withdraw	(Optional) Withdraw all redistributed routes
<i>retries</i>	(Optional) No of times to retry to get redist routes again
<i>timeout</i>	(Optional) Time between the retries

Command Mode

- /exec/configure/router-isis/router-isis-af-ipv4

redistribute maximum-prefix

```
redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] | no redistribute maximum-prefix [ <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] ]
```

Syntax Description

no	Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
maximum-prefix	Max number of prefixes redistributed
<i>maximum</i>	max number
<i>threshold</i>	(Optional) Threshold in %, at which message is generated
warning-only	(Optional) Warning msg is logged when max is reached
withdraw	(Optional) Withdraw all redistributed routes
<i>retries</i>	(Optional) No of times to retry to get redist routes again
<i>timeout</i>	(Optional) Time between the retries

Command Mode

- /exec/configure/router-isis/router-isis-af-ipv6

redistribute maximum-prefix

```
{ redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] } | { no redistribute maximum-prefix }
```

Syntax Description

no	Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
maximum-prefix	Maximum number of prefixes redistributed to protocol
<i>maximum</i>	Maximum number of IP prefixes redistributed
<i>threshold</i>	(Optional) Threshold value (%) at which to generate a warning message
warning-only	(Optional) Log a warning message when limit is exceeded
withdraw	(Optional) Withdraw all redistributed routes
<i>retries</i>	(Optional) Number of times to retry to get the redistributed routes again
<i>timeout</i>	(Optional) Timeout between each retries

Command Mode

- /exec/configure/router-ospf3/router-ospf3-af-ipv6 /exec/configure/router-ospf3/vrf/router-ospf3-af-ipv6

redistribute maximum-prefix

```
redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout>
]] | no redistribute maximum-prefix [ <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries>
<timeout> ] ] ]
```

Syntax Description

no	Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
maximum-prefix	Max number of prefixes redistributed
<i>maximum</i>	max number
<i>threshold</i>	(Optional) Threshold in %, at which message is generated
warning-only	(Optional) Warning msg is logged when threshold is reached
withdraw	(Optional) Withdraw all redistributed routes
<i>retries</i>	(Optional) Number of attempts to receive redistributed routes after max is reached
<i>timeout</i>	(Optional) Retry interval

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

redistribute maximum-prefix

```
{ redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] } | { no redistribute maximum-prefix <maximum> [ <threshold> ] [ warning-only | withdraw [ <retries> <timeout> ] ] }
```

Syntax Description

no	Negate a command or set its defaults
redistribute	Redistribute information from another routing protocol
maximum-prefix	Maximum number of prefixes redistributed to protocol
<i>maximum</i>	Maximum number of IP prefixes redistributed
<i>threshold</i>	(Optional) Threshold value (%) at which to generate a warning message
warning-only	(Optional) Log a warning message when limit is exceeded
withdraw	(Optional) Withdraw all redistributed routes
<i>retries</i>	(Optional) Number of times to retry to get the redistributed routes again
<i>timeout</i>	(Optional) Timeout between each retries

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

redistribute route-map

[no] redistribute { static | direct | amt | lisp | am | hmm | { { eigrp | isis | ospfv3 | rip } <tag> } } route-map <rmap-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
redistribute	Configure redistribution
static	Static routes
direct	Directly connected
isis	ISO IS-IS
ospfv3	Open Shortest Path First, version 3 (OSPFv3)
rip	Routing Information Protocol (RIP)
eigrp	Enhanced Interior Gateway Protocol
amt	AMT anycast prefix
lisp	LISP EID-prefixes in the non-default VRF
hmm	HMM prefix
am	AM routes (learned via ARP)
route-map	Route-map applied to redistributed routes
<i>rmap-name</i>	Route-map name
<i>tag</i>	Source protocol tag

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv6 /exec/configure/router-bgp/router-bgp-vrf-af-ipv6

redundancy-group

[no] redundancy-group

Syntax Description

no	(Optional) Negate a command or set its defaults
redundancy-group	Configure a redundancy-group node

Command Mode

- /exec/configure/if-nve

reference-bandwidth

[no] reference-bandwidth { <ref-bw-mbps> [Mbps] | <ref-bw-gbps> Gbps }

Syntax Description

no	(Optional) Negate a command or set its defaults
reference-bandwidth	Change reference bandwidth used for setting interface metric
<i>ref-bw-mbps</i>	Bandwidth in Mbps (Default)
Mbps	(Optional) Specify in Mbps
<i>ref-bw-gbps</i>	Bandwidth in Gbps
Gbps	Specify in Gbps

Command Mode

- /exec/configure/router-isis/router-isis-vrf-common

reference-bandwidth

[no] reference-bandwidth { <ref-bw-mbps> [Mbps] | <ref-bw-gbps> Gbps }

Syntax Description

no	(Optional) Negate a command or set its defaults
reference-bandwidth	Change reference bandwidth used for setting interface metric
<i>ref-bw-mbps</i>	Bandwidth in Mbps (Default)
Mbps	(Optional) Specify in Mbps
<i>ref-bw-gbps</i>	Bandwidth in Gbps
Gbps	Specify in Gbps

Command Mode

- /exec/configure/12mp-isis/12mp-isis-vrf-common /exec/configure/12mp-isis/12mp-isis-l2-topo

region

{ region <i0> | no region [<i0>] }

Syntax Description

no	Negate a command or set its defaults
region	Configure the autonomous region for FSPF
<i>i0</i>	region ID

Command Mode

- /exec/configure/(fspf-config)

register-database-mapping

{ [no] register-database-mapping }

Syntax Description

no	(Optional) Negate a command or set its defaults
register-database-mapping	Register database-mapping EID-prefix to Map-Server

Command Mode

- /exec/configure/lisp-dynamic-oid /exec/configure/vrf/lisp-dynamic-oid

register-route-notifications

{ [no] register-route-notifications }

Syntax Description

no	(Optional) Negate a command or set its defaults
register-route-notifications	Register more-specific routes of the database-mapping EID-prefix to Map-Server

Command Mode

- /exec/configure/lisp-dynamic-eid /exec/configure/vrf/lisp-dynamic-eid

reload

reload [e2fsck]

Syntax Description

e2fsck	(Optional) Set the e2fsck -y flag during reboot
reload	reboot the entire box

Command Mode

- /exec

reload cancel

reload cancel

Syntax Description

reload	reboot the entire box
cancel	Cancel scheduling of the reload

Command Mode

- /exec

reload in

reload in <secs>

Syntax Description

reload	reboot the entire box
in	Schedule a reload after some time
<i>secs</i>	Reload after n seconds

Command Mode

- /exec

reload module

reload module <lem-aware-module>

Syntax Description

reload	reboot the entire box
module	reboot a specific module
<i>lem-aware-module</i>	please enter the module number

Command Mode

- /exec

reload module force-dnld

reload module <module> force-dnld

Syntax Description

reload	reboot the entire box
module	reboot a specific module
<i>module</i>	please enter the module number
force-dnld	reboot a specific module to force NetBoot and image download

Command Mode

- /exec

reload non-interruptive

reload non-interruptive

Syntax Description

reload	reboot the entire box
non-interruptive	Reboot without interruption

Command Mode

- /exec

reload sync-adjacency

reload sync-adjacency

Syntax Description

reload	reboot the entire box
sync-adjacency	Reload with sync adjacency

Command Mode

- /exec

reload timer

reload timer <secs>

Syntax Description

reload	reboot the entire box
timer	reboot after a delay <5-3600> seconds
<i>secs</i>	delay in seconds

Command Mode

- /exec

reload vdc

reload vdc

Syntax Description

vdc	Restart the current vdc
reload	Power cycle

Command Mode

- /exec

reload vdc

reload vdc <d-vdc>

Syntax Description

vdc	Restart the current vdc
reload	Power cycle
<i>d-vdc</i>	Enter Virtual Device Context <vdc-id>

Command Mode

- /exec

remark

```
{ [ <seqno> ] | no } remark <comment>
```

Syntax Description

<code>no</code>	Negate a command or set its defaults
<code>seqno</code>	(Optional) Sequence number
<code>remark</code>	Time range entry comment
<code>comment</code>	Comment, up to 100 characters

Command Mode

- /exec/configure/arpacl /exec/configure/timerange

remark

{ [<seqno>] | no } remark <comment>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	(Optional) Sequence number
remark	Access list entry comment
<i>comment</i>	Comment, up to 100 characters

Command Mode

- /exec/configure/ipacl /exec/configure/ipv6acl

remark

```
{ [ <seqno> ] | no } remark <comment>
```

Syntax Description

<code>no</code>	Negate a command or set its defaults
<code>seqno</code>	(Optional) Sequence number
<code>remark</code>	Access list entry comment
<code>comment</code>	Comment, up to 100 characters

Command Mode

- /exec/configure/macacl

remote-as

```
{ remote-as <asn> } | { { no | default } remote-as [ <asn> ] }
```

Syntax Description

no	Negate a command or set its defaults
default	Inherit values from a peer template
remote-as	Specify Autonomous System Number of the neighbor
<i>asn</i>	Autonomous System Number

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor-sess

remote-span

[no] remote-span

Syntax Description

no	(Optional) Negate a command or set its defaults
remote-span	Enable remote span VLAN

Command Mode

- /exec/configure/vlan

remove-private-as

[no | default] remove-private-as [all | replace-as]

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
remove-private-as	Remove private AS number from outbound updates
all	(Optional) All
replace-as	(Optional) Replace

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor-sess

replay-protection

[no] replay-protection

Syntax Description

replay-protection	Enable replay-protection (the default use the no form to disable)
-------------------	---

Command Mode

- /exec/configure/cts-dot1x /exec/configure/cts-manual

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/sel4

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/se13

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/sel5

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/sel6

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/sel7

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/outsel0

report

report

Syntax Description

report	Show trigger report
--------	---------------------

Command Mode

- /exec/elamns/outsel5

request-data-size

{ { no | default } request-data-size | request-data-size <bytes-in-payload> }

Syntax Description

no	
default	Set a command to its defaults
request-data-size	Request data size
<i>bytes-in-payload</i>	Number of bytes in payload

Command Mode

- /exec/configure/ip-sla/udp

request-data-size

{ { no | default } request-data-size | request-data-size <bytes-in-payload> }

Syntax Description

no	
default	Set a command to its defaults
request-data-size	Request data size
<i>bytes-in-payload</i>	Number of bytes in payload

Command Mode

- /exec/configure/ip-sla/icmpEcho

request-data-size

{ { no | default } request-data-size | request-data-size <bytes-in-payload> }

Syntax Description

no	
default	Set a command to its defaults
request-data-size	Request data size
<i>bytes-in-payload</i>	Number of bytes in payload

Command Mode

- /exec/configure/ip-sla/jitter

resequence access

resequence { { <ip_ipv6_mac_arp> access-list } | time-range } <name> <number> <increment>

Syntax Description

resequence	Resequence a list with sequence numbers
<i>ip_ipv6_mac_arp</i>	IP/IPv6/MAC/ARP
access-list	Resequence an access list
time-range	Resequence a time-range
<i>name</i>	List name
<i>number</i>	Starting sequence number
<i>increment</i>	Step to increment the sequence number

Command Mode

- /exec/configure

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/se15

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/sel3

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/se14

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/sel6

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/sel7

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/outsel0

reset

reset

Syntax Description

reset	Reset Trigger conditions
-------	--------------------------

Command Mode

- /exec/elamns/outsel5

restart amt

restart amt

Syntax Description

restart	Manually restart a component
amt	Restart the AMT multicast routing protocol

Command Mode

- /exec

restart bgp

restart bgp <as>

Syntax Description

restart	Manually restart a component
bgp	Border Gateway Protocol (BGP)
<i>as</i>	Autonomous

Command Mode

- /exec

restart eigrp

restart eigrp <eigrp-ptag>

Syntax Description

restart	Manually restart a component
eigrp	Enhanced Interior Gateway Routing Protocol (EIGRP)
<i>eigrp-ptag</i>	Process tag

Command Mode

- /exec

restart fabric_mcast

```
restart { fabric_mcast | ngmvpn }
```

Syntax Description

restart	Manually restart a component
fabric_mcast	Restart NGMVPN
ngmvpn	Restart NGMVPN

Command Mode

- /exec

restart fabricpath domain

restart fabricpath domain

Syntax Description

restart	Manually restart a component
fabricpath	Data Center Intermediate System to Intermediate System (L2MP-IS-IS)
domain	Fabricpath IS-IS domain

Command Mode

- /exec

restart igmp

restart igmp

Syntax Description

restart	Manually restart a component
igmp	Restart the IGMP multicast routing protocol

Command Mode

- /exec

restart isis

restart isis <tag>

Syntax Description

restart	Manually restart a component
isis	Intermediate System to Intermediate System (IS-IS)
<i>tag</i>	Routing process tag

Command Mode

- /exec

restart mld

restart mld

Syntax Description

restart	Manually restart a component
mld	Restart the MLD routing protocol

Command Mode

- /exec

restart msdp

restart msdp

Syntax Description

restart	Manually restart a component
msdp	Restart the MSDP multicast routing protocol

Command Mode

- /exec

restart ospf

restart ospf <tag>

Syntax Description

restart	Manually restart a component
ospf	Open Shortest Path First (OSPF)
<i>tag</i>	Process tag

Command Mode

- /exec

restart ospfv3

restart ospfv3 <tag>

Syntax Description

restart	Manually restart a component
ospfv3	Open Shortest Path First (OSPF) (Version 3)
<i>tag</i>	Process tag

Command Mode

- /exec

restart otv-isis

restart otv-isis <tag>

Syntax Description

restart	Manually restart a component
otv-isis	Intermediate System to Intermediate System (IS-IS)
<i>tag</i>	Routing process tag

Command Mode

- /exec

restart pim

restart pim

Syntax Description

restart	Manually restart a component
pim	Restart the PIM multicast routing protocol

Command Mode

- /exec

restart pim6

restart pim6

Syntax Description

restart	Manually restart a component
pim6	Restart the PIM6 multicast routing protocol

Command Mode

- /exec

restart rip

restart rip <tag>

Syntax Description

restart	Manually restart a component
rip	Routing Information Protocol (RIP)
<i>tag</i>	Process ID

Command Mode

- /exec

resync-database

resync-database

Syntax Description

resync-database	Re-synchronize switch-profile database
-----------------	--

Command Mode

- /exec/configure

retain route-target all

[no] retain route-target { all | route-map <rmap-name> }

Syntax Description

no	(Optional) Negate a command or set its defaults
retain	Retain the routes based on Target VPN Extended Communities
route-target	Specify Target VPN Extended Communities
all	All the routes regardless of Target-VPN community
route-map	Apply route-map to filter routes
<i>rmap-name</i>	Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-af-vpnv4 /exec/configure/router-bgp/router-bgp-af-vpnv6
/exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn
/exec/configure/router-bgp/router-bgp-af-ipv4-mvpn /exec/configure/router-bgp/router-bgp-af-ipv6-mvpn

retain route-target all

[no] retain route-target { all | route-map <rmap-name> }

Syntax Description

no	(Optional) Negate a command or set its defaults
retain	Retain the routes based on Target VPN Extended Communities
route-target	Specify Target VPN Extended Communities
all	All the routes regardless of Target-VPN community
route-map	Apply route-map to filter routes
<i>rmap-name</i>	Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-af-l2vpn-vpls

retransmit-interval

{ { retransmit-interval <interval> } | { no retransmit-interval [<interval>] } }

Syntax Description

no	Negate a command or set its defaults
retransmit-interval	Packet retransmission interval
<i>interval</i>	(seconds)

Command Mode

- /exec/configure/router-ospf/vrf/router-ospf-slink

retransmit-interval

{ { retransmit-interval <interval> } | { no retransmit-interval [<interval>] } }

Syntax Description

no	Negate a command or set its defaults
retransmit-interval	Packet retransmission interval
<i>interval</i>	(seconds)

Command Mode

- /exec/configure/router-ospf3/router-ospf3-vlink /exec/configure/router-ospf3/vrf/router-ospf3-vlink

retransmit-interval

{ { retransmit-interval <interval> } | { no retransmit-interval [<interval>] } }

Syntax Description

no	Negate a command or set its defaults
retransmit-interval	Packet retransmission interval
<i>interval</i>	(seconds)

Command Mode

- /exec/configure/router-ospf/router-ospf-vlink /exec/configure/router-ospf/vrf/router-ospf-vlink

reverse

[no] reverse { { ip <rev-ip-addr> | ipv6 <rev-ipv6-addr> | interface <revinterface> } + }

Syntax Description

no	(Optional) Negate a command or set its defaults
reverse	Details of reverse service-end-point instance
ip	IPv4 address of service node
ipv6	IPv6 address of service node
interface	Interface through which service is connected
<i>rev-ip-addr</i>	IPv4 address in format i.i.i.i
<i>revinterface</i>	Interface

Command Mode

- /exec/configure/epbr-sess/fwd-svc

reverse

[no] reverse { { ip <rev-ip-addr> | ipv6 <rev-ipv6-addr> | interface <revinterface> } + }

Syntax Description

no	(Optional) Negate a command or set its defaults
reverse	Details of reverse service-end-point instance
ip	IPv4 address of service node
ipv6	IPv6 address of service node
interface	Interface through which service is connected
<i>rev-ip-addr</i>	IPv4 address in format i.i.i.i
<i>revinterface</i>	Interface

Command Mode

- /exec/configure/epbr/fwd-svc

revision

revision <rev-id> | no revision [<rev-id>]

Syntax Description

no	Negate a command or set its defaults
revision	Set configuration revision number
<i>rev-id</i>	Configuration revision number

Command Mode

- /exec/configure/spanning-tree/mst/configuration

revocation-check

```
[no] revocation-check { crl [ { none | oosp [ none ] } ] | none | oosp [ { crl [ none ] | none } ] }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
revocation-check	Configure trustpoint revocation check methods
crl	Configure revocation check using crl
none	(Optional) Configure revocation check using none
oosp	(Optional) Configure revocation check using oosp
none	(Optional) Configure revocation check using none
none	Configure revocation check using none
oosp	Configure revocation check using oosp
crl	(Optional) Configure revocation check using crl
none	(Optional) Configure revocation check using none
none	(Optional) Configure revocation check using none

Command Mode

- /exec/configure/trustpoint

rewrite-evpn-rt-asn

[no | default] rewrite-evpn-rt-asn

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
rewrite-evpn-rt-asn	Auto generate RTs for EBGP neighbor

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-l2vpn-evpn

rewrite-rt-asn

[no | default] rewrite-rt-asn

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
rewrite-rt-asn	Auto generate RTs for EBGP neighbor

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mvpn
/exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-mvpn

rfc1583compatibility

[no] rfc1583compatibility [ios-compatibility]

Syntax Description

no	(Optional) Negate a command or set its defaults
rfc1583compatibility	Configure 1583 compatibility for external path preferences
ios-compatibility	(Optional) Option for IOS XE/XR compatibility: [intra asbr path preferred over cost]

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

rib verification-report

[no] rib verification-report { label module <i0> | multicast module1 <i1> | unicast module2 <i2> }

Syntax Description

no	(Optional) Negate a command or set its defaults
rib	Configure RIB parameters
verification-report	Generate RIB route verification report
label	Generate label report
module	Line card module number
<i>i0</i>	Enter module number
multicast	Generate multicast report
module1	Line card module number
<i>i1</i>	Enter module number
unicast	Generate unicast report
module2	Line card module number
<i>i2</i>	Enter module number

Command Mode

- /exec/configure

rip shutdown

[no] rip shutdown

Syntax Description

no	(Optional) Negate a command or set its defaults
rip	RIP configuration commands
shutdown	Shutdown RIP on this interface

Command Mode

- /exec/configure/if-igp

rmdir

rmdir { <uri0> | <uri1> }

Syntax Description

rmdir	Delete a directory
<i>uri0</i>	Delete a directory
<i>uri1</i>	Delete a directory on expansion flash

Command Mode

- /exec

rmon alarm absolute rising-threshold falling-threshold

```
rmon alarm <i0> <s0> <i1> { absolute | delta } rising-threshold <i2> [ <i3> ] falling-threshold <i4> [ <i5> ]
[ owner <s1> ] | no rmon alarm <i0>
```

Syntax Description

no	Negate a command or set its defaults
rmon	Remote Monitoring
alarm	Configure an RMON alarm
<i>i0</i>	Alarm number
<i>s0</i>	MIB object to monitor
<i>i1</i>	Sample interval
absolute	Test each sample directly
delta	Test delta between samples
rising-threshold	Configure the rising threshold
<i>i2</i>	Rising threshold value
<i>i3</i>	(Optional) Event to fire on rising threshold crossing
falling-threshold	Configure the falling threshold
<i>i4</i>	Falling threshold value
<i>i5</i>	(Optional) Event to fire on falling threshold crossing
owner	(Optional) Specify an owner for the alarm
<i>s1</i>	(Optional) Alarm owner

Command Mode

- /exec/configure

rmon event

rmon event <i0> [log] [trap <s0>] [description <s1>] [owner <s2>] | no rmon event <i0>

Syntax Description

no	Negate a command or set its defaults
rmon	Remote Monitoring
event	Configure an RMON event
<i>i0</i>	Event number
log	(Optional) Generate RMON log when the event fires
trap	(Optional) Generate SNMP trap when event fires
<i>s0</i>	(Optional) SNMP community string
description	(Optional) Specify a description of the event
<i>s1</i>	(Optional) Event description
owner	(Optional) Specify an owner for the event
<i>s2</i>	(Optional) Event owner

Command Mode

- /exec/configure

rmon hcalarm absolute startupalarm rising-threshold falling-threshold owner

rmon hcalarm <i0> <s0> <i1> { absolute | delta } startupalarm <i2> rising-threshold <i3> <i4> falling-threshold <i5> <i6> owner <s1> | no rmon hcalarm <i0>

Syntax Description

no	Negate a command or set its defaults
rmon	Remote Monitoring
hcalarm	Configure an High Capacity RMON alarm
<i>i0</i>	Alarm number
<i>s0</i>	MIB object to monitor
<i>i1</i>	Sample interval
absolute	Test each sample directly
delta	Test delta between samples
startupalarm	Configure alarm type
<i>i2</i>	Startup alarm type, rising(1) falling(2) risingorfalling(3)
rising-threshold	Configure the rising threshold
<i>i3</i>	Rising threshold value in bytes
<i>i4</i>	Event to fire on rising threshold crossing
falling-threshold	Configure the falling threshold
<i>i5</i>	Falling threshold value in bytes
<i>i6</i>	Event to fire on falling threshold crossing
owner	Specify an owner for the alarm
<i>s1</i>	Alarm owner

Command Mode

- /exec/configure

roaming-eid-prefix

```
{ [ no ] roaming-eid-prefix { <eid-prefix> | <eid-prefix6> } }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
roaming-eid-prefix	Configures what EID-prefixes allowed to roam
<i>eid-prefix</i>	IPv4 roaming EID-prefix

Command Mode

- /exec/configure/lisp-dynamic-eid /exec/configure/vrf/lisp-dynamic-eid

role feature-group name

[no] role feature-group name <arg6>

Syntax Description

no	(Optional) Negate a command or set its defaults
role	Configure roles
feature-group	Configure role feature-group
name	Feature-group name
<i>arg6</i>	Enter feature-group name

Command Mode

- /exec/configure

role name

[no] role name <arg2>

Syntax Description

no	(Optional) Negate a command or set its defaults
role	Configure roles
name	Enter the role name
<i>arg2</i>	Enter the role name

Command Mode

- /exec/configure

role priority

role priority <priority_value> | no role priority

Syntax Description

no	Negate a command or set its defaults
role	Role related configuration
priority	Configure priority to be used during vPC role (primary/secondary) election
<i>priority_value</i>	specify priority value

Command Mode

- /exec/configure/vpc-domain

rollback configuration to

rollback configuration to <conf-commit-id>

Syntax Description

rollback	Rollback configuration
configuration	committed configuration
to	to choose a committed ID
<i>conf-commit-id</i>	commit ID

Command Mode

- /exec

rollback running-config checkpoint

```
rollback running-config { checkpoint <chkpoint_name> | file <file_uri> } [ best-effort | stop-at-first-failure |
atomic ] [ verbose ]
```

Syntax Description

rollback	Rollback configuration
running-config	Rollback running configuration
checkpoint	Rollback running configuration to checkpoint
<i>chkpoint_name</i>	Checkpoint name
file	Rollback running configuration to configuration file
<i>file_uri</i>	Checkpoint file path
best-effort	(Optional) Skip errors and proceed with rollback
stop-at-first-failure	(Optional) Stop rollback at the first error
atomic	(Optional) Stop rollback and revert to original configuration (default)
verbose	(Optional) Show the execution log

Command Mode

- /exec

root-priority

[no] root-priority <root-pri>

Syntax Description

no	(Optional) Negate a command or set its defaults
root-priority	Set priority with which nodes becomes root
<i>root-pri</i>	Root priority value per topology

Command Mode

- /exec/configure/l2mp-isis/l2mp-isis-vrf-common /exec/configure/l2mp-isis/l2mp-isis-l2-topo

route-map

route-map <rtmap-name> [permit | deny]

Syntax Description

route-map	Create route-map or enter route-map command mode
<i>rtmap-name</i>	Route-map name
permit	(Optional) Route map permits set operations
deny	(Optional) Route map denies set operations

Command Mode

- /exec/configure

route-map

```
route-map <rtmap-name> [ permit | deny ] <seq>
```

Syntax Description

route-map	Create route-map or enter route-map command mode
<i>rtmap-name</i>	Route-map name
permit	(Optional) Route map permits set operations
deny	(Optional) Route map denies set operations
<i>seq</i>	Sequence to insert to/delete from existing route-map entry

Command Mode

- /exec/configure

route-map

[no] route-map { <rtmap-name> | <rtmap-name> } [permit | deny]

Syntax Description

no	Negate a command or set its defaults
route-map	Create route-map or enter route-map command mode
<i>rtmap-name</i>	Route-map name
<i>rtmap-name</i>	Known route-map name
permit	(Optional) Route map permits set operations
deny	(Optional) Route map denies set operations

Command Mode

- /exec/configure

route-map

[no] route-map { <rtmap-name> | <rtmap-name> } [permit | deny] <seq>

Syntax Description

no	Negate a command or set its defaults
route-map	Create route-map or enter route-map command mode
<i>rtmap-name</i>	Route-map name
<i>rtmap-name</i>	Known route-map name
permit	(Optional) Route map permits set operations
deny	(Optional) Route map denies set operations
<i>seq</i>	Sequence to insert to/delete from existing route-map entry

Command Mode

- /exec/configure

route-map out

[no | default] route-map <rmap-name> { out | in }

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
route-map	Apply route-map to neighbor
<i>rmap-name</i>	Route-map name
out	Apply policy to outgoing routes
in	Apply policy to incoming routes

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv4
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv6
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-l2vpn-vpls
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mvpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-mvpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-l2vpn-evpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-label

route-map pbr-statistics

```
route-map <route-map-name> pbr-statistics | no route-map { <route-map-name> | <route-map-name> }  
pbr-statistics
```

Syntax Description

no	Negate a command or set its defaults
route-map	Create route-map or enter route-map command mode
<i>route-map-name</i>	Route-map name
<i>route-map-name</i>	Route-map name
<i>route-map-name</i>	Known route-map name
pbr-statistics	Statistics for policy based routing

Command Mode

- /exec/configure

route-reflector-client

[no | default] route-reflector-client

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
route-reflector-client	Configure a neighbor as Route reflector client

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-l2vpn-evpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv4
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv6
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mvpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-mvpn
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-link-state
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt

route-reflector-client

[no | default] route-reflector-client

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
route-reflector-client	Configure a neighbor as Route reflector client

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-l2vpn-vpls

route-target both

```
{ route-target both { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target both {
<ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
both	Export and Import Target-VPN community
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi-sr

route-target both auto

```
{ route-target both { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target both { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
auto	Generate RT automatically
both	Export and Import Target-VPN community
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi

route-target both auto

```
{ route-target both { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } [ evpn | mvpn ] } | { no route-target
both [ auto [ evpn | mvpn ] | <ext-comm-rt-aa2nn4> [ evpn | mvpn ] | <ext-comm-rt-aa4nn2> [ evpn | mvpn
] ] }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
both	Export And Import Target-VPN community
auto	Generate route target automatically
evpn	(Optional) Specify Target for EVPN routes
mvpn	(Optional) Specify Target for MVPN routes
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/vrf-af-ipv4 /exec/configure/vrf-af-ipv6

route-target export

```
{ route-target export { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } [ evpn | mvpn ] } | { no route-target
export { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } [ evpn | mvpn ] }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
export	Export Target-VPN community
evpn	(Optional) Specify Target for EVPN routes
mvpn	(Optional) Specify Target for MVPN routes
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/vrf-af-ipv4 /exec/configure/vrf-af-ipv6

route-target export

```
{ route-target export { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target export {
<ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
export	Export Target-VPN community
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi-sr

route-target export auto

```
{ route-target export { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target export { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
auto	Generate RT automatically
export	Export Target-VPN community
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi

route-target import

```
{ route-target import { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target import {
<ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
import	Import Target-VPN community
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi-sr

route-target import

```
{ route-target import { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } [ evpn | mvpn ] } | { no route-target
import { <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } [ evpn | mvpn ] }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
import	Import Target-VPN community
evpn	(Optional) Specify Target for EVPN routes
mvpn	(Optional) Specify Target for MVPN routes
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/vrf-af-ipv4 /exec/configure/vrf-af-ipv6

route-target import auto

```
{ route-target import { auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } } | { no route-target import
{ auto | <ext-comm-rt-aa2nn4> | <ext-comm-rt-aa4nn2> } }
```

Syntax Description

no	Negate a command or set its defaults
route-target	Specify Target VPN Extended Communities
import	Import Target-VPN community
auto	Generate RT automatically
<i>ext-comm-rt-aa4nn2</i>	RT extcommunity in aa4:nn or ip:nn format
<i>ext-comm-rt-aa2nn4</i>	RT extcommunity in aa:nn format

Command Mode

- /exec/configure/evpn/evi

route

```
[no] route { vrf { <vrf-name> | <vrf-known-name> } } { <ip-addr> <ip-mask> | <ip-prefix> | <ipv6-prefix>
} { <next-hop> [ next-hop-vrf { <nh-vrf-name> | <nh-vrf-known-name> | default } ] { vni <id> { dest-vtep-mac
<next-hop-mac> } } | remote-locator <remote-loc> function <function> [ via policy { name <te-policy> |
color <color> endpoint <end-point> } ] | via policy { name <te-policy> | color <color> endpoint <end-point>
} [ remote-locator <remote-loc> function <function> ] }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
route	Route information
vrf	VRF for host route
<i>vrf-name</i>	VRF name
<i>vrf-known-name</i>	Known VRF name
<i>ip-addr</i>	IP prefix in format i.i.i.i
<i>ip-mask</i>	IP network mask in format m.m.m.m
<i>ip-prefix</i>	IP prefix and network mask length in format x.x.x.x/m
<i>next-hop</i>	IP next-hop address in format i.i.i.i
next-hop-vrf	(Optional) VRF for next-hop. Default is vrf 'default'
default	(Optional) Default next hop VRF
<i>nh-vrf-name</i>	(Optional) VRF name
<i>nh-vrf-known-name</i>	(Optional) Known VRF name
dest-vtep-mac	Remote VTEP MAC address
<i>next-hop-mac</i>	MAC Address of remote VTEP
vni	Virtual Network Identifier
via	(Optional) Via SrV6 TE policy
policy	(Optional) Traffic engineering-policy
name	(Optional) Te-policy policy
<i>te-policy</i>	(Optional) policy Name
color	(Optional) Te-policy color
<i>color</i>	(Optional) color name
endpoint	(Optional) SRV6 End-point

remote-locator	Ipv6 locator of remote srv6 peer
function	Function
<i>function</i>	Function in the remote sid
<i>id</i>	vni, Example: 4096,6099

Command Mode

- /exec/configure/tunnel-profile

router-guard ip multicast

[no] router-guard ip multicast [vlan <vlan_id>]

Syntax Description

no	(Optional) Negate a command or set its defaults
router-guard	Configures router guard for all interfaces
ip	Configure IP features
multicast	router-guard for multicast packet processing
vlan	(Optional) Configures router guard for specified vlan only(only in trunk ports)
<i>vlan_id</i>	(Optional) Specify vlan-id

Command Mode

- /exec/configure/if-switching

router-guard ip multicast switchports

[no] router-guard ip multicast switchports

Syntax Description

no	(Optional) Negate a command or set its defaults
router-guard	Configures router guard for all interfaces
ip	Configure IP features
multicast	router-guard for multicast packet processing
switchports	configures on all switchports globally

Command Mode

- /exec/configure

router-guard ipv6 multicast

[no] router-guard ipv6 multicast [vlan <vlan_id>]

Syntax Description

no	(Optional) Negate a command or set its defaults
router-guard	Configures router guard for all interfaces
ipv6	Configure IPv6 features
multicast	router-guard for multicast packet processing
vlan	(Optional) Configures router guard for specified vlan only(only in trunk ports)
<i>vlan_id</i>	(Optional) Specify vlan-id

Command Mode

- /exec/configure/if-switching

router-guard ipv6 multicast switchports

[no] router-guard ipv6 multicast switchports

Syntax Description

no	(Optional) Negate a command or set its defaults
router-guard	Configures router guard for all interfaces
ipv6	Configure IPv6 features
multicast	router-guard for multicast packet processing
switchports	configures on all switchports globally

Command Mode

- /exec/configure

router-id

[no] router-id <router-id>

Syntax Description

no	(Optional) Negate a command or set its defaults
router-id	Specify the IP address to use as router-id
<i>router-id</i>	Manually configured router identifier

Command Mode

- /exec/configure/router-bgp/vrf-cmds

router-id

```
[no] router-id { <interface> | <rid> }
```

Syntax Description

<code>no</code>	(Optional) Negate a command or set its defaults
<code>router-id</code>	Router-ID
<i>interface</i>	Interface to provide IP address for router-id
<i>rid</i>	IP address to become router-id

Command Mode

- /exec/configure/router-isis/router-isis-af-ipv4

router-id

```
{ { router-id <id> } | { no router-id [ <id> ] } }
```

Syntax Description

no	Negate a command or set its defaults
router-id	Set OSPFv3 process router-id
<i>id</i>	Router ID Value

Command Mode

- /exec/configure/router-ospf3 /exec/configure/router-ospf3/vrf

router-id

```
{ { [ eigrp ] router-id <id> } | { no [ eigrp ] router-id [ <id> ] } }
```

Syntax Description

no	Negate a command or set its defaults
eigrp	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
router-id	router-id for this EIGRP process
<i>id</i>	EIGRP Router-ID in IP address format

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

router-id

{ { router-id <id> } | { no router-id [<id>] } }

Syntax Description

no	Negate a command or set its defaults
router-id	Set OSPF process router-id
<i>id</i>	Router ID Value

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

router-id

```
router-id [ vrf { <vrf-name> | <vrf-known-name> } ] <interface> [ force ] | no router-id [ { vrf { <vrf-name> | <vrf-known-name> } | <interface> [ force ] } ]
```

Syntax Description

no	Negate a command or set its defaults
router-id	Select interface to prefer for LDP identifier address
vrf	(Optional) VRF Routing/Forwarding instance information
<i>vrf-name</i>	(Optional) VPN Routing/Forwarding instance name
<i>vrf-known-name</i>	(Optional) Known VRF name
<i>interface</i>	
force	(Optional) Forcibly change the LDP router id

Command Mode

- /exec/configure/ldp

router-preference maximum

[no] router-preference maximum <prefopts>

Syntax Description

no	(Optional) Negate a command or set its defaults
<i>prefopts</i>	

Command Mode

- /exec/configure/config-ra-guard

router bgp

[no] router bgp <as>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
bgp	Border Gateway Protocol (BGP)
as	Autonomous

Command Mode

- /exec/configure

router eigrp

[no] router eigrp <eigrp-ptag>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
eigrp	Enhanced Interior Gateway Routing Protocol (EIGRP)
<i>eigrp-ptag</i>	Process tag

Command Mode

- /exec/configure

router isis

[no] router isis <tag>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
isis	Intermediate System to Intermediate System (IS-IS)
<i>tag</i>	Routing process tag

Command Mode

- /exec/configure

router ospf

[no] router ospf <tag>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
ospf	Open Shortest Path First (OSPF)
<i>tag</i>	Process tag

Command Mode

- /exec/configure

router ospfv3

[no] router ospfv3 <tag>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
ospfv3	Open Shortest Path First (OSPF) (Version 3)
<i>tag</i>	Process tag

Command Mode

- /exec/configure

router rip

[no] router rip <tag>

Syntax Description

no	(Optional) Negate a command or set its defaults
router	Enable a routing process
rip	Routing Information Protocol (RIP)
<i>tag</i>	Process ID

Command Mode

- /exec/configure

routing-context vrf

```
routing-context vrf <vrf-known-name>
```

Syntax Description

routing-context	Set the routing context
vrf	The new routing-context VRF
<i>vrf-known-name</i>	Known VRF name

Command Mode

- /exec

rsakeypair

[no] rsakeypair <s0> [<i0>]

Syntax Description

no	(Optional) Negate a command or set its defaults
rsakeypair	Configure trustpoint rsa key-pair details
s0	key-pair label
i0	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED

Command Mode

- /exec/configure/trustpoint

rtr etr eid

[no] { rtr | etr | eid } { <locator> | <locator6> } [strict | probe] + <seq>

Syntax Description

no	(Optional) Negate a command or set its defaults
rtr	Configure RTR in ELP ordered list
etr	Configure ETR in ELP ordered list
eid	Configure EID in ELP ordered list
<i>locator</i>	IPv4 locator for RTR/ETR or EID
strict	(Optional) ELP hop must be used in Explicit Locator Path
probe	(Optional) RLOC-probe next-hop in ELP
<i>seq</i>	Sequence to insert or delete RTR/ETR/EID ELP entry

Command Mode

- /exec/configure/lisp-elp /exec/configure/vrf/lisp-elp

rule

rule <number> { <action> } { { <permission> [<featuretype> <name>] } } | no rule <number>

Syntax Description

no	Negate a command or set its defaults
rule	Enter the rule number
<i>number</i>	Enter the rule number
<i>action</i>	Action
<i>permission</i>	Permission
<i>featuretype</i>	(Optional) Feature type
<i>name</i>	(Optional) Enter the access entity name

Command Mode

- /exec/configure/role

rule command

```
rule <number> { <action> } { command <cmd_line> } | no rule <number>
```

Syntax Description

no	Negate a command or set its defaults
rule	Enter the rule number
<i>number</i>	Enter the rule number
<i>action</i>	Action
command	Command line
<i>cmd_line</i>	Enter the command (use space+' ' for command separator) e.g. config t role *

Command Mode

- /exec/configure/role

rule oid

rule <number> <action> <permission> oid <snmp_oid> | no rule <number>

Syntax Description

no	Negate a command or set its defaults
rule	Enter the rule number
<i>number</i>	Enter the rule number
<i>action</i>	Action
<i>permission</i>	Permission
oid	SNMP oid (up to 32 elements)
<i>snmp_oid</i>	Enter snmp oid instance name

Command Mode

- /exec/configure/role

run-script

run-script <uri0>

Syntax Description

run-script	Run shell scripts
<i>uri0</i>	Enter script file name

Command Mode

- /exec

run2 guestshell

```
run2 guestshell [ { <cmd_args> } ]
```

Syntax Description

run2	execute/run program
guestshell	The guest shell Linux-bash
<i>cmd_args</i>	(Optional) The command to execute

Command Mode

- /exec

run bash

run bash [<cmd>]

Syntax Description

run	execute/run program
bash	linux-bash
<i>cmd</i>	(Optional) the command to execute

Command Mode

- /exec

run cid

run cid

Syntax Description

run	execute/run debug shell
cid	Cisco Interactive Debug shell

Command Mode

- /exec

