

---

## Goals of this Document

The goals of this document are to elaborate on the requirements and deployment procedures for infrastructure connectivity and logical tenant communication between two ACI sites using Border Gateways. It specifically focuses on APIC configuration without relying on external tools such as Nexus Dashboard. The guide covers Layer 2, Layer 3, shared services, and end-to-end policy extension, ensuring consistent policy enforcement across interconnected ACI sites.

This guide details infrastructure VXLAN connectivity using either direct BGP EVPN peering (non-Route Server) or a Border Gateway Route Server. While both are covered, the design focus remains on the non-Route Server model. The “[User Tenant Baseline Configuration](#)” section is essential for understanding the subsequent use cases; readers should review this foundational content and the following scenarios in the order presented.

Note: Throughout this document, the terms “site” and “fabric” are used interchangeably.

## Terminology

This document uses the following terms, with which you will need to be familiar:

- BD: bridge domain
- EPG: endpoint group
- ESG: endpoint security group
- EP: endpoint residing in an ACI fabric
- L3Out: Layer 3 Out or external routed network
- L3Out EPG also known as External EPG: subnet-based EPG in L3Out
- VRF: Virtual Routing and Forwarding
- Border leaf: ACI leaf where L3Out is deployed
- Border gateway: ACI leaf that is used to connect to other VXLAN EVPN domain
- ISN: The Inter-Site Network that provides connectivity between Border Gateways deployed in separate ACI sites
- pcTag: Policy Class Tag is a numeric ID used for internal representation of EPG/ESG also referred to as Source Class (sclass) or Destination Class (dclass)
- CLI: Command-Line Interface
- DF: Designated Forwarder, a role assigned to a specific Border Gateway that is responsible for forwarding BUM (Broadcast, Unknown Unicast, and Multicast) traffic within a given Bridge Domain (BD)
- PIP: Primary IP Address, a unique loopback IP address assigned to each individual Border Gateway, it is used as source for VXLAN tunnel

## Prerequisites

### Reader Prerequisite Knowledge

- Familiarity with Cisco ACI core concepts such as Tenants, BDs, EPGs, and ESGs.
- Understanding of VXLAN and BGP EVPN technologies.
- For more information, see the [Cisco ACI white papers listing](#).

## Deployment Requirements

- ACI Release: 6.1(5) or higher is required to support multiple independent ACI sites communicating through border gateways and to leverage enhanced features such as Layer 2, Layer 3 connectivity and policy extension between sites.
- Logical Model: ESGs are required, and BDs must be configured in Flooding mode for Unknown Unicast traffic. ESGs are the required security model for flexible and scalable endpoint classification in Multi-Site deployments.
- Border Gateway hardware: Cisco Nexus 9000 Series switches of the FX generation or later, with a minimum of 32 GB of RAM, are required to support Border Gateway functionality. At the time of writing, a Border Gateway in Cisco ACI is a dedicated leaf node that cannot host a tenant L3Out or an endpoint in an EPG/ESG.
- Inter-Site Network: The Inter-Site Network must support external BGP (eBGP) for underlay connectivity.

## Introduction

As of ACI Release 6.1(5), interconnecting multiple ACI Sites via Border Gateways became a supported capability. Broadly, there are three primary methods for connecting ACI sites:

- Independent Sites: In this model, each ACI site operates autonomously. Local APIC administrators are responsible for configuring tenants, VRFs, BDs and Contracts independently on each site. One ACI site perceives the other as an external Layer 2 or Layer 3 network, with no inherent policy synchronization. Networking services rely solely on EPG static path binding and L3Out. This architecture presents several limitations, including complex contract management, lack of support for an “app-centric mode” (where multiple EPGs share a single stretched BD), and the absence of a pervasive gateway across sites.
- Nexus Dashboard Orchestrator (NDO): Now known as Orchestration Service in Nexus Dashboard (ND) starting from ND release 4.1(1), NDO provides a single pane of glass for configuring inter-site connectivity and applying consistent network and policy across ACI sites. Site-to-site VXLAN connectivity is established between ACI spines.
- Border Gateway Interconnect: This newer design option centralizes the interconnectivity between ACI sites through dedicated Border Gateways. It facilitates Layer 2 and Layer 3 networking services and policy using standard VXLAN encapsulation for the data plane and BGP EVPN for the control plane. The VXLAN connectivity between sites is key to maintaining a pervasive gateway across ACI sites. Centralized provisioning can be achieved through programmatic interfaces, including the APIC REST API, as well as automation frameworks such as Ansible and Terraform. As a roadmap, Nexus Dashboard will evolve into a central orchestrator for both infrastructure connectivity and logical tenant extension between sites.




This document further elaborates on the requirements and deployment procedures for infrastructure connectivity and logical tenant communication, encompassing Layer 2, Layer 3, and shared services between two ACI sites using Border Gateway.

In this document, the terms “site” and “fabric” are used interchangeably. Both refer to the same ACI domain managed by a single APIC cluster. This ACI domain can be either a single-pod ACI site or a multi-pod ACI site.

## Reference Topology

### Topology


The topology below is intended for configuration and deployment demonstrations only. For production environments requiring high availability and specific business requirements, this topology can be scaled by adding more leaf, border gateway and spine switches.



**Figure 1.** Reference physical topology

### IP Addressing and BGP ASN

The figure below illustrates the IP addressing and BGP AS numbers used in the guide. Although the examples in this guide use /30 subnets for point-to-point links, /31 subnets are also valid options.



**Figure 2.** IP Addressing and BGP AS numbers

- The External Data Plane IP, also known as the Multi-Site External VIP, is a virtual IP shared across all Border Gateways within the same ACI Pod. This loopback IP is user-configured per Pod and serves as the next-hop for Type-2 and Type-5 EVPN routes advertised to remote ACI site (VXLAN EVPN fabric). It is set up when creating Border Gateway Sets on the APIC controller.
- EVPN Loopback, also referred to as BGW PIP or VXLAN-RTEP, is a unique loopback IP address assigned to each Border Gateway. It serves as the source IP for all traffic destined to the remote VXLAN EVPN domain and functions as the next-hop for Type-5 prefixes received from the remote ACI site (VXLAN EVPN domain), which are injected into the local ACI fabric via VPNv4/VPNv6. This loopback address is configured during the setup of the VXLAN Infra L3Out.

## Supported Use Cases

This section introduces several supported use cases between ACI sites utilizing Border Gateways:

- Intra-subnet Communication (Bridged Flow): Stretched Layer 2 Network: Communication between endpoints residing in the same subnet across different ACI sites.
- Inter-subnet Communication (Routed Flow): Layer 3 communication between:
  - Directly connected endpoints across ACI Sites (e.g., an endpoint in Site 1 communicating with an endpoint in Site 2).
  - External endpoints across ACI Sites (e.g., an external endpoint through Site 1 communicating with an external endpoint through Site 2).
- North-South Communication across sites: Communication from internal endpoint in one site to external endpoint in another Site through L3Out in the same VRF.
- Shared Service (Inter-VRF): Communication between endpoints located in different VRFs across different ACI sites.
- Shared L3Out: Communication between endpoints located in one VRF in one ACI Site to external endpoint in a different VRF in another ACI Site.


For details, please refer to this section [Overlay Networking and Use Cases Deployment Details](#).

## Control Plane

### Control Plane Overview

This section provides an overview of the control plane established between two ACI sites. ACI Border Gateways (BGWs) build full-mesh BGP EVPN sessions with each other to facilitate this inter-site communication. Starting from ACI release 6.1(6) and 6.2(2), Route-Server deployments are also supported as an alternative topology, providing greater scalability and simplified BGP peering management.

Several types of EVPN sessions are established between ACI Border Gateways:



**Figure 3.** Border Gateways EVPN Sessions

- EVPN sessions between Border Gateways within the same Pod.
- EVPN sessions between Border Gateways and spine switches within the same Pod.
- EVPN sessions between Border Gateways across different Pods, which are part of the same ACI Site.
- EVPN sessions between Border Gateways across different ACI sites.
- The primary purpose of these EVPN sessions is to advertise EVPN routes both within and across sites. Although these routes include Type-2, Type-3, Type-4, and Type-5 routes, this document will focus on Type-2 and Type-5 routes.
- Type-2 routes are used to advertise endpoint information, including MAC and MAC-IP addresses.
- Type-5 routes, conversely, advertise subnet reachability across ACI sites both for BD subnets and external prefixes reachable via L3Outs.
- Type-3 routes, also known as Inclusive Multicast Ethernet Tag (IMET) routes, are exchanged between ACI Border Gateways (BGWs) to build the Bridge Domain (BD) flood list toward the remote ACI Site.
- Type-4 Ethernet Segment routes are used for Designated Forwarder (DF) election among all ACI BGWs across all Pods within the same ACI Site for each deployed Bridge Domain. The DF election


ensures that only one BGW is responsible for sending and receiving BUM (Broadcast, Unknown Unicast, and Multicast) traffic to and from the remote ACI Sites, preventing duplicate traffic forwarding.

As ACI is a policy-aware site, the EVPN route type is extended to carry the pcTag (policy-control Tag), also known as Class ID information, across ACI sites. Based on the pcTag information learned from the BGP EVPN control plane, ACI Border Gateways apply policies to allow or deny communication across sites. For VRFs stretched via Border Gateways, the use of Endpoint Security Groups (ESGs) is mandatory, as ESGs provide the policy classification required for consistent enforcement across sites. Policy implementation is, as usual, achieved using the contract model. Communication between endpoints within the same ESG is permitted without a contract, while communication between endpoints in different ESGs requires a contract with a permit filter.

EVPN establishes overlay sessions between the loopback interfaces (PIPs) of the Border Gateways. The reachability between these loopback interfaces is handled by the underlay protocol, which in this case is BGP. ACI Border Gateways are configured with external BGP (eBGP) peering to the Inter-Site Network (ISN) to ensure loopback address reachability between Border Gateways across Pods and sites. The configuration of the ISN devices can be automated by Nexus Dashboard or by API, or it can be performed manually using the CLI. The configuration on the ACI Border Gateway itself is managed via the APIC in each site. Centralized configuration for both ACI sites will be supported through Nexus Dashboard beginning with Release 4.4(1).

## Namespace Normalization

APIC automates the allocation of VXLAN VNIs for both VRF and BD VNIs. Consequently, it is common to see different VNI values for the same network constructs across different ACI sites. As shown in the screenshot below, site 1 uses VRF VNI 2162688, while site 2 uses VRF VNI 2097152. This same discrepancy occurs with BD VNIs. Without VNI normalization or translation, routes cannot be successfully exchanged between these sites and consequently the network constructs (VRFs or BDs) cannot be functionally extended.




**Figure 4.** Local VRF VNI on each ACI Site

To support route exchange between ACI sites with differing local VNIs, Cisco ACI utilizes a normalized VNI (also known as a global VNI). Essentially, the Border Gateway (BGW) facilitates all inter-site route exchanges through this normalized VNI. At a high level, when a BGW receives a local route from its home site, it performs a VNI translation from the local VNI to the normalized VNI before advertising the route. Conversely, the BGW at the destination site receives these updates and translates the normalized VNI back to its own local VNI before propagating the update to the spines within its home site.

While the normalized VNI is defined individually on each ACI site, the assigned values must be identical across all sites when stretching a VRF or BD to another site. The normalized VNI is defined when

associating them with the site's Border Gateway Set. Similarly, when deploying the same ESG across sites, the normalized pcTag must also be identical across all sites. This ESG is used to classify local resources (such as endpoints and prefixes from local L3Out) and/or remote resources to consistently apply the policy. These concepts and their associated workflows are introduced in the subsequent sections of this document. The figure below illustrates the local VRF (Layer 3) VNIs and their corresponding Normalized VNIs. The same applies to local Bridge Domain (Layer 2) VNIs and their corresponding Normalized BD VNIs.



**Figure 5.** Normalized VNI two-way translations

## Data Plane

Intra-site traffic behavior remains unchanged and continues to use iVXLAN encapsulation, which is the standard ACI data plane behavior. For inter-site traffic, however, the ACI Border Gateways (BGWs) on each site encapsulate traffic using standard VXLAN before forwarding it across the inter-site network.

The VXLAN tunnel source is a unique loopback IP address provisioned on each Border Gateway, commonly referred to as the BGW Primary IP (PIP) or EVPN Loopback IP. The VXLAN tunnel destination is an anycast IP address shared by all Border Gateways within the same ACI fabric (for single Pod fabrics) or within the same Pod (for Multi-Pod fabrics), commonly referred to as the Multi-Site External Virtual IP (VIP) or Multi-Site External Anycast IP. Both the PIP and VIP are defined during the provisioning of the VXLAN Infra Layer 3 Outside (L3Out) and the VXLAN Border Gateway policies, as described in the subsequent sections.

The VNI value carried in the VXLAN header is determined by the type of communication:

- **Layer 2 (Bridged) Communication:** The VNI used is the Layer 2 Normalized VNI, also referred to as the Bridge Domain Normalized VNI. This value is assigned by the administrator during the configuration of a stretched Bridge Domain across sites via the Border Gateway.
- **Layer 3 (Routed) Communication:** The VNI used is the Layer 3 Normalized VNI, also referred to as the VRF Normalized VNI. This value is assigned by the administrator during the configuration of a stretched VRF across sites via the Border Gateway.
- **Shared Service Communication:** A specialized form of routed communication in which the source and destination endpoints reside in different VRFs. In this communication model, the Normalized VNI of the destination VRF is used in the VXLAN header. Specifically:

◦For an inter-site traffic flow between VRF 1 and VRF 2, the VNI used is the Layer 3 Normalized VNI of VRF 2.


- For the corresponding reply from VRF 2 to VRF 1, the VNI used is the Layer 3 Normalized VNI of VRF 1.
- Shared L3Out Communication: A specialized form of Shared Service Communication in which one endpoint is a directly connected endpoint within an ACI site, while the other endpoint resides in an external network reachable via the L3Out connection of a different ACI site and belongs to a different VRF.

Traffic captures illustrating selected inter-site communication flows including Bridged, Routed, Shared Service (Inter-VRF), and Shared L3Out are provided within their respective use case sections. It is strongly recommended that readers review the [Bridged \(Layer 2\) Communication](#) section first, as it contains detailed information that is applicable to all subsequent communication flows.

## Underlay and Overlay Infrastructure Configuration

The infra tenant in ACI is a special predefined tenant that represents the underlay network of the fabric. All underlay and overlay sessions originating from the ACI Border Gateway including connectivity to the ISN (underlay) and to other ACI sites (overlay) are configured within this tenant. This section provides a step-by-step configuration for both the underlay and the overlay networks. As the overlay relies on the underlay to exchange the routes for the loopback IP addresses, it is essential to complete the underlay configuration before proceeding with the overlay setup.

Within the infra tenant, several new objects have been introduced to facilitate the construction of underlay and overlay networks for site interconnection.



**Figure 6.** Infra tenant VXLAN Infra L3Outs and VXLAN Gateway


- VXLAN Infra L3Outs: This serves as the foundational “underlay” connection, used to connect ACI Border Gateways (BGWs) to the Inter-Site Network (ISN). The VXLAN Infra L3Out is associated with a Border Gateway Set, an object representing a group of ACI Border Gateways part of the same fabric, to signal that these gateways should utilize this specific Infra L3Out for overlay connectivity.

- **VXLAN Gateway:** This sub-menu under Policies contains the logical configuration required to represent the ACI site as a “site” within a broader VXLAN EVPN ecosystem. It consists of three key objects:
  - **VXLAN Site:** Defines the local ACI site as a unique EVPN site. It requires a site ID, which ensures the site is uniquely identified when exchanging routes with remote sites, thereby preventing routing loops.
  - **Border Gateway Sets:** This object represents the collection of all Border Gateways within the ACI site. In a Multi-Pod environment, Border Gateways must be deployed in each pod. As an administrator, you must assign a unique External Anycast (External Data Plane IP also known as Multi-Site external VIP) to the Border Gateways in each pod. For example, if you have two pods with Border Gateways, you must assign two separate External Anycast IP addresses, one for each pod’s group of Border Gateways. This External Anycast IP acts as the destination tunnel endpoint for remote VXLAN sites communicating with the ACI site. Note that there is only one Border Gateway Set per site. Additionally, the APIC automatically assigns a unique Internal Anycast IP to all Border Gateways in the site for internal data plane communication within the ACI site. The Border Gateway Set is then linked to the Remote VXLAN Sites configuration.
  - **Remote VXLAN Sites:** Defines the external VXLAN EVPN sites you wish to interconnect with. For instance, from the perspective of ACI site 1, ACI site 2 is defined as a Remote VXLAN site. This is where you specify reachability information, such as the remote site’s BGW loopback IP addresses, to establish the EVPN Multi-Site relationship. Starting from ACI releases 6.1(6) and 6.2(2), this same configuration is also used to define connectivity to a Route-Server, providing an alternative to full-mesh BGP EVPN peering between Border Gateways.

In this example, the underlay BGP configuration on the ISN device is configured manually via Cisco NX-OS CLI. For each ACI site, the underlay configuration is done using the APIC GUI. Detailed steps, including screenshots, will be provided in the following sections.

## Inter-Site Network Configuration - Underlay

The figure below shows the IP addresses and interfaces used in the underlay BGP configuration example.



**Figure 7.** ISN Underlay IP addressing

To provide underlay connectivity between the two sites to communicate using VXLAN BGP EVPN, the ISN devices must provide a routed transport to carry the EVPN control plane and VXLAN data plane. To accommodate this, each ISN device will have the BGP enabled, and will peer eBGP to Border Gateways in both ACI sites. This ensures that any IP address injected from each site will automatically be advertised to



---

the other sites and allow IP reachability to be established. Although this reference topology uses single ISN device to represent ISN network, it is recommended to use at least two ISN devices for redundancy.

The following outlines the primary configuration steps on the ISN device which is Cisco Nexus 9000 running NX-OS. Note that object names, such as VRF, are provided for reference only; you should employ names consistent with your network's naming conventions.

Proceed with the following key configuration steps on the ISN device.

- If the ISN device is shared between other function, it is recommended to create a dedicated VRF for inter-site control plane and data plane traffic forwarding.
- Assign IP addresses and the relevant VRF to the physical interfaces connecting the ISN device to the Border Gateways of each site.
- Configure BGP and establish BGP peers with the Border Gateways of each site, and between individual Border Gateways, using the appropriate Autonomous System Numbers.

The sample configuration below uses routed physical interfaces on the ISN to connect to the Border Gateways. If the use of routed sub-interface is preferred, any appropriate VLAN ID can be used; the commonly referenced VLAN 4 is supported but not required.

```
# Create a VRF
vrf context bgw
    address-family ipv4 unicast

# Interface configuration
interface Ethernet1/15
    description --> bgw-leaf1 51
    mtu 9216
    vrf member bgw
    ip address 172.16.63.6/30
    no shutdown

interface Ethernet1/18
    description --> bgw-leaf2 e1/52
    mtu 9216
    vrf member bgw
    ip address 172.16.63.2/30
    no shutdown

interface Ethernet1/21
    description bgw-leaf202 e1/21
    mtu 9216
    vrf member bgw
    ip address 172.16.63.18/30
    no shutdown
```



```
interface Ethernet1/22
  description --> qt-bgw-805
  mtu 9216
  vrf member bgw
  ip address 172.16.63.30/30
  no shutdown

# BGP configuration
router bgp 65100
  vrf bgw
    neighbor 172.16.63.1
      remote-as 100
      update-source Ethernet1/18
      address-family ipv4 unicast

    neighbor 172.16.63.5
      remote-as 100
      update-source Ethernet1/15
      address-family ipv4 unicast

    neighbor 172.16.63.17
      remote-as 100
      update-source Ethernet1/21
      address-family ipv4 unicast

    neighbor 172.16.63.29
      remote-as 400
      update-source Ethernet1/22
      address-family ipv4 unicast
```

## ACI VXLAN L3Out - VXLAN Gateway

The followings are the pre-requisite and steps to configure VXLAN L3Out that is an infra L3Out object to build underlay BGP peering from ACI Border Gateway to ISN device.

- Make sure ACI leaf nodes are registered with Border Gateway role
- In the infra tenant, create a VXLAN L3Out to do underlay BGP peering with ISN devices

ACI releases 6.1(6) and 6.2(2) add support for the Border Gateway Route Server, which streamlines the BGP overlay control plane by reducing the required number of overlay BGP sessions. This model uses overlay BGP EVPN sessions between the ACI Border Gateways and Route Servers, providing an alternative to full-mesh inter-site overlay BGP EVPN peering between Border Gateways. Configuration steps and best practices are covered at the end of this section.

## ACI Site 1 - Inventory

Border Gateway is new role; we need to explicitly register the leaf with Border Gateway role. If the leaf had been already registered with leaf role, it must be decommissioned and re-registered with Border Gateway role. The leaf will be displayed with the Node Type “Border Gateway Leaf” in the fabric inventory.




Figure 8. ACI Site 1 Inventory Fabric Membership

## ACI Site 1 - Border Gateway Sets

At the time of writing, only one Border Gateway Set is permitted per site. As an APIC administrator, you must manually define a unique External Data Plane IP Address for each ACI Pod. The External


Data Plane IP is an anycast IP address shared by all Border Gateways within the same Pod. Also known as the Multi-Site External VIP, this IP address has the following properties and purposes:

- Used as the next-hop for Type-2 and Type-5 EVPN routes advertised to remote VXLAN EVPN fabrics.
- Serves as the destination IP for Layer 2 and Layer 3 communications initiated from the VXLAN EVPN domain toward endpoints or external networks via ACI fabric.
- Has a unique value per Pod.

The Internal Anycast IP Address (Internal Anycast TEP) is automatically assigned by the APIC to all Border Gateways within the same ACI site. Also known as the Multi-Site Internal VIP, this Internal Anycast IP address has the following properties and purposes:


- Used as the source IP for all traffic received from the remote ACI sites and re-encapsulated to be sent into the ACI fabric.
- Used as the destination IP for all traffic destined to remote endpoints that are part of stretched BDs.
- Assigned as a common value to all ACI Border Gateways within the same site (regardless of single Pod or Multi-Pod).

The Border Gateway Set is associated with the Remote VXLAN Sites object, which is configured in the following step.



**Figure 9.** ACI Site 1 Border Gateway Sets

To create a Border Gateway Set, navigate to Policies -> VXLAN Gateway in the infra tenant. Right-click on Border Gateway Sets and select Create Border Gateway Set Policy. A workflow will open to guide you through the creation process. Once the set is created, it can be used in the VXLAN Infra L3Out creation workflow to reference the Border Gateway Set to the VXLAN Infra L3Out.



**Figure 10.** Create a Border Gateway Set Policy


## ACI Site 1 - VXLAN Infra L3Outs

Upon joining the fabric, the Border Gateway, like any other leaf switch, automatically obtains a router ID from the ACI site's TEP pool (in this example, 10.1.248.7 for the first Border Gateway). This router ID is used for the MP-BGP sessions to the spines and is referred to as the Operational Router ID.

When configuring the VXLAN Infra L3Out, it is recommended to leave the Router ID field blank to retain the existing Router ID. In this case, the Router ID field will display as 0.0.0.0, while the actual router ID, referred to as the Operational Router ID (10.1.248.7), remains in use. While it is technically possible to configure a different router ID, doing so will cause the existing MP-BGP sessions on the Border Gateway to flap.


When configuring a node profile, you can specify the loopback interface under the node. The IP address assigned to the loopback interface on the Border Gateway is used to establish BGP EVPN control plane peering with Border Gateways in other ACI sites or with a Route Server.

To create VXLAN Infra L3Out, from infra tenant, navigate to Networking, right click on VXLAN Infra L3Outs.



**Figure 11.** Create a VXLAN Infra L3Out

Give it a name for example vxlan-infra and hit Next to continue.



**Figure 12.** VXLAN Infra L3Out vxlan-infra

Choose a Border Gateway from the Node ID drop-down list. A warning message appears with additional information about the Operational Router ID. Click OK to continue.

\_\_\_\_\_

Configure the following fields:

- Node Profile name
- Interface Profile name
- Loopback Address: The source IP address used to establish the BGP EVPN control plane to remote Border Gateways or a Route Server.
- Interface IPv4 address: The IP address of the local interface.
- Peer IPv4 Address: The IP address of the connected ISN interface.
- Remote ASN: The BGP ASN of the ISN device.
- MTU: Use the default value 9216

This example uses a routed interface, but routed sub-interfaces are also supported. Any VLAN ID can be used for routed sub-interfaces, there is no requirement to use VLAN 4, which is required for spine uplinks in ACI Multi-Pod and Multi-Site deployments. The Border Gateway must use a downlink port to connect to the ISN device. Default uplink ports are intended for connectivity to the ACI spines; however, if needed, an uplink port can be converted to a downlink port and used for ISN connectivity. To add more interfaces, click the + button. Once complete, click Next to continue.

Create VXLAN Infra L3Out

1. Connectivity 2. Nodes And Interfaces 3. Policy Configuration

**Nodes and Interfaces**  
Select the Border Gateway nodes (BGWs) for the VXLAN configuration.

Node Profile Name: vxlan-infra-node-pod1

Interface Profile Name: bgw-leaf1

BFD Interface Policy: select a value

Interface Types  
Layer 3: ☒ Interface ☐ Sub-Interface  
Layer 2: Port

Nodes

| Node ID              | Router ID | Loopback Address |                                                  |
|----------------------|-----------|------------------|--------------------------------------------------|
| bgw-leaf1 (Node-1T1) |           | 111.101          | <input type="button" value="+"/> Hide Interfaces |

| Interface                                                                     | MTU (bytes) | IPv4 Address                                  | Peer IPv4 Address | Remote ASN |                                  |
|-------------------------------------------------------------------------------|-------------|-----------------------------------------------|-------------------|------------|----------------------------------|
| eth1/51<br><small>CE-eth1/51 topology (pod1-leaf1-101/pathsp-eth1/23)</small> | 9216        | 172.16.63.5/30<br><small>address/mask</small> | 172.16.63.6       | 65100      | <input type="button" value="+"/> |

Previous Cancel Next

**Figure 14.** VXLAN Infra L3Out node, interface profile, peer.

On the next screen, select the Border Gateway Set created in the previous step and click Finish to complete the configuration. You may check the “Configure VXLAN Remote Fabrics” checkbox to proceed a VXLAN Remote Fabric configuration in the same wizard.

Create VXLAN Infra L3Out

1. Connectivity 2. Nodes And Interfaces 3. Policy Configuration

**VXLAN Policy Configuration**  
VXLAN Border Gateway Set and VXLAN Remote Fabrics.

Border Gateway Set

Policy: bgw

Configure VXLAN Remote Fabrics: ☐

Previous Cancel Finish

**Figure 15.** VXLAN Infra L3Out Attach Border Gateway Set

If a Border Gateway Set has not yet been created, click the dropdown list and select “Create Border Gateway Set Policy” to launch the creation workflow. Once a Border Gateway Set is created, the configuration workflow returns to this main window.

Create VXLAN Infra L3Out




Figure 16. Create Border Gateway Set inside VXLAN Infra L3Out creation workflow.




Figure 17. VXLAN Infra L3Out

The figure above shows the completed VXLAN Infra L3Out object and its Border Gateway Set Policy. This set represents all Border Gateways in the site. You can define the set during the VXLAN L3Out creation workflow or later in the Policy tab. However, the VXLAN Infra L3Out must be attached to a Border Gateway Set Policy to successfully create the overlay EVPN session. The next screenshots show completed objects including node profiles, interface profiles.

ACI Site 1 - Border Gateway Node Profiles




Figure 18. ACI Site 1 BGW Logical Node Profile






Figure 19. ACI Site 1 bgw-leaf1 Node Association




Figure 20. ACI Site 1 bgw-leaf2 Node Association

## ACI Site 1 - Border Gateway Interface Profiles







Figure 21. ACI Site 1 Border Gateway bgw-leaf1 Logical Interface Profile




**Figure 22.** ACI Site 1 Border Gateway bgw-leaf1 BGP Peer Connectivity Profile




**Figure 23.** ACI Site 1 Border Gateway bgw-leaf2 Logical Interface Profile




**Figure 24.** ACI Site 1 Border Gateway bgw-leaf2 BGP Peer Connectivity Profile



**Figure 25.** ACI Site 1 bgw-leaf202 (in pod2) Node Association




**Figure 26.** ACI Site 1 bgw-leaf202 (in pod2) Logical Interface Profile



**Figure 27.** ACI Site 1 bgw-leaf202 (in pod2) BGP Peer Connectivity Profile

## ACI Site 1 - VXLAN Site ID

The VXLAN Site object uniquely identifies the local site, which in this example is ACI Site 1 (site1). At the time of writing, only one VXLAN Site is permitted per site; therefore, the APIC UI prevents the creation of a new VXLAN Site if one already exists. It is a common practice to use the BGP Autonomous System Number (ASN) as the Site ID though it is not mandatory.




**Figure 28.** ACI Site 1 VXLAN Site

## ACI Site 1 - Remote VXLAN Sites

The Remote VXLAN Sites object (displayed as Remote VXLAN Fabrics in the APIC GUI) defines the external site to which local ACI site (site1 in this example) will connect. In this step, specify the Peer IP Address (5.5.5.105 in this example), which is the loopback address of the Border Gateway in the remote site (ACI site2).

The Remote VXLAN Sites object is also used to define a Route Server, enabling all ACI site Border Gateways to establish BGP EVPN control plane peering to the Route Server. This eliminates the need for direct peering between Border Gateways across sites.

As an APIC administrator, you must also associate the Remote VXLAN Site with the local Border Gateway Set to complete the configuration.



**Figure 29.** ACI Site 1 Remote VXLAN Fabric

# ACI Site 2 - Inventory




Figure 30. ACI Site 2 Inventory – Fabric Membership

# ACI Site 2 - Border Gateway Sets

Since ACI Site 2 (site2) is a single-pod site, only one External Data Plane IP needs to be configured.




Figure 31. ACI Site 2 Border Gateway Sets

# ACI Site 2 - VXLAN Infra L3Outs




Figure 32. ACI Site 2 VXLAN Infra L3Outs

# ACI Site 2 - Border Gateway Node Profiles




Figure 33. ACI Site 2 Border Gateway qt-bgw805 Logical Node Profile

## ACI Site 2 - Border Gateway Interface Node Profiles

The screenshot shows the ACI APIC (site2) interface. The left sidebar displays the navigation tree with 'infra' and 'qt-vxlan-infra' highlighted. The main panel shows the 'Logical Interface Profile - qt-vxlan-infra\_interfaceProfile' configuration. The 'Properties' section includes 'Name: qt-vxlan-infra\_interfaceProfile' and 'Description: optional'. The 'Sub-Interfaces' table is empty, with a note: 'No items have been found. Select Actions to create a new item.' The 'Interfaces' table at the bottom contains one entry: 'Pod-1/Node-805/eth1/49' with IP Address '172.16.63.29/30', MAC Address '00:22:BD:F8:19:FF', and MTU (bytes) '9216'.

| Path                   | IP Address      | MAC Address       | MTU (bytes) | VLAN Encap |
|------------------------|-----------------|-------------------|-------------|------------|
| Pod-1/Node-805/eth1/49 | 172.16.63.29/30 | 00:22:BD:F8:19:FF | 9216        |            |

Figure 34. ACI Site 2 Border Gateway - Logical Interface Profile

The screenshot shows the ACI APIC (site2) interface. The left sidebar displays the navigation tree with 'infra' and 'qt-vxlan-infra' highlighted. The main panel shows the 'BGP Peer Connectivity Profile' configuration. The 'Properties' section includes 'Peer IPv4 Address: 172.16.63.30/30', 'Description: optional', 'Remote AS: 65100', 'Admin State: Disabled', 'Password:', 'Confirm Password:', 'Peer Controls: Bidirectional Forwarding Detection', 'Address Type Controls: AF Ucast', 'TTL: 1', 'BGP Peer Prefix Policy: select a value', 'Local-AS Number Config:', and 'Local-AS Number:'. The 'BGP Peer 172.16.63.30/30- Node-805/1/49' is highlighted in the left sidebar.

| Path                   | IP Address      | MAC Address       | MTU (bytes) |
|------------------------|-----------------|-------------------|-------------|
| Pod-1/Node-805/eth1/49 | 172.16.63.29/30 | 00:22:BD:F8:19:FF | 9216        |

Figure 35. ACI Site 2 Border Gateway qt-leaf805 BGP Peer Connectivity Profile

## ACI Site 2 - VXLAN Site

The VXLAN Site can be assigned any descriptive name; in this example, the site representing ACI Site 2 is named qt-site. It is common practice to use the BGP Autonomous System Number (ASN) as the Site ID.






Figure 36. ACI Site 2 VXLAN Site

## ACI Site 2 - Remote VXLAN Sites

Because the remote VXLAN site (ACI Site 1) consists of three Border Gateways: two in Pod 1 and one in Pod 2, we must configure three corresponding EVPN peers. These are defined using the loopback IP addresses of the ACI Site 1 Border Gateways: 1.1.1.101, 1.1.1.102, and 2.2.2.202.





Figure 37. ACI Site 2 Remote VXLAN Fabrics

## Verification

This section covers verification of the underlay and overlay configurations by validating routing and control plane reachability. For reference, the topology with IP addressing is shown again below:



**Figure 38.** Topology with IP addressing

While CLI commands are available for detailed troubleshooting, the APIC GUI offers built-in features that simplify the process of monitoring BGP EVPN adjacency status.

The following figures show the successful configuration, where the first Border Gateway in ACI Site 1 has established five EVPN adjacencies.

- 1.1.1.102: The second Border Gateway in Pod 1 of ACI Site 1
  - This EVPN session is used to exchange EVPN Type-4 routes for Designated Forwarder (DF) election.
- 2.2.2.102: The first Border Gateway in Pod 2 of ACI Site 1
  - This EVPN session is used to exchange EVPN Type-4 routes for Designated Forwarder (DF) election.
- 5.5.5.105: The Border Gateway in the remote site, ACI Site 2
  - This EVPN session is used to exchange EVPN Type-2, Type-3, Type-5 routes.
- 10.1.248.0: The first spine in Pod 1 of ACI Site 1
  - This EVPN session is used to exchange EVPN Type-2 between Border Gateway and Spine.
- 10.1.248.1: The second spine in Pod 1 of ACI Site 1
  - This EVPN session is used to exchange EVPN Type-2 between Border Gateway and Spine.

**APIC (site1)**

System **Tenants** Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | infra | vc9-demo | tmerkerl | tmerkecluster1

**infra**

- Quick Start
- infra
  - Application Profiles
  - Networking
    - Bridge Domains
    - VRFs
    - L2Outs
    - L3Outs
    - SR-MPLS Infra L3Outs
    - VXLAN Infra L3Outs**
      - vxlan-infra
        - Logical Node Profiles
          - vlan-infra-node-pod1
            - Configured Nodes
              - topology/pod-1/node-102
              - topology/pod-1/node-111
                - ARP for VRF-overlay-1
                - BGP for VRF-overlay-1
                - Neighbors**
        - Logical Interface Profiles
          - vlan-infra-node-pod2
        - Dot1Q Tunnels

**Neighbors**

| Name        | State       | Neighbor Address Family     | Neighbor Address Family Capability |
|-------------|-------------|-----------------------------|------------------------------------|
| 1.1.1.102   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 2.2.2.202   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 5.5.5.105   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 10.1.248.0  | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 10.1.248.1  | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 172.16.63.6 | established | IPv4 Unicast Address Family | First EOR Received                 |

**Figure 39.** ACI Site 1 Border Gateway bgw-leaf1 BGP EVPN neighbors

**APIC (site1)**

System **Tenants** Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | infra | vc9-demo | tmerkerl | tmerkecluster1

**infra**

- Quick Start
- infra
  - Application Profiles
  - Networking
    - Bridge Domains
    - VRFs
    - L2Outs
    - L3Outs
    - SR-MPLS Infra L3Outs
    - VXLAN Infra L3Outs**
      - vxlan-infra
        - Logical Node Profiles
          - vlan-infra-node-pod1
            - Configured Nodes
              - topology/pod-1/node-102
              - topology/pod-1/node-111
                - ARP for VRF-overlay-1
                - BGP for VRF-overlay-1
                - Neighbors**
        - Logical Interface Profiles
          - vlan-infra-node-pod2
        - Dot1Q Tunnels

**Neighbors**

| Name        | State       | Neighbor Address Family     | Neighbor Address Family Capability |
|-------------|-------------|-----------------------------|------------------------------------|
| 1.1.1.101   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 2.2.2.202   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 5.5.5.105   | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 10.1.248.0  | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 10.1.248.1  | established | L2VPN EVPN Address Family   | First EOR Received                 |
| 172.16.63.2 | established | IPv4 Unicast Address Family | First EOR Received                 |

**Figure 40.** ACI Site 1 Border Gateway bgw-leaf2 BGP EVPN neighbors




Figure 41. ACI Site 1 Border Gateway bgw-leaf202 BGP EVPN neighbors




Figure 42. ACI Site 2 Border Gateway qt-bgw805 BGP EVPN neighbors

## Using Route Server

With the Border Gateway Route Server (or “Route Server” for short), BGP EVPN sessions are established between ACI Border Gateways and the Route Servers, eliminating the need for direct inter-site BGP EVPN peering. These sessions are built between the loopback interfaces of the ACI Border Gateways and the Route Server. Loopback reachability is carried via BGP IPv4, while the Inter-Site Network (ISN) continues to handle underlay BGP functions exclusively.


- A Route Server is a dedicated node that acts as a centralized EVPN BGP route reflector like entity between fabrics using eBGP.
- Deployment model: Supported as dedicated standalone nodes; also supports co-location where the same physical node serves as both the Route Server and the ISN (Inter-Site Network) forwarding node.
- Protocol: All sessions between BGWs and Route Servers are eBGP sessions.
- Redundancy: On production it is recommended to deploy more than one Route Server for redundancy; no BGP overlay session is required between the Route Servers themselves.
- AS Flexibility: The Route Server cluster can reside within a single AS or be spread across multiple ASes.

Although the Route Server and ISN functions can reside on the same device, this deployment example utilizes a dedicated Nexus 9000 NX-OS for the Route Server. For production environments, deploying Route Servers in a redundant pair is recommended to ensure high availability.

## Routing Sessions

The architecture consists of three primary session types:

- BGP IPv4 sessions between the ACI Border Gateways (in each Pod/Site) and the ISN.
- BGP IPv4 sessions between the Route Server and the ISN.
- BGP EVPN sessions between the ACI Border Gateways and the Route Server.



**Figure 43.** Infra VXLAN L3Out Route Server option

## Configuration Logic

From a configuration perspective, the underlay VXLAN infrastructure remains unchanged across both ACI sites. The only modification is to the overlay BGP EVPN sessions. Instead of defining the peer ACI site as a remote site, both Site 1 and Site 2 now point to the Route Server as the remote site.

## Configuration Steps

- Configure external underlay BGP sessions between the ISN and the ACI Border Gateways.
- Configure external underlay BGP sessions between the ISN and the Route Server.
- On the Route Server, advertise the Loopback0 interface into BGP.
- On the Route Server, configure BGP EVPN peering with the ACI Border Gateways.
- On both ACI sites, configure the Route Server as a Remote VXLAN Fabric.
- (Optional) Remove any existing legacy remote VXLAN fabric configurations if transitioning from a non-Route Server environment. Create Route Server as Remote VXLAN fabric.

## ISN configuration

```
# Create a VRF
vrf context bgw
  address-family ipv4 unicast

# Interface configuration
interface Ethernet1/15
  description --> bgw-leaf1 51
  mtu 9216
  vrf member bgw
  ip address 172.16.63.6/30
  no shutdown

interface Ethernet1/18
  description --> bgw-leaf2 e1/52
  mtu 9216
  vrf member bgw
  ip address 172.16.63.2/30
  no shutdown

interface Ethernet1/21
  description bgw-leaf202 e1/21
  mtu 9216
  vrf member bgw
  ip address 172.16.63.18/30
  no shutdown

interface Ethernet1/22
```

```
description --> qt-bgw-805
mtu 9216
vrf member bgw
ip address 172.16.63.30/30
no shutdown

interface Ethernet1/35
description --> Route-Server
mtu 9216
vrf member bgw
ip address 172.16.63.34/30
no shutdown

# BGP configuration
router bgp 65100
vrf bgw
neighbor 172.16.63.1
remote-as 100
update-source Ethernet1/18
address-family ipv4 unicast
disable-peer-as-check

neighbor 172.16.63.5
remote-as 100
update-source Ethernet1/15
address-family ipv4 unicast
disable-peer-as-check

neighbor 172.16.63.17
remote-as 100
update-source Ethernet1/21
address-family ipv4 unicast
disable-peer-as-check

neighbor 172.16.63.29
remote-as 400
update-source Ethernet1/22
address-family ipv4 unicast

neighbor 172.16.63.33
remote-as 65109
update-source Ethernet1/35
```

```
address-family ipv4 unicast
```

### Route Server configuration

```
# Interface configuration
```

```
interface loopback0
```

```
ip address 9.9.9.109/32 tag 54321
```

```
interface Ethernet1/51
```

```
description --> ISN
```

```
no switchport
```

```
ip address 172.16.63.33/30 tag 54321
```

```
no shutdown
```

```
# Route-map configuration
```

```
route-map rmap-redist-direct permit 10
```

```
match tag 54321
```

```
route-map unchanged permit 10
```

```
set ip next-hop unchanged
```

```
# BGP IPv4 Unicast and BGP EVPN configuration
```

```
router bgp 65109
```

```
address-family ipv4 unicast
```

```
network 9.9.9.109/32
```

```
address-family l2vpn evpn
```

```
retain route-target all
```

```
template peer OVERLAY-PEERING
```

```
update-source loopback0
```

```
ebgp-multihop 5
```

```
address-family l2vpn evpn
```

```
send-community
```

```
send-community extended
```

```
route-map unchanged out
```

```
neighbor 1.1.1.101
```

```
inherit peer OVERLAY-PEERING
```

```
remote-as 100
```

```
description multi-site overlay session to ACI Site 1 BGW bgw-leaf1
```

```
address-family l2vpn evpn
```

```
rewrite-evpn-rt-asn
```

```
neighbor 1.1.1.102
```

```
inherit peer OVERLAY-PEERING
```

```
remote-as 100
```

```
description multi-site overlay session to ACI Site 1 BGW bgw-leaf2
```



```
address-family l2vpn evpn
    rewrite-evpn-rt-asn
neighbor 2.2.2.202
    inherit peer OVERLAY-PEERING
    remote-as 100
    description multi-site overlay session to ACI Site 1 BGW bgw-leaf202
address-family l2vpn evpn
    rewrite-evpn-rt-asn
neighbor 5.5.5.105
    inherit peer OVERLAY-PEERING
    remote-as 400
    description multi-site overlay session to ACI Site 2 BGW qt-leaf805
address-family l2vpn evpn
    rewrite-evpn-rt-asn
neighbor 172.16.63.34
    remote-as 65100
    description BGP session to ISN
    update-source Ethernet1/51
    address-family ipv4 unicast
```


Since both ACI Sites are using RT in the same format ASN:VNI, and Border Gateway and Route Server are in different ASNs, it is critical to include the “rewrite-evpn-rt-asn” command (supported in Nexus 9000 platform) in your Route Server configuration. This command ensures the Route Server modifies the EVPN Route Target (RT) and Autonomous System Number (ASN) before forwarding updates to BGP EVPN peers. For example, if the ACI Site 1 Border Gateway sends an update with RT 100:30004, the Route Server rewrites it to 65109:30004 before advertising it to Site 2. Without this rewrite, the Site 2 Border Gateway would reject the update because it does not maintain a direct BGP EVPN session with Site 1 and therefore cannot process the original RT. If the Route Server is deployed different platform than Nexus 9000 then the manual rewrite must be utilized.

Unlike the default eBGP behavior, the Route Server must not rewrite the next hop to itself. Instead, it must preserve the original next hop, which is the external anycast address of the originating Border Gateway. Accordingly, a route map must be configured under “address-family l2vpn evpn” to ensure that the next-hop attribute is preserved.

#### **Peer ACI Border Gateway with Route Server**

The underlay infrastructure, specifically the VXLAN Infra L3Out connectivity between the ACI Border Gateway and the ISN device, remains unchanged. Ensure that these underlay configuration steps are completed before proceeding. This section outlines the integration of the Route Server, enabling the ACI Border Gateway to establish BGP EVPN control-plane peering with the Route Server. When using the Route Server model, from the perspective of an ACI site, the Route Server functions as the remote VXLAN fabric, since the ACI Border Gateways do not establish direct peering with the remote fabric but instead peer with the Route Server.

Navigate to Infra tenant, Policies, VXLAN Gateway, right click on Remote VXLAN Fabrics and click Create Remote VXLAN Fabric.



**Figure 44.** ACI Site 1 Create Remote VXLAN Fabric

Configure a name for the Remote VXLAN fabric. Since it is a route server, this example uses “Route-Server” as the name. Then, click “+” to add the route server information such as the IP address and AS number.

The screenshot shows the 'Create Remote EVPN Peer' dialog box. The 'Peer IP Address' is set to '9.9.9.109', 'Remote AS' is '65109', and 'Admin State' is 'Enabled'. The 'Peer Type' is 'VXLAN BGW Connectivity'. The 'BGP Peer Prefix Policy' is 'select a value'. The 'Local-AS Number' is '1'.

**Figure 45.** Create a Remote EVPN Peer using the Route Server IP address and ASN

Click OK to proceed. The next step is to associate the Route Server with the Border Gateway Sets. In the Associated Border Gateway Set, click “+” to add Border Gateway Sets.

The screenshot shows the 'Create Remote VXLAN Fabric' dialog box. The 'Name' is 'Route-Server'. The 'Remote EVPN Peers' table shows one entry: '9.9.9.109' with 'TTL' '8'. The 'Associated Border Gateway Set' is 'Border Gateway Set'.

**Figure 46.** ACI Site 1 Associate Route Server to a Border Gateway Set

Create Remote VXLAN Fabric

Name: Route-Server

Remote EVPN Peers:

| Peer IP Address | TTL |
|-----------------|-----|
| 9.9.9.109       | 8   |

Associated Border Gateway Set:

Border Gateway Set

bgw

Cancel

Submit

**Figure 47.** Click Submit to associate the Border Gateway Set

The Route Server now appears as a Remote VXLAN Fabric.

APIC (site1)

System

Tenants

Fabric

Virtual Networking

Admin

Operations

Integrations

ALL TENANTS

Add Tenant

Tenant Search: name or descr

common

infra

bgw

Fortune

demo

infra

Quick Start

infra

Application Profiles

Networking

Contracts

Policies

Protocol

Troubleshooting

Host Protection

Monitoring

NetFlow

VMM

Endpoint Tags

VXLAN Gateway

VXLAN Site

Border Gateway Sets

Remote VXLAN Fabrics

aci-site2

Route-Server

Services

Remote VXLAN Fabric

Name: Route-Server

Remote EVPN Peers:

| Peer IP Address | TTL |
|-----------------|-----|
| 9.9.9.109       | 8   |


Associated Border Gateway Set:

Border Gateway Set

bgw


**Figure 48.** ACI Site 1 Route Server as a remote VXLAN Fabric

If Site 2 was previously configured as a remote site, it can now be removed. In the Remote VXLAN Fabrics window, right-click aci-site2 and select Delete.



**Figure 49.** ACI Site 1 Delete the old aci-site2

Repeat the same steps for ACI Site 2. Once the Route Server is added and the old remote site is deleted, the configuration should appear as follows.



**Figure 50.** ACI Site 2 Route Server

### Route Server Verification

The verification process is identical to a setup without a Route Server. When a Route Server is deployed, the BGP EVPN control plane is established between each ACI site Border Gateway and the Route Server, eliminating the need for direct BGP EVPN sessions between Border Gateways across different sites.

On the Route Server, the show “bgp l2vpn evpn summary” command displays four established BGP EVPN sessions with the ACI Border Gateways (three from ACI Site 1 and one from ACI Site 2).

```

Route-Server# show bgp l2vpn evpn summary
BGP summary information for VRF default, address family L2VPN EVPN
BGP router identifier 9.9.9.109, local AS number 65109
BGP table version is 325, L2VPN EVPN config peers 4, capable peers 4
116 network entries and 151 paths using 45864 bytes of memory
BGP attribute entries [86/31648], BGP AS path entries [9/106]
BGP community entries [0/0], BGP clusterlist entries [0/0]


Neighbor      V   AS    MsgRcvd  MsgSent  TblVer  InQ  OutQ  Up/Down  State/PfxRcd
1.1.1.101     4   100      447      389      325   0    0  05:55:19  45
1.1.1.102     4   100      447      389      325   0    0  05:55:17  45
2.2.2.202     4   100      388      389      325   0    0  05:55:17  27
5.5.5.105     4   400      398      403      325   0    0  05:50:53  34

Neighbor      T   AS Type-1   Type-2   Type-3   Type-4   Type-5   Type-6   Type-7   Type-8   Type-12
1.1.1.101     I  100 0        22        7         0        16        0        0        0        0
1.1.1.102     I  100 0        22        7         0        16        0        0        0        0
2.2.2.202     I  100 0         7         7         0        13        0        0        0        0
5.5.5.105     I  400 0        15         5         0        14        0        0        0        0

```

**Figure 51.** Route server evpn summary

Established BGP EVPN sessions can be verified via the APIC GUI at each site or through the CLI on the respective Border Gateways. Within the APIC GUI, status is available under the Inventory tab or the infra tenant; this section demonstrates verification through the infra tenant. The output below focuses on the first Border Gateway in ACI Site 1, Pod 1. A similar verification procedure can be applied to all other Border Gateways and ACI sites.



**Figure 52.** L2VPN EVPN Address Family

Alternatively, checks the status using the command on the Border Gateway in vsh mode.

```

bgw-leaf1# show bgp l2vpn evpn summary
BGP summary information for VRF overlay-1, address family L2VPN EVPN
BGP router identifier 10.1.248.7, local AS number 100
BGP table version is 39014, L2VPN EVPN config peers 5, capable peers 5
126 network entries and 149 paths using 39672 bytes of memory
BGP attribute entries [74/26048], BGP AS path entries [0/0]
BGP community entries [0/0], BGP clusterlist entries [5/28]

Neighbor      V   AS    MsgRcvd  MsgSent  TblVer  InQ  OutQ  Up/Down  State/PfxRcd
1.1.1.102     4   100  40337    40319    39014   0    0    3w3d    1
2.2.2.202     4   100  48610    48595    39014   0    0    4w2d    1
9.9.9.109     4  65109     390      376     39014   0    0  05:57:22  26
10.1.248.0    4   100  55960    48907    39014   0    0    4w5d    23
10.1.248.1    4   100  56019    48907    39014   0    0    4w5d    23

```

**Figure 53.** ACI Site 1 - BGP EVPN established session from Border Gateway to Route Server

Please note that after this section, the design will revert to the non-Route Server design. From a high-level architectural perspective, there is no difference in data plane forwarding behavior between the Route Server and Non-Route Server designs, as the Route Server does not participate in the data plane.

---

## Overlay Networking and Use Cases Deployment Details

### Section Overview


This section describes the tenant-based baseline configuration and the supported use cases built on top of it. The baseline configuration introduced in the first subsection provides the foundation for most of the scenarios covered later in this document. It is recommended to review that subsection first, as it defines the common building blocks used throughout this section, including stretched VRFs, stretched Bridge Domains (BDs), and Endpoint Security Groups (ESGs) configuration with normalized pcTags.

The following use cases are covered in this section.

- [Use Case 1: Intra-Subnet Communication](#)  
Endpoints are in the same IP subnet and the same BD. The endpoints are in the same EPG/ESG, thus communication between them does not require a contract.
- [Use Case 2: Inter-Subnet Communication with Stretched BDs and Multiple ESGs](#)  
Endpoints are in different IP subnets and in different stretched BDs. The endpoints are in different ESGs, thus communication between them requires a contract.
- [Use Case 3: Inter-Subnet Communication with Non-Stretched BDs and Single ESG](#)  
Endpoints are in different IP subnets and in different local (non-stretched) BDs. The endpoints are in the same ESG, thus communication between them does not require a contract.
- [Use Case 4: Inter-Subnet Communication with Non-stretched BDs and Multiple ESGs](#)  
Endpoints are in different IP subnets and in different non-stretched (local) BDs. The endpoints are in the different ESGs, thus communication between them require a contract.
- [Use Case 5: North-South Communication Across ACI Sites with a Stretched BD](#)  
Endpoints in a stretched BD communicate with external endpoints through the other site.
- [Use Case 6: North-South Communication Across ACI Sites with a Non-stretched BD](#)  
Endpoints in a non-stretched (local) BD communicate with external endpoints through the other site.
- [Use Case 7: Transit Routing Across ACI Sites](#)  
External endpoints communicate with external endpoints through the other site.
- [Use Case 8: Design Considerations and Traffic Flow Optimization for Overlapping Prefixes in Multi-L3Out Deployments](#)  
The same IP prefix is advertised from multiple L3Outs in different sites. This use case presents design considerations along with inbound and outbound traffic flow optimization.
- [Use Case 9: Inter-VRF Communication \(Shared Services\) with Stretched BDs](#)  
Communication between endpoints located in different stretched BD in different stretched VRFs.
- [Use Case 10: Inter-VRF Communication \(Shared Services\) with Non-stretched BDs](#)  
Communication between endpoints located in different non-stretched BD in different stretched VRFs.
- [Use Case 11: Inter-VRF Communication \(Shared Services\) with Shared L3Out](#)  
Endpoint in a VRF communicates with an external endpoint in a different VRF through the other site.
- [Use Case 12: Service Node Integration](#)  
Explains inter-site traffic flow with L4-L7 service nodes insertion. The service insertion is performed independently within each site.

## User Tenant Baseline Configuration

Completion of this baseline is a prerequisite before proceeding to the specific use cases. Additionally, it is assumed that all necessary access policies and domains have already been configured accordingly.



**Figure 54.** User Tenant Baseline Configuration

Baseline configuration is the following:

- Tenant: bgw
- VRF: vrf1
- Bridge Domain: bd1, bd2 (Unknown Unicast Flooding ON)
- Application Profile ap1 (Note: Not depicted in the diagram)
- Endpoint Group: ep1, ep2

Note: As of APIC release 6.2(2), “Unknown Unicast Flooding” must be ON for the stretched BDs and it is enforced by APIC.

The EPGs are associated with the appropriate domains; for this example, a VMM domain is utilized. EPGs are later migrated to ESGs. The following endpoints are available for connectivity testing:

- ESG esg1 endpoints:
  - 192.168.1.11: endpoint in Pod 1 ACI Site 1
  - 192.168.1.41: endpoint in Pod 2 ACI Site 1
  - 192.168.1.201: endpoint in ACI Site 2
- ESG esg2 endpoints:
  - 192.168.2.11: endpoint in Pod 1 ACI Site 1
  - 192.168.2.21: endpoint in Pod 2 ACI Site 1
  - 192.168.2.201: endpoint in ACI Site 2

The VRF and BDs are stretched across both ACI sites by associating them with the Border Gateway on each site. This ensures that the network objects are correctly deployed to the Border Gateways of both sites. The screenshots below show the baseline configuration for EPGs and the stretched VRF/BD constructs applied across the sites.

# Logical Construct




Figure 55. ACI Site 1 tenant and vrf1




Figure 56. ACI Site 1 bd1




Figure 57. ACI Site 1 bd1 subnet






Figure 58. ACI Site 1 bd2




Figure 59. ACI Site 1 bd2 subnet




Figure 60. ACI Site 1 ep1 endpoints




Figure 61. ACI Site 1 epg2 endpoints




Figure 62. ACI Site 2 tenant and vrf1




Figure 63. ACI Site 2 bd1

**Bridge Domain - bd1**

Summary Policy Operational Stats

General L3 Configurations

Properties

Unicast Routing: ☒

Operational Value for Unicast Routing: true

Custom MAC Address: 00:22:BD:F8:19:FF

Virtual MAC Address: Not Configured

Subnets:

| Gateway Address  | Description | Scope               | Primary IP Address | Virtual IP | Subnet Control | Match |
|------------------|-------------|---------------------|--------------------|------------|----------------|-------|
| 192.168.1.254/24 | Advertis... | Advertised Exter... | False              | False      |                |       |

**Figure 64. ACI Site 2 bd1 subnet**

, Enable Scaled L2 Only (Legacy) Mode: ☐, Scaled L2 Only (Legacy) Mode: No, VRF: vrf1, Resolved VRF: bgw/vrf1, L3 Unknown Multicast Flooding: Flood, Optimized Flood, IPv6 L3 Unknown Multicast: Flood, Optimized Flood, and Multi Destination Flooding: Flood in BD, Drop, Flood in Encapsulation."/>

**Bridge Domain - bd2**

Summary Policy Operational Stats

General

Properties

Name: bd2

Alias:

Description: optional

Global Alias:

Annotations: Click to add a new annotation

Type: fc regular

Advertise Host Routes: ☐

Enable Scaled L2 Only (Legacy) Mode: ☐

Scaled L2 Only (Legacy) Mode: No

VRF: vrf1

Resolved VRF: bgw/vrf1

L2 Unknown Unicast: Flood Hardware Proxy

L3 Unknown Multicast Flooding: Flood Optimized Flood

IPv6 L3 Unknown Multicast: Flood Optimized Flood

Multi Destination Flooding: Flood in BD Drop Flood in Encapsulation

**Figure 65. ACI Site 2 bd2**

**Bridge Domain - bd2**

Summary Policy Operational Stats

General L3 Configurations

Properties

Unicast Routing: ☒

Operational Value for Unicast Routing: true


Custom MAC Address: 00:22:BD:F8:19:FF

Virtual MAC Address: Not Configured


Subnets:

| Gateway Address  | Description | Scope               | Primary IP Address | Virtual IP | Subnet Control | Match |
|------------------|-------------|---------------------|--------------------|------------|----------------|-------|
| 192.168.2.254/24 | Advertis... | Advertised Exter... | False              | False      |                |       |

**Figure 66. ACI Site 2 bd2 subnet**



**Figure 67.** ACI Site 2 epg1 endpoints




**Figure 68.** ACI Site 2 epg2 endpoints

## Stretched VRF and Bridge Domain


The following figures show the configuration steps to stretch vrf1, then bd1 and bd2 for ACI Site 1. The process is the same on both sites.

Navigate to bgw tenant -> Networking -> VXLAN Stretch -> VRF Stretch -> "+" button.




**Figure 69.** ACI Site 1 stretch vrf1 step 1

On Create VXLAN VRF Stretch window, from drop-down menu, choose vrf1 and a Border Gateway Set, fill in 50001 as Normalized VNI, and then click Submit.




**Figure 70.** ACI Site 1 stretch vrf1 step 2

Now that vrf1 is stretched, it is visible within the VRF Stretch sub-menu.




**Figure 71. ACI Site 1 vrf1 stretched**

Navigate to bgw tenant -> Networking -> VXLAN Stretch -> BD Stretch -> "+" button.




**Figure 72. ACI Site 1 stretch bd1 step 1**

On Create VXLAN BD Stretch window, from drop-down menu choose bd1 and a Border Gateway Set, fill in 30001 as Normalized VNI, and then click Submit.




**Figure 73. ACI Site 1 stretch bd1 step 2**

Now that bd1 is stretched, it is visible within the BD Stretch sub-menu.



**Figure 74. ACI Site 1 bd1 stretched**

Follow similar process to stretch bd2 with 30002 as Normalized VNI. Below figure shows the result including both stretched bd1 and bd2.




**Figure 75.** ACI Site 1 bd1 and bd2 stretched

The configuration process for ACI Site 2 follows the same steps as ACI Site 1. However, to make the object functionally stretched across the two APIC domains, the same Normalized VNI value must be configured on both sites. The following figures show the resulting configuration on ACI Site 2.




**Figure 76.** ACI Site 2 vrf1 stretched




**Figure 77.** ACI Site 2 bd1 and bd2 stretched


The APIC user interface may vary slightly on different ACI versions. For instance, the VRF and BD stretch views do not display VNI information if your ACI version is prior to 6.2(1). To display detail info about VRF and BD VNI, you can double click on the entry below VRF Stretch and BD Stretch.



**Figure 78.** ACI Site 2 vrf1 Normalized VNI and Local VNI



**Figure 79.** ACI Site 2 bd1 Normalized VNI and Local VNI




**Figure 80.** ACI Site 2 bd2 Normalized VNI and Local VNI

Once the VRF and BDs are stretched, they are deployed across all Border Gateways within the site's Border Gateway Set. You may now proceed to the next section, which covers detailed use cases along with control plane and data plane verification. Any requirements for additional BD stretching will be explicitly mentioned within those specific use cases.

## Use Case 1: Intra-Subnet Communication

### Use Case Overview

Intra-subnet communication involves endpoints in the same subnet, regardless of whether they reside in a single or multiple ACI sites. Locally, endpoints in the same EPG communicate without contracts. For Multi-Site scenarios, however, you must migrate from EPGs to ESGs. This is typically done by creating an ESG and selecting an EPG as its member to ensure policy consistency across sites.



**Figure 81.** Intra-Subnet Communication

There are several key steps that must be performed across both ACI sites. It is assumed that the baseline tenant configuration is already complete, including the creation of Tenants, VRFs, BDs, Application Profiles,


and EPGs, as well as the stretching of VRFs and BDs. The subsequent steps involve creating Endpoint Security Groups (ESGs) and configuring normalized pcTags to facilitate seamless end-to-end communication across the sites.

### Migrate EPG to ESG

A script is available to assist with the EPG-to-ESG migration. The script can be accessed from the following GitHub repository: <https://github.com/datacenter/ACI-ESG-Migration-Assistant>

Each EPG or ESG is assigned with a unique pcTag, also known as a Class ID. Like the local VNI values used for stretched VRFs and BDs, pcTags are typically assigned locally within each APIC domain. As a result, the pcTag assigned to esg1 in ACI Site 1 may not match the pcTag assigned to esg1 in ACI Site 2.


To ensure consistent security enforcement across the multi-site domain, ACI uses a Normalized pcTag. In this example, the Normalized pcTag for esg1 is set to 1001 on both sites.



**Figure 82.** ESG esg1 pcTag and Normalized pcTag

By using this consistent global identifier, endpoints classified as part of esg1 across both sites are recognized as members of the same security group, allowing them to communicate without requiring a contract.

Within the BGW tenant on each ACI site, create an ESG named esg1. To do this, navigate to Endpoint Security Groups and select Create Endpoint Security Group from the Toolbox icon drop-down menu. Alternatively, right-click the Endpoint Security Groups folder in the left navigation pane and select Create Endpoint Security Group.



**Figure 83.** ACI Site 1 Create ESG step 1

Name the ESG “esg1” and select “vrf1” from the VRF dropdown menu. Click Next to proceed to the Selectors configuration.



Create Endpoint Security Group

STEP 1 • Identity

1. Identity 2. Selectors 3. VXLAN BGW (Optional) 4. Advanced (Optional)

Name: esg1

Description: optional

VRF: vrf1

ESG Admin State: Admin Up Admin Shut

Previous Cancel Next

**Figure 84.** ACI Site 1 Create ESG step 2

Within the Selectors window, click the plus (+) icon on the right side of the EPG/External EPG/Selectors section to add a new selector.

Create Endpoint Security Group

STEP 2 • Selectors

1. Identity 2. Selectors 3. VXLAN BGW (Optional) 4. Advanced (Optional)

Tag Selectors:

| Tag Key | Value Operator | Tag Value | Description | State |
|---------|----------------|-----------|-------------|-------|
|         |                |           |             |       |

EPG/External EPG Selectors:

| EPG | Description |
|-----|-------------|
|     |             |


IP Subnet Selectors:

| IP Subnet | Description | State |
|-----------|-------------|-------|
|           |             |       |

Previous Cancel Next


**Figure 85.** ACI Site 1 Add Selector step 3

In the Create an EPG/External EPG Selector window, select epq1 and click OK to proceed.



**Figure 86.** ACI Site 1 Choose epg1 as selector

After clicking OK, select Next to proceed to the VXLAN BGW (optional) window. Enter 1001 into the Normalized pcTag field.



**Figure 87.** ACI Site 1 Set Normalized pcTag 1001

In the Advanced (optional) window, keep everything default. Adding an EPG to an ESG selector changes the pcTag assigned to the endpoints that match the selector. This policy reclassification may cause a temporary traffic outage while the endpoints are moved from the EPG to the ESG. Click Finish to complete.

Create Endpoint Security Group ✕

STEP 4 • Advanced (Optional) 1. Identity 2. Selectors 3. VXLAN BGW (Optional) 4. Advanced (Optional)

Intra ESG Isolation: Enforced Unenforced

Preferred Group Member: Exclude Include

Deployment Immediacy: Immediate On Demand

ESG Contract Master: +

ESGs

Previous Cancel Finish

**Figure 88.** ACI Site 1 esg1 creation completion

Once created, you can review the information for esg1 and modify the configuration as needed. Note that the local pcTag value (e.g., 10947) is automatically assigned by the APIC during the creation process and cannot be manually changed. The most critical parameter is the Normalized pcTag, which must be identical for esg1 across both ACI sites. If you need to update the normalized pcTag for an existing ESG, ensure that the Set Normalized pcTag checkbox is selected before entering the value.

**APIC (site1)** admin

System **Tenants** Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS | Add Tenant | Tenant Search:  | common | **bgw** | infra | tenant1 | tenant2

**bgw**

- Quick Start
- bgw**
- Application Profiles
  - ap1
    - Application EPGs
      - epg1
      - epg2
    - uSeg EPGs
    - Endpoint Security Groups
      - esg1**
  - Networking
  - Contracts
  - Policies
  - Services

**ESG - esg1** Summary **Policy** Operational

Topology **General**

Properties

Name: esg1

Description: optional

Annotations: + Click to add a new annotation

pcTag(sclass): 10947

☒ Set Normalized pcTag Normalized pcTag: 1001

Configuration Status: applied

Configuration Issues:

VRF: vrf1

Resolved VRF: uni/tn-bgw/ctx-vrf1

ESG Admin State: Admin Up Admin Shut

Deployment Immediacy: Immediate On Demand

**Figure 89.** ACI Site 1 esg1 general information

The figure below displays the selectors for esg1. You can update a selector by right clicking the relevant entry in the left navigation pane.




Figure 90. ACI Site 1 esg1 selectors




Figure 91. ACI Site 1 esg1 endpoints

The process for creating esg1 on ACI Site 2 is identical. The following image illustrates the resulting configuration for esg1 on the second site.






Figure 92. ACI Site 2 esg1 general information




**Figure 93.** ACI Site 2 esg1 selectors



**Figure 94.** ACI Site 2 esg1 endpoints


## Control Plane Verification

This section is intended for advanced users seeking a technical deep dive into how routing and policy enforcement function across the site. At a high level, the block diagram below illustrates the control plane advertisement from ACI Site 1 to ACI Site 2. The same process occurs in reverse, from ACI Site 2 to ACI Site 1.



**Figure 95.** Control Plane across sites

To ensure clarity, the topology diagram illustrates only the essential devices required for this specific configuration.



**Figure 96.** Control Plane verification topology

Leaf1 on ACI Site 1 learns endpoint MAC address 0050.56bf.7a53.

```
leaf1# show system internal epm endpoint mac 0050.56bf.7a53

MAC : 0050.56bf.7a53 ::: Num IPs : 1
IP# 0 : 192.168.1.11 ::: IP# 0 flags : host-tracked| ::: l3-sw-hit: Yes ::: flags2 :
Vlan id : 17 ::: Vlan vnid : 8465 ::: VRF name : bgw:vrf1
BD vnid : 15007704 ::: VRF vnid : 2162688
Phy If : 0x1a002000 ::: Tunnel If : 0
Interface : Ethernet1/3
Flags : 0x80005c04 ::: sclass : 10947 ::: Ref count : 5
EP Create Timestamp : 12/27/2025 19:39:55.399532
EP Update Timestamp : 01/21/2026 21:19:43.628794
EP Flags : local|IP|MAC|host-tracked|sclass|timer|
```

**Figure 97.** ACI Site 1 - leaf1 learns local endpoint MAC address

When bd1 is configured as Layer 3 BD with unicast routing enabled, Leaf1 learns IP address 192.168.1.11 as well.

```
leaf1# show system internal epm endpoint ip 192.168.1.11

MAC : 0050.56bf.7a53 ::: Num IPs : 1
IP# 0 : 192.168.1.11 ::: IP# 0 flags : host-tracked| ::: l3-sw-hit: Yes ::: flags2 :
Vlan id : 17 ::: Vlan vnid : 8465 ::: VRF name : bgw:vrf1
BD vnid : 15007704 ::: VRF vnid : 2162688
Phy If : 0x1a002000 ::: Tunnel If : 0
Interface : Ethernet1/3
Flags : 0x80005c04 ::: sclass : 10947 ::: Ref count : 5
EP Create Timestamp : 12/27/2025 19:39:55.399532
EP Update Timestamp : 01/21/2026 21:19:43.628794
EP Flags : local|IP|MAC|host-tracked|sclass|timer|
```

**Figure 98.** ACI Site leaf1 learns endpoint IP address

Verify the COOP entry for the endpoint MAC address on one of the spines. The value 15007704 represents the local VNI for bd1 in ACI Site 1. Note that the COOP output has been truncated to show only the relevant information. For reference, the PcTag value 0x1002ac3 can be converted to decimal by removing the “0x1” prefix and converting “002ac3” from hexadecimal to decimal. This results in 10947, which correctly matches the esg1 pcTag.

```
spine688# show coop internal info repo ep key 15007704 0050.56bf.7a53
```

```
Repo Hdr Checksum : 44357
Repo Hdr record timestamp : 01 21 2026 13:38:48 320039868
Repo Hdr last pub timestamp : 01 21 2026 13:38:48 321550678
Repo Hdr last dampen timestamp : 01 01 1970 00:00:00 0
Repo Hdr dampen penalty : 0
Repo Hdr flags : IN_OBJ EXPORT ACTIVE
EP bd vnid : 15007704
EP mac : 00:50:56:BF:7A:53
flags : 0x80
repo flags : 0x122
Seq No In Use: No
Vrf vnid : 2162688
PcTag : 0x1002ac3
EVPN Seq no : 0
```

**Figure 99.** Local endpoint COOP entry

In the same output, the IN\_OBJ EXPORT flag indicates that this COOP entry has been exported to the BGP process.

```
IPv4 Repo Hdr record timestamp : 01 26 2026 22:38:49 677605688
IPv4 Repo Hdr last pub timestamp : 01 26 2026 22:38:49 679132001
IPv4 Repo Hdr last dampen timestamp : 01 01 1970 00:00:00 0
IPv4 Repo Hdr dampen penalty : 0
IPv4 Repo Hdr flags : IN_OBJ EXPORT
Real IPv4 EP : 192.168.1.11
Synthetic Flags IPv4 EP : 0x25
EVPN Seq no : 0
PcTag: 0x1002ac3
Remote publish timestamp: 01 01 1970 00:00:00 0
Current publisher_id: 10.1.248.3
BackupTunnel nh : 0.0.0.0
MAC Tunnel : 10.1.248.3
IPv4 Tunnel : 10.1.248.3
IPv6 Tunnel : 10.1.248.3
```

**Figure 100.** COOP exports to BGP

ACI Site 1 spines advertise local endpoint information to the ACI Site 1 Border Gateways and to spine switches in other pods, such as Pod-2 in this example. This is standard ACI Multi-Pod behavior and is not specific to the Border Gateway implementation.

```
spine688# show bgp l2vpn evpn 0050.56bf.7a53
Route Distinguisher: 1:16777199 (L2VNI 1)
BGP routing table entry for [2]:[0]:[15007704]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/216, version 632 dest ptr 0x7fefc49c4b78
BGW RD: 100:15007704 (L2VNI 15007704)
Local Route Distinguisher: 1:16777199 (L2VNI 1)
Paths: (1 available, best #1)
Flags: (0x00000000000010a 0000000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP
```

```
Advertised path-id 1
Path type (0x7fefba057608): local 0x4000008c 0x40000000 ref 0 adv path ref 1, path is valid, is best path
AS-Path: NONE, path locally originated
0.0.0.0 (metric 0) from 0.0.0.0 (199.6.8.8)
Origin IGP, MED not set, localpref 100, weight 32768 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 15007704
Extcommunity: RT:5:16 PCTAG:01:0:11:10947
```

```
Path-id 1 advertised to peers:
10.1.248.2      10.1.248.7      199.8.8.8
```



**Figure 101.** ACI Site 1 - Spine advertises local EP to Border Gateways and Spine in another Pod

Note that the local pcTag 10947 is included in the BGP EVPN update.

After the Border Gateway in the same pod receives the endpoint information, it advertises this information to the Border Gateway in the remote ACI site (ACI Site 2 in this example) using the Normalized VNI and Normalized pcTag.

Note that the CLI output on the local Border Gateway, in this case the Border Gateway in ACI Site 1, currently displays the local VNI and local pcTag values. In the screenshot below, 15007704 represents the local VNI configured in ACI Site 1, and 10947 represents the local pcTag assigned to esg1. The corresponding normalized values are observed on the remote Border Gateway in ACI Site 2 by issuing command in vsh mode.

```
bgw-leaf1# show bgp l2vpn evpn 0050.56bf.7a53
<snip>

Route Distinguisher: 100:31784920 (L2VNI 15007704)
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/216, version 210 dest ptr 0x7f687caca184
Paths: (1 available, best #1)
Flags: (0x0000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f6870e87d10): internal 0xc0000018 0x400 ref 0 adv path ref 1, path is valid, is best path, in rib
Imported from (0x7f6870fe6b2c) 100:15007704:[2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/112
AS-Path: NONE, path sourced internal to AS
10.1.144.67 (metric 2) from 10.1.248.0 (199.6.8.8)
Origin IGP, MED not set, localpref 100, weight 0 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 15007704
Extcommunity: RT:100:15007704 S00:1:1 ENCAP:8 PCTAG:01:0:11:10947

Path-id 1 advertised to peers:
5.5.5.105
↓
qt-bgw805 ACI Fabric 2 Border Gateway
```

**Figure 102.** ACI Site 1- Border Gateway advertises endpoint to ACI Site 2 Border Gateway

ACI Site 2 Border Gateway receives endpoint information via a BGP EVPN Type-2 update. Subsequently, this endpoint information is forwarded to the ACI Site 2 spine using BGP EVPN Type-2, with the pcTag updated to 10930, which corresponds to the local pcTag for esg1 in Site 2. The screenshot below taken from ACI Site 2 Border Gateway shows the remote endpoint EVPN Type-2 route learned the remote ACI site (ACI Site 1). The route is first displayed under the remote Route Distinguisher, 100:31784920, with paths learned from the Border Gateways in ACI Site 1. In this section of the output, the route carries the normalized VNI and pcTag information received from ACI Site 1 Border Gateways.

In the following output, “Received label 30001” represents Normalized BD VNI. The pcTag value 1001 represents Normalized esg1 pcTag.

```
qt-bgw805# show bgp l2vpn evpn 0050.56bf.7a53
Route Distinguisher: 100:31784920
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/216, version 18151 dest ptr 0x7f250b90ea14
Paths: (2 available, best #2)
Flags: (0x0000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Path type (0x7f24fff2058c): external 0x40000028 0x4002000 ref 0 adv path ref 0, path is valid, not best reason: Router ID
AS-Path: 100 , path sourced external to AS
100.100.100.102 (metric 0) from 1.1.1.101 (10.1.248.7)
Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 30001
Extcommunity: RT:400:30001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:80:0:0:1001

Advertised path-id 1
Path type (0x7f24fff25698): external 0x40000028 0x4002000 ref 1 adv path ref 1, path is valid, is best path
Imported to 1 destination(s)
AS-Path: 100 , path sourced external to AS
100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 30001
Extcommunity: RT:400:30001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:80:0:0:1001
```

**Figure 103.** ACI Site 2 Border Gateway received section of EVPN Route




In the same CLI output, the same route is then imported into the local site context under Route Distinguisher 400:31883212 and local L2VNI 15105996. The “Imported from” field identifies the original remote EVPN route, while the “Path-id 1 advertised to peers” field confirms that the imported route is advertised to the local spine peer, 10.118.112.65. The value 10930 represents the esg1 local pcTag.

```
qt-bgw805# show bgp l2vpn evpn 0050.56bf.7a53
<snip>
Route Distinguisher: 400:31883212 (L2VNI 15105996)
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/216, version 189 dest ptr 0x7f922465e1e4
Paths: (1 available, best #1)
Flags: (0x0000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f9218a35d0c): external 0xc0000028 0x400 ref 0 adv path ref 1, path is valid, is best path, in rib
Imported from (0x7f9218c8538c) 100:31784920:[2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/112
AS-Path: 100 , path sourced external to AS
100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 30001
Extcommunity: RT:400:30001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:00:0:0:10930

Path-id 1 advertised to peers:
10.118.112.65
```



**Figure 104.** ACI Site 2 Border Gateway receives endpoint information through BGP EVPN update

ACI Site 2 spine receives endpoint information through BGP EVPN update from ACI site 2 Border Gateway, subsequently it imports endpoint information to spine COOP.

```
qt-spine811# show bgp l2vpn evpn 0050.56bf.7a53
<snip>
Route Distinguisher: 400:15105996 (L2VNI 15105996)
BGP routing table entry for [2]:[0]:[15105996]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/216, version 64 dest ptr 0x7f6ed7c34046
BGW RD: 400:15105996 (L2VNI 15105996)
Local Route Distinguisher: 1:16777199 (L2VNI 1)
Paths: (1 available, best #1)
Flags: (0x000000000000021a 0x00000009) on xmit-list, is in rib/evpn, is not in HW, is in l2rib mpod shard, is in l2rib
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f6ecd23efa0): internal 0xc0000018 0x220000 ref 0 adv path ref 1, path is valid, is best path, is in l2rib
Imported from (0x7f6ecd2b1f20) 400:31883212:[2]:[0]:[0]:[48]:[0050.56bf.7a53]:[0]:[0.0.0.0]/112
AS-Path: 100 , path sourced external to AS
10.118.176.68 (metric 2) from 10.118.112.67 (10.118.112.67)
Origin IGP, MED not set, localpref 100, weight 0 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 15105996
Extcommunity: RT:400:15105996 S00:400:2432696301
COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:00:0:0:10930

Path-id 1 not advertised to any peer
```

**Figure 105.** ACI Site 2 spine receives endpoint information from Border Gateway through BGP EVPN update

As shown in the figure above, ACI Site spine receives endpoint information from the Border Gateway via a BGP EVPN update. This is indicated by the output line “from 10.118.112.67”, which refers to the Border Gateway PTEP. The spine then imports this information into its COOP database.

ACI Site spine now has endpoint information in its COOP database. On Site 2 spine:

```
qt-spine811# show coop internal info repo ep key 15105996 0050.56bf.7a53
```

```
Repo Hdr Checksum : 30692
Repo Hdr record timestamp : 01 01 1970 00:00:00 0
Repo Hdr last pub timestamp : 01 01 1970 00:00:00 0
Repo Hdr last dampen timestamp : 01 01 1970 00:00:00 0
Repo Hdr dampen penalty : 0
Repo Hdr flags : IN_OBJ REMOTE ACTIVE
EP bd vnid : 15105996
EP mac : 00:50:56:BF:7A:53
flags : 0x1080
repo flags : 0x182
Remote Type : External Fabric
Seq No In Use: Yes
Vrf vnid : 2097152
PcTag : 0x1002ab2
EVPN Seq no : 0
Remote publish timestamp: 01 18 2026 14:49:15 882610657
Snapshot timestamp: 01 01 1970 00:00:00 0
Tunnel nh : 10.118.176.68
MAC Tunnel : 10.118.176.68
IPv4 Tunnel : 10.118.176.68
IPv6 Tunnel : 10.118.176.68
ETEP Tunnel : 0.0.0.0
num of active ipv4 addresses : 1
num of anycast ipv4 addresses : 0
num of ipv4 addresses : 1
num of active ipv6 addresses : 0
num of anycast ipv6 addresses : 0
num of ipv6 addresses : 0
Primary Path:
Current published TEP : 10.118.176.68
```


**Figure 106.** ACI Site 2 spine COOP entry of remote endpoint

Keep in mind that the Bridge Domain (BD) VNID is 15105996, which is the local VNID for bd1 on ACI Site 2. In the COOP entry, “Remote Type: External Site” indicates that this endpoint originates from a remote site (ACI Site 1). We can derive the pcTag in decimal from the value “PcTag: 0x1002ab2” by converting the hexadecimal portion “002ab2” to decimal. The result is 10930, which corresponds to the local pcTag of esg1 configured on ACI Site 2. The tunnel next-hop, 10.118.176.68, represents the internal VXLAN anycast address.

At this stage the control plane information of endpoint in ACI Site 1 has been sent successfully to ACI Site 2. In the reverse direction endpoint information from ACI Site 2 is also sent to ACI Site 1.

## Data Plane Verification

Communication occurs between two endpoints, EP-1 and EP-2, residing in the same stretched Bridge Domain but on different ACI Sites. In this example EP-1 resides in ACI Site 1 Pod-1, EP-2 resides in ACI Site 2 Pod-1. The Normalized VNI 30001 is defined by the administrator by configuring the normalized BD VNI when stretching the BD across the sites.



**Figure 107.** Data plane Bridged Communication across sites

From endpoint in esg1 ACI Site 1 ping endpoint in esg1 ACI Site 2.

```
cisco@aci-ubu-1:~$ ifconfig ens192
ens192: flags=4163<UP,BROADCAST,RUNNING,MULTICAST> mtu 1500
    inet 192.168.1.11 netmask 255.255.255.0 broadcast 192.168.1.255
    inet6 fe80::250:56ff:febf:7a53 prefixlen 64 scopeid 0x20<link>
    ether 00:50:56:bf:7a:53 txqueuelen 1000 (Ethernet)
    RX packets 2464804 bytes 238370272 (238.3 MB)
    RX errors 0 dropped 151 overruns 0 frame 0
    TX packets 2714106 bytes 261335724 (261.3 MB)
    TX errors 0 dropped 0 overruns 0 carrier 0 collisions 0
```


**Figure 108.** Endpoint in esg1 ACI Site 1

```
cisco@aci-ubu-1:~$ ping 192.168.1.201
PING 192.168.1.201 (192.168.1.201) 56(84) bytes of data.
 64 bytes from 192.168.1.201: icmp_seq=1 ttl=64 time=0.153 ms
 64 bytes from 192.168.1.201: icmp_seq=2 ttl=64 time=0.294 ms
 64 bytes from 192.168.1.201: icmp_seq=3 ttl=64 time=0.258 ms
 64 bytes from 192.168.1.201: icmp_seq=4 ttl=64 time=0.260 ms
 64 bytes from 192.168.1.201: icmp_seq=5 ttl=64 time=0.306 ms
```

**Figure 109.** Ping from endpoint in esg1 ACI Site 1 to endpoint in esg1 ACI Site 2

The following packet capture was obtained via ERSPAN traffic from ISN device.

The packet capture of the ICMP request from EP-1 to EP-2 confirms that the Layer 2 (BD) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 110.** ICMP request from EP-1 (192.168.1.11) to EP-2 (192.168.1.201)

As illustrated in the figure above, an ICMP packet originating from source 192.168.1.11 (EP-1) destined for 192.168.1.201 (EP-2) is encapsulated in standard VXLAN using the standard destination UDP port 4789.

The VXLAN header confirms that the VNI value is 30001, which matches the value configured by the administrator. Of particular interest is the Group Policy ID field, which is set to 0.

To understand the significance of this, it is important to note how the Group Policy ID is used in standard ACI intra-site traffic. Within an ACI fabric, intra-site traffic uses the iVXLAN header, which carries a non-zero Group Policy ID value. This value is also referred to as the Policy Control Tag (pcTag) and represents the EPG/ESG membership of the endpoint. The pcTag is used for policy enforcement to determine whether traffic should be permitted or dropped.

In the ACI Border Gateway implementation, the Group Policy ID (pcTag) is set to 0 in the VXLAN header whenever the Border Gateway sends traffic out of its local site. This is by design rather than relying on the Group Policy ID field for policy enforcement, the BGW leverages the BGP EVPN control plane to carry both routing information and pcTag information within the BGP EVPN route attributes. The policy enforcement decision is therefore made based on the information exchanged through the BGP EVPN control plane, rather than carried via the VXLAN data plane header.

The figure above also illustrates the VXLAN tunnel source address as 1.1.1.102, which is the BGW Primary IP (PIP) also referred to as the EVPN Loopback IP of the second Border Gateway in ACI Site 1. The VXLAN tunnel destination is the Multi-Site External Anycast IP of the Border Gateways in ACI Site 2, Pod-1.

It is important to note that the selection of the VXLAN tunnel source, specifically which Border Gateway PIP is used, is determined by a hashing algorithm. Intra-fabric ECMP determines the path between the local leaf and the local Border Gateway. If multiple Border Gateways exist within the same ACI Pod, the intra-fabric ECMP selects one based on the hash outcome. Once the selected Border Gateway receives the flow, it sources the VXLAN tunnel using its own PIP and forwards the packet toward the remote Border Gateways' Multi-Site External VIP.

The packet capture of the ICMP reply from EP-2 to EP-1 confirms that the Layer 2 (BD) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                               |
|-----|----------|---------------|---------------|----------|--------|--------------------------------------------------------------------|
| 47  | 0.986706 | 192.168.1.11  | 192.168.1.201 | ICMP     | 198    | Echo (ping) request id=0x1e5a, seq=790/5635, ttl=64 (reply in 48)  |
| 48  | 0.986898 | 192.168.1.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5a, seq=790/5635, ttl=64 (request in 47)  |
| 100 | 2.010751 | 192.168.1.11  | 192.168.1.201 | ICMP     | 198    | Echo (ping) request id=0x1e5a, seq=791/5891, ttl=64 (reply in 101) |
| 101 | 2.010869 | 192.168.1.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5a, seq=791/5891, ttl=64 (request in 100) |
| 157 | 3.034749 | 192.168.1.11  | 192.168.1.201 | ICMP     | 198    | Echo (ping) request id=0x1e5a, seq=792/6147, ttl=64 (reply in 158) |
| 158 | 3.034888 | 192.168.1.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5a, seq=792/6147, ttl=64 (request in 157) |
| 204 | 4.058748 | 192.168.1.11  | 192.168.1.201 | ICMP     | 198    | Echo (ping) request id=0x1e5a, seq=793/6403, ttl=64 (reply in 205) |
| 205 | 4.058874 | 192.168.1.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5a, seq=793/6403, ttl=64 (request in 204) |
| 257 | 5.082776 | 192.168.1.11  | 192.168.1.201 | ICMP     | 198    | Echo (ping) request id=0x1e5a, seq=794/6659, ttl=64 (reply in 258) |

> Frame 48: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device...  
 > Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)  
 > Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100  
 > Generic Routing Encapsulation (ERSPAN)  
 > Encapsulated Remote Switch Packet Analysis Type II  
 > Ethernet II, Src: Cisco\_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47)  
 > Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102  
 > User Datagram Protocol, Src Port: 50874, Dst Port: 4789  
 > Virtual eXtensible Local Area Network  
 > Flags: 0x0800, VXLAN Network ID (VNI)  
 > Group Policy ID: 0  
 > VXLAN Network Identifier (VNI): 30001  
 > Reserved: 0  
 > Ethernet II, Src: VMware\_bf:58:81 (00:50:56:bf:58:81), Dst: VMware\_bf:7a:53 (00:50:56:bf:7a:53)  
 > Internet Protocol Version 4, Src: 192.168.1.201, Dst: 192.168.1.11  
 > Internet Control Message Protocol


**Figure 111.** ICMP reply from EP-2 (192.168.1.201) to EP-1 (192.168.1.11)

The information displayed in the ICMP reply capture is almost identical to that of the request. One of the most notable differences is that the VXLAN tunnel source address is now 5.5.5.105, which is the BGW Primary IP (PIP) of the first Border Gateway in ACI Site 2. The VXLAN tunnel destination address is 100.100.100.102, which is the Multi-Site External Virtual IP (VIP) of the Border Gateways in ACI Site 1, Pod-1.

It is important to note that the Multi-Site External VIP is unique per ACI Pod. Therefore, traffic returning from ACI Site 2 is always destined for the Multi-Site External VIP associated with the specific Pod in ACI Site 1 from which the original request was sourced.

## Policy Enforcement

The figure below illustrates the policy enforcement locations for intra-subnet communication. The same logic applies for returning flow from ACI Site 2 to ACI Site 1.



**Figure 112.** Intra-Subnet communication policy enforcement

For Layer 2 communication, policy enforcement occurs on the compute leaf where the traffic enters the ACI fabric. This is possible because the compute leaf has learned the remote endpoint MAC address, along with the associated pcTag, through data-plane activity. If the compute leaf has not learned the required MAC endpoint information, the Border Gateway performs policy enforcement instead. Since the traffic is


bridged within the same Layer 2 domain, ACI performs the policy based on the source and destination MAC addresses.

- Source site: If the destination endpoint MAC is learned, the compute leaf applies policy, else the Border Gateway applies policy.
- Destination site: The compute leaf applies policy.

## Use Case 2: Inter-Subnet Communication with Stretched BDs and Multiple ESGs

### Use Case Overview

The figure below illustrates the logical design. In this use case, the source and the destination endpoints are in the different stretched BD subnets and are classified to different ESGs.



**Figure 113.** Inter-Subnet Communication

It is assumed that the baseline tenant configuration has already been completed, including the creation of tenants, VRFs, BDs, application profiles, and EPGs, as well as the stretching of VRFs and BDs. It is also assumed that you are already familiar with the process of migrating an EPG to an ESG and configuring a normalized pcTag for an ESG. The following screenshot shows the completed configuration for esg2.

### Migrate EPG to ESG

ESG esg2 uses EPG epg1 as EPG selector.






Figure 114. ACI Site 1 esg2




Figure 115. ACI Site 1 esg2 normalized pcTag




Figure 116. ACI Site 1 esg2 endpoints




Figure 117. ACI Site 2 esg2




Figure 118. ACI Site 2 esg2 normalized pcTag




Figure 119. ACI Site 2 esg2 endpoints

## Create and Apply Contract

Since the endpoints in BD1 and BD2 are classified into different ESGs, a contract is required to enable communication between them. In this example, esg1 is the consumer and esg2 is the provider. The policy must be configured consistently across both APIC domains to ensure the intended communication behavior. Nexus Dashboard could help address this operational challenge in a future release by providing a centralized point for policy authoring.



APIC (site1)

System | **Tenants** | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | **bgw** | demo | tenant1 | Fortune

bgw

Quick Start

Application Profiles

Application EPGs

uSeg EPGs

Endpoint Security Groups

**esg1**

Contracts

Selectors

**Contracts**

Contracts | Inherited Contracts | Contracts Via EPG Selectors | Inherited Contracts Via EPG Selectors

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg-ext-core  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg-to-ext-1  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg1-esg2     | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | share-svc     | Contract      | Consumed            | Unspecified | Formed |

**Figure 120. ACI Site 1 esg1 contract consumer**

APIC (site1)

System | **Tenants** | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | **bgw** | demo | tenant1 | Fortune

bgw

Quick Start

Application Profiles

Application EPGs

uSeg EPGs

Endpoint Security Groups

**esg1**

Contracts

Selectors

**Contracts**

Contracts | Inherited Contracts | Contracts Via EPG Selectors | Inherited Contracts Via EPG Selectors

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg1-esg2     | Contract      | Provided            | Unspecified | Formed |

**Figure 121. ACI Site 1 esg1 contract provider**

APIC (site2)

System | **Tenants** | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | **bgw** | queenstown | mgmt | infra

bgw

Quick Start

Application Profiles

Application EPGs

uSeg EPGs

Endpoint Security Groups

**esg1**

Contracts

Selectors

**Contracts**

Contracts | Inherited Contracts | Contracts Via EPG Selectors | Inherited Contracts Via EPG Selectors

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg-ext-core  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg-to-ext-1  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg1-esg2     | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | share-svc     | Contract      | Consumed            | Unspecified | Formed |

**Figure 122. ACI Site 2 esg1 contract consumer**

APIC (site2)

System | **Tenants** | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | **bgw** | queenstown | mgmt | infra

bgw

Quick Start

Application Profiles

Application EPGs

uSeg EPGs

Endpoint Security Groups

**esg1**

Contracts

Selectors

**Contracts**

Contracts | Inherited Contracts | Contracts Via EPG Selectors | Inherited Contracts Via EPG Selectors

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg1-esg2     | Contract      | Provided            | Unspecified | Formed |

**Figure 123. ACI Site 2 esg2 contract provider**

## Control Plane Verification

Control plane verification is very similar to intra-subnet communication in the previous section. Border Gateway in ACI Site 1 learns endpoint information of endpoints in esg2 in ACI Site 2. Endpoints information

includes MAC address and IP address since BD2 also has Unicast routing on. Below are few screenshots for illustration purpose, the similar information could be seen on ACI Site 2.

```
bgw-leaf1# show bgp l2vpn evpn 0050.56bf.8ec0
Route Distinguisher: 100:32341911 (L2VNI 15564695)
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[0]:[0.0.0.0]/216, version 145 dest ptr 0x7fb8a32497b8
Paths: (1 available, best #1)
Flags: (0x000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP

  Advertised path-id 1
    Path type (0x7fb897607934): external 0xc0000028 0x400 ref 0 adv path ref 1, path is valid, is best path, in rib
      Imported from (0x7fb89776764c) 400:31981504:[2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[0]:[0.0.0.0]/112
    AS-Path: 400 , path sourced external to AS
      105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
      Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
      Received label 30002
      Extcommunity: RT:100:30002 S00:100:1694498797 COST:pre-bestpath:170:1610612736
      ENCAP:8 PCTAG:00:0:0:10948

    Path-id 1 advertised to peers:
      10.1.248.0 10.1.248.1
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[32]:[192.168.2.201]/272, version 146 dest ptr 0x7fb8a32496ba
Paths: (1 available, best #1)
Flags: (0x000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP

  Advertised path-id 1
    Path type (0x7fb8976077ec): external 0xc0000028 0x400 ref 0 adv path ref 1, path is valid, is best path, remote nh not installed, in rib
      Imported from (0x7fb8977675b0) 400:31981504:[2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[32]:[192.168.2.201]/144
    AS-Path: 400 , path sourced external to AS
      105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
      Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
      Received label 30002 50001
      Extcommunity: RT:100:30002 RT:100:50001 S00:100:1694498797
      COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:00:0:0:10948
      Router MAC:080f.e5e2.bb99

    Path-id 1 advertised to peers:
      10.1.248.0 10.1.248.1
```

**Figure 124.** ACI Site 1 Border Gateway learns MAC endpoint from ACI Site 2

Although the endpoint is in ACI Site 2 and is associated with a different pcTag in that site, the border gateway in ACI Site 1 learns the endpoint with the local pcTag of esg2 in ACI Site 1, which is 10948.

```
bgw-leaf1# show bgp l2vpn evpn 192.168.2.201
Route Distinguisher: 100:32341911 (L2VNI 15564695)
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[32]:[192.168.2.201]/272, version 146 dest ptr 0x7fb8a32496ba
Paths: (1 available, best #1)
Flags: (0x000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP


  Advertised path-id 1
    Path type (0x7fb8976077ec): external 0xc0000028 0x400 ref 0 adv path ref 1, path is valid, is best path, remote nh not installed, in rib
      Imported from (0x7fb8977675b0) 400:31981504:[2]:[0]:[0]:[48]:[0050.56bf.8ec0]:[32]:[192.168.2.201]/144
    AS-Path: 400 , path sourced external to AS
      105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
      Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
      Received label 30002 50001
      Extcommunity: RT:100:30002 RT:100:50001 S00:100:1694498797
      COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:00:0:0:10948
      Router MAC:080f.e5e2.bb99

    Path-id 1 advertised to peers:
      10.1.248.0 10.1.248.1
```

**Figure 125.** ACI Site 1 Border Gateway learns IP endpoint from ACI Site 2

## Data Plane Verification

Communication happens between two endpoints EP-1 and EP-3 across sites. Normalized VNI 50001 is defined by administrator by configuring the normalized VRF VNI when stretching VRF across two sites.



**Figure 126.** Data plane Routed Communication across sites

The following packet capture was obtained via ERSPAN traffic from ISN device. The packet capture of the ICMP request from EP-1 to EP-3 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

esg1-esg2-aci.pcapng

\_ws.col.protocol == "ICMP"

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                               |
|-----|----------|---------------|---------------|----------|--------|--------------------------------------------------------------------|
| 33  | 0.472346 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=69/17664, ttl=62 (reply in 34)  |
| 34  | 0.472547 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=69/17664, ttl=62 (request in 33)  |
| 79  | 1.496362 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=70/17920, ttl=62 (reply in 80)  |
| 80  | 1.496495 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=70/17920, ttl=62 (request in 79)  |
| 129 | 2.520393 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=71/18176, ttl=62 (reply in 130) |
| 130 | 2.520531 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=71/18176, ttl=62 (request in 129) |
| 179 | 3.544369 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=72/18432, ttl=62 (reply in 180) |
| 180 | 3.544516 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=72/18432, ttl=62 (request in 179) |
| 225 | 4.568426 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=73/18688, ttl=62 (reply in 226) |

> Frame 33: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF\_{5D6AB595-A...}

> Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)

> Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100

> Generic Routing Encapsulation (ERSPAN)

> Encapsulated Remote Switch Packet Analysis Type II

> Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: Cisco\_f8:19:ff (00:22:bd:f8:19:ff)

> Internet Protocol Version 4, Src: 1.1.1.102, Dst: 105.105.105.105

> User Datagram Protocol, Src Port: 5063, Dst Port: 4789

> Virtual eXtensible Local Area Network

> Flags: 0x0800, VXLAN Network ID (VNI)

> Group Policy ID: 0

> VXLAN Network Identifier (VNI): 50001

> Reserved: 0

> Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco\_e2:bb:99 (08:0f:e5:e2:bb:99)

> Internet Protocol Version 4, Src: 192.168.1.11, Dst: 192.168.2.201

> Internet Control Message Protocol

**Figure 127.** ICMP request from EP-1 (192.168.1.11) to EP-3 (192.168.2.201)

The packet capture of the ICMP reply from EP-3 to EP-1 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                               |
|-----|----------|---------------|---------------|----------|--------|--------------------------------------------------------------------|
| 33  | 0.472346 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=69/17664, ttl=62 (reply in 34)  |
| 34  | 0.472547 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=69/17664, ttl=62 (request in 33)  |
| 79  | 1.496362 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=70/17920, ttl=62 (reply in 80)  |
| 80  | 1.496495 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=70/17920, ttl=62 (request in 79)  |
| 129 | 2.520393 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=71/18176, ttl=62 (reply in 130) |
| 130 | 2.520531 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=71/18176, ttl=62 (request in 129) |
| 179 | 3.544369 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=72/18432, ttl=62 (reply in 180) |
| 180 | 3.544516 | 192.168.2.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e5e, seq=72/18432, ttl=62 (request in 179) |
| 225 | 4.568426 | 192.168.1.11  | 192.168.2.201 | ICMP     | 198    | Echo (ping) request id=0x1e5e, seq=73/18688, ttl=62 (reply in 226) |


  

|                                                                                                                         |      |                |
|-------------------------------------------------------------------------------------------------------------------------|------|----------------|
| > Frame 34: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF_{5D6AB595-A} | 0000 | 00 50 56 bf d4 |
| > Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware_bf:d4:e1 (00:50:56:bf:d4:e1)                        | 0010 | 00 b8 f9 4e 00 |
| > Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100                                                        | 0020 | 50 64 10 00 88 |
| > Generic Routing Encapsulation (ERSPAN)                                                                                | 0030 | 01 3d 4c 77 6d |
| > Encapsulated Remote Switch Packet Analysis Type II                                                                    | 0040 | 45 00 00 86 00 |
| > Ethernet II, Src: Cisco_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47)                         | 0050 | 64 64 64 66 c5 |
| > Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102                                                     | 0060 | 00 c3 51 00 00 |
| > User Datagram Protocol, Src Port: 50539, Dst Port: 4789                                                               | 0070 | 08 00 45 00 00 |
| > Virtual eXtensible Local Area Network                                                                                 | 0080 | 02 c9 c0 a8 01 |
| > Flags: 0x0800, VXLAN Network ID (VNI)                                                                                 | 0090 | 40 6a 00 00 00 |
| > Group Policy ID: 0                                                                                                    | 00a0 | 12 13 14 15 16 |
| > VXLAN Network Identifier (VNI): 50001                                                                                 | 00b0 | 22 23 24 25 26 |
| > Reserved: 0                                                                                                           | 00c0 | 32 33 34 35 36 |
| > Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco_eb:c5:99 (00:5d:73:eb:c5:99)                |      |                |
| > Internet Protocol Version 4, Src: 192.168.2.201, Dst: 192.168.1.11                                                    |      |                |
| > Internet Control Message Protocol                                                                                     |      |                |

**Figure 128.** ICMP reply from EP-3 (192.168.2.201) to EP-1 (192.168.1.11)


## Policy Enforcement

The figure below illustrates the policy enforcement locations for inter-subnet communication.



**Figure 129.** Inter-subnet communication policy enforcement Site 1 to Site 2

Traffic from ACI Site 1 to ACI Site 2: The ACI Site 1 Border Gateway and the ACI Site 2 compute leaf enforce policy for this traffic flow. From the ACI Site 1 perspective, the destination endpoint in ACI Site 2 is a remote endpoint. The remote endpoint information is advertised to the ACI Site 1 Border Gateway and then advertised to the ACI Site 1 spines through EVPN. The endpoint information is subsequently stored in the spine COOP database. This information is not advertised to the ACI Site 1 compute leaf, which is consistent with the standard ACI COOP behavior designed to conserve hardware resources on the compute leaf. At the same time, the remote endpoint IP is not learned on the compute leaf, even based on received data plane traffic. This is because the local Border Gateway sets the Do-Not-Learn bit to the traffic received from remote site that is re-encapsulated toward to the local compute leaf. The ACI Site 1 Border Gateway has the required remote endpoint classification context and performs policy enforcement for traffic leaving the site. In ACI Site 2, although Border Gateway has endpoint information advertised by a local spine, it does not program the information to local hardware table for scalability reason, the compute leaf attached to the destination endpoint enforces policy based on the locally learned endpoint information.




**Figure 130.** Inter-subnet communication policy enforcement Site 2 to Site 1

Traffic from ACI Site 2 to ACI Site 1: The same logic applies to the reverse direction. The ACI Site 2 Border Gateway enforces policy for traffic leaving the site, whereas the ACI Site 1 compute leaf enforces the policy for traffic destined to the locally attached endpoint.

### Use Case 3: Inter-Subnet Communication with Non-stretched BDs and Single ESG

#### Use Case Overview

This use case describes communication between endpoints residing in different subnets. It differs from Use Case 2, in which the BDs are deployed locally on each site and a single ESG is used to classify endpoints part of both subnets. Because the endpoints belong to the same ESG, they can communicate without a contract and for that to work the ESG normalized pcTag must be identical on both sites. The following diagram illustrates this scenario.



**Figure 131.** Inter-Subnet Communication Non-Stretched BDs Single ESG

As shown in the above diagram, bd10 is deployed locally in ACI Site 1, and bd20 is deployed locally in ACI Site 2. The ESG esg1020 is stretched across the two ACI sites; however, its selectors differ between the sites. At a high level, the following are the main configuration steps, assuming that VRF vrf1 has already been deployed and stretched across the sites.

- On ACI Site 1, create bd10 with the subnet defined with “Advertised Externally” scope enabled.
- On ACI Site 1, deploy bd10 to Border Gateway by associating the BD to the Border Gateway Set.
- Create epg10 in bd10, create esg1020 and use EPG selector epg10, use 1020 as Normalized pcTag.

- On ACI Site 2, create bd20 with the subnet defined with “Advertised Externally” scope enabled.
- On ACI Site 2, deploy bd20 to Border Gateway by associating the BD to the Border Gateway Set.
- Create epg20 in bd20, create esg1020 and use EPG selector epg20, use 1020 as Normalized pcTag.

After the above steps are completed, the EVPN Type-5 route is exchanged between the two sites. In addition, because the BDs are deployed on the Border Gateway, the EVPN Type-2 route carrying the pcTag is also exchanged across sites. As a result, endpoint EP1 in bd10 in ACI Site 1 can communicate with endpoint EP2 in bd20 in ACI Site 2. The next section covers configuration result and verification.

## Create non-stretched local Bridge Domain and ESG

On ACI Site 1 create Bridge Domain bd10:

- L2 Unknown Unicast: Flood
- L3 Configurations: Unicast Routing (checked)
  - Subnet 192.168.10.254/24 has scope Advertised Externally

The “Advertised Externally” scope must be enabled to allow subnet advertisement (EVPN type-5 routes) to remote ACI sites.




Figure 132. ACI Site 1 bd10 L2 Unknown Unicast Flood




Figure 133. ACI Site 1 bd10 L3 Configurations

Deploy BD bd10 and associate it with the Border Gateway. This association is required even when the subnet remains local to the site, because it enables the Border Gateway to advertise EVPN Type-2 endpoint routes carrying pcTag information to the remote site. The remote site uses this pcTag information for endpoint classification and policy enforcement. A BD is considered local to a site when its Normalized VNI is unique across multiple ACI sites (independently from the name assigned to the BD). In this example, Normalized VNI 30010 is assigned to bd10. Conversely, in ACI Site 2, Normalized VNI 30020 is assigned to bd20.

| Bridge Domain | Border Gateway Set | Normalized VNI | Local VNI |
|---------------|--------------------|----------------|-----------|
| bd-share1     | bgw                | 31000          | 15138760  |
| bd1           | bgw                | 30001          | 15007704  |
| bd2           | bgw                | 30002          | 15564695  |
| bd10          | bgw                | 30010          | 14680065  |

**Figure 134.** ACI Site 1 deploy bd10 on border gateway

The subsequent step is to create the ESG esg1020. Consistent with the preceding procedures, the associated EPG must be defined prior to the creation of the ESG.

**EPG - epg10**

Summary | Policy | Operational | Stats

Topology | General

**Properties**

Annotations: [Click to add a new annotation](#)

Global Alias:

uSeg EPG: false

pcTag(sclass): 49153

Contract Exception Tag:

QoS class: Level3 (Default)

Custom QoS: select a value

Data-Plane Policer: select a value

Intra EPG Isolation: **Enforced** | Unenforced

Preferred Group Member: **Exclude** | Include

Flood in Encapsulation: **Disabled** | Enabled

Configuration Status: applied

Configuration Issues:

Label Match Criteria: At Least One


Bridge Domain: bd10

Resolved Bridge Domain: bgw/bd10

**Figure 135.** ACI Site 1 epg10


ESG esg1020 uses EPG epg10 as EPG selector.





**Figure 136.** ACI Site 1 esg1020 EPG selector

Set the Normalized pcTag to 1020 for ESG esg1020.




**Figure 137.** ACI Site 1 esg1020 Normalized pcTag

On ACI Site 2 create Bridge Domain bd20:


- L2 Unknown Unicast: Flood
- L3 Configurations: Unicast Routing (checked)
  - Subnet 192.168.20.254/24 has scope Advertised Externally

The “Advertised Externally” scope must be enabled to allow subnet advertisement to remote ACI sites.






**Figure 138.** ACI Site 2 bd20 L2 Unknown Unicast Flood




**Figure 139.** ACI Site 2 bd20 L3 Configurations

Deploy BD bd20 by associating it with the Border Gateway. In this example, the Normalized VNI 30020 is distinct from the VNI 30010 assigned to bd10 on ACI Site 1. This distinction indicates that bd10 on ACI Site 1 and bd20 on ACI Site 2 are independent, non-stretched entities, each deployed locally on its respective site Border Gateway to advertise EVPN Type-2 route.




**Figure 140.** ACI Site 2 deploy bd20 on Border Gateway

The subsequent step is to create ESG esg1020. Consistent with the preceding procedures, the associated EPG must be defined prior to the creation of the ESG.




**Figure 141.** ACI Site 2 epg20

Create ESG esg1020 using EPG epg20 as EPG Selector.




**Figure 142.** ACI Site 2 esg1020 EPG selector

Set the Normalized pcTag to 1020 for ESG esg1020.



**Figure 143.** ACI Site 2 esg1020 Normalized pcTag

## Control Plane Verification




**Figure 144.** ESG esg1020

The control-plane verification for this use case follows the same general approach as the previous use case, “[Use Case 2: Inter-Subnet Communication with Stretched BDs and Multiple ESGs](#)”. The key difference is that bd10 and bd20 are deployed locally in ACI Site 1 and ACI Site 2, respectively, rather than being configured as stretched BDs. As a result, the verification in this scenario should focus on both EVPN Type-5 and EVPN Type-2 route advertisements across the two sites.

Because the BDs are locally deployed, EVPN Type-5 routes are required to exchange subnet reachability information between the sites otherwise compute leaf in local site does not have route to the non-stretched (local) BD subnet defined in the remote site. In this example, IP subnet 192.168.10.0/24 must be advertised to ACI Site 2, and IP subnet 192.168.20.0/24 must be advertised to ACI Site 1.

In addition, EVPN Type-2 routes are required to exchange endpoint reachability information and support end-to-end communication across the two sites. EVPN Type-2 routes also carry the pcTag information needed for endpoint classification and policy enforcement. Without this Type-2 route exchange, pcTag information would not be shared across sites, and policy enforcement for inter-site traffic is not possible. In this example, IP host route 192.168.10.11/32 must be advertised to ACI Site 2, and IP host route 192.168.20.201/32 must be advertised to ACI Site 1. The EVPN Type-2 route also carries the endpoint pcTag information when the endpoint is advertised to the remote site.

The block diagram below illustrates the EVPN Type-5 advertisement workflow from ACI Site 1 to ACI Site 2. Note that if only EVPN Type-5 route exchange is required between the sites, the BD does not need to be deployed on the Border Gateway. However, deployment of the BD on the Border Gateway is required when EVPN Type-2 route exchange is needed for policy enforcement. The same procedure applies in the reverse direction, from ACI Site 2 to ACI Site 1.



**Figure 145.** BGP EVPN Type-5 from Site 1 to Site 2

The next screenshots focus on the first Border Gateway in ACI Site 1, keep in mind that all Border Gateways in ACI Site 1 require the same procedure to advertise route to ACI Site 2.

ACI Site 1 Border Gateway has bd10 subnet 192.168.10.0/24 locally:

```
bgw-leaf1# show ip route 192.168.10.0 vrf bgw:vrf1
```

```
IP Route Table for VRF "bgw:vrf1"
```

```
'*' denotes best ucast next-hop
```

```
'**' denotes best mcast next-hop
```

```
'[x/y]' denotes [preference/metric]
```

```
'%<string>' in via output denotes VRF <string>
```

```
192.168.10.0/24, ubest/mbest: 1/0, attached, direct, pervasive, dcs
```

```
*via 10.1.144.66%overlay-1, [1/0], 4w1d, static
```

```
bgw-leaf1#
```

**Figure 146.** ACI Site 1 Border Gateway non-stretched (local) BD subnet

Non-stretched (local) BD subnet 192.168.10.0/24 is advertised by ACI Site 1 Border Gateways to ACI Site 2 Border Gateways through BGP EVPN. The IP 5.5.5.105 is loopback0 address of ACI Site 2 Border Gateway.

```
bgw-leaf1# show bgp l2vpn evpn 192.168.10.0
```

```
Route Distinguisher: 100:18939904 (L3VNI 2162688)
```

```
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.10.0]:[0.0.0.0]/224, version 30890 dest ptr 0x7fd05824c858
```

```
Paths: (1 available, best #1)
```

```
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn
```

```
Multipath: eBGP iBGP
```

```
Advertised path-id 1
```

```
Path type (0x7fd04c76ebf0): local 0x4000008c 0x4400000 ref 0 adv path ref 1, path is valid, is best path
```

```
AS-Path: NONE, path locally originated
```

```
0.0.0.0 (metric 0) from 0.0.0.0 (10.1.248.7)
```

```
Origin incomplete, MED 0, localpref 100, weight 32768 tag 0, propagate 0, floating svi 0, tunnel resolved 0
```

```
Received label 2162688
```

```
Extcommunity: RT:100:2162688 VNID:2162688
```

```
Path-id 1 advertised to peers:
```

```
5.5.5.105
```

**Figure 147.** ACI Site 1 First Border Gateway advertises EVPN Type-5

As mentioned above, all Border Gateways in ACI Site 1 advertise the same BD subnet, for completion the EVPN output of the second Border Gateway (in ACI Site 1 Pod-1) and third Border Gateway (in ACI Site 1 Pod-2) are as follows:

```
bgw-leaf2# show bgp l2vpn evpn 192.168.10.0
```

```
Route Distinguisher: 100:18939904 (L3VNI 2162688)
```

```
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.10.0]:[0.0.0.0]/224, version 24123 dest ptr 0xa242a898
```

```
Paths: (1 available, best #1)
```

```
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn
```

```
Multipath: eBGP iBGP
```

```
Advertised path-id 1
```

```
Path type (0x96876e40): local 0x4000008c 0x4400000 ref 0 adv path ref 1, path is valid, is best path
```

```
AS-Path: NONE, path locally originated
```

```
0.0.0.0 (metric 0) from 0.0.0.0 (10.1.248.2)
```

```
Origin incomplete, MED 0, localpref 100, weight 32768 tag 0, propagate 0, floating svi 0, tunnel resolved 0
```

```
Received label 2162688
```

```
Extcommunity: RT:100:2162688 VNID:2162688
```

```
Path-id 1 advertised to peers:
```

```
5.5.5.105
```

**Figure 148.** ACI Site 1 Second Border Gateway advertises EVPN Type-5

```

bgw-leaf202# show bgp l2vpn evpn 192.168.10.0
Route Distinguisher: 100:35717120 (L3VNI 2162688)
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.10.0]:[0.0.0.0]/224, version 22007 dest ptr 0xa23a2a04
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x967e2480): local 0x4000000c 0x44000000 ref 0 adv path ref 1, path is valid, is best path
AS-Path: NONE, path locally originated
0.0.0.0 (metric 0) from 0.0.0.0 (10.2.208.66)
Origin incomplete, MED 0, localpref 100, weight 32768 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 2162688
Extcommunity: RT:100:2162688 VNID:2162688

Path-id 1 advertised to peers:
5.5.5.105

```

**Figure 149.** ACI Site 1 Third Border Gateway advertises EVPN Type-5

As a result, ACI Site 2 Border Gateways receive the route to 192.168.10.0/24 through BGP EVPN from three Border Gateways in ACI Site 1.

```

qt-bgw005# show bgp l2vpn evpn 192.168.10.0
Route Distinguisher: 100:18939904
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.10.0]:[0.0.0.0]/224, version 18143 dest ptr 0x7f250b90cd4e
Paths: (2 available, best #2)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Path type (0x7f24fff20a6c): external 0x40000028 0x40000000 ref 0 adv path ref 0, path is valid, not best reason: Router Id, remote nh not installed
AS-Path: 100 , path sourced external to AS
100.100.100.102 (metric 0) from 1.1.1.101 (10.1.248.7)
Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 50001
Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:80:0:0:1 Router MAC:6408.64ca.393a

Advertised path-id 1
Path type (0x7f24fff24a68): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
Imported to 1 destination(s)
AS-Path: 100 , path sourced external to AS
100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 50001
Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:80:0:0:1 Router MAC:005d.73eb.c599

Path-id 1 not advertised to any peer

Route Distinguisher: 100:35717120
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.10.0]:[0.0.0.0]/224, version 18122 dest ptr 0x7f250b90ffe8
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f24fff27030): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
Imported to 1 destination(s)
AS-Path: 100 , path sourced external to AS
200.200.200.202 (metric 0) from 2.2.2.202 (10.2.208.66)
Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 50001
Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
ENCAP:8 PCTAG:80:0:0:1 Router MAC:2cd0.2d23.1736

Path-id 1 not advertised to any peer

```

**Figure 150.** ACI Site 2 Border Gateway receive EVPN Type-5

- 100.100.100.102: ACI Site 1 Pod-1 Multi-Site External VIP (Anycast External VIP)
- 1.1.1.101: ACI Site 1 Pod-1 first Border Gateway TEP (EVPN loopback)
- 1.1.1.102: ACI Site 1 Pod-1 second Border Gateway TEP (EVPN loopback)
- 200.200.200.202: ACI Site 1 Pod-2 Multi-Site External VIP (Anycast External VIP)
- 2.2.2.202: ACI Site 1 Pod-2 Border Gateway TEP (EVPN loopback)

The field “Path-id 1 not advertised to any peer” means ACI Site 2 Border Gateway receives the EVPN Type-5 route, but it does not forward this route (re-advertise) through BGP EVPN. Instead, this route is then advertised to ACI Site 2 Spine through BGP VPNv4. ACI Site 2 Spine then reflects the route to ACI Site 2 compute leaf. As a result on ACI Site 2 compute leaf, the route to 192.168.10.0/24 is received in BGP VPNv4 table then is installed in the routing table.

```

qt-leaf802# show bgp vpnv4 unicast vrf all
BGP routing table information for VRF overlay-1, address family VPNv4 Unicast
BGP table version is 1241, local router ID is 10.118.112.64
Status: s-suppressed, x-deleted, S-stale, d-dampened, h-history, *-valid, >-best
Path type: i-internal, e-external, c-confed, l-local, a-aggregate, r-redist, I-injected
Origin codes: i - IGP, e - EGP, ? - incomplete, | - multipath, & - backup

```

| Network                                         | Next Hop      | Metric | LocPrf | Weight | Path      |
|-------------------------------------------------|---------------|--------|--------|--------|-----------|
| Route Distinguisher: 801:2097152                |               |        |        |        |           |
| *>12.2.2.18/32                                  | 10.118.112.66 | 0      | 100    | 0      | ?         |
| *>100.68.1.0/24                                 | 10.118.112.66 | 0      | 100    | 0      | 900 i     |
| *>172.16.164.0/24                               | 10.118.112.66 | 0      | 100    | 0      | ?         |
| Route Distinguisher: 802:2097152 (VRF bgw:vrf1) |               |        |        |        |           |
| *>12.2.2.18/32                                  | 10.118.112.66 | 0      | 100    | 0      | ?         |
| *>100.64.1.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.64.2.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.64.3.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.64.4.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.64.5.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.64.6.0/24                                 | 10.118.112.67 | 0      | 100    | 0      | 100 600 i |
| *>100.68.1.0/24                                 | 10.118.112.66 | 0      | 100    | 0      | 900 i     |
| *>172.16.161.0/30                               | 10.118.112.67 | 0      | 100    | 0      | 100 ?     |
| *>172.16.164.0/24                               | 10.118.112.66 | 0      | 100    | 0      | ?         |
| *>192.168.10.0/24                               | 10.118.112.67 | 0      | 100    | 0      | 100 ?     |
| *>192.168.50.0/24                               | 10.118.112.67 | 0      | 100    | 0      | 100 ?     |

**Figure 151.** ACI Site 2 compute leaf BGP VPNv4

The route is installed in the compute leaf routing table with the Border Gateway PTEP as the next hop.

```

qt-leaf802# show ip route 192.168.10.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.10.0/24, ubest/mbest: 1/0
  *via 10.118.112.67%overlay-1, [200/0], 01w04d, bgp-400, internal, tag 100, pc-tag: 1
    recursive next hop: 10.118.112.67/32%overlay-1

```

**Figure 152.** ACI Site 2 compute leaf routing table

Following the same procedure, IP subnet route 192.168.20.0/24 is advertised from ACI Site 2 to ACI Site 1. In this example, the ACI Site 1 Border Gateway receives the route through BGP EVPN and then advertises it to the ACI Site 1 spines through BGP VPNv4. The spines subsequently reflect the route to the compute leaf switches.

The Next-hop IP 105.105.105.105 is the Multi-Site External VIP (Anycast External IP) of ACI Site 2 Border Gateway, 5.5.5.105 is loopback0 IP address of ACI Site 2 Border Gateway.

```

bgw-leaf1# show bgp l2vpn evpn 192.168.20.0
Route Distinguisher: 400:18874368
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.20.0]:[0.0.0.0]/224, version 42124 dest ptr 0x7fd05824d53e
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c76da44): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 400 , path sourced external to AS
  105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
  Received label 50001
  Extcommunity: RT:100:50001 S00:100:1694498797 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:1 Router MAC:080f.e5e2.bb99

  Path-id 1 not advertised to any peer

```

**Figure 153.** ACI Site 1 Border Gateway learn ACI Site 2 bd20 subnet

The IP subnet route 192.168.20.0/24 then is programmed in the routing table.



```

bgw-leaf1# show ip route 192.168.20.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.20.0/24, ubest/mbest: 1/0
  *via 105.105.105.105%overlay-1, [20/0], 1w4d, bgp-100, external, tag 400
bgw-leaf1#

```

**Figure 154.** ACI Site 1 Border Gateway routing table

ACI Site 1 compute leaf switches have the route in its BGP VPNv4 table, then in the routing table.

```

leaf1# show bgp vpnv4 unicast vrf all
BGP routing table information for VRF overlay-1, address family VPNv4 Unicast
BGP table version is 3133, local router ID is 10.1.248.3
Status: s-suppressed, x-deleted, S-stale, d-dampened, h-history, *-valid, >-best
Path type: i-internal, e-external, c-confed, l-local, a-aggregate, r-redist, I-injected
Origin codes: i - IGP, e - EGP, ? - incomplete, | - multipath, & - backup

  Network          Next Hop          Metric      LocPrf      Weight Path
Route Distinguisher: 101:2097153 (VRF common:rke-tmerkecluster1-vrf)
*>r0.0.0.0/0       0.0.0.0           0           100         32768 ?
*>r1.1.1.1/32      0.0.0.0           0           100         32768 ?
*>r2.2.0.0/16      0.0.0.0           0           100         32768 ?
*>r192.168.1.0/24  0.0.0.0           0           100         32768 ?
*>r192.168.2.0/24  0.0.0.0           0           100         32768 ?

Route Distinguisher: 101:2162688 (VRF bgw:vrf1)
*>r1.1.1.101/32    0.0.0.0           0           100         32768 ?
*>e100.64.1.0/24   172.16.161.2      0           0           600 i
*>e100.64.2.0/24   172.16.161.2      0           0           600 i
*>e100.64.3.0/24   172.16.161.2      0           0           600 i
*>e100.64.4.0/24   172.16.161.2      0           0           600 i
*>e100.64.5.0/24   172.16.161.2      0           0           600 i
*>e100.64.6.0/24   172.16.161.2      0           0           600 i
*>i100.68.1.0/24   10.1.248.2        0           100         400 900 i
*|i               10.1.248.7        0           100         400 900 i
*>r172.16.31.0/24  0.0.0.0           0           100         32768 ?
*>r172.16.161.0/30 0.0.0.0           0           100         32768 ?
*>i172.16.164.0/24 10.1.248.2        0           100         400 ?
*|i               10.1.248.7        0           100         400 ?
*>r192.168.1.0/24  0.0.0.0           0           100         32768 ?
*>r192.168.1.7/32  0.0.0.0           0           100         32760 ?
*>r192.168.1.11/32 0.0.0.0           0           100         32760 ?
*>r192.168.1.29/32 0.0.0.0           0           100         32760 ?
*>r192.168.2.0/24  0.0.0.0           0           100         32768 ?
*>r192.168.10.0/24 0.0.0.0           0           100         32768 ?
*>i192.168.20.0/24 10.1.248.2        0           100         400 ?
*|i               10.1.248.7        0           100         400 ?

```

**Figure 155.** ACI Site 1 compute leaf BGP VPNv4 table

```

leaf1# show ip route 192.168.20.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.20.0/24, ubest/mbest: 2/0
  *via 10.1.248.2%overlay-1, [200/0], 01w04d, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.2/32%overlay-1
  *via 10.1.248.7%overlay-1, [200/0], 01w04d, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.7/32%overlay-1

```

**Figure 156.** ACI Site 1 compute leaf routing table

Note that, in this use case, the EVPN Type-5 route does not carry pcTag information. Instead, the pcTag information is carried in the EVPN Type-2 route. This behavior is consistent with the [“Inter-Subnet Communication with Stretched BDs and Multiple ESGs”](#) use cases. ACI Site 1 Border Gateway learns EVPN Type-2 for remote endpoint 192.168.20.201 from Site 2. The figure below shows output of first Border Gateway. The pcTag 1020 is Normalized pcTag, this value later is translated to the local pcTag when the route is installed in the routing table.

```

bgw-leaf1# show bgp l2vpn evpn 192.168.20.201
Route Distinguisher: 400:32210852
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.5559]:[32]:[192.168.20.201]/272, version 42126 dest ptr 0x7fd05825661a
Paths: (1 available, best #1)
Flags: (0x000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7fd04c76cb08): external 0x40000028 0x4002000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
Imported to 1 destination(s)
AS-Path: 400 , path sourced external to AS
105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 30020 50001
Extcommunity: RT:100:30020 RT:100:50001 S00:100:1694498797
COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:1020
Router MAC:080f.e5e2.bb99

Path-id 1 not advertised to any peer

```

**Figure 157.** ACI Site 1 Border Gateway learns remote endpoint through EVPN Type-2

Note that the local pcTag is shown only when using the exec mode (default mode, non-vsh mode)

```

bgw-leaf1# show ip route 192.168.20.201 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
'**' denotes best mcast next-hop
'[x/y]' denotes [preference/metric]
'%<string>' in via output denotes VRF <string>

192.168.20.201/32, ubest/mbest: 1/0
 *via 105.105.105.105%overlay-1, [20/0], 01w04d, bgp-100, external, tag 400, redist-only, pc-tag: 5476
 recursive next hop: 105.105.105.105/32%overlay-1
bgw-leaf1#

```

**Figure 158.** ACI Site 1 Border Gateway displays remote endpoint with local pcTag

## Data Plane Verification

Because ESG esg1020 is deployed in both sites with the same Normalized pcTag, endpoints within this ESG can communicate each other across both ACI sites without a contract.


The screenshot shows the APIC (site1) interface. The left sidebar displays a tree view under 'bgw' with 'Application Profiles' expanded, showing 'ap1' and 'Endpoint Security Groups' with 'esg1', 'esg2', 'esg1020', and 'ext-1'. The main panel shows the 'ESG - esg1020' configuration. The 'Operational' tab is active, displaying a table of client endpoints. The table has columns: MAC/IP, Endpoint Name, Learning Source, Hosting Server, Reporting Controller Name, Interface (learned), Encap, Base EPG, and Policy Tags. One endpoint is listed with MAC/IP 00:50:56:BF:F9:82, Endpoint Name aci-ubu-10, Learning Source Learned VMM, Hosting Server 10.68.235.139, Reporting Controller Name vcenter, Interface (learned) Pod-1/Node-101/eth1/3..., Encap vlan-235, Base EPG bgw.ac1.esg10, and Policy Tags bgw.ac1.esg10. The MAC/IP and Endpoint Name are highlighted with a red box.

**Figure 159.** ACI Site 1 esg1020 endpoint

The screenshot shows the APIC (site2) interface. The left sidebar displays a tree view under 'bgw' with 'Application Profiles' expanded, showing 'ap1' and 'Endpoint Security Groups' with 'esg1', 'esg2', 'esg1020', and 'ext-1'. The main panel shows the 'ESG - esg1020' configuration. The 'Operational' tab is active, displaying a table of client endpoints. The table has columns: MAC/IP, Endpoint Name, Learning Source, Hosting Server, Reporting Controller Name, Interface (learned), Encap, Base EPG, and Policy Tags. One endpoint is listed with MAC/IP 00:50:56:BF:55:59, Endpoint Name site2-aci-ubu-20, Learning Source Learned VMM, Hosting Server 172.16.0.4, Reporting Controller Name QT-DC, Interface (learned) Pod-1/Node-802/eth1/..., Encap vlan-370, Base EPG bgw.ac1.esg20, and Policy Tags bgw.ac1.esg20. The MAC/IP and Endpoint Name are highlighted with a red box.



**Figure 160.** ACI Site 2 esg1020 endpoint



**Figure 161.** Data plane Inter-Subnet Communication with Non-stretched BDs and Single ESG

An endpoint in ESG esg1020 in ACI Site 1 can ping an endpoint in the same ESG in ACI Site 2. The following packet capture was obtained via ERSPAN traffic from ISN device. The packet capture of the ICMP request from EP-10 to EP-20 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source         | Destination    | Protocol | Length | Info                                                              |
|-----|----------|----------------|----------------|----------|--------|-------------------------------------------------------------------|
| 29  | 0.580223 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=10/2560, ttl=62 (reply in 30)  |
| 30  | 0.580307 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=10/2560, ttl=62 (request in 29)  |
| 80  | 1.604226 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=11/2816, ttl=62 (reply in 81)  |
| 81  | 1.604383 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=11/2816, ttl=62 (request in 80)  |
| 131 | 2.628214 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=12/3072, ttl=62 (reply in 132) |
| 132 | 2.628352 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=12/3072, ttl=62 (request in 131) |
| 179 | 3.652284 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=13/3328, ttl=62 (reply in 180) |
| 180 | 3.652353 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=13/3328, ttl=62 (request in 179) |
| 230 | 4.676218 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=14/3584, ttl=62 (reply in 231) |
| 231 | 4.676365 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=14/3584, ttl=62 (request in 230) |

|                                                                                                                         |      |                      |
|-------------------------------------------------------------------------------------------------------------------------|------|----------------------|
| > Frame 29: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF_{5D6AB595-A} | 0000 | 00 50 56 bf d4 e1 4c |
| > Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware_bf:d4:e1 (00:50:56:bf:d4:e1)                        | 0010 | 00 b8 f8 4e 00 00 ff |
| > Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100                                                        | 0020 | 50 64 10 00 88 be 00 |
| > Generic Routing Encapsulation (ERSPAN)                                                                                | 0030 | 00 0c 00 22 bd f8 19 |
| > Encapsulated Remote Switch Packet Analysis Type II                                                                    | 0040 | 45 00 00 86 00 00 00 |
| > Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: Cisco_f8:19:ff (00:22:bd:f8:19:ff)                         | 0050 | 69 69 69 2a e0 12    |
| > Internet Protocol Version 4, Src: 1.1.1.102, Dst: 105.105.105.105                                                     | 0060 | 00 c3 51 00 08 0f e5 |
| > User Datagram Protocol, Src Port: 10976, Dst Port: 4789                                                               | 0070 | 08 00 45 00 00 54 e9 |
| > Virtual eXtensible Local Area Network                                                                                 | 0080 | 0a 0b c0 a8 14 c9 08 |
| > Flags: 0x0800, VXLAN Network ID (VNI)                                                                                 | 0090 | 47 6a 00 00 00 00 58 |
| > Group Policy ID: 0                                                                                                    | 00a0 | 12 13 14 15 16 17 18 |
| > VXLAN Network Identifier (VNI): 50001                                                                                 | 00b0 | 22 23 24 25 26 27 28 |
| > Reserved: 0                                                                                                           | 00c0 | 32 33 34 35 36 37    |
| > Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco_e2:bb:99 (08:0f:e5:e2:bb:99)                |      |                      |
| > Internet Protocol Version 4, Src: 192.168.10.11, Dst: 192.168.20.201                                                  |      |                      |
| > Internet Control Message Protocol                                                                                     |      |                      |

**Figure 162.** ICMP request from EP-10 (192.168.10.11) to EP-20 (192.168.20.201)

The packet capture of the ICMP reply from EP-20 to EP-10 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source         | Destination    | Protocol | Length | Info                                                              |
|-----|----------|----------------|----------------|----------|--------|-------------------------------------------------------------------|
| 29  | 0.580223 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=10/2560, ttl=62 (reply in 30)  |
| 30  | 0.580307 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=10/2560, ttl=62 (request in 29)  |
| 80  | 1.604226 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=11/2816, ttl=62 (reply in 81)  |
| 81  | 1.604383 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=11/2816, ttl=62 (request in 80)  |
| 131 | 2.628214 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=12/3072, ttl=62 (reply in 132) |
| 132 | 2.628352 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=12/3072, ttl=62 (request in 131) |
| 179 | 3.652284 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=13/3328, ttl=62 (reply in 180) |
| 180 | 3.652353 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=13/3328, ttl=62 (request in 179) |
| 230 | 4.676218 | 192.168.10.11  | 192.168.20.201 | ICMP     | 198    | Echo (ping) request id=0x7c07, seq=14/3584, ttl=62 (reply in 231) |
| 231 | 4.676365 | 192.168.20.201 | 192.168.10.11  | ICMP     | 198    | Echo (ping) reply id=0x7c07, seq=14/3584, ttl=62 (request in 230) |


  

|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                                                                                                                                                                                                                                                                                                                                          |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <ul style="list-style-type: none"> <li>Frame 30: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF_{5D6AB595-A...}</li> <li>Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware_bf:d4:e1 (00:50:56:bf:d4:e1)</li> <li>Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100</li> <li>Generic Routing Encapsulation (ERSPAN)</li> <li>Encapsulated Remote Switch Packet Analysis Type II</li> <li>Ethernet II, Src: Cisco_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47)</li> <li>Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102</li> <li>User Datagram Protocol, Src Port: 9455, Dst Port: 4789</li> <li>Virtual eXtensible Local Area Network <ul style="list-style-type: none"> <li>Flags: 0x0800, VXLAN Network ID (VNI)</li> <li>Group Policy ID: 0</li> <li>VXLAN Network Identifier (VNI): 50001</li> <li>Reserved: 0</li> </ul> </li> <li>Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco_eb:c5:99 (00:5d:73:eb:c5:99)</li> <li>Internet Protocol Version 4, Src: 192.168.20.201, Dst: 192.168.10.11</li> <li>Internet Control Message Protocol</li> </ul> | <pre> 0000  00 50 56 bf d4 e1 4c 0010  00 b8 19 2b 00 00 ff 0020  50 64 10 00 88 be 00 0030  01 3d 4c 77 6d d5 bb 0040  45 00 00 86 00 00 00 0050  64 64 64 66 24 ef 12 0060  00 c3 51 00 00 5d 73 0070  08 00 45 00 00 54 19 0080  14 c9 c0 a8 0a 0b 00 0090  47 6a 00 00 00 00 58 00a0  12 13 14 15 16 17 18 00b0  22 23 24 25 26 27 28 00c0  32 33 34 35 36 37 </pre> |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

**Figure 163.** ICMP reply from EP-20 (192.168.20.201) to EP-10 (192.168.10.201)

## Policy Enforcement

From a policy enforcement location perspective, this use case is identical to the previous use case, “[Inter-Subnet Communication with Stretched BDs and Multiple ESGs](#)” between ESGs. Although endpoints 192.168.10.11 (Site 1) and 192.168.20.201 (Site 2) are members of the same ESG (esg1020), their communication is inter-subnet (routed), which is same as the previous use case. The topology below illustrates the policy enforcement points for traffic originating in Site 1 and destined for Site 2. The same logic applies to the return path from Site 2 to Site 1; the egress switch enforces the policy in each site.



**Figure 164.** Intra-ESG Inter-Subnet communication policy enforcement


In ACI Site 2, although Border Gateway has endpoint information advertised by local spine, it ignores the IP part to save hardware resource, the Border Gateway does not enforce policy, instead the compute leaf attached to the destination endpoint enforces policy based on the locally learned endpoint information.

## Use Case 4: Inter-Subnet Communication with Non-stretched BDs and Multiple ESGs

### Use Case Overview

This use case describes communication between endpoints residing in different subnets. It is similar to [Use Case 3: Inter-Subnet Communication Non-stretched BDs and Single ESG](#); however, the main difference

lies in the security segmentation model based on ESGs. In this use case, each site contains two ESGs: one ESG is used for local endpoint classification, with an ESG selector for actual endpoints assigned to it, and the other ESG is used for remote endpoint classification, this ESG does not need any local ESG selectors.



**Figure 165. Inter-Subnet Communication Non-stretched BD Multiple ESGs**


As shown in the above diagram, all the objects including ESGs and BDs are locally defined. At a high level, the following are the main configuration steps, assuming that VRF vrf1 has already been deployed and stretched across the sites.

### Create non-stretched local Bridge Domain, ESGs, Contract


On ACI Site 1 create Bridge Domain bd50:

- L2 Unknown Unicast: Flood
- L3 Configurations: Unicast Routing (checked)
  - Subnet 192.168.50.254/24 has scope Advertised Externally

The “Advertised Externally” scope must be enabled to allow subnet advertisement to the remote ACI site.




**Figure 166.** ACI Site 1 bd50 L2 Unknown Unicast Flood




**Figure 167.** ACI Site 1 bd50 L3 Configurations

Deploy BD bd50 by associating it with the Border Gateway. A Bridge Domain is considered local to a site when its Normalized VNI is unique across multiple ACI sites. In this example, Normalized VNI 30050 is assigned to bd50. Conversely, in ACI Site 2, Normalized VNI 30060 is assigned to bd60.




**Figure 168.** ACI Site 1 deploy bd50 on border gateway

Create epg50 and associate it to bd50, then create esg50 using epg50 as EPG Selector.




**Figure 169.** ACI Site 1 ep50




**Figure 170.** ACI Site 1 esg50 EPG Selector

Set the Normalized pcTag to 1050 for ESG esg50.




**Figure 171.** ACI Site 1 esg50 Normalized pcTag

Create ESG esg60 without EPG selectors and assign a normalized pcTag of 1060. Subsequently, create and apply a contract between esg50 and esg60 to permit traffic from esg60 endpoints in ACI Site 2 to esg50 endpoints in ACI Site 1.




**Figure 172.** ACI Site 1 esg60 without selector




**Figure 173.** ACI Site 1 esg60 normalized pcTag

Create contract esg50-esg60 with permit IP filter. Since the ESGs are in the same VRF, the scope is set to VRF.




**Figure 174.** ACI Site 2 esg50 Normalized pcTag




**Figure 175.** ACI Site 1 esg50-esg60 contract

Apply contract esg50-esg60 between ESG esg50 and esg60. The ESG esg50 is the consumer, esg60 is the provider.



**Figure 176.** ACI Site 1 esg50 contract consumer




**Figure 177.** ACI Site 1 esg60 contract provider

On ACI Site 2 create Bridge Domain bd60:


- L2 Unknown Unicast: Flood
- L3 Configurations: Unicast Routing (checked)

- Subnet 192.168.60.254/24 has scope Advertised Externally

The “Advertised Externally” scope must be enabled to allow subnet advertisements to the remote ACI site.




**Figure 178.** ACI Site 2 bd60 L2 Unknown Unicast Flood



**Figure 179.** ACI Site 2 bd60 L3 Configurations


Deploy BD bd60 by associating it with the Border Gateway. In this example, the Normalized VNI 30060 is distinct from the VNI 30050 assigned to bd50 on ACI Site 1. This distinction indicates that bd50 on ACI Site 1 and bd60 on ACI Site 2 are independent, non-stretched entities and deployed locally on its respective site Border Gateway.




**Figure 180.** ACI Site 2 deploy bd60 on border gateway

Create ep60 and associate it to bd60, then create esg60 using ep60 as EPG Selector.






**Figure 181.** ACI Site 2 ep60




**Figure 182.** ACI Site 2 esg60 EPG Selector

Create ESG esg50 without EPG selectors and assign a normalized pcTag of 1050. Subsequently, create and apply a contract between esg50 and esg60 to permit traffic from esg50 endpoints in ACI Site 1 to esg60 endpoints in ACI Site 2.




**Figure 183.** ACI Site 2 esg50 without selector

Create contract esg50-esg60 with permit IP filter. Since the ESGs are in the same VRF, the scope is set to VRF.




**Figure 184.** ACI Site 2 esg50-esg60 contract

Apply contract esg50-esg60 to ESG esg50 and esg60. The ESG esg50 is consumer, esg60 is provider.




**Figure 185.** ACI Site 2 esg50 contract consumer



**Figure 186.** ACI Site 2 esg60 contract provider

## Control Plane Verification

The verification steps for this use case are similar to those of the previous Use Case 3: [Inter-Subnet Communication Non-Stretched BDs Single ESG](#). The primary difference is that this scenario includes multiple ESGs, specifically esg50 and esg60. As a result, the control-plane verification process remains largely the same.



**Figure 187.** Non-stretch BD multiple ESGs

ACI Site 1 Border Gateways learn the route to 192.168.60.0/24 through BGP EVPN advertised by ACI Site 2 Border Gateway.

```

bgw-leaf1# show bgp l2vpn evpn 192.168.60.0
Route Distinguisher: 400:18874368
BGP routing table entry for [5]:[0]:[0]:[24]:[192.168.60.0]:[0.0.0.0]/224, version 42125 dest ptr 0x7fd058252a92
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c76e05c): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 400 , path sourced external to AS
  105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:100:50001 S00:100:1694498797 COST:pre-bestpath:170:1610612736
      ENCAP:8 PCTAG:80:0:0:1 Router MAC:080f.e5e2.bb99

  Path-id 1 not advertised to any peer

```

**Figure 188.** ACI Site 1 Border Gateway learns route 192.168.60.0

The route to 192.168.60.0/24 is then advertised to the ACI Site 1 spine switches through BGP VPNv4 and subsequently reflected to the compute leaf switches.

The compute leaf switches in ACI Site 1 learn the IP subnet route 192.168.60.0/24 with the Border Gateways in the same ACI Pod as the next hops.

```

leaf1# show ip route 192.168.60.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.60.0/24, ubest/mbest: 2/0
  *via 10.1.248.2%overlay-1, [200/0], 01w04d, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.2/32%overlay-1
  *via 10.1.248.7%overlay-1, [200/0], 01w04d, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.7/32%overlay-1
leaf1#

```

**Figure 189.** ACI Site 1 Compute leaf learns the route to 192.168.60.0/24

In addition, the ACI Site 1 Border Gateways learn the EVPN Type-2 route for the endpoint 192.168.60.201 located in ACI Site 2. As shown in the output below, pcTag 1060 corresponds to the esg60 Normalized pcTag configured in ACI Site 2.

```

bgw-leaf1# show bgp l2vpn evpn 192.168.60.201
Route Distinguisher: 400:32014268
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.653e]:[32]:[192.168.60.201]/272, version 42133 dest ptr 0x7fd0582522a2
Paths: (1 available, best #1)
Flags: (0x0000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c771254): external 0x40000028 0x40020000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 400 , path sourced external to AS
  105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
    Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 30060 50001
    Extcommunity: RT:100:30060 RT:100:50001 S00:100:1694498797
      COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:1060
      Router MAC:080f.e5e2.bb99

  Path-id 1 not advertised to any peer

```

**Figure 190.** ACI Site 1 Border Gateway learns the EVPN Type-2 route to 192.168.60.201.

The ACI Site 1 Border Gateway programs the host route for the endpoint 192.168.60.201, with the pcTag translated to the local esg60 pcTag value of 10942. The local pcTag value is displayed only when the command is executed in non-vsh mode.

```


bgw-leaf1# show ip route 192.168.60.201 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.60.201/32, ubest/mbest: 1/0
  *via 105.105.105.105%overlay-1, [20/0], 00:01:16, bgp-100, external, tag 400, redistrib-only, pc-tag: 10942
    recursive next hop: 105.105.105.105/32%overlay-1
bgw-leaf1#

```

**Figure 191.** ACI Site 1 Border Gateway program the host route in the routing table with the local site ESG pcTag

**Failure scenario (inconsistent normalized pcTag):** As shown previously in Figure 211, pcTag 1060 represents the normalized pcTag configured for esg60 in ACI Site 2. If the normalized pcTag for esg60 in ACI Site 2 is changed from 1060 to 10601, the ACI Site 1 Border Gateway still receives the EVPN Type-2 route for endpoint 192.168.60.201 with the updated pcTag value of 10601.



**Figure 192.** ACI Site 2 Change esg60 Normalized pcTag to 10601

```

bgw-leaf1# show bgp l2vpn evpn 192.168.60.201
Route Distinguisher: 400:32014268
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.653e]:[32]:[192.168.60.201]/272, version 51197 dest ptr 0x7fd0582522a2
Paths: (1 available, best #1)
Flags: (0x0000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c771254): external 0x40000028 0x4002000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 400 , path sourced external to AS
    105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
    Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 30060 50001
    Extcommunity: RT:100:30060 RT:100:50001 S00:100:1694498797
    COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:10601
    Router MAC:080f.e5e2.bb99

  Path-id 1 not advertised to any peer

```

**Figure 193.** ACI Site 1 Border Gateway receive the EVPN Type-2 route with the updated pcTag 10601

However, because pcTag 10601 does not exist in ACI Site 1, the ACI Site 1 Border Gateway cannot map the received normalized pcTag to a locally defined policy object. As a result, when the Border Gateway programs the host route into the routing table, it uses the reserved pcTag value of 12.

```

bgw-leaf1# show ip route 192.168.60.201 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.60.201/32, ubest/mbest: 1/0
  *via 105.105.105.105%overlay-1, [20/0], 00:03:57, bgp-100, external, tag 400, redistrib-only, pc-tag: 12
    recursive next hop: 105.105.105.105/32%overlay-1
bgw-leaf1#

```

**Figure 194.** ACI Site 1 Border Gateway use the reserved pcTag of 12 for the unclassified endpoint

The reserved pcTag value of 12 indicates that the endpoint is unclassified from the perspective of ACI Site 1. In other words, ACI Site 1 cannot associate the remote endpoint with any locally recognized policy. Consequently, communication from endpoint 192.168.50.11 in ACI Site 1 to endpoint 192.168.60.201 in ACI Site 2 fails.

This behavior highlights the importance of careful normalized pcTag planning across sites. Consistent pcTag allocation is required to ensure that remote endpoints are correctly classified and that inter-site communication is enforced as intended.

The same verification procedure applies to ACI Site 2, for the sake of brevity, the results are shown below.

ACI Site 2 Border Gateway learns the route to 192.168.50.0/24 through BGP EVPN advertised by ACI Site 1 Border Gateways.

```

qt-bgw005# show bgp l2vpn evpn 192.168.50.0
Route Distinguisher: 100:18939904
BGP routing table entry for [5]:[0]:[24]:[192.168.50.0]:[0.0.0]/224, version 18144 dest ptr 0x7f250b9104de
Paths: (2 available, best #2)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Path type (0x7f24fff209d0): external 0x40000028 0x40000000 ref 0 adv path ref 0, path is valid, not best reason: Router Id, remote nh not installed
AS-Path: 100, path sourced external to AS
  100.100.100.102 (metric 0) from 1.1.1.101 (10.1.248.7)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:1 Router MAC:6408.64ca.393a

Advertised path-id 1
Path type (0x7f24fff24cd8): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
  Imported to 1 destination(s)
AS-Path: 100, path sourced external to AS
  100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:1 Router MAC:005d.73eb.c599

Path-id 1 not advertised to any peer

Route Distinguisher: 100:35717120
BGP routing table entry for [5]:[0]:[24]:[192.168.50.0]:[0.0.0]/224, version 18123 dest ptr 0x7f250b90e420
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f24fff24450): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
  Imported to 1 destination(s)
AS-Path: 100, path sourced external to AS
  200.200.200.202 (metric 0) from 2.2.2.202 (10.2.208.66)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:1 Router MAC:2cd0.2d23.1736

Path-id 1 not advertised to any peer

```

**Figure 195.** ACI Site 2 Border Gateway receive the EVNP Type-5 route

ACI Site 2 compute leaf switches have the route to 192.168.50.0/24 in its routing table.

```

qt-leaf802# show ip route 192.168.50.0 vrf bgw:vrfl
IP Route Table for VRF "bgw:vrfl"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.50.0/24, ubest/mbest: 1/0
  *via 10.118.112.67%overlay-1, [200/0], 01w04d, bgp-400, internal, tag 100, pc-tag: 1
    recursive next hop: 10.118.112.67/32%overlay-1
qt-leaf802#

```

**Figure 196.** ACI Site 2 Compute leaf route table entry

ACI Site 2 Border Gateway also learns EVPN Type-2 route for the host 192.168.50.11 from ACI Site 1. As shown in the output below, pcTag 1050 corresponds to the esg50 Normalized pcTag configured in ACI Site 1.

```

qt-bgw805# show bgp l2vpn evpn 192.168.50.11
Route Distinguisher: 100:32341913
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.ef09]:[32]:[192.168.50.11]/272, version 18150 dest ptr 0x7f250b90c65c
Paths: (2 available, best #2)
Flags: (0x000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Path type (0x7f24fff20628): external 0x40000028 0x4002000 ref 0 adv path ref 0, path is valid, not best reason: Router Id, remote nh not installed
AS-Path: 100 , path sourced external to AS
  100.100.100.102 (metric 0) from 1.1.1.101 (10.1.248.7)
    Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 30050 50001
    Extcommunity: RT:400:30050 RT:400:50001 S00:400:2432696301
    COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:1050
    Router MAC:6408.64ca.393a

Advertised path-id 1
Path type (0x7f24fff25428): external 0x40000028 0x4002000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
  Imported to 1 destination(s)
AS-Path: 100 , path sourced external to AS
  100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
    Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 30050 50001
    Extcommunity: RT:400:30050 RT:400:50001 S00:400:2432696301
    COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:1050
    Router MAC:005d.73eb.c599

Path-id 1 not advertised to any peer

```

**Figure 197.** ACI Site 2 Border Gateway learns the EVPN Type-2 route to 192.168.50.11

The ACI Site 2 Border Gateway programs the host route for endpoint 192.168.50.11, with the pcTag translated to the local esg50 pcTag value of 25. The local pcTag value is displayed only when the command is executed in non-vsh mode.

```

qt-bgw805# show ip route 192.168.50.11 vrf bgw:vrfl
IP Route Table for VRF "bgw:vrfl"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.50.11/32, ubest/mbest: 1/0
  *via 100.100.100.102%overlay-1, [20/0], 01w04d, bgp-400, external, tag 100, redist-only, pc-tag: 25
    recursive next hop: 100.100.100.102/32%overlay-1
qt-bgw805#

```


**Figure 198.** ACI Site 2 Border Gateway program the host route in the routing table with the local site ESG pcTag

## Data Plane Verification


In this use case, both esg50 and esg60 are configured on ACI Site 1 and ACI Site 2. However, on ACI Site 1, esg60 has no selectors assigned; and no endpoints belong to esg60 in the site. Similarly, on ACI Site 2, esg50 has no selectors assigned, no endpoints belong to esg50 in the site.

The communication between endpoints in esg50 and esg60, such as between 192.168.50.11(esg50) in ACI Site 1 and 192.168.60.201(esg60) in ACI Site 2 is permitted because a contract is configured between esg50 and esg60 on each site.






**Figure 199.** ACI Site 1 esg50 endpoint



**Figure 200.** ACI Site 2 esg60 endpoint



**Figure 201.** Data plane Inter-Subnet Communication with Non-stretched BDs and Multiple ESGs

An endpoint in esg50 in ACI Site 1 can ping to an endpoint in esg60 in ACI Site 2. The following packet capture was obtained via ERSPAN traffic from ISN device. The packet capture of the ICMP request from EP-50 to EP-60 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



| No. | Time     | Source         | Destination    | Protocol | Length | Info                                                                |
|-----|----------|----------------|----------------|----------|--------|---------------------------------------------------------------------|
| 7   | 0.147008 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=100/25600, ttl=62 (reply in 8)   |
| 8   | 0.147118 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=100/25600, ttl=62 (request in 7)   |
| 58  | 1.171091 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=101/25856, ttl=62 (reply in 59)  |
| 59  | 1.171156 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=101/25856, ttl=62 (request in 58)  |
| 104 | 2.195114 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=102/26112, ttl=62 (reply in 105) |
| 105 | 2.195173 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=102/26112, ttl=62 (request in 104) |
| 157 | 3.219021 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=103/26368, ttl=62 (reply in 158) |
| 158 | 3.219166 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=103/26368, ttl=62 (request in 157) |
| 205 | 4.247039 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=104/26624, ttl=62 (reply in 206) |
| 206 | 4.247183 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=104/26624, ttl=62 (request in 205) |
| 249 | 5.267008 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=105/26880, ttl=62 (reply in 250) |

Frame 7: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF\_{5D6AB595-A2} Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)  
 Destination: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)  
 ... .. = LG bit: Globally unique address (factory default)  
 ... .. = IG bit: Individual address (unicast)  
 Source: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47)  
 Type: IPv4 (0x0800)  
 [Stream index: 6]  
 Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100  
 Generic Routing Encapsulation (ERSPAN)  
 Encapsulated Remote Switch Packet Analysis Type II  
 Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: Cisco\_f8:19:ff (00:22:bd:f8:19:ff)  
 Internet Protocol Version 4, Src: 1.1.1.101, Dst: 105.105.105.105  
 User Datagram Protocol, Src Port: 16346, Dst Port: 4789  
 Virtual eXtensible Local Area Network  
 Flags: 0x0800, VXLAN Network ID (VNI)  
 Group Policy ID: 0  
 VXLAN Network Identifier (VNI): 50001  
 Reserved: 0  
 Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco\_e2:bb:99 (08:0f:e5:e2:bb:99)  
 Internet Protocol Version 4, Src: 192.168.50.11, Dst: 192.168.60.201  
 Internet Control Message Protocol

**Figure 202.** ICMP request from EP-50 (192.168.50.11) to EP-60 (192.168.60.201)

The packet capture of the ICMP reply from EP-60 to EP-50 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.


| No. | Time     | Source         | Destination    | Protocol | Length | Info                                                                |
|-----|----------|----------------|----------------|----------|--------|---------------------------------------------------------------------|
| 7   | 0.147008 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=100/25600, ttl=62 (reply in 8)   |
| 8   | 0.147118 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=100/25600, ttl=62 (request in 7)   |
| 58  | 1.171091 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=101/25856, ttl=62 (reply in 59)  |
| 59  | 1.171156 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=101/25856, ttl=62 (request in 58)  |
| 104 | 2.195114 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=102/26112, ttl=62 (reply in 105) |
| 105 | 2.195173 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=102/26112, ttl=62 (request in 104) |
| 157 | 3.219021 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=103/26368, ttl=62 (reply in 158) |
| 158 | 3.219166 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=103/26368, ttl=62 (request in 157) |
| 205 | 4.247039 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=104/26624, ttl=62 (reply in 206) |
| 206 | 4.247183 | 192.168.60.201 | 192.168.50.11  | ICMP     | 198    | Echo (ping) reply id=0x5fd9, seq=104/26624, ttl=62 (request in 205) |
| 249 | 5.267008 | 192.168.50.11  | 192.168.60.201 | ICMP     | 198    | Echo (ping) request id=0x5fd9, seq=105/26880, ttl=62 (reply in 250) |

Frame 8: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF\_{5D6AB595-A2} Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)  
 Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100  
 Generic Routing Encapsulation (ERSPAN)  
 Encapsulated Remote Switch Packet Analysis Type II  
 Ethernet II, Src: Cisco\_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47)  
 Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102  
 User Datagram Protocol, Src Port: 34921, Dst Port: 4789  
 Virtual eXtensible Local Area Network  
 Flags: 0x0800, VXLAN Network ID (VNI)  
 Group Policy ID: 0  
 VXLAN Network Identifier (VNI): 50001  
 Reserved: 0  
 Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco\_eb:c5:99 (00:5d:73:eb:c5:99)  
 Internet Protocol Version 4, Src: 192.168.60.201, Dst: 192.168.50.11  
 Internet Control Message Protocol

**Figure 203.** ICMP reply from EP-60 (192.168.60.201) to EP-50 (192.168.50.11)

## Policy Enforcement

From a policy enforcement location perspective, this use case is identical to Use Case 3: [Inter-Subnet Communication Non-stretched BDs Single ESG](#).




**Figure 204.** Inter-ESG Inter-Subnet communication policy enforcement

## Use Case 5: North-South Communication Across ACI Sites with Stretched BD

### Use Case Overview


This use case is North-South communication from an endpoint in ACI Site 1 to an external endpoint located behind the L3Out of ACI Site 2, and vice versa, from an endpoint in ACI Site 2 to an external endpoint located behind the L3Out of ACI Site 1.



**Figure 205.** North-South Communication across ACI Sites

In this use case, the new feature starting from ACI release 6.1(4) is used to classify external prefixes to a specific ESG by using external subnet selectors. So that it will be a contract between ESGs from contract configuration perspective, which is like other use cases.

For more detail, please refer to this link <https://www.cisco.com/c/en/us/td/docs/dcn/aci/apic/6x/security-configuration/cisco-apic-security-configuration-guide-61x/endpoint-security-groups-61x.html>



**Figure 206.** North-South Communication across ACI Sites

It is assumed that readers are familiar with ACI fundamental concepts such as L3Out and able to configure ACI L3Out.

### Considerations for Endpoint Security Groups (ESG) with External Subnet Selectors

When implementing Endpoint Security Groups (ESGs) using External Subnet Selectors to classify L3Out traffic, network administrators must adhere to specific configuration guidelines to ensure deterministic traffic classification and maintain data plane connectivity. These considerations are applicable to all deployment scenarios involving L3Out connectivity, encompassing both local North-South traffic flows and cross-site communication.


#### 1. Overlapping and Exact Match External Subnet Selectors

To ensure predictable classification, the configuration of External Subnet Selectors must be unique across all ESGs within the same VRF. Also, the configured external subnet selectors should always exactly match the external prefixes learned via the L3Out connection.

Though Cisco APIC allows the configuration of overlapping prefixes (e.g., 100.64.0.0/24 in ESG ext-1 and 100.64.0.0/16 in ESG ext-2) to classify routes received from the external network on the L3Out, this practice is strongly discouraged. Due to current implementation specifics within the ACI fabric, the use of overlapping prefixes may result in non-deterministic or incorrect classification. The same considerations apply to the specific use case where specific prefixes and a default-route are learned via the L3Out. If an external subnet selector is defined to classify the default route 0.0.0.0/0, the same non-deterministic or incorrect classification issue may arise, since such route represents a prefix that overlaps (i.e. “covers”) all more specific prefixes.

**Note:** Always ensure that External Subnet Selector prefixes do not overlap across ESGs to maintain stable policy enforcement. This is a current requirement in ACI; however, a future ACI release is planned to address this issue. The paper will be updated accordingly once the enhancement is available.

The figure below illustrates an example where communication from ESG esg1 to ESG ex-1 may break when a new ESG ext-1-a with an overlapping External Subnet Selector is introduced.




**Figure 207.** Communication is broken due to a mismatch between ESGs with overlapping External Subnet Selectors

## 2. Alignment Between Selectors and the Routing Table Prefixes

As explained in the point above, for successful classification, an External Subnet Selector must correspond to a specific prefix present in the routing table (RIB) of the L3Out (e.g. the prefix is learned via the L3Out) and an exact prefix matching is required in the External Subnet Selector.

Defining a more specific prefix (e.g., 100.64.1.0/24) as a selector when only the default route (0.0.0.0/0) is learned via the L3Out will result in a failure of data plane communication between the remote site endpoint (EP-2 in Site 2) and external endpoint in Site 1 (ExtEP-1 in Site 1).

The figure below illustrates the connectivity failures that occur when the External Subnet Selector does not align with the received routes. In this scenario, traffic from EP-2 to ExtEP-1 is dropped by the Border Gateway in Site 2. This occurs because the Border Gateway lacks a specific pcTag mapping for the 100.64.1.0/24 external subnet where ExtEP-1 resides (since that prefix was never learned via the L3Out of Site 1 and therefore could not be propagated toward Site 2 via EVPN control plane). Instead, the Border Gateway only learns via EVPN the 0.0.0.0/0 default route, which is associated with the pcTag 12, the reserved tag for unclassified destinations (this is because in this example, an External Subnet Selector for 0.0.0.0/0 was not defined in Site 1). Consequently, the Border Gateway treats ExtEP-1 as an unclassified endpoint, resulting in a policy drop.



**Figure 208.** Cross-site data plane broken due to a mismatch between the External Subnet Selector and the received prefix.

The same logic applies to the supernet use case, where an external device advertises only 100.64.0.0/16 to Site 1, and Site 1 ESG ext-1 configures the External Subnet Selector as 100.64.1.0/24.

## Configure ACI L3Out, External EPG, ESG with External Subnet Selector

In this use case, BGP is used for the routing protocol between the ACI border leaf switches and the external router. Although OSPF and static routing are also valid options, BGP is the preferred option. An external EPG is required to deploy IP interfaces and BGP configuration on the border leaf switches based on the L3Out configuration, but no external EPG subnet configuration is required because the classification of external prefixes will be done by external subnet selectors. The figures below show the configuration examples in ACI Site 1.




Figure 209. ACI Site 1 L3Out and External EPG

Create ESG ext-1 and set normalized pcTag to 8001. The same configuration will be applied to ACI Site 2 later.






Figure 210. ACI Site 1 ESG ext-1

Define External Subnet Selector for ESG ext-1. This step is crucial: make sure to select “External Subnet Selector” as the selector for ESG ext-1, specify the subnet 100.64.1.0/24 as the external subnet in the selector.




**Figure 211.** ACI Site 1 ESG ext-1 with external subnet selector

Create a contract “esg-to-ext-1” and configure a filter as needed; in this example, the contract has a filter to allow all IP traffic. Apply this contract between esg1 and ext-1, ensuring that one side is set as the consumer and the other as the provider.




**Figure 212.** ACI Site 1 – ESG esg1 contract consumer




**Figure 213.** ACI Site 1 ESG ext-1 contract provider

Similar to the configuration shown for ACI Site 1, the following figures illustrate configuration examples for ACI Site 2. Begin by configuring an L3Out and creating an external EPG without any associated subnet. Note that at least one L3Out EPG is required to deploy a routing protocol and configure related interface parameters on the leaf switches. Although the L3Out EPG functions as a security construct similar to other EPGs, it does not represent the routing protocol configuration itself. For detailed information, please refer to the Cisco ACI Fabric L3Out White Paper at <https://www.cisco.com/c/en/us/solutions/collateral/data-center-virtualization/application-centric-infrastructure/guide-c07-743150.html>




**Figure 214.** ACI Site 2 L3Out and External EPG

Create ESG ext-1 and set the normalized pcTag to 8001.




**Figure 215.** ACI Site 2 ESG ext-1

Define External Subnet Selector for ESG ext-1. This step is crucial: make sure to select “External Subnet Selector” as the selector for ESG ext-1, specify the subnet 100.68.1.0/24 as the external subnet in the selector.




**Figure 216.** ACI Site 2 ESG ext-1 with external subnet selector

Create a contract “esg-to-ext-1” and configure a filter as needed; in this example, the contract has a filter to permit all IP traffic. Apply this contract between ESG1 and ext-1, ensuring that one side is set as the consumer and the other as the provider.






**Figure 217.** ACI Site 2 ESG esg1 contract consumer



**Figure 218.** ACI Site 2 ESG ext-1 contract provider

## Control Plane Verification


The figure below shows the parameters used for the control plane verification example in this section.



**Figure 219.** EVPN Type 5 Route exchange across ACI Sites

Note that bd1 (subnet 192.168.1.254/24) is stretched bridge domains, as defined in the section Tenant-Based Line Configuration.

The block diagram below illustrates the EVPN Type-5 route exchange process between ACI sites. While the diagram depicts the route advertisement from ACI Site 1 to ACI Site 2, the same logic applies to advertisement from ACI Site 2 to ACI Site 1.




**Figure 220.** EVPN Type-5 update from ACI Site 1 to Site 2

ACI Site 1 border leaf learns the route from the external device; it is a general behavior, not specific to Multi-Site design. In this example, leaf1 serves a dual role as both a border leaf and a compute leaf.

```


leaf1# show ip route 100.64.1.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
'**' denotes best mcast next-hop
'[x/y]' denotes [preference/metric]
'%<string>' in via output denotes VRF <string>

100.64.1.0/24, ubest/mbest: 1/0
  *via 172.16.161.2%bgw:vrf1, [20/0], -02w06d, bgp-100, external, tag 600
    recursive next hop: 172.16.161.2/32%bgw:vrf1
  
```



**Figure 221.** ACI Site 1 Border Leaf learns external route

The border leaf assigns the local pcTag to the external subnet based on the external subnet selector for ESG. In this example, ESG ext-1 is assigned a local pcTag of 27.



**Figure 222.** ESG ext-1 pcTag

The external subnet route, along with its associated local pcTag of 27, is carried via VPNv4 from the border leaf to the Border Gateway in the same ACI site. Specifically, the border leaf advertises the route to the spine, which in turn reflects the route to the other switches including Border Gateways. The Border Gateways receive the route via VPNv4, identifying the border leaf PTEP (10.1.248.3) as the next hop.

```

bgw-leaf1# show bgp vpnv4 unicast vrf bgw:vrf1 | grep 100.64.1.0
*>i100.64.1.0/24      10.1.248.3      0      100      0 600 i

bgw-leaf1# show ip route 100.64.1.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
'**' denotes best mcast next-hop
'[x/y]' denotes [preference/metric]
'%<string>' in via output denotes VRF <string>

100.64.1.0/24, ubest/mbest: 1/0
  *via 10.1.248.3%overlay-1, [200/0], 01w02d, bgp-100, internal, tag 600
    recursive next hop: 10.1.248.3/32%overlay-1

```

**Figure 223.** ACI Site 1 Border Gateway learns external route

The ACI Site 1 Border Gateways advertise the route 100.64.1.0/24 to the ACI Site 2 Border Gateways via BGP EVPN. This advertised route can be verified in the BGP EVPN output, as shown in the screenshot below. As highlighted in the output, the value 27 represents the local pcTag carried from the ACI Site 1 Border Leaf. The IP address 5.5.5.15 is the loopback interface IP Address of ACI Site 2 Border Gateway.

```

bgw-leaf1# show bgp l2vpn evpn 100.64.1.0
Route Distinguisher: 100:18939904 (L3VNI 2162688)
BGP routing table entry for [5]:[0]:[0]:[24]:[100.64.1.0]:[0.0.0.0]/224, version 35409 dest ptr 0x7fd05825455c
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c772ef8): local 0x4000008c 0x40000000 ref 0 adv path ref 1, path is valid, is best path
  AS-Path: 600 , path sourced external to AS
    0.0.0.0 (metric 0) from 0.0.0.0 (10.1.248.7)
    Origin IGP, MED 0, localpref 100, weight 0 tag 0, propagate 0, floating svi 0, tunnel resolved 0
    Received label 2162688
    Extcommunity: RT:100:2162688 PCTAG:01:0:0:27 VNID:2162688
    Originator: 10.1.248.3 Cluster list: 199.6.8.8

  Path-id 1 advertised to peers:
    5.5.5.105

```

**Figure 224.** ACI Site 1 Border Gateway advertises EVPN Type-5

It is important to note that when advertising the route to another site, the ACI Site 1 Border Gateway uses the normalized pcTag value of 8001 (configured at ESG ext-1). The normalized pcTag value of 8001 can also be observed on the receiving side, which is the ACI Site 2 Border Gateway. Now on ACI Site 2 Border Gateways, EVPN Type-5 route is received, which verifies the route is advertised properly.

```

qt-bgw005# show bgp l2vpn evpn 100.64.1.0
Route Distinguisher: 100:18939904
BGP routing table entry for [5]:[0]:[0]:[24]:[100.64.1.0]:[0.0.0.0]/224, version 3920 dest ptr 0x7f9224661e6a
Paths: (2 available, best #2)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Path type (0x7f9218c844ec): external 0x40000028 0x40000000 ref 0 adv path ref 0, path is valid, not best reason: newer EBGP path, remote nh not installed
  AS-Path: 100 600 , path sourced external to AS
    100.100.100.102 (metric 0) from 1.1.1.101 (10.1.248.7)
    Origin IGP, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:8001 Router MAC:6408.64ca.393a

  Advertised path-id 1
  Path type (0x7f9218c84f48): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 100 600 , path sourced external to AS
    100.100.100.102 (metric 0) from 1.1.1.102 (10.1.248.2)
    Origin IGP, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 50001
    Extcommunity: RT:400:50001 S00:400:2432696301 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:8001 Router MAC:005d.73eb.c599

  Path-id 1 not advertised to any peer

```

**Figure 225.** ACI Site 2 Border Gateway receives EVPN Type-5 route

As shown above, the pcTag value (8001) is carried within the EVPN Type-5 update. This value represents the normalized pcTag for the ESG ext-1 configured on ACI Site 1. The IP address 100.100.100.102 is External Data Plane IP, also known as Multi-Site External VIP of Border Gateway in Pod-1 in ACI Site 1. The

value 50001 in “Received label 50001” indicates that the border gateway receives the EVPN route in VNI 50001, which is the normalized VNI of VRF vrf1 used in both ACI sites.




Figure 226. ACI Site 1 ESG ext-1




Figure 227. ACI Site 1 Border Gateway Set

ACI Site 2 Border Gateway then imports the route to 100.64.1.0/24 from EVPN to BGP VPNv4.

```
qt-bgw805# show bgp vpnv4 unicast vrf bgw:vrf1
BGP routing table information for VRF overlay-1, address family VPNv4 Unicast
BGP table version is 237, local router ID is 10.118.112.67
Status: s-suppressed, x-deleted, S-stale, d-dampened, h-history, *-valid, >-best
Path type: i-internal, e-external, c-confed, l-local, a-aggregate, r-redist, I-injected
Origin codes: i - IGP, e - EGP, ? - incomplete, | - multipath, & - backup
```

| Network                                         | Next Hop        | Metric | LocPrf | Weight           | Path |
|-------------------------------------------------|-----------------|--------|--------|------------------|------|
| Route Distinguisher: 805:2097152 (VRF bgw:vrf1) |                 |        |        |                  |      |
| *>e1.1.1.101/32                                 | 100.100.100.102 | 0      |        | 0 100 ?          |      |
| *>e1.1.1.201/32                                 | 200.200.200.202 | 0      |        | 0 100 ?          |      |
| *>i2.2.2.18/32                                  | 10.118.112.66   | 0      | 100    | 0 ?              |      |
| *>e4.0.13.250/32                                | 200.200.200.202 |        |        | 0 100 700 800 i  |      |
| *>e4.0.14.250/32                                | 100.100.100.102 | 0      |        | 0 100 ?          |      |
| *>e8.8.8.0/24                                   | 100.100.100.102 |        |        | 0 100 600 1000 i |      |
| *>e100.64.1.0/24                                | 100.100.100.102 | 0      |        | 0 100 600 i      |      |
| *>e100.64.2.0/24                                | 100.100.100.102 | 0      |        | 0 100 600 i      |      |
| *>e100.64.3.0/24                                | 100.100.100.102 | 0      |        | 0 100 600 i      |      |

**Figure 228.** ACI Site 2 Border Gateway imports the EVPN route to VPNv4

Note that 100 is ACI Site 1 BGP ASN, 600 is BGP ASN of the external router connecting to ACI Site 1 border leaf. ACI Site 2 Border Gateway installs the route to its routing table.

```
qt-bgw805# show ip route 100.64.1.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

100.64.1.0/24, ubest/mbest: 1/0
  *via 100.100.100.102%overlay-1, [20/0], 5d05h, bgp-400, external, tag 100, pc-tag: 10931
    recursive next hop: 100.100.100.102/32%overlay-1
```

**Figure 229.** ACI Site 2 Border Gateway routing table

100.100.100.102 is ACI Site 1 Pod 1 External Data Plane IP also known as Multi-Site External VIP. The value 10931 is the local pcTag of ESG ext-1 configured on ACI Site 2.

This route is reflected to ACI Site 2 spine through BGP VPNv4.

```
qt-spine811# show bgp vpnv4 unicast vrf bgw:vrf1
BGP routing table information for VRF overlay-1, address family VPNv4 Unicast
BGP table version is 217, local router ID is 10.118.112.65
Status: s-suppressed, x-deleted, S-stale, d-dampened, h-history, *-valid, >-best
Path type: i-internal, e-external, c-confed, l-local, a-aggregate, r-redist, I-injected
Origin codes: i - IGP, e - EGP, ? - incomplete, | - multipath, & - backup

Network          Next Hop          Metric      LocPrf      Weight Path
Route Distinguisher: 811:2097152 (VRF bgw:vrf1)
*>i2.2.2.18/32    10.118.112.66      0           100         0 ?
*>i4.0.13.250/32  10.118.112.67      0           100         0 100 700 800 i
*>i4.0.14.250/32  10.118.112.67      0           100         0 100 ?
*>i8.8.8.0/24     10.118.112.67      0           100         0 100 600 1000 i
*>i100.64.1.0/24  10.118.112.67      0           100         0 100 600 i
*>i100.64.2.0/24  10.118.112.67      0           100         0 100 600 i
*>i100.64.3.0/24  10.118.112.67      0           100         0 100 600 i
```

**Figure 230.** ACI Site 2 Spine VPNv4 route

The spine reflects the route to ACI Site 2 compute leaf switches. The next hop 10.118.112.67 is ACI Site 2 Border Gateway PTEP.

```
qt-leaf802# show bgp vpnv4 unicast vrf bgw:vrf1
BGP routing table information for VRF overlay-1, address family VPNv4 Unicast
BGP table version is 1193, local router ID is 10.118.112.64
Status: s-suppressed, x-deleted, S-stale, d-dampened, h-history, *-valid, >-best
Path type: i-internal, e-external, c-confed, l-local, a-aggregate, r-redist, I-injected
Origin codes: i - IGP, e - EGP, ? - incomplete, | - multipath, & - backup

Network          Next Hop          Metric      LocPrf      Weight Path
Route Distinguisher: 802:2097152 (VRF bgw:vrf1)
*>i0.0.0.0/0      10.118.112.66      0           100         0 900 800 i
*>i2.2.2.18/32    10.118.112.66      0           100         0 ?
*>i4.0.13.250/32  10.118.112.67      0           100         0 100 700 800 i
*>i4.0.14.250/32  10.118.112.67      0           100         0 100 700 800 i
*>i8.8.8.0/24     10.118.112.66      0           100         0 900 800 i
*>i100.64.1.0/24  10.118.112.67      0           100         0 100 600 i
*>i100.64.2.0/24  10.118.112.67      0           100         0 100 600 i
*>i100.64.3.0/24  10.118.112.67      0           100         0 100 600 i
```

**Figure 231.** ACI Site 2 Compute leaf VPNv4 route

ACI Site 2 compute leaf then installs the route to its routing table.

```
qt-leaf802# show ip route 100.64.1.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

100.64.1.0/24, ubest/mbest: 1/0
  *via 10.118.112.67%overlay-1, [200/0], 06:53:18, bgp-400, internal, tag 100, pc-tag: 1
    recursive next hop: 10.118.112.67/32%overlay-1
```

**Figure 232.** ACI Site 2 Compute leaf routing table

The Site 2 Border Gateway has route to 100.64.1.0/24 with proper pcTag defined in Site 2 ESG ext-1. However, once this route is reflected to the compute leaf, the leaf resets the pcTag to 1. Consequently, the leaf implicitly allows traffic to the remote external subnet without contract enforcement, as pcTag 1 is the default allowed destination.


It verifies that the external route (100.64.1.0/24) from ACI Site 1 has been successfully advertised all the way to the compute leaf switches in ACI Site 2. The external Router 1 (Site1-C8K-1) in ACI Site 1 learns the bd1 subnet (192.168.1.254/24) advertised by the ACI Site 1 border leaf.

```
Site1-C8K-1#show ip route 192.168.1.0
Routing entry for 192.168.1.0/24
  Known via "bgp 600", distance 20, metric 0
  Tag 100, type external
  Last update from 172.16.161.1 1d21h ago
Routing Descriptor Blocks:
  * 172.16.161.1, from 172.16.161.1, 1d21h ago
    opaque_ptr 0x7F0A9158B1A0
    Route metric is 0, traffic share count is 1
    AS Hops 1
    Route tag 100
    MPLS label: none
Site1-C8K-1#
Site1-C8K-1#show ip route | in 192.168.1.0
B    192.168.1.0/24 [20/0] via 172.16.161.1, 1d21h
Site1-C8K-1#
```

**Figure 233.** Site 1 external router learns ACI bd1 subnet

## Data Plane Verification


The figure below illustrates a routed communication scenario between directly connected endpoint and external endpoint. Communication occurs between endpoint EP-2, a directly connected endpoint in ACI Site 2, and endpoint ExtEP-1, an external endpoint reachable through the L3Out in ACI Site 1. The Normalized VNI 50001 is defined by administrator by configuring the normalized VRF VNI when stretching VRF across two sites.



**Figure 234.** Data plane North-South Communication Across ACI Sites with Stretched BD




From endpoint EP-2 (192.168.1.201) pings endpoint ExtEP-1 (100.64.1.10). The packet capture of the ICMP request from EP-2 to ExtEP-1 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 235.** ICMP request from EP-2 (192.168.1.201) to ExtEP-1 (100.64.1.10)


The packet capture of the ICMP reply from ExtEP-1 to EP-2 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 236.** ICMP reply from ExtEP-1 (100.64.1.10) to EP-2 (192.168.1.201)

## Policy Enforcement


The figure below illustrates the policy enforcement locations for traffic an endpoint in ACI Site 2 to an external endpoint in ACI Site 1.



**Figure 237.** ACI Site 2 internal endpoint to ACI Site 1 external endpoint

Traffic from esg1 ACI Site 2 to ACI Site 1 external endpoint: the Border Gateways apply the policy in each site. At ACI Site 2, the Border Gateway maintains the pcTag information for the external subnet advertised from Site 1. However, when sending the route information to the spine switches, it uses pcTag 1 instead of the original pcTag. As a result, the compute leaf receives the route with pcTag 1. Consequently, the compute leaf does not apply the policy for the traffic destined to the external subnet. Instead, the Border Gateway enforces the policy in ACI Site 2. Upon traffic reaching Site 1, Site 1 Border Gateway can derive the source class of the source endpoint using the BGP EVPN control plane and the destination class based on the external subnet because of the external subnet selector. As a result, the Border Gateway enforces the policy and forwards the traffic to the border leaf.

The figure below illustrates the policy enforcement locations for the return traffic.



**Figure 238.** ACI Site 1 external endpoint to ACI Site 2 internal endpoint


Traffic from an external endpoint through ACI Site 1 to an endpoint in ACI Site 1: At ACI Site 1, the Border Gateway enforces the security policy for traffic from an external endpoint to an endpoint in ACI Site 2 because the border leaf in Site 1 cannot derive destination class based on the destination IP address. It is because the Border Gateways in ACI Site 1 sets the Do-Not-Learn bit on traffic received from Site 2, which prevents the border leaf from learning the remote endpoint. As a result, policy enforcement at Site 1 is performed by the Border Gateway. When the traffic reaches ACI Site 2, the Border Gateway does not apply the policy. Although the Border Gateway in ACI Site 2 has the destination endpoint information advertised by local spine switches, it does not program the information to the hardware table for scalability reason. As a result, the compute leaf attached to the destination endpoint enforces the policy.



## Use Case 6: North-South Communication Across ACI Sites with Non-stretched BD

### Use Case Overview

This use case describes communication between an endpoint and an external endpoint in different ACI sites, like the Use Case 5: North-South Communication Across ACI Sites with Stretched BD, but the BD is deployed locally, not stretched. The figure below illustrates the logical design; an endpoint in a locally defined BD in ACI Site 1 talks to an external endpoint behind the L3Out of ACI Site 2, and vice versa.



**Figure 239.** North-South Communication across ACI sites with non-stretched (local) BD

Because BD bd50 is local to ACI Site 1, advertising its subnets to the external router connected to ACI Site 2 requires creating a route-map in ACI Site 2. This route-map facilitates advertising the bd50 subnet (192.168.50.0/24 in this example) to the external network (L3Out-2). Most of the configuration elements including ESG ext-1, L3Out-2, bd50, and esg50 are assumed to be configured as per previous use cases.

The main configuration steps are as follows:

On ACI Site 1:


- Advertise the bd50 subnet (192.168.50.0/24) to the external router connected to ACI Site 2.
- Add 100.68.1.0/24 as an external subnet selector to ESG ext-1.
- Create and apply a contract between esg50 and ext-1 to permit communication from the bd50 subnet to 100.68.1.0/24.

On ACI Site 2:

- Create a default-export route map to permit 100.68.1.0/24
- Create and apply a contract between esg50 and ext-1 to allow communication from the bd50 subnet to subnet 100.68.1.0/24.


### Configuration Details

The figures below show the configuration examples in ACI Site 1. Add 100.68.1.0/24 as to External Subnet Selector ESG ext-1.




**Figure 240.** Add 100.68.1.0/24 to external subnet selectors of ESG ext-1

Create a contract “esg50-to-ext-1”, and configure a filter as needed; in this example, the contract has a filter to allow all IP traffic.




**Figure 241.** ACI Site 1 contract esg50-to-ext-1

Apply this contract between esg1 and ext-1, ensuring that one side is set as the consumer and the other as the provider.




**Figure 242.** ACI Site 1 esg50 contract consumer



**Figure 243.** ACI Site 1 ESG ext-1 contract provider

The figures below show the configuration examples in ACI Site 2. On ACI Site 2, in the L3Out object (c8k-1-bgp in this example), right click on Route-map for Import and export route control, choose “Create default-export route-map”.



**Figure 244.** ACI Site 2 create default-export route-map

From the drop-down list, choose default-export then click “+” to add the context entry.

Create Route map for import and export route control

Name:

Type: ☒ Match Prefix AND Routing Policy ☐ Match Routing Policy Only

Description:

Route-Map Continue: ☐ This action will be applied on all the entries which are part of BGP Route-map.

Contexts

| Order | Name | Action | Description |
|-------|------|--------|-------------|
|       |      |        |             |

**Figure 245.** Choose default-export contract and add context entry

Give a descriptive context name, fill in description text box if needed, and then click “+”.

Create Route Control Context

Order: 0

Name: site1-bd50

Action: Deny Permit

Description: 192.168.50.0/24

Associated Matched Rules:

| Rule Name |
|-----------|
|-----------|

Set Rule: select a value

Cancel OK

**Figure 246.** Create context

From the Rule Name drop-down list, click Create match Rule for a Route-map, this step is used to create a match rule to match prefix 192.168.50.0/24.

Create Route Control Context

Order: 0

Name: site1-bd50

Action: Deny Permit

Description: 192.168.50.0/24

Associated Matched Rules:

| Rule Name                         |
|-----------------------------------|
| select an option                  |
| Create Match Rule for a Route Map |

**Figure 247.** Create a match rule

Give match rule a descriptive Name for example site1-bd50-subnet, then click “+” in the Match Prefix working area.

Create Match Rule

Name: site1-bd50-subnet

Description: 192.168.50.0/24

Match Regex Community Terms:

| Name | Regular Expression | Community Type | Description |
|------|--------------------|----------------|-------------|
|------|--------------------|----------------|-------------|

Match Community Terms:

| Name | Description |
|------|-------------|
|------|-------------|

Match AS Path Regex Terms:

| Name | Regular Expression | Description |
|------|--------------------|-------------|
|------|--------------------|-------------|

Match Prefix:

| IP | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|----|-------------|-----------|--------------------|-----------------|
|----|-------------|-----------|--------------------|-----------------|

Cancel Submit

**Figure 248.** Create match prefix

In the IP field, type 192.168.50.0/24 then click OK.

Create Match Route Destination Rule

IP: 192.168.50.0/24

Description: optional

Aggregate: ☐

Cancel

OK

**Figure 249.** Type 192.168.50.0/24 for IP field

Then, click Submit to create the match rule.

Create Match Rule

Name: site1-bd50-subnet

Description: 192.168.50.0/24

Match Regex Community Terms:

| Name | Regular Expression | Community Type | Description |
|------|--------------------|----------------|-------------|
|------|--------------------|----------------|-------------|

Match Community Terms:

| Name | Description |
|------|-------------|
|------|-------------|

Match AS Path Regex Terms:

| Name | Regular Expression | Description |
|------|--------------------|-------------|
|------|--------------------|-------------|

Match Prefix:

| IP              | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|-----------------|-------------|-----------|--------------------|-----------------|
| 192.168.50.0/24 |             | False     | 0                  | 0               |

Cancel

Submit

**Figure 250.** Submit to finish creating a match rule

Click Update to associate the match rule to the route control context.

Create Route Control Context

Order: 0

Name: site1-bd50

Action: Deny Permit

Description: 192.168.50.0/24

Associated Matched Rules:

| Rule Name         |
|-------------------|
| site1-bd50-subnet |

Set Rule: select a value

Update

Cancel

Cancel

OK

**Figure 251.** Update the rule

Then click OK to add the route control context entry to default-export route-map.

Create Route Control Context

Order: 0

Name: site1-bd50

Action: Deny Permit

Description: 192.168.50.0/24

Associated Matched Rules:

Rule Name

site1-bd50-subnet

Set Rule: select a value

Cancel

OK

Figure 252. Click OK

Click Submit to complete default-export route-map creation.

Create Route map for import and export route control

Name: default-export

Type: Match Prefix AND Routing Policy Match Routing Policy Only

Description: optional

Route-Map Continue: ☐ This action will be applied on all the entries which are part of BGP Route-map.

Contexts

| Order | Name       | Action | Description     |
|-------|------------|--------|-----------------|
| 0     | site1-bd50 | Permit | 192.168.50.0/24 |

Cancel

Submit

Figure 253. Submit to finish default-export route-map creation

Confirm default-export route-map is created.

APIC (site2)

System | Tenants | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: | common | queenstown | infra | mgmt | bgw

bgw

- Quick Start
- Application Profiles
- Network
  - VXLAN Stretch
  - Bridge Domains
  - VRFs
  - L2Outs
  - L3Outs
    - cbk-1-bgp
      - Logical Node Profiles
      - External EPGs
      - Route map for import and export route control
        - default-export

Route Control Profile - default-export

Policy

Properties

Name: default-export

Type: Match Prefix AND Routing Policy Match Routing Policy Only

Description: optional

Route-Map Continue: ☐ This action will be applied on all the entries which are part of BGP Route-map.

Contexts


| Order | Name       | Action | Description     |
|-------|------------|--------|-----------------|
| 0     | site1-bd50 | Permit | 192.168.50.0/24 |

Figure 254. Default-export route-map completion

Create contract “esg50-to-ext-1” and configure a filter as needed; in this example, the contract has a filter to allow all IP traffic.


© 2026 Cisco and/or its affiliates. All rights reserved.

Page 119 of 204




**Figure 255.** ACI Site 2 contract esg50-to-ext-1

Apply this contract between esg1 and ext-1, ensuring that one side is set as the consumer and the other as the provider.




**Figure 256.** ACI Site 2 ESG esg50 contract consumer




**Figure 257.** ACI Site 2 ESG ext-1 contract provider

## Control Plane Verification

The following diagram illustrates the topology used in this verification.



**Figure 258.** North-South Communication Across Sites with non-stretched (local) BD



**Figure 259.** ESG esg50 and ESG ext-1 pcTag

Verify that the external router Site2-C8K-1 in ACI Site 2 has successfully received and installed the route to subnet 192.168.50.0/24, which originates from ACI Site 1, in its routing table.

```
Site2-C8K-1#show ip bgp 192.168.50.0
BGP routing table entry for 192.168.50.0/24, version 33
Paths: (1 available, best #1, table default)
  Advertised to update-groups:
    290
  Refresh Epoch 1
  400 100
    172.16.164.1 from 172.16.164.1 (2.2.2.18)
      Origin incomplete, localpref 100, valid, external, best
      rx pathid: 0, tx pathid: 0x0
      Updated on Jun 4 2026 15:57:56 UTC
Site2-C8K-1#
Site2-C8K-1#show ip route | in 192.168.50.0
B    192.168.50.0/24 [200/0] via 172.16.164.1, 16:35:32
Site2-C8K-1#
```

**Figure 260.** ACI Site 2 External router learns ACI Site 1 non-stretched (local) BD Subnet

For reference, and in line with the previous use case, the compute leaf switches in ACI Site 1 learns the external subnet 100.68.1.0/24 located in ACI Site 2 via the ACI Site 1 Border Gateways. 10.1.248.2 and 10.1.248.7 are the PTEP addresses of Border Gateway 1 and Border Gateway 2 in ACI Site 2, respectively.

```
leaf1# show ip route 100.68.1.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>


100.68.1.0/24, ubest/mbest: 2/0
  *via 10.1.248.2%overlay-1, [200/0], 17:51:49, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.2/32%overlay-1
  *via 10.1.248.7%overlay-1, [200/0], 17:51:49, bgp-100, internal, tag 400, pc-tag: 1
    recursive next hop: 10.1.248.7/32%overlay-1
leaf1#
```

**Figure 261.** ACI Site 1 Compute leaf learns ACI Site 2 external subnet




## Data Plane Verification

The figure below illustrates a routed communication scenario between directly connected endpoint and external endpoint. Communication occurs between endpoint EP-1, a directly connected endpoint in ACI Site 1, and endpoint ExtEP-2, an external endpoint reachable through the L3Out in ACI Site 2. The Normalized VNI 50001 is defined by administrator by configuring the normalized VRF VNI when stretching VRF across two sites



**Figure 262.** Data plane North-South Communication Across ACI Sites with Non-stretched BD

Ping from an endpoint (192.168.50.11) in ACI Site 1 to an external endpoint (100.68.1.20) in ACI Site 2. The packet capture of the ICMP request from EP-1 to ExtEP-2 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 263.** ICMP request from EP-1 (192.168.50.11) to ExtEP-2 (100.68.1.20)

The packet capture of the ICMP reply from ExtEP-2 to EP-1 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                              |
|-----|----------|---------------|---------------|----------|--------|-------------------------------------------------------------------|
| 12  | 0.286628 | 192.168.50.11 | 100.68.1.20   | ICMP     | 198    | Echo (ping) request id=0x6093, seq=16/4096, ttl=62 (reply in 13)  |
| 13  | 0.286487 | 100.68.1.20   | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x6093, seq=16/4096, ttl=61 (request in 12)  |
| 62  | 1.310028 | 192.168.50.11 | 100.68.1.20   | ICMP     | 198    | Echo (ping) request id=0x6093, seq=17/4352, ttl=62 (reply in 63)  |
| 63  | 1.310514 | 100.68.1.20   | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x6093, seq=17/4352, ttl=61 (request in 62)  |
| 111 | 2.334821 | 192.168.50.11 | 100.68.1.20   | ICMP     | 198    | Echo (ping) request id=0x6093, seq=18/4608, ttl=62 (reply in 112) |
| 112 | 2.334663 | 100.68.1.20   | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x6093, seq=18/4608, ttl=61 (request in 111) |
| 161 | 3.358012 | 192.168.50.11 | 100.68.1.20   | ICMP     | 198    | Echo (ping) request id=0x6093, seq=19/4864, ttl=62 (reply in 162) |
| 162 | 3.358554 | 100.68.1.20   | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x6093, seq=19/4864, ttl=61 (request in 161) |
| 211 | 4.382045 | 192.168.50.11 | 100.68.1.20   | ICMP     | 198    | Echo (ping) request id=0x6093, seq=20/5120, ttl=62 (reply in 212) |
| 212 | 4.382567 | 100.68.1.20   | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x6093, seq=20/5120, ttl=61 (request in 211) |


```

Frame 13: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF_{5D6AB595-A}
Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware_bf:d4:e1 (00:50:56:bf:d4:e1)
Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.00.100
Generic Routing Encapsulation (ERSPAN)
Encapsulated Remote Switch Packet Analysis Type II
Ethernet II, Src: Cisco_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47)
Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102
User Datagram Protocol, Src Port: 13450, Dst Port: 4789
Virtual extensible Local Area Network
Flags: 0x0800, VXLAN Network ID (VNI): 50001
Group Policy ID: 0
VXLAN Network Identifier (VNI): 50001
Reserved: 0
Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco_eb:c5:99 (00:5d:73:eb:c5:99)
Internet Protocol Version 4, Src: 100.68.1.20, Dst: 192.168.50.11
Internet Control Message Protocol
  
```

**Figure 264.** ICMP reply from ExtEP-2 (100.68.1.20) to EP-1 (192.168.50.11)

## Policy Enforcement


The figure below illustrates the policy enforcement locations for traffic an endpoint in ACI Site 1 to an external endpoint in ACI Site 2.



**Figure 265.** ACI Site 1 internal endpoint to ACI Site 2 external endpoint

Traffic from an endpoint in ACI Site 1 to an external endpoint through ACI Site 2: The Border Gateway applies policy in each site. Site 1 Border Gateway learns remote external subnet from Site 2 with pcTag advertised by Site 2 Border Gateway, which uses pcTag of 1 when it is advertised within ACI Site 1. It results that ACI Site 1 compute leaf does not apply the policy for the traffic destined to the remote external subnet and ACI Site 1 Border Gateway applies the policy instead. Upon traffic reaching ACI Site 2, ACI Site 2 Border Gateway applies policy because both source and destination class IDs can be derived.

The figure below illustrates the policy enforcement locations for the return traffic.



**Figure 266.** ACI Site 2 external endpoint to ACI Site 1 internal endpoint

Traffic an external endpoint through ACI Site 2 to an endpoint in ACI Site 1: the Border Gateway applies the policy for traffic from an external endpoint to an endpoint in ACI Site 1 because Site 2 border leaf in ACI Site 2 cannot derive destination class based on the destination IP address. It is because the Border Gateways in ACI Site 2 sets the Do-Not-Learn bit on traffic received from Site 1, which prevents the border leaf from learning the remote endpoint. As a result, policy enforcement at Site 2 is performed by the Border Gateway. When the traffic reaches ACI Site 1, the compute leaf applies the policy because the Border Gateways do not learn local endpoints in the same sit, which means Border Gateways will implicitly permit the traffic.

### Use Case 7: Transit Routing Across ACI Sites


#### Use Case Overview

In this use case, the two ACI Sites play a transit function to forward traffic between L3Outs across ACI Sites. The figure below illustrates the logical diagram. An external endpoint via L3Out-1 in ACI Site 1 communicate with an external endpoint via L3Out-2 in ACI Site 2.



**Figure 267.** Transit routing across ACI Sites

The figure below illustrates the topology and IP addresses used in this section.



**Figure 268.** Transit routing across ACI Sites networking view


To enable communication between the two external endpoints (100.64.1.10 and 100.68.1.20), both external routes must be exchanged between ACI Sites; 100.64.1.0/24 from ACI Site 1 must be advertised to Router 2, and the route 100.68.1.0/24 from ACI Site 2 must be advertised to Router 1.

## Configure Transit Routing

Transit routing configuration has been documented in detail at

<https://www.cisco.com/c/en/us/td/docs/dcn/aci/apic/6x/l3-configuration/cisco-apic-layer-3-networking-configuration-guide-62x/transit-routing-layer3-config-62x.html>

Configure a route-map for advertising external route from ACI Site 2 to ACI Site 1. On ACI Site 1 L3Out, right click on L3Out object and choose “Create Route map for import and export route control”.



**Figure 269.** ACI Site 1 Create route map for import and export route control

Name the route map for example “transit-100-68”, keep Type as default “Match Prefix AND Routing Policy”, click “+” to add a Context.

Create Route map for import and export route control

Name:

Type: Match Prefix AND Routing Policy Match Routing Policy Only

Description:

Contexts

| Order | Name | Action | Description |
|-------|------|--------|-------------|
|       |      |        |             |

Figure 270. ACI Site 1 Route-map

Name the context, for example 100-68, then click “+” to add a match rule which is to match the prefix 100.68.1.0/24 that is the external prefix from ACI Site 2.

Create Route Control Context

Order:

Name:

Action: Deny Permit

Description:

Associated Matched Rules:

| Rule Name |
|-----------|
|           |

Figure 271. ACI Site 1 Route-map route control context

Click the drop-down list and scroll all the way to the bottom then choose “Create Match Rule for a Route Map”

Create Route Control Context

Order:

Name:

Action: Deny Permit

Description:

Associated Matched Rules:

| Rule Name                                     |
|-----------------------------------------------|
| <input type="text" value="Select an option"/> |
| lo14-c8kv-3                                   |
| bgw                                           |
| permit-any                                    |
| bgw                                           |
| routerloopback                                |
| bgw                                           |
| soo                                           |
| bgw                                           |
| test                                          |
| bgw                                           |
| Create Match Rule for a Route Map             |

Submit

Figure 272. ACI Site 1 Create a match rule

Name the match rule for example “100-68-1”, then click “+” in the Match prefix pane.

Create Match Rule

Name: 100-68-1

Description: optional

Match Regex Community Terms:

| Name | Regular Expression | Community Type | Description |
|------|--------------------|----------------|-------------|
|      |                    |                |             |

Match Community Terms:

| Name | Description |
|------|-------------|
|      |             |

Match AS Path Regex Terms:

| Name | Regular Expression | Description |
|------|--------------------|-------------|
|      |                    |             |

Match Prefix:

| IP | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|----|-------------|-----------|--------------------|-----------------|
|    |             |           |                    |                 |

Cancel

Submit

**Figure 273.** ACI Site 1 Add Match Prefix for a match rule

In the IP field, type 100.68.1.0/24, then click OK to complete.

Create Match Route Destination Rule

IP: 100.68.1.0/24

Description: optional

Aggregate: ☐

Cancel

OK

**Figure 274.** ACI Site 1 Route-map match rule add prefix

Click Submit to create a match rule.

Create Match Rule

Name: 100-68-1

Description: optional

Match Regex Community Terms:

| Name | Regular Expression | Community Type | Description |
|------|--------------------|----------------|-------------|
|      |                    |                |             |

Match Community Terms:

| Name | Description |
|------|-------------|
|      |             |

Match AS Path Regex Terms:

| Name | Regular Expression | Description |
|------|--------------------|-------------|
|      |                    |             |

Match Prefix:

| IP            | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|---------------|-------------|-----------|--------------------|-----------------|
| 100.68.1.0/24 |             | False     | 0                  | 0               |

Cancel

Submit

**Figure 275.** ACI Site 1 Create Match rule completion

Click Update to associate the match rule.

Create Route Control Context

Order: 0

Name: 100-68

Action:

Deny

Permit

Description: optional

Associated Matched Rules:

| Rule Name |
|-----------|
| 100-68-1  |

Update

Cancel

Set Rule: select a value

Cancel

OK

**Figure 276.** ACI Site 1 Create update to utilize matched rule

Click OK to complete the route-map route control context creation.

Create Route Control Context

Order: 0

Name: 100-68

Action: **Deny** **Permit**

Description: optional

Associated Matched Rules:

| Rule Name |
|-----------|
| 100-68-1  |

Set Rule: select a value

**Cancel** **OK**

**Figure 277.** ACI Site 1 Click OK to complete route-map route control context creation

Click Submit to complete the route-map creation.

Create Route map for import and export route control

Name: transit-100-68-1

Type: **Match Prefix AND Routing Policy** **Match Routing Policy Only**

Description: optional

Contexts

| Order | Name   | Action | Description |
|-------|--------|--------|-------------|
| 0     | 100-68 | Permit |             |

**Cancel** **Submit**

**Figure 278.** ACI Site 1 Submit to finish route-map creation

The newly created route-map appears under “Route map for import and export route control” sub-menu.

APIC (site1)

System | **Tenants** | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | **bgw** | infra | vc3-demo | tmerkerl

**bgw**

- Quick Start
- bgw
  - Application Profiles
    - ap1
    - ap-share
  - Networking
    - VXLAN Stretch
    - Bridge Domains
    - VRFs
    - L2Outs
    - L3Outs
      - bgp-cbkv**
        - Logical Node Profiles
        - External EPGs
        - Route map for import and export route control**
          - transit-100-68-1**

**Route Control Profile - transit-100-68-1**

Properties

Name: transit-100-68-1

Type: **Match Prefix AND Routing Policy** **Match Routing Policy Only**

Description: optional


Contexts

| Order | Name   | Action |
|-------|--------|--------|
| 0     | 100-68 | Permit |

**Figure 279.** ACI Site 1 Route-map completion


To apply the route-map, navigate to external EPG -> Policy -> General then scroll down to Route Control Profile section and click “+”.





**Figure 280.** ACI Site 1 Apply route-map

In the Name drop-down list, choose “transit-100-68-1” which is the route-map created above, and choose Route Export Policy for Direction.



**Figure 281.** ACI Site 1 Apply route-map export direction

Verify that the external router in ACI Site 1 learns 100.68.1.0/24 from the ACI Site1 border leaf switch.

```
Site1-C8K-1#show ip route bgp
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2, m - OMP
n - NAT, N1 - NAT inside, No - NAT outside, Nd - NAT DTA
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
H - NHRP, G - NHRP registered, g - NHRP registration summary
o - ODR, P - periodic downloaded static route, l - LISP
a - application route
+ - replicated route, % - next hop override, p - overrides from PFR
& - replicated local route overrides by connected

Gateway of last resort is not set

  8.0.0.0/24 is subnetted, 1 subnets
    B       8.0.0.0 [20/0] via 11.0.0.1, 7w0d
  100.0.0.0/8 is variably subnetted, 13 subnets, 2 masks
    B       100.68.1.0/24 [20/0] via 172.16.161.1, 3d10h
    B       192.168.1.0/24 [20/0] via 172.16.161.1, 3d11h
Site1-C8K-1#
```

**Figure 282.** ACI Site 1 External router learns remote route

The configuration steps on ACI Site 2 are identical to those on ACI Site 1, with the exception that the match rule is o match subnet 100.64.1.0/24 that is the external subnet from ACI Site 1.

## Match Rule - 100-64-1

Match AS Path Regexp Terms:

| Name                                                              | Regular Expression | Description |
|-------------------------------------------------------------------|--------------------|-------------|
| No items have been found.<br>Select Actions to create a new item. |                    |             |

Match Prefix:

| IP            | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|---------------|-------------|-----------|--------------------|-----------------|
| 100.64.1.0/24 |             | False     | 0                  | 0               |

**Figure 283.** ACI Site 2 Match rule

APIC (site2)

System | Tenants | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | bgw | queenstown | infra | mgmt

bgw

Quick Start

bgw

- Application Profiles
- Networking
  - VXLAN Stretch
  - Bridge Domains
  - VRFs
  - L2Outs
  - L3Outs
    - c8k-1-bgp
      - Logical Node Profiles
      - External EPGs
        - ext-1
          - Route map for import and export route control
            - default-export
            - transit-100-64-1

External EPG - ext-1

Summary | Policy | Operational

General | Contracts | Inherited Contracts

Properties

L3Out Contract Masters:

| Name                                                              | Description |
|-------------------------------------------------------------------|-------------|
| No items have been found.<br>Select Actions to create a new item. |             |

Route Control Profile:

| Name             | Direction           |
|------------------|---------------------|
| transit-100-64-1 | Route Export Policy |

**Figure 284.** ACI Site 2 Apply route-map export direction

Verify that the external router in ACI Site 2 learns 100.64.1.0/24 from the ACI Site 2 border leaf switch.


```
Site2-C8K-1#show ip route bgp
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
       D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
       N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
       E1 - OSPF external type 1, E2 - OSPF external type 2, m - OMP
       n - NAT, Ni - NAT inside, No - NAT outside, Nd - NAT DIA
       i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
       ia - IS-IS inter area, * - candidate default, U - per-user static route
       H - NHRP, G - NHRP registered, g - NHRP registration summary
       o - ODR, P - periodic downloaded static route, l - LISP
       a - application route
       + - replicated route, % - next hop override, p - overrides from PfR
       & - replicated local route overrides by connected

Gateway of last resort is 172.16.0.1 to network 0.0.0.0

100.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
B    100.64.1.0/24 [20/0] via 172.16.164.1, 3d11h
B    192.168.1.0/24 [20/0] via 172.16.164.1, 5w2d
Site2-C8K-1#
```


**Figure 285.** ACI Site 2 External router learns remote route

It is important to note that the default-export route map configured in [Use Case 6: North-South Communication Across ACI sites with Non-stretched BD](#) can also be leveraged for transit routing purposes. To utilize this capability, a new match context for subnet 100.64.1.0/24 must be added to the existing default-export route map configuration.



**Figure 286.** Add new context to default-export route-map


Follow similar step to add a new context.



**Figure 287.** ACI Site 2 Add new context to default-export

## Control Plane Verification

The following diagram illustrates the topology used in this verification.



**Figure 288.** Transit Routing control plane verification



**Figure 289.** ESG ext-1 with normalized pcTag 8001

As this use case is analogous to [Use Case 5 North-South Communication Across ACI Sites with Stretched BD](#), this section briefly reviews the routing table entries on the external routers on both sites. The expected outcome is that Router 1 (Site1-C8K-1) learns 100.68.1.0/24 and Router 2 (Site2-C8K-1) learns 100.64.1.0/24.

```
Site1-C8K-1#show ip route 100.68.1.0
Routing entry for 100.68.1.0/24
  Known via "bgp 600", distance 20, metric 0
  Tag 100, type external
  Last update from 172.16.161.1 15:26:32 ago
  Routing Descriptor Blocks:
    * 172.16.161.1, from 172.16.161.1, 15:26:32 ago
      opaque_ptr 0x7F0A9158B2E0
      Route metric is 0, traffic share count is 1
      AS Hops 3
      Route tag 100
      MPLS label: none
Site1-C8K-1#
```


**Figure 290.** ACI Site 1 Router 1 learns route from Router 2

```
Site2-C8K-1#show ip route 100.64.1.0
Routing entry for 100.64.1.0/24
  Known via "bgp 900", distance 20, metric 0
  Tag 400, type external
  Last update from 172.16.164.1 15:05:56 ago
  Routing Descriptor Blocks:
    * 172.16.164.1, from 172.16.164.1, 15:05:56 ago
      opaque_ptr 0x7B7C90E2EB38
      Route metric is 0, traffic share count is 1
      AS Hops 3
      Route tag 400
      MPLS label: none
Site2-C8K-1#
```

**Figure 291.** ACI Site 2 Router 2 learns route from Router 1

## Data Plane Verification


The figure below illustrates a transit routing communication scenario. Communication occurs between ExtEP-1, an external endpoint reachable through the L3Out in ACI Site 1, and ExtEP-2, an external endpoint reachable through the L3Out in ACI Site 2.



**Figure 292.** Transit Routing


Ping from an external endpoint ExtEP-1 (100.64.1.10) in ACI Site 1 to an external endpoint ExtEP-2 (100.68.1.20) in ACI Site 2. Communication works even without any contract between ESG ext-1 in ACI Site 1 and ESG ext-1 in ACI Site 2, the reason is that the same normalized pcTag 8001 is used for ESG ext-1 Site 1 and ESG ext-1 Site 2, which means that the external prefixes received from the local L3Out and from the other site are part of the same ESG.

The packet capture of the ICMP request from ExtEP-1 to ExtEP-2 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 293.** ICMP request from ExtEP-1 (100.64.1.10) to ExtEP-2 (100.68.1.20)


The packet capture of the ICMP reply from ExtEP-2 to ExtEP-1 confirms that the Layer 3 (VRF) Normalized VNI is used in the VXLAN header for inter-site data plane forwarding.



**Figure 294.** ICMP reply from ExtEP-2 (100.68.1.20) to ExtEP-1 (100.64.1.10)

## Policy Enforcement

The figure below illustrates the policy enforcement locations for traffic from an external endpoint in ACI Site 1 to an external endpoint in ACI Site 2.



**Figure 295.** Policy enforcement Transit Routing across sites

Policy is enforced at the Border Gateways at both ACI sites in both directions, as the Border Gateways retain the route and the associated pcTag through BGP EVPN Type-5 route exchange. Conversely, the compute leaf receives the route but resets the pcTag to 1, resulting in traffic being forwarded without contract enforcement.

## Use Case 8: Design Considerations with Overlapping Prefixes in Multi-L3Out Deployments


### Use Case Overview

In this use case, each ACI site maintains its own dedicated L3Out connection to the external WAN.

The figure below illustrates the design. The external routers (Router 1 In ACI Site 1 and Router 2 in ACI Site 2) establish BGP sessions with the Core-WAN router (BGP ASN 800), which serves as the gateway to the external WAN. The Core-WAN router advertises 108.0.0.0/24 to both ACI sites. As a result, both ACI sites

learn the same prefixes through their local L3Outs as well as through the other site, which requires a traffic-engineering for path-selection and failover to ensure optimal forwarding behavior, efficient WAN-link utilization, and seamless recovery if the local L3Out becomes unavailable.

It is important to note that, with the introduction of Core-WAN router in this specific design, the two ACI sites no longer serve as transit points between Router 1 and Router 2. For example, 100.64.1.0/24 behind Router 1 is now advertised through Core-WAN router to Router 2 via BGP. In the reverse direction, 100.68.1.0/24 behind Router 2 is advertised through Core-WAN router to Router 1 via BGP.



**Figure 296.** Overlapping Prefix multiple L3Outs

### Create common prefix ESG and apply policy

The ESG ext-core is configured on both ACI sites using the same External Subnet Selector and the normalized pcTag to maintain policy consistency. In this use case, under normal conditions when both L3Outs are operational, both ACI Sites learn the same external prefix (108.0.0.0/24) from the Core-WAN. It is required to configure the “External Subnet Selector” on both ACI Sites to match the subnet 108.0.0.0/24 for the ESG ext-core to classify traffic correctly. This configuration allows traffic originating from the local L3Out to be recognized and permitted once the contract between esg1 and ext-core is applied.

To permit traffic between EP-1 in esg1 to EP-3 in esg-ext-core, create a contract named esg-ext-core, between esg1 and ext-core. The following figures are ESG and contract configuration in both ACI sites.




Figure 297. ACI Site 1 ESG ext-core




Figure 298. ACI Site 1 ESG ext-core External Subnet Selector






Figure 299. ACI Site 1 ESG ext-core contract provider







**Figure 300.** ACI Site 1 ESG esg1 contract consumer




**Figure 301.** ACI Site 2 ESG ext-core



**Figure 302.** ACI Site 2 ESG ext-core External Subnet Selector



**Figure 303.** ACI Site 2 ESG ext-core contract provider



**Figure 304.** ACI Site 2 esg1 contract consumer

## Default Traffic Flow

By default, in an ACI fabric, a local L3Out is always preferred for outbound communication from an ACI local endpoint to an external network. As a result, outbound traffic is deterministic whereas inbound traffic from an external client (108.0.0.10 in this example) to an ACI local endpoint might not be deterministic depending on how to advertise the ACI internal subnet to the external network.



**Figure 305.** Outbound flow from ACI Site connected endpoint to external

The following is a BGP configuration example on Core-WAN router:

```
Core-WAN#show run | sec bgp
router bgp 800
  bgp log-neighbor-changes
  neighbor 11.0.0.2 remote-as 600
  neighbor 11.0.0.2 fall-over bfd
  neighbor 12.0.0.2 remote-as 900
  neighbor 12.0.0.2 fall-over bfd
!
address-family ipv4
  network 0.0.0.0
  network 8.8.8.0 mask 255.255.255.0
  network 108.0.0.0 mask 255.255.255.0
  neighbor 11.0.0.2 activate
  neighbor 12.0.0.2 activate
exit-address-family
```

The BGP table on Core-WAN router shows two entries for the same destination prefix 192.168.1.0/24 (BD1 subnet), with next-hops 11.0.0.2 and 12.0.0.2 corresponding to Router 1 (Site 1) and Router 2 (Site 2). Following the default BGP best path selection process, only one route is selected as the best path. In this case, the route via 12.0.0.2 is selected as it happens to be the oldest route. Although BGP multipath can be enabled to install multiple equal-cost paths for load balancing, it does not address suboptimal inbound traffic to ACI Sites.

```
Core-WAN#show ip bgp
BGP table version is 98, local router ID is 8.8.8.8
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
               r RIB-failure, S Stale, m multipath, b backup-path, f RT-Filter,
               x best-external, a additional-path, c RIB-compressed,
               t secondary path, L long-lived-stale,
Origin codes: i - IGP, e - EGP, ? - incomplete
RPKI validation codes: V valid, I invalid, N Not found

  Network        Next Hop        Metric LocPrf Weight Path
*> 0.0.0.0        172.16.0.1        0          32768 i
*> 8.8.8.0/24     0.0.0.0           0          32768 i
*> 100.64.1.0/24  11.0.0.2          0           600 i
*> 100.64.2.0/24  11.0.0.2          0           600 i
*> 100.64.3.0/24  11.0.0.2          0           600 i
*> 100.64.4.0/24  11.0.0.2          0           600 i
*> 100.64.5.0/24  11.0.0.2          0           600 i
*> 100.64.6.0/24  11.0.0.2          0           600 i
*> 100.68.1.0/24  12.0.0.2          0           900 i
*> 108.0.0.0/24   0.0.0.0           0          32768 i
*> 172.16.31.0/24 11.0.0.2          0           600 100 ?
* 192.168.1.0     11.0.0.2          0           600 100 ?
*>                12.0.0.2          0           900 400 ?
Core-WAN#
```

Figure 306. Core-WAN BGP Table

The following is the routing table for 192.168.1.0/24 (BD-1 subnet) on Core-WAN, which uses 12.0.0.2 (Router 2) as the next hop.


```

Core-WAN#show ip route 192.168.1.0
Routing entry for 192.168.1.0/24
  Known via "bgp 800", distance 20, metric 0
  Tag 900, type external
  Last update from 12.0.0.2 00:06:52 ago
  Routing Descriptor Blocks:
  * 12.0.0.2, from 12.0.0.2, 00:06:52 ago
    opaque_ptr 0x7F3F8500CA8
    Route metric is 0, traffic share count is 1
    AS Hops 2
    Route tag 900
    MPLS label: none
Core-WAN#
Core-WAN#
Core-WAN#show ip route | in 192.168.1.0
B 192.168.1.0/24 [20/0] via 12.0.0.2, 00:07:03
Core-WAN#

```

**Figure 307. Core-WAN Routing Table**

Based on the routing table on Core-WAN, inbound traffic from the external endpoint behind Core-WAN is always forwarded through Router 2 connected to ACI Site 2, regardless of the actual location of the destination endpoint in 192.168.1.0/24. Moreover, the inbound traffic path is not deterministic. For example, if Router 2 is reloaded or the L3Out-2 BGP session is reset, the Core-WAN router will shift its best path next-hop to Router 1, redirecting all inbound traffic from the external WAN to 192.168.1.0/24 accordingly. This non-deterministic inbound traffic behavior introduces challenges in deployments where a stateful device resides between the Core-WAN router and the ACI sites, as such stateful devices may drop asymmetric traffic. Furthermore, with this default configuration, one of the L3Out connections remains consistently idle for inbound traffic, resulting in suboptimal utilization of the available WAN links.



**Figure 308. Non-optimal incoming flow**


### Inbound Traffic Flow Optimization

To optimize inbound traffic from the external WAN to ACI local endpoints, host-based routing can be enabled on both ACI sites. By configuring the “Advertised Host Route” option on bd1 in both ACI Site 1 and ACI Site 2, each site advertises /32 host routes (/128 for IPv6) for every active endpoint in bd1 to Core-WAN router via their respective local L3Outs.


As a result, Core-WAN router learns /32 host routes from both ACI sites simultaneously. Since each /32 host route is advertised exclusively by the site where the endpoint resides, Core-WAN router can accurately determine the optimal next-hop for each destination endpoint. This ensures that inbound traffic from the external WAN is always forwarded to the correct ACI site, regardless of endpoint location, eliminating the non-deterministic inbound traffic behavior described previously.

When enabling host-based routing, it is important to carefully consider the routing table capacity of all external devices along the path between the ACI sites and Core-WAN router. Intermediate routers, such as Router 1 and Router 2, will also learn and carry the /32 host routes in their routing tables. As the number of active endpoints grows, the volume of advertised host routes increases proportionally, which may exceed the routing table capacity of intermediate devices if not properly planned.

The following figures show the bd1 configuration in both ACI sites.



**Figure 309.** ACI Site 1 bd1 Advertise Host Routes



**Figure 310.** ACI Site 2 bd1 Advertise Host Routes

With host-based routing enabled on bd1, Core-WAN router learns /32 host routes for all active endpoints such as 192.168.1.11 in ACI Site 1 via Router 1 and 192.168.1.201 in ACI Site 2 via Router 2.

The following figures is the routing table for 192.168.1.0/24 and the hosts routes on Core-WAN.

```
Core-WAN#show ip route | in 192.168.1
192.168.1.0/24 is variably subnetted, 5 subnets, 2 masks
B    192.168.1.0/24 [20/0] via 12.0.0.2, 01:44:57
B    192.168.1.7/32 [20/0] via 11.0.0.2, 00:12:32
B    192.168.1.11/32 [20/0] via 11.0.0.2, 00:13:02
B    192.168.1.29/32 [20/0] via 11.0.0.2, 00:13:02
B    192.168.1.201/32 [20/0] via 12.0.0.2, 00:16:12
Core-WAN#
```

**Figure 311.** Core-WAN Router learns host routes

The figures below show traceroute outputs on an external endpoint 108.0.0.10, which are to 192.168.1.11 and 192.168.1.201.

```

cisco@core-wan-endpoint:~$ ifconfig ens192
ens192: flags=4163<UP,BROADCAST,RUNNING,MULTICAST> mtu 1500
inet 108.0.0.10 netmask 255.255.255.0 broadcast 108.0.0.255
inet6 fe80::250:56ff:febf:9618 prefixlen 64 scopeid 0x20<link>
ether 00:50:56:bf:96:18 txqueuelen 1000 (Ethernet)
RX packets 638402621 bytes 38978668129 (38.9 GB)
RX errors 0 dropped 9362820 overruns 0 frame 0
TX packets 19175142 bytes 879826624 (879.8 MB)
TX errors 0 dropped 0 overruns 0 carrier 0 collisions 0

cisco@core-wan-endpoint:~$

```

**Figure 312.** Core WAN external endpoint

```

cisco@core-wan-endpoint:~$ traceroute 192.168.1.11
traceroute to 192.168.1.11 (192.168.1.11), 30 hops max, 60 byte packets
 1 _gateway (108.0.0.1) 0.859 ms 0.839 ms 0.808 ms
 2 11.0.0.2 (11.0.0.2) 1.319 ms 1.305 ms 1.284 ms
 3 172.16.161.1 (172.16.161.1) 2.216 ms 2.630 ms 3.062 ms
 4 192.168.1.11 (192.168.1.11) 1.599 ms 1.918 ms 1.898 ms
cisco@core-wan-endpoint:~$

```

**Figure 313.** Traceroute from core wan external endpoint to ACI Site 1 endpoint

```


cisco@core-wan-endpoint:~$ traceroute 192.168.1.201
traceroute to 192.168.1.201 (192.168.1.201), 30 hops max, 60 byte packets
 1 _gateway (108.0.0.1) 0.465 ms 0.434 ms 0.409 ms
 2 12.0.0.2 (12.0.0.2) 1.183 ms 1.169 ms 1.152 ms
 3 172.16.164.1 (172.16.164.1) 2.003 ms 2.438 ms 2.606 ms
 4 192.168.1.254 (192.168.1.254) 2.391 ms 2.814 ms 3.402 ms
 5 192.168.1.201 (192.168.1.201) 1.744 ms 1.747 ms 1.732 ms
cisco@core-wan-endpoint:~$

```

**Figure 314.** Traceroute from core wan external endpoint to ACI Site 2 endpoint

### Incoming default route (0/0) consideration

This subsection discusses key considerations when an external router advertises the default route (0.0.0.0/0) to both ACI sites.




**Figure 315.** External router advertises default route to both ACI sites


In a typical scenario where both L3Outs are operational and without route manipulation, local L3Out is always preferred for outgoing communication. The bi-directional communication between EP-1, EP-2, and EP-3 remains uninterrupted, provided that the subnet 108.0.0.0/24 or 0.0.0.0/0 is configured as an external Subnet Selector in the ESG ext-core on both ACI sites. Although incoming traffic from EP-3 may follow a suboptimal path such as using Site 1 as a transit to reach EP-2—the data plane between EP-1, EP-2, and EP-3 functions correctly. However, if Core-WAN advertises only 0.0.0.0/0 and a specific subnet,

108.0.0.0/24, is defined as the External Subnet Selector on both ACI Sites, then if L3Out-2 goes down, communication from EP-3 to EP-2 will be disrupted. Similarly, if L3Out-1 goes down, communication from EP-3 to EP-1 will be disrupted. This behavior was previously discussed in the sub-section [“Considerations for Endpoint Security Groups \(ESG\) with External Subnet Selectors.”](#)

To support the failover scenario where either of the two L3Outs could go down, and the WAN device advertises only the default route (0.0.0.0/0), it is required to configure 0.0.0.0/0 as the External Subnet Selector in the ESG ext-core on both sites.



**Figure 316.** ACI Site 2 traffic failover when L3Out-2 down



**Figure 317.** ACI Site 1 traffic failover when L3Out-1 down

The same consideration applies to non-default routes. For example, if the WAN device advertises only the 108.0.0.0/16 prefix, the External Subnet Selector on both sites must be configured exactly as 108.0.0.0/16.

To achieve fine granularity on the ESG ext-core by defining a non-default subnet instead of 0.0.0.0/0 for example, using 108.0.0.0/24 as the External Subnet Selector to restrict traffic only to and from 108.0.0.0/24, the WAN side must advertise the specific route, including 108.0.0.0/24, to the ACI Sites. This ensures that only the designated subnet is classified and allowed through the ESG ext-core, providing more precise traffic control.


Cross-site data plane connectivity may be disrupted if an existing Endpoint Security Group (ESG) uses an External Subnet Selector configured as a supernet or default route (0.0.0.0/0). For example, if an existing ESG has 108.0.0.0/16 as its External Subnet Selector, defining a new ESG with an overlapping selector such as 108.0.0.0/24 could cause data plane failures. In summary, ensure that ESGs use non-overlapping External Subnet Selectors that correspond to the prefixes received from the local L3Out.

## Use Case 9: Inter-VRF Communication (Shared Services) with Stretched BDs

### Use Case Overview

This section covers an inter-VRF communication use case, also called shared service, where the source and the destination reside in different VRFs.

The figure below illustrates an example used in the section. Although this example shows stretched VRFs, Bridge Domains, and ESGs, only the VRF must be stretched. The BD and ESG may remain local to each site. A contract is configured between ESG esg1 in VRF1 and ESG share1 in VRF Share.



**Figure 318.** Shared Service use case

The assumption is that the VRF vrf1, BD bd1, and ESG esg1 were already created in the previous sub-section [User Tenant Baseline Configuration](#) and [Use Case 1: Intra-Subnet Communication](#).

On both sites, the required configuration steps are following:

1. Create the VRF named “share” and stretch it by deploying it on the Border Gateway, ensuring the same normalized VNI is set (60001 in this example).
2. Create the BD bd-share1 in VRF share with subnet 172.16.31.254/24 and stretch it by deploying it on Border Gateway, ensuring the same normalized VNI is set (31000 in this example).
3. Create the EPG share1 mapped to BD bd-share1, associate it to domain.



4. Create the ESG share1 ensuring the same normalized pcTag is set (2001 in this example), use EPG share1 as selector.
5. Configure route leak between VRF vrf1 and VRF share, make sure the leaked subnet cover /32 host routes:
  - leak Internal Prefix 192.168.1.0/24 with less than or equal (prefix) of 32 from VRF vrf1 to VRF share
  - leak Internal Prefix 172.16.31.0/24 with less than or equal (prefix) of 32 from VRF share to VRF vrf1
6. Apply a tenant-scope contract between ESG esg1 and ESG share1.

Please note that the steps above are not necessarily in a fixed order. Steps 2, 3, and 4 can be performed in any sequence.

## Create Provider VRF and Bridge Domain

The figures below are VRF and BD configurations in ACI Site 1.




Figure 319. ACI Site 1 VRF share






Figure 320. ACI Site 1 BD bd-share1

The figures below are normalized VNIs configuration in ACI Site 1.

- VRF share: normalized VNI 60001
- BD bd-share1: normalized VNI 31000




**Figure 321.** ACI Site 1 stretched VRF share




**Figure 322.** ACI Site 1 stretched BD bd-share1

The figures below are VRF and BD configurations in ACI Site 2.



**Figure 323.** ACI Site 2 VRF share



**Figure 324.** ACI Site 2 BD bd-share1

The figures below are normalized VNIs configuration in ACI Site 2.

- VRF share: normalized VNI 60001
- BD bd-share1: normalized VNI 31000

| VRF   | Border Gateway Set | Normalized VNI | Local VNI |
|-------|--------------------|----------------|-----------|
| vrf1  | qt-aci             | 50001          | 2097152   |
| share | qt-aci             | 60001          | 2490368   |
| vrf3  | qt-aci             | 50003          | 2260992   |

Figure 325. ACI Site 2 stretched VRF share

| Bridge Domain | Border Gateway Set | Normalized VNI | Local VNI |
|---------------|--------------------|----------------|-----------|
| bd1           | qt-aci             | 30001          | 15105996  |
| bd2           | qt-aci             | 30002          | 15204288  |
| bd92          | qt-aci             | 30082          | 14811120  |
| bd-share1     | qt-aci             | 31000          | 15204288  |

Figure 326. ACI Site 2 stretched BD bd-share1

### Create Provider ESG

The figures below are ESG share1 configurations in ACI Site 1.

ESG - share1

Summary Policy Operational

Topology General

Properties

Name: share1

Description: optional

Annotations: Click to add a new annotation

pcTag/class: 10934

Set Normalized pcTag: ☒ Normalized pcTag: 2001

Configuration Status: applied

Configuration Issues: VRF: share

Resolved VRF: uni/tn-bgwctx-share

ESG Admin State: Admin Up Admin Shut

Deployment Immediacy: Immediate On Demand

Figure 327. ACI Site 1 ESG share1

Selectors

Tag Selectors:

Tag Key Value Operator

Other Selectors:

Page 0 of 0

Selector Type Condition

EPG bgw/ac-shares/share1

Figure 328. ACI Site 1 ESG share1 EPG Selector

The figures below are ESG share1 configurations in ACI Site 2.




Figure 329. ACI Site 2 ESG share1




Figure 330. ACI Site 2 ESG share1 EPG Selector

### Create and Apply Tenant Scope Contract

The figures below are contract configurations in ACI Site 1. Note that the contract scope is set to “Tenant” instead of “VRF” because it is for inter-VRF communication for ESGs in the same tenant.




Figure 331. ACI Site 1 tenant scope contract

APIC (site1) Contracts table:

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg-ext-core  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg-to-ext-1  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg1-esg2     | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | share-svc     | Contract      | Consumed            | Unspecified | Formed |

Figure 332. ACI Site 1 ESG esg1 contract consumer

APIC (site1) Contracts table:

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | share-svc     | Contract      | Provided            | Unspecified | Formed |

Figure 333. ACI Site 1 ESG share1 contract provider

The figures below are contract configurations in ACI Site 2.

APIC (site2) Contract - share-svc configuration:

Properties:

- Name: share-svc
- Alias:
- Global Alias:
- Scope: Tenant
- QoS Class: Unspecified
- Target DSCP: Unspecified
- Target DSCP Marking works only if the QoS Class is set
- Description: optional
- Annotations: Click to add a new annotation
- Subjects:
 


| Name | Alias | Filters |
|------|-------|---------|
| ip   |       | bgw/ip  |

Figure 334. ACI Site 2 tenant scope contract

APIC (site2) Contracts table:

| Tenant Name             | Tenant Alias | Contract Name | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|---------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |               |               |                     |             |        |
| bgw                     |              | esg-ext-core  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg-to-ext-1  | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | esg1-esg2     | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | share-svc     | Contract      | Consumed            | Unspecified | Formed |

Figure 335. ACI Site 2 ESG esg1 contract consumer




**Figure 336.** ACI Site 2 ESG share1 contract provider

## Configure Route Leak

Although the tenant-scope contract between ESGs was created in the previous step to define the security policies allowing communication, this contract alone does not establish network connectivity between the endpoints. Because the endpoints reside in different VRFs, route leaking must be configured to enable routing reachability between these VRFs. Without this route leaking configuration, the endpoints cannot communicate despite the contract being in place.

The next step is to configure route leak between VRF vrf1 and VRF share. The configuration steps are identical on both ACI Sites.

In ACI Site 1, navigate to VRFs -> vrf1 -> Inter-VRF Leaked Routes for ESG -> Internal Prefixes. From the toolbox dropdown list, choose “Create Leaked Internal Prefix”.



**Figure 337.** ACI Site 1 Create Leaked Internal Prefix from VRF vrf1 to VRF share

Configure 192.168.1.0/24 in IP field. Although bd1 subnet is 192.168.1.254/24, to include the /32 host routes (so that host routes for endpoints in vrf1 are leaked to the other VRF), “Less Than or Equal (Prefix)” needs to be set to 32. (In the case of IPv6 host routes, it needs to be set to 128.)

**Figure 338.** Create Leaked Internal Prefix 192.168.1.0/24

Click “+” to add the destination VRF (which is VRF share in this example).

Create Tenant and VRF Destination

Tenant and VRF: bgw share

Description: optional

Allow L3Out Advertisement (Overridden): Inherit False True

Cancel OK

**Figure 339.** ACI Site 1 choose share as the destination VRF

Click Submit to finish Inter-VRF route leak configuration for the route from VRF vrf1 to VRF share.

APIC (site1)

System Tenants Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS Add Tenant Tenant Search bgw | common | bgw | infra | tenant1 | tenant2

bgw

Quick Start

Application Profiles

Networking

VLAN Stretch

Bridge Domains

VRFs

share

vrf1

Multicast

Multicast IPv6

Inter-VRF Leaked Routes for ESG

EPG/BD Subnets External Prefixes Internal Prefixes Faults History

| IP             | Description | Allow L3Out Advertisement | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target VRF Present? | Deployed |
|----------------|-------------|---------------------------|--------------------------------|-----------------------------|---------------|------------------------|----------|
| 192.168.1.0/24 |             | False                     | Unspecified                    | 32                          | bgw/share     | Yes                    | Yes      |

**Figure 340.** ACI Site 1 route leak from VRF vrf1 to VRF share completion

For the other direction, which is from VRF share to VRF vrf1, navigate to VRFs -> share -> Inter-VRF Leaked Routes for ESG -> Internal Prefixes. From the toolbox dropdown list, choose “Create Leaked Internal Prefix”.

APIC (site1)

System Tenants Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS Add Tenant Tenant Search bgw | common | bgw | infra | tenant1 | tenant2

bgw

Quick Start

Application Profiles

Networking

VLAN Stretch

Bridge Domains

VRFs

share

Multicast

Multicast IPv6

Inter-VRF Leaked Routes for ESG

EPG/BD Subnets External Prefixes Internal Prefixes Faults History

| IP | Description | Allow L3Out Advertisement | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target Present? | Toolbox                       |
|----|-------------|---------------------------|--------------------------------|-----------------------------|---------------|--------------------|-------------------------------|
|    |             |                           |                                |                             |               |                    | Create Leaked Internal Prefix |

**Figure 341.** ACI Site 1 Create Leaked Internal Prefix from VRF share to VRF vrf1

Configure 172.16.31.0/24 in IP field. Although bd-share1 subnet is 172.16.31.254/24, to include the /32 host routes (so that host routes for endpoints in VRF share are leaked to the other VRF), “Less Than or Equal (Prefix)” needs to be set to 32. (In the case of IPv6 host routes, it needs to be set to 128).

Create Leaked Internal Prefix

IP: 172.16.31.0/24  
address/optional mask

Description: optional

Greater Than or Equal (Prefix): unspecified

Less Than or Equal (Prefix): 32

Allow L3Out Advertisement: ☐ False ☒ True

Tenant and VRF Destinations:

| Tenant Name | VRF Name | Description | Allow L3Out Advertisement (Overridden) |
|-------------|----------|-------------|----------------------------------------|
|             |          |             |                                        |

Cancel Submit

**Figure 342.** Create Leaked Internal Prefix 172.16.31.0/24

Click “+” to add the destination VRF (which is VRF vrf1 in this example).

Create Tenant and VRF Destination

Tenant and VRF: bgw vrf1  
Tenant VRF

Description: optional

Allow L3Out Advertisement (Overridden): ☒ Inherit ☐ False ☐ True

Cancel OK

**Figure 343.** ACI Site 1 choose vrf1 as destination VRF

APIC (site1)

System Tenants Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS Add Tenant Tenant Search: name or device common bgw vrf-demo innerker innerkercluster1

bgw

Quick Start

bgw

- Application Profiles
- Network
- VLAN Stretch
- Bridge Domains
- VRFs
- share
- Multicast
- Multicast IPv6
- Inter-VRF Leaked Routes for ESG
- EPG/BD Subnets
- External Prefixes
- Internal Prefixes
- 172.16.31.0/24

Inter-VRF Leaked Routes for ESG

| IP             | Description | Allow L3Out Advertisement | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target VRF Present? | Deployed |
|----------------|-------------|---------------------------|--------------------------------|-----------------------------|---------------|------------------------|----------|
| 172.16.31.0/24 |             | False                     | Unspecified                    | 32                          | bgw/vrf1      | Yes                    | Yes      |

**Figure 344.** ACI Site 1 Route Leak from VRF share to VRF vrf1 completion

The procedure to configure route leaking is identical in ACI Site 2. The figures below are examples.

APIC (site2)

System Tenants Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS Add Tenant Tenant Search: name or device common bgw mgmt infra

bgw

Quick Start

bgw

- Application Profiles
- Network
- VLAN Stretch
- Bridge Domains
- VRFs
- share
- Multicast
- Multicast IPv6
- Inter-VRF Leaked Routes for ESG
- EPG/BD Subnets
- External Prefixes
- Internal Prefixes
- 192.168.1.0/24

Inter-VRF Leaked Routes for ESG

| IP             | Description | Allow L3Out Advertisement | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target VRF Present? | Deployed |
|----------------|-------------|---------------------------|--------------------------------|-----------------------------|---------------|------------------------|----------|
| 192.168.1.0/24 |             | False                     | Unspecified                    | 32                          | bgw/share     | yes                    | Yes      |

**Figure 345.** ACI Site 2 Route Leak from VRF vrf1 to VRF share completion




| IP             | Description | Allow L3Out Advertisement | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target VRF Present? | Deployed |
|----------------|-------------|---------------------------|--------------------------------|-----------------------------|---------------|------------------------|----------|
| 172.16.31.0/24 |             | False                     | Unspecified                    | 32                          | bgw/vrf1      | yes                    | Yes      |

**Figure 346.** ACI Site 2 Route Leak from VRF share to VRF vrf1 completion

## Control Plane Verification

The following figure illustrates IP subnets used in this verification section.



**Figure 347.** Route Leak diagram

Each VRF learns the route from the other VRF.

For example, the following figures are routing table information on a compute leaf in ACI Site 1.

```
leaf1# show ip route 172.16.31.0/24 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.31.0/24, ubest/mbest: 1/0, attached, direct, pervasive
 *via 10.1.144.66%overlay-1, [1/0], 4d11h, static, tag 4294967294, rwVnid: vxlan-2228225
 recursive next hop: 10.1.144.66/32%overlay-1
```

**Figure 348.** ACI Site 1 Compute Leaf VRF vrf1 Route Table

VRF share learns 192.168.1.0/24 from VRF vrf1. The VNI is 2162688, that is the VNI of VRF vrf1.

```
leaf1# show ip route 192.168.1.0/24 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.1.0/24, ubest/mbest: 1/0, attached, direct, pervasive
 *via 10.1.144.66%overlay-1, [1/0], 4d11h, static, tag 4294967294, rwVnid: vxlan-2162688
 recursive next hop: 10.1.144.66/32%overlay-1
```

**Figure 349.** ACI Site 1 Compute Leaf VRF share Route Table

The following figures are routing table information on a Border Gateway in ACI Site 1. VRF vrf1 learns 172.16.31.0/24 from VRF share. The VNI is 2228225, that is the VNI of VRF share.

```

bgw-leaf1# show ip route 172.16.31.0/24 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.31.0/24, ubest/mbest: 1/0, attached, direct, pervasive
 *via 10.1.144.66%overlay-1, [1/0], 4d11h, static, tag 4294967294, rwVnid: vxlan-2228225
 recursive next hop: 10.1.144.66/32%overlay-1

```

**Figure 350.** ACI Site 1 Border Gateway VRF vrf1 Route Table

VRF share learns 192.168.1.0/24 from VRF vrf1. The VNI is 2162688, that is the VNI of VRF vrf1.

```

bgw-leaf1# show ip route 192.168.1.0/24 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.1.0/24, ubest/mbest: 1/0, attached, direct, pervasive
 *via 10.1.144.66%overlay-1, [1/0], 4d11h, static, tag 4294967294, rwVnid: vxlan-2162688
 recursive next hop: 10.1.144.66/32%overlay-1

```

**Figure 351.** ACI Site 1 Border Gateway VRF share Route Table

From endpoint learning perspective, Border Gateways in ACI Site 1 learn remote endpoints (endpoints in ACI Site 2) which reside in different VRF. For example, 172.16.31.201 that is in VRF share in ACI Site 2 is learned in VRF vrf1 too.

```

bgw-leaf1# show endpoint ip 172.16.31.201
Legend:
S - static          s - arp          L - local          O - peer-attached
V - vpc-attached   a - local-aged   p - peer-aged      M - span
B - bounce         H - vtep        R - peer-attached-rl D - bounce-to-proxy
E - shared-service m - svc-mgr      C - control-ep     Rv - remote-vxlan-ep

+-----+-----+-----+-----+-----+
| VLAN/ | Encap | MAC Address | MAC Info/ | Interface |
| Domain | VLAN  | IP Address  | IP Info   |            |
+-----+-----+-----+-----+-----+
| bgw:share |      | 172.16.31.201 | Rv        | tunnel21  |
| bgw:vrf1  |      | 172.16.31.201 | RvE       | tunnel21  |
+-----+-----+-----+-----+-----+

```

**Figure 352.** ACI Site 1 Border Gateway learns remote endpoint across VRF

Similarly, the endpoint 192.168.1.201, which is in VRF vrf1 at ACI Site 2, is also learned in the VRF share at ACI Site 1.

```

bgw-leaf1# show endpoint ip 192.168.1.201
Legend:
S - static          s - arp          L - local          O - peer-attached
V - vpc-attached   a - local-aged   p - peer-aged      M - span
B - bounce         H - vtep        R - peer-attached-rl D - bounce-to-proxy
E - shared-service m - svc-mgr      C - control-ep     Rv - remote-vxlan-ep

+-----+-----+-----+-----+-----+
| VLAN/ | Encap | MAC Address | MAC Info/ | Interface |
| Domain | VLAN  | IP Address  | IP Info   |            |
+-----+-----+-----+-----+-----+
| bgw:share |      | 192.168.1.201 | RvE       | tunnel21  |
| bgw:vrf1  |      | 192.168.1.201 | Rv        | tunnel21  |
+-----+-----+-----+-----+-----+

```

**Figure 353.** ACI Site 1 Border Gateway learns remote endpoint across VRF

The following figures are routing table information on a compute leaf in ACI Site 2. The results are similar information to the one in ACI Site 1. VRF vrf1 learns 172.16.31.0/24 from VRF share.

```

qt-leaf802# show ip route 172.16.31.0/24 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.31.0/24, ubest/mbest: 1/0, attached, direct, pervasive
 *via 10.118.176.64%overlay-1, [1/0], 06w03d, static, tag 4294967294, rwVnid: vxlan-2490368
 recursive next hop: 10.118.176.64/32%overlay-1

```

**Figure 354.** ACI Site 2 Compute Leaf VRF vrf1 Route Table

VRF share learns 192.168.1.0/24 from VRF vrf1.

```
qt-leaf802# show ip route 192.168.1.0/24 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.1.0/24, ubest/mbest: 1/0, attached, direct, pervasive
  *via 10.118.176.64%overlay-1, [1/0], 05w03d, static, tag 4294967294, rwVnid: vxlan-2097152
    recursive next hop: 10.118.176.64/32%overlay-1
```

**Figure 355.** ACI Site 2 Compute Leaf VRF share Route Table

The following figures are routing table information on a Border Gateway in ACI Site 2. VRF vrf1 learns 172.16.31.0/24 from VRF share.

```
qt-bgw805# show ip route 172.16.31.0/24 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.31.0/24, ubest/mbest: 1/0, attached, direct, pervasive
  *via 10.118.176.64%overlay-1, [1/0], 05w03d, static, tag 4294967294, rwVnid: vxlan-2490368
    recursive next hop: 10.118.176.64/32%overlay-1
```

**Figure 356.** ACI Site 2 Border Gateway VRF vrf1 Route Table

VRF share learns 192.168.1.0/24 from VRF vrf1.

```
qt-bgw805# show ip route 192.168.1.0/24 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.1.0/24, ubest/mbest: 1/0, attached, direct, pervasive
  *via 10.118.176.64%overlay-1, [1/0], 05w03d, static, tag 4294967294, rwVnid: vxlan-2097152
    recursive next hop: 10.118.176.64/32%overlay-1
```

**Figure 357.** ACI Site 2 Border Gateway VRF share Route Table

Border Gateways in ACI Site 2 learn remote endpoints (endpoints in ACI Site 1) which reside in different VRF. For example, the endpoint 172.16.31.11, which is in VRF share at ACI Site 1, is also learned in the VRF vrf1 at ACI Site 2.

```
qt-bgw805# show endpoint ip 172.16.31.11
Legend:
S - static          s - arp          L - local          O - peer-attached
V - vpc-attached   a - local-aged   p - peer-aged      M - span
B - bounce         H - vtep         R - peer-attached-rl D - bounce-to-proxy
E - shared-service m - svc-mgr      C - control-ep     Rv - remote-vxlan-ep
```

| VLAN/<br>Domain | Encap<br>VLAN | MAC Address<br>IP Address | MAC Info/<br>IP Info | Interface |
|-----------------|---------------|---------------------------|----------------------|-----------|
| bgw:vrf1        |               | 172.16.31.11 RvE          |                      | tunnel18  |
| bgw:share       |               | 172.16.31.11 Rv           |                      | tunnel18  |

**Figure 358.** ACI Site 2 Border Gateway learns remote endpoint across VRF

Similar to this, the endpoint 192.168.1.11, which is in VRF vrf1 at ACI Site 1, is also learned in the VRF share at ACI Site 2.

```

qt-bgw805# show endpoint ip 192.168.1.11
Legend:
S - static          s - arp          L - local          O - peer-attached
V - vpc-attached   a - local-aged   p - peer-aged      M - span
B - bounce         H - vtep         R - peer-attached-rL D - bounce-to-proxy
E - shared-service m - svc-mgr      C - control-ep     Rv - remote-vxlan-ep


```

| VLAN/<br>Domain | Encap<br>VLAN | MAC Address<br>IP Address | MAC Info/<br>IP Info | Interface |
|-----------------|---------------|---------------------------|----------------------|-----------|
| bgw:vrf1        |               | 192.168.1.11              | Rv                   | tunnel18  |
| bgw:share       |               | 192.168.1.11              | RvE                  | tunnel18  |

**Figure 359.** ACI Site 2 Border Gateway learns remote endpoint across VRF


## Data Plane Verification

The figure below shows the endpoints used in this use case.




**Figure 360.** Endpoint communication across VRFs across Sites


The figure below illustrates the policy enforcement location and VNI translation behavior for traffic from 192.168.1.11 (VRF vrf1) in ACI Site 1 to 172.16.31.201 (VRF share) in ACI Site 2. In the case of inter-VRF communication, ingress compute leaf performs “VRF switch” also known as VRF re-write, from the source VRF to the destination VRF using the local source and destination VNI numbers, since the compute leaf is not aware of the normalized VNI.



**Figure 361.** ACI Site 1 VRF vrf1 to ACI Site 2 VRF share, ingress leaf performs VRF switch



**Figure 362.** ACI Site 2 VRF share to ACI Site 1 VRF vrf1, ingress leaf performs VRF switch



**Figure 363.** Data plane Shared service communication

Ping from 192.168.1.11 in ACI Site 1 VRF vrf1 to 172.16.31.201 in ACI Site 2 VRF share. The packet capture of the ICMP request from EP-1 to EP-5 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF share) is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                             |
|-----|----------|---------------|---------------|----------|--------|------------------------------------------------------------------|
| 19  | 0.467714 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=6/1536, ttl=62 (reply in 20)  |
| 20  | 0.467795 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=6/1536, ttl=62 (request in 19)  |
| 70  | 1.491677 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=7/1792, ttl=62 (reply in 71)  |
| 71  | 1.491819 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=7/1792, ttl=62 (request in 70)  |
| 119 | 2.515746 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=8/2048, ttl=62 (reply in 120) |
| 120 | 2.515887 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=8/2048, ttl=62 (request in 119) |
| 170 | 3.539807 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=9/2304, ttl=62 (reply in 171) |
| 171 | 3.539893 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=9/2304, ttl=62 (request in 170) |

Frame 19: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF\_{5D6AB595-A...}

Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)

Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100

Generic Routing Encapsulation (ERSPAN)

Encapsulated Remote Switch Packet Analysis Type II

Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: Cisco\_f8:19:ff (00:22:bd:f8:19:ff)

Internet Protocol Version 4, Src: 1.1.1.102, Dst: 105.105.105.105

User Datagram Protocol, Src Port: 13669, Dst Port: 4789

Virtual eXtensible Local Area Network

Flags: 0x0800, VXLAN Network ID (VNI): 60001

Group Policy ID: 0

VXLAN Network Identifier (VNI): 60001

Reserved: 0

Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco\_e2:bb:99 (08:0f:e5:e2:bb:99)

Internet Protocol Version 4, Src: 192.168.1.11, Dst: 172.16.31.201

Internet Control Message Protocol

**Figure 364.** ICMP request from EP-1 (192.168.1.11) to EP-5 (172.16.31.201)

The packet capture of the ICMP reply from EP-5 to EP-1 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF vrf1) is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                             |
|-----|----------|---------------|---------------|----------|--------|------------------------------------------------------------------|
| 19  | 0.467714 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=6/1536, ttl=62 (reply in 20)  |
| 20  | 0.467795 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=6/1536, ttl=62 (request in 19)  |
| 70  | 1.491677 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=7/1792, ttl=62 (reply in 71)  |
| 71  | 1.491819 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=7/1792, ttl=62 (request in 70)  |
| 119 | 2.515746 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=8/2048, ttl=62 (reply in 120) |
| 120 | 2.515887 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=8/2048, ttl=62 (request in 119) |
| 170 | 3.539807 | 192.168.1.11  | 172.16.31.201 | ICMP     | 198    | Echo (ping) request id=0x1e63, seq=9/2304, ttl=62 (reply in 171) |
| 171 | 3.539893 | 172.16.31.201 | 192.168.1.11  | ICMP     | 198    | Echo (ping) reply id=0x1e63, seq=9/2304, ttl=62 (request in 170) |

Frame 20: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF\_{5D6AB595-A...}

Ethernet II, Src: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware\_bf:d4:e1 (00:50:56:bf:d4:e1)

Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100

Generic Routing Encapsulation (ERSPAN)

Encapsulated Remote Switch Packet Analysis Type II

Ethernet II, Src: Cisco\_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco\_d5:bb:47 (4c:77:6d:d5:bb:47)

Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102

User Datagram Protocol, Src Port: 31742, Dst Port: 4789

Virtual eXtensible Local Area Network

Flags: 0x0800, VXLAN Network ID (VNI): 50001

Group Policy ID: 0

VXLAN Network Identifier (VNI): 50001

Reserved: 0

Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco\_eb:c5:99 (00:5d:73:eb:c5:99)


Internet Protocol Version 4, Src: 172.16.31.201, Dst: 192.168.1.11

Internet Control Message Protocol

**Figure 365.** ICMP reply from EP-5 (172.16.31.201) to EP-1 (192.168.1.11)

## Policy Enforcement

The figure below illustrates the policy enforcement location for traffic from 192.168.1.11 (endpoint in ESG esg1 in VRF vrf1) in ACI Site 1 to 172.16.31.201 (endpoint in ESG share in VRF share) in ACI Site 2.




**Figure 366.** Policy enforcement VRF vrf1 to VRF share, from ACI Site 1 to ACI Site 2

As outlined in the Data Plane verification, the compute leaf at the source site (Site 1 in this flow) performs a VRF switch from VRF vrf1 to VRF share. Following this VRF switch, the policy enforcement aligns with the behavior described in [Use Case 2: Inter-Subnet Communication Stretched BDs Multiple ESGs](#). Specifically, for traffic flowing from ACI Site 1 to ACI Site 2 (from VRF vrf1 to VRF share):

- ACI Site 1 Border Gateway applies policy in VRF share
- ACI Site 2 Compute Leaf applies policy in VRF share

The figure below illustrates the policy enforcement location for traffic from 172.16.31.201 (endpoint in ESG share in VRF share) in ACI Site 2 to 192.168.1.11 (endpoint in ESG esg1 in VRF vrf1) in ACI Site 1.



**Figure 367.** Policy enforcement VRF share to VRF vrf1, from ACI Site 2 to ACI Site 1

Similarly, the compute leaf at the source site (Site 2 in this flow) performs a VRF switch from VRF share to VRF vrf1. Following this VRF switch, the policy enforcement aligns with the behavior described in Use Case 2: Inter-Subnet Communication Stretched BDs Multiple ESGs. Specifically, for traffic flowing from ACI Site 2 to ACI Site 1 (from VRF share to VRF vrf1):

- ACI Site 2 Border Gateway applies policy in VRF vrf1
- ACI Site 1 Compute Leaf applies policy in VRF vrf1




## Use Case 10: Inter-VRF Communication (Shared Services) with Non-stretched BDs

### Use Case Overview

This use case is similar to [Use Case 9: Inter-VRF Communication \(Shared Services\) with Stretched BDs](#). The main difference is that, in this case, both Bridge Domains (BDs) are non-stretched and are deployed locally at each site. A normalized VNI is still configured when each BD is deployed on the local Border Gateway; however, the normalized VNI values are different between the two sites.

The figure below illustrates an example used in the section.



**Figure 368.** Shared Service with Non-stretched BDs

Most of the required objects were created in the previous use cases. Bridge Domain (BD) bd50 and ESG esg50 were introduced in [Use Case 4: Inter-Subnet Communication with Non-Stretched BDs and Multiple ESGs](#). This section focuses on the new objects introduced for this use case, including ESG share2 in ACI Site 1, and BD bd-share2 and ESG share2 in ACI Site 2.

The route leaking configuration is similar to that described in [Use Case 9: Inter-VRF Communication \(Shared Services\) with Stretched BDs](#). Any differences specific to this use case are called out explicitly.

The BD bd50, ESG esg50 were created in the previous [Use Case 4: Inter-Subnet Communication with Non-stretched BDs Multiple ESGs](#).

For the purpose of completion, the required configuration steps are as follows:

On ACI Site 1:

- Create BD bd50, with subnet “Advertised Externally” scope enabled. Without “Advertised Externally” scope enabled, Border Gateway does not advertise Type-5 route through BGP EVPN.
- Create ESG esg50 with normalized pcTag 1050 and selector EPG esg50.
- Create ESG share2 with normalized pcTag 2002 and no ESG need selectors configured.
- Configure route leak between VRF vrf1 and VRF share, make sure the leaked subnet cover /32 host routes:
  - leak Internal Prefix 192.168.50.0/24 with “Less Than or Equal (Prefix)” of 32 from VRF vrf1 to VRF share
  - leak Internal Prefix 172.16.32.0/24 with “Less Than or Equal (Prefix)” of 32 from VRF share to VRF vrf1




- Apply a contract with tenant scope between esg50 and share2
- On ACI Site 2:

- Create BD bd-share2, with subnet “Advertised Externally” scope enabled. Without “Advertised Externally” scope enabled, Border Gateway does not advertise Type-5 route through BGP EVPN.
- Deploy the Bridge Domain bd-share2 on the Border Gateway by associating it with the Border Gateway Set. You may assign a Normalized VNI but note that this value does not exist on Site 1.
- Create ESG share2 with normalized pcTag 2002 and selector EPG share2.
- Create ESG esg50 with normalized pcTag 1050 and no ESG need selectors configured.
- Configure route leak between VRF vrf1 and VRF share, make sure the leaked subnet cover /32 host routes.
  - leak Internal Prefix 192.168.50.0/24 with less “Less Than or Equal (Prefix)” of 32 from VRF vrf1 to VRF share
  - leak Internal Prefix 172.16.32.0/24 with less “Less Than or Equal (Prefix)” of 32 from VRF share to VRF vrf1
- Apply a contract with tenant scope between esg50 and share2.

### Create Provider VRF and Bridge Domain


Note that the Bridge Domain (BD) bd50 was previously created on Site 1 in [Use Case 4: Inter-Subnet Communication with Non-Stretched BDs and Multiple ESGs](#).

Please verify that the BD subnet has the “Advertised Externally” scope enabled. Since bd50 is local to Site 1, if the “Advertised Externally” scope is not enabled, the BD subnet 192.168.50.0/24 will not be advertised to Site 2 through BGP EVPN.




**Figure 369.** ACI Site 1 bd50 subnet Advertised Externally scope enabled

The figures below are BD bd-share2 configurations in ACI Site 2.




**Figure 370.** ACI Site 2 BD bd-share2

Ensure that the BD subnet has the “Advertised Externally” scope enabled. Since bd-share2 is local to Site 2, if the “Advertised Externally” scope is not enabled, the BD subnet 172.16.32.0/24 will not be advertised to Site 1 through BGP EVPN.



**Figure 371.** ACI Site 2 bd-share2 subnet Advertised Externally scope enabled


On Site 2, deploy the Bridge Domain bd-share2 on the Border Gateway by associating it with the Border Gateway Set. The normalized VNI 32000 does not exist in Site 1.




**Figure 372.** ACI Site 2 deploy BD bd-share2 to Border Gateway

## Create ESG

On both ACI Site 1 and Site 2, ESG esg50 were already created in [Use Case 4: Inter-Subnet Communication with Non-Stretched BDs and Multiple ESGs](#). They are shown here for completeness. ESG esg50 uses 1050 as the Normalized pcTag.




**Figure 373.** ACI Site 1 ESG esg50 Normalized pcTag




**Figure 374.** ACI Site 2 ESG esg50 Normalized pcTag

Although the Bridge Domain bd-share2 is deployed locally only in Site 2, it is necessary to create the Endpoint Security Group (ESG) share2 in Site 1 with the same normalized pcTag as the ESG share2 in Site 2. The ESG share2 in Site 1 does not have an ESG selector and is used solely to classify traffic originating from the ESG share2 in Site 1. The figures below are ESG share2 configurations in ACI Site 1.




**Figure 375.** ACI Site 1 ESG share2 without selector

ACI Site 1 ESG share2 Normalized pcTag is set to 2002, later the same normalized value is used for ESG share2 in ACI Site 2.




**Figure 376.** ACI Site 1 ESG share2 Normalized pcTag

The figures below are ESG share2 configurations in ACI Site 2.




**Figure 377.** ACI Site 2 ESG share2 with EPG share2 as selector




**Figure 378.** ACI Site 2 ESG share2 Normalized pcTag

## Create and Apply Tenant Scope Contract

On both ACI Sites, create a tenant-scope contract named “esg50-share2”. Apply the contract esg50-share2 to ESG esg50 and ESG share2, making esg50 the contract consumer and share2 the contract provider. The figures below are contract configurations in ACI Site 1. Note that the contract scope is set to “Tenant” instead of “VRF” because it is for inter-VRF communication for ESGs in the same tenant.



**Figure 379.** ACI Site 1 tenant scope contract esg50-share2



**Figure 380.** ACI Site 1 ESG esg50 contract consumer




Figure 381. ACI Site 1 ESG share2 contract provider

The figures below are contract configurations in ACI Site 2.




Figure 382. ACI Site 2 tenant scope contract esg50-share2




Figure 383. ACI Site 2 ESG esg50 contract consumer





Figure 384. ACI Site 2 ESG share2 contract provider

## Configure Route Leak


Although the tenant-scope contract between ESGs was created in the previous step to define the security policies allowing communication, this contract alone does not establish network connectivity between the endpoints. Because the endpoints reside in different VRFs, route leaking must be configured to enable routing reachability between these VRFs. Without this route leaking configuration, the endpoints cannot communicate despite the contract being in place.



**Figure 385.** Route Leak diagram


The next step is to configure route leaking between VRF vrf1 and VRF share. This involves leaking the subnet 192.168.50.0/24 from VRF vrf1 to VRF share, and the subnet 172.16.32.0/24 from VRF share to VRF vrf1. It is essential to ensure that the route leak covers not only the /24 prefixes but also the /32 host routes. This guarantees that host routes can be exchanged across VRFs and sites, allowing the destination to program the host route in its respective routing table with the appropriate pcTag for policy enforcement. Since this configuration is similar to [Use Case 9: Inter-VRF Communication \(Shared Services\) with Stretched BDs](#), this section presents the configuration results rather than the detailed steps.

On ACI Site 1, leak Internal Prefix 192.168.50.0/24 from VRF vrf1 to VRF share.




**Figure 386.** ACI Site 1 leak prefix 192.168.50.0/24 from VRF vrf1 to VRF share

On ACI Site 1, leak Internal Prefix 172.16.32.0/24 from VRF share to VRF vrf1.




**Figure 387.** ACI Site 1 leak prefix 172.16.32.0/24 from VRF share to VRF vrf1

On ACI Site 2, leak Internal Prefix 192.168.50.0/24 from VRF vrf1 to VRF share.



**Figure 388.** ACI Site 2 leak prefix 192.168.50.0/24 from VRF vrf1 to VRF share

On ACI Site 2, leak Internal Prefix 172.16.32.0/24 from VRF share to VRF vrf1.




**Figure 389.** ACI Site 2 leak prefix 172.16.32.0/24 from VRF share to VRF vrf1

## Control Plane Verification

The following figure illustrates IP subnets used in this verification section. Note that BD bd50 is local to ACI Site 1, BD bd-share2 is local to ACI Site 2.





**Figure 390.** Route Leak diagram

Note that route leaking depends on the configuration of each site. Specifically, regardless of the configuration on Site 2, the subnet 172.16.32.0/24 is leaked from VRF share to VRF vrf2 on Site 1 only if the route leak configuration is completed on Site 1 itself. On ACI Site 2, compute leaf has the route 172.16.32.0/24 in VRF vrf1.

Since both VRFs are stretched, EVPN Routes Type 5 are advertised by default across sites within the same VRF, provided that the Bridge Domain (BD) subnets have the “Advertised Externally” scope enabled. Specifically, Site 1 Border Gateways learn the 172.16.32.0/24 route in VRF share, while Site 2 Border Gateways learn the 192.168.50.0/24 route in VRF vrf1. Once these routes are learned, route leaking is initiated by the route leak configuration on the local site.

Also note that although BDs are not stretched, they are deployed on Border Gateways so that EVPN Type-2 routes for endpoints are always exchanged between sites within the same VRF. For example, Site 1 Border Gateways learn the 172.16.32.201/32 host route in VRF share, and Site 2 Border Gateways learn the 192.168.50.11/32 host route in VRF vrf1.

To enable data plane communication between endpoint EP-5 (192.168.50.11) in Site 1 VRF vrf1 and endpoint EP-6 (172.16.32.201) in Site 2 VRF share, the Site 1 compute leaf must learn the 172.16.32.0/24 route in VRF vrf1, and the Site 2 compute leaf must learn the 192.168.50.0/24 route in VRF share. Additionally, the Border Gateway on each site must learn the remote endpoints from the other site to facilitate proper forwarding and policy enforcement.

Let’s verify how the route 172.16.32.0/24 is imported into VRF vrf1 on the Site 1 compute leaf.

The route 172.16.32.0/24 is advertised through BGP EVPN to Border Gateways in ACI Site 1. In vsh mode, on ACI Site 2 Border Gateway:

```
qt-bgw805# show bgp l2vpn evpn 172.16.32.0
Route Distinguisher: 400:19267584 (L3VNI 2490368)
BGP routing table entry for [5]:[0]:[0]:[24]:[172.16.32.0]:[0.0.0.0]/224, version 27328 dest ptr 0x7f250b9102e2
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f24fff212f4): local 0x4000000c 0x4400000 ref 0 adv path ref 1, path is valid, is best path
AS-Path: NONE, path locally originated
0.0.0.0 (metric 0) from 0.0.0.0 (10.118.112.67)
Origin incomplete, MED 0, localpref 100, weight 32768 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 2490368
Extcommunity: RT:400:2490368 VNID:2490368

Path-id 1 advertised to peers:
1.1.1.101 1.1.1.102 2.2.2.202
```

**Figure 391.** ACI Site 2 Border Gateway advertises EVPN Route Type 5 to Site 1 Border Gateways.

In the figure above, 1.1.1.101, 1.1.1.102, 2.2.2.202 are loopback IP of Border Gateways bgw-leaf1, bgw-leaf2, bgw-leaf202 in ACI Site 1 respectively. Site 1 Border Gateways receive route 172.16.32.0/24 through EVPN. Below is output in vsh mode of the first Border Gateway in Site 1.

```
bgw-leaf1# show bgp l2vpn evpn 172.16.32.0
Route Distinguisher: 400:19267584
BGP routing table entry for [5]:[0]:[0]:[24]:[172.16.32.0]:[0.0.0.0]/224, version 66658 dest ptr 0x7fd0582518b6
Paths: (1 available, best #1)
Flags: (0x0000000000000002 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

  Advertised path-id 1
  Path type (0x7fd04c76f8bc): external 0x40000028 0x40000000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
    Imported to 1 destination(s)
  AS-Path: 400 , path sourced external to AS
    105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
    Origin incomplete, MED 0, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
    Received label 60001
    Extcommunity: RT:100:60001 S00:100:1694498797 COST:pre-bestpath:170:1610612736
    ENCAP:8 PCTAG:80:0:0:1 Router MAC:080f.e5e2.bb99

  Path-id 1 not advertised to any peer
```

**Figure 392.** ACI Site 1 Border Gateway receives EVPN Route Type 5 from Site 2 Border Gateway.

In the figure above, 5.5.5.105 is Site 2 Border Gateway loopback IP. The value 60001 represents the normalized L3 VNI of VRF share. After route leak is configured on Site 1, the route 172.16.32.0/24 is leaked to VRF vrf1.

```
bgw-leaf1# show ip route 172.16.32.0 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.32.0/24, ubest/mbest: 1/0
  *via 105.105.105.105%overlay-1, [200/0], 00:40:08, bgp-100, external, tag 400, rwVnid: vxlan-60001, pc-tag: 11
    recursive next hop: 105.105.105.105/32%overlay-1
bgw-leaf1#
```

**Figure 393.** ACI Site 1 Border Gateway VRF vrf1 route table

The route 172.16.32.0/24 is then advertised to Spine through BGP VPNv4 and later it is reflected to compute leaf leaf1.

```
leaf1# show ip route 172.16.32.0/24 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.32.0/24, ubest/mbest: 2/0
  *via 10.1.248.2%overlay-1, [200/0], 00:47:56, bgp-100, internal, tag 400, rwVnid: vxlan-2228225, pc-tag: 14
    recursive next hop: 10.1.248.2/32%overlay-1
  *via 10.1.248.7%overlay-1, [200/0], 00:47:56, bgp-100, internal, tag 400, rwVnid: vxlan-2228225, pc-tag: 14
    recursive next hop: 10.1.248.7/32%overlay-1
```

**Figure 394.** ACI Site 1 Compute Leaf VRF vrf1 route table

Let's verify how the endpoint route 172.16.32.201/32 is imported into VRF vrf1 on the Site 1 Border Gateway. As mentioned above, host route 172.16.32.201/32 is advertised from Site 2 Border Gateway to Site 1 Border Gateway. In vsh mode, on ACI Site 2 Border Gateway:

```

qt-bgw805# show bgp l2vpn evpn 172.16.32.201
Route Distinguisher: 400:15564693
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.2e90]:[32]:[172.16.32.201]/272, version 27055 dest ptr 0x7f250b90d73a
Paths: (1 available, best #1)
Flags: (0x000000000000202 0x00000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f24fff21390): internal 0x40000018 0x4002000 ref 2 adv path ref 1, path is valid, is best path, remote nh not installed
Imported to 2 destination(s)
AS-Path: NONE, path sourced internal to AS
10.118.176.64 (metric 2) from 10.118.112.65 (10.118.112.65)
Origin IGP, MED not set, localpref 100, weight 0 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 15564693 2490368
Extcommunity: RT:400:2490368 RT:400:15564693 S00:1:1 ENCAP:8 PCTAG:01:0:0:26
Router MAC:0200.0000.0000

Path-id 1 not advertised to any peer

Route Distinguisher: 400:32341909 (L2VNI 15564693)
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.2e90]:[32]:[172.16.32.201]/272, version 27064 dest ptr 0x7f250b914262
Paths: (1 available, best #1)
Flags: (0x000000000000212 0000000000) on xmit-list, is in rib/evpn, is not in HW
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7f24ffcd6e58): internal 0xc0000018 0x400 ref 0 adv path ref 1, path is valid, is best path, remote nh not installed, in rib
Imported from (0x7f24fff21390) 400:15564693:[2]:[0]:[0]:[48]:[0050.56bf.2e90]:[32]:[172.16.32.201]/144
AS-Path: NONE, path sourced internal to AS
10.118.176.64 (metric 2) from 10.118.112.65 (10.118.112.65)
Origin IGP, MED not set, localpref 100, weight 0 tag 0, propagate 0, floating svi 0, tunnel resolved 0
Received label 15564693 2490368
Extcommunity: RT:400:2490368 RT:400:15564693 S00:1:1 ENCAP:8 PCTAG:01:0:0:26
Router MAC:0200.0000.0000

Path-id 1 advertised to peers:
1.1.1.101 1.1.1.102 2.2.2.202

```

**Figure 395.** ACI Site 2 Border Gateway advertises EVPN Route Type 2

ACI Site 1 Border Gateways receive EVPN Type 2 route 172.16.32.201 from Site 2 Border Gateway. In vsh mode, Site 1 first Border Gateway:

```

bgw-leaf1# show bgp l2vpn evpn 172.16.32.201
Route Distinguisher: 400:32341909
BGP routing table entry for [2]:[0]:[0]:[48]:[0050.56bf.2e90]:[32]:[172.16.32.201]/272, version 65647 dest ptr 0x7fd05825269a
Paths: (1 available, best #1)
Flags: (0x000000000000202 0000000000) on xmit-list, is not in rib/evpn, is not in HW, is locked
Multipath: eBGP iBGP

Advertised path-id 1
Path type (0x7fd04c771b78): external 0x40000028 0x4002000 ref 1 adv path ref 1, path is valid, is best path, remote nh not installed
Imported to 1 destination(s)
AS-Path: 400 , path sourced external to AS
105.105.105.105 (metric 0) from 5.5.5.105 (10.118.112.67)
Origin IGP, MED not set, localpref 100, weight 0 tag 4294966000, propagate 0, floating svi 0, tunnel resolved 0
Received label 32000 60001
Extcommunity: RT:100:32000 RT:100:60001 S00:100:1694498797
COST:pre-bestpath:170:1610612736 ENCAP:8 PCTAG:80:0:0:2002
Router MAC:080f.e5e2.bb99

Path-id 1 not advertised to any peer

```

**Figure 396.** ACI Site 1 Border Gateway receives EVPN Route Type 2 for 172.16.31.201

In the figure above, 5.5.5.105 is Site 2 Border Gateway loopback IP. The value 60001 represents the normalized L3 VNI of VRF share.

Since Site 1 has route leak configuration with Internal Prefixes 172.16.32.0/24 and “Less than or Equal (Prefix)” set to 32, the host route 172.16.32.201 is leaked from VRF share to VRF vrf1 with proper pcTag. In exec mode on Site 1 Border Gateway, in VRF vrf1, Border Gateway has route with pcTag of 31 which is local pcTag of ESG share2 on Site1 itself.

```


bgw-leaf1# show ip route 172.16.32.201 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
'*'*' denotes best mcast next-hop
'[x/y]' denotes [preference/metric]
'%<string>' in via output denotes VRF <string>

172.16.32.201/32, ubest/mbest: 1/0
 *via 105.105.105.105%overlay-1, [20/0], 00:01:01, bgp-100, external, tag 400, redist-only, rwnid: vxlan-60001, pc-tag: 31
 recursive next hop: 105.105.105.105/32%overlay-1

```


**Figure 397.** ACI Site 1 Border Gateway receives host route with proper local pcTag

Here shown the local pcTag of ESG share2 in Site1 for reference:



**Figure 398.** ACI Site 1 ESG share2 local pcTag


For easy of verification, it is shown here the route leak configuration on Site 1.



**Figure 399.** ACI Site 1 route leak from VRF share to VRF vrf1

Note that the value 32 in “Less Than or Equal(Prefix)” is critical, without it the host route is still leaked to VRF vrf1 however the pcTag is wrong causing data plane broken between EP-5 and EP-6.

**Failure scenario (Leaked prefix does not cover host route):** Let do quick verification by set “Less Than or Equal(Prefix)” to 32 or unspecified.



**Figure 400.** ACI Site 1 leak route “Less Than or Equal(Prefix)” set to 31

As shown in the figure below, the Site 1 Border Gateway does not have the endpoint (host route) in VRF vrf1, so it assigns pcTag 11 to the host route. pcTag 11 is a reserved tag that indicates the endpoint is not learned in the control plane. This signals the compute leaf in the same site to drop packets originating from that endpoint.

```
bgw-leaf1# show ip route 172.16.32.201 vrf bgw:vrf1
IP Route Table for VRF "bgw:vrf1"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

172.16.32.0/24, ubest/mbest: 1/0
  *via 105.105.105.105%overlay-1, [20/0], 03:57:05, bgp-100, external, tag 400, rwnid: vxlan-60001, pc-tag: 11
    recursive next hop: 105.105.105.105/32%overlay-1
```

**Figure 401.** ACI Site 1 Border Gateway receives only subnet route and set endpoint with pcTag 11

Following the same procedure, it is verified that in VRF share, ACI Site 2 Border Gateway learns host route 192.168.50.11 with proper pcTag and compute leaf learns route to 192.168.50.0/24. ACI Site 2 compute leaf VRF share route table.

```
qt-leaf802# show ip route 192.168.50.0/24 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.50.0/24, ubest/mbest: 1/0
  *via 10.118.112.67%overlay-1, [200/0], 16:26:22, bgp-400, internal, tag 100, rwnid: vxlan-2097152, pc-tag: 14
    recursive next hop: 10.118.112.67/32%overlay-1
```


**Figure 402.** ACI Site 2 compute leaf VRF share route table

ACI Site 2 Border Gateway learns host route and sets proper local pcTag.

```
qt-bgw805# show ip route 192.168.50.11 vrf bgw:share
IP Route Table for VRF "bgw:share"
'*' denotes best ucast next-hop
 '**' denotes best mcast next-hop
 '[x/y]' denotes [preference/metric]
 '%<string>' in via output denotes VRF <string>

192.168.50.11/32, ubest/mbest: 1/0
  *via 100.100.100.102%overlay-1, [20/0], 04:49:44, bgp-400, external, tag 100, redistrib-only, rwnid: vxlan-50001, pc-tag: 25
    recursive next hop: 100.100.100.102/32%overlay-1
```


**Figure 403.** ACI Site 2 Border Gateway learns host route in VRF share




**Figure 404.** ACI Site 2 ESG esg50 local pcTag

## Data Plane Verification

The figure below illustrates the policy enforcement location and VNI translation behavior for traffic from 192.168.50.11 (VRF vrf1) in ACI Site 1 to 172.16.32.201 (VRF share) in ACI Site 2. In the case of inter-VRF communication, ingress compute leaf performs “VRF switch” also known as VRF re-write, from the source VRF to the destination VRF using the local source and destination VNI numbers, since the compute leaf is not aware of the normalized VNI.




**Figure 405.** ACI Site 1 VRF vrf1 to ACI Site 2 VRF share, ingress leaf performs VRF switch




**Figure 406.** ACI Site 2 VRF share to ACI Site 1 VRF vrf1, ingress leaf performs VRF switch





**Figure 407.** Data plane Inter-VRF Communication (Shared Services) with Non-stretched BDs

Ping from 192.168.50.11 in ACI Site 1 to 172.16.32.201 in ACI Site 2. The packet capture of the ICMP request from EP-5 to EP-6 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF share) is used in the VXLAN header for inter-site data plane forwarding.



**Figure 408.** ICMP request from EP-5 (192.168.50.11) to EP-6 (172.16.32.201)

The packet capture of the ICMP reply from EP-6 to EP-5 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF vrf1) is used in the VXLAN header for inter-site data plane forwarding.

| No. | Time     | Source        | Destination   | Protocol | Length | Info                                                              |
|-----|----------|---------------|---------------|----------|--------|-------------------------------------------------------------------|
| 42  | 0.866086 | 192.168.50.11 | 172.16.32.201 | ICMP     | 198    | Echo (ping) request id=0x609a, seq=12/3072, ttl=62 (reply in 43)  |
| 43  | 0.866226 | 172.16.32.201 | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x609a, seq=12/3072, ttl=62 (request in 42)  |
| 99  | 1.890128 | 192.168.50.11 | 172.16.32.201 | ICMP     | 198    | Echo (ping) request id=0x609a, seq=13/3328, ttl=62 (reply in 100) |
| 100 | 1.890211 | 172.16.32.201 | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x609a, seq=13/3328, ttl=62 (request in 99)  |
| 146 | 2.914094 | 192.168.50.11 | 172.16.32.201 | ICMP     | 198    | Echo (ping) request id=0x609a, seq=14/3584, ttl=62 (reply in 147) |
| 147 | 2.914220 | 172.16.32.201 | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x609a, seq=14/3584, ttl=62 (request in 146) |
| 193 | 3.938080 | 192.168.50.11 | 172.16.32.201 | ICMP     | 198    | Echo (ping) request id=0x609a, seq=15/3840, ttl=62 (reply in 194) |
| 194 | 3.938243 | 172.16.32.201 | 192.168.50.11 | ICMP     | 198    | Echo (ping) reply id=0x609a, seq=15/3840, ttl=62 (request in 193) |


  

|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |                                                                                                                                                                                                                                                                                                                                                                                    |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Frame 43: Packet, 198 bytes on wire (1584 bits), 198 bytes captured (1584 bits) on interface \Device\NPF_{5D6AB595-A...<br>Ethernet II, Src: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47), Dst: VMware_bf:d4:e1 (00:50:56:bf:d4:e1)<br>Internet Protocol Version 4, Src: 10.0.0.1, Dst: 172.16.80.100<br>Generic Routing Encapsulation (ERSPAN)<br>Encapsulated Remote Switch Packet Analysis Type II<br>Ethernet II, Src: Cisco_f8:19:ff (00:22:bd:f8:19:ff), Dst: Cisco_d5:bb:47 (4c:77:6d:d5:bb:47)<br>Internet Protocol Version 4, Src: 5.5.5.105, Dst: 100.100.100.102<br>User Datagram Protocol, Src Port: 4077, Dst Port: 4789<br>Virtual eXtensible Local Area Network<br>Flags: 0x0800, VXLAN Network ID (VNI): 50001<br>Group Policy ID: 0<br>VXLAN Network Identifier (VNI): 50001<br>Reserved: 0<br>Ethernet II, Src: Cisco-ACI-Gleaning-Leaf (00:0c:0c:0c:0c:0c), Dst: Cisco_eb:c5:99 (00:5d:73:eb:c5:99)<br>Internet Protocol Version 4, Src: 172.16.32.201, Dst: 192.168.50.11<br>Internet Control Message Protocol | 0000 00 50 56 bf d4 e1 4c<br>0010 00 b8 f8 61 00 00 ff<br>0020 50 64 10 00 88 be 00<br>0030 01 3d 4c 77 6d d5 bf<br>0040 45 00 00 86 00 00 00<br>0050 64 64 64 66 0f ed 12<br>0060 00 c3 51 00 00 5d 73<br>0070 00 00 45 00 00 54 d2<br>0080 20 c9 c0 a8 32 0b 00<br>0090 47 6a 00 00 00 00 c0<br>00a0 12 13 14 15 16 17 1f<br>00b0 22 23 24 25 26 27 2f<br>00c0 32 33 34 35 36 37 |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

**Figure 409.** ICMP reply from EP-6 (172.16.32.201) to EP-5 (192.168.50.11)

## Policy Enforcement

The figure below illustrates the policy enforcement location for traffic from 192.168.50.11 (endpoint in ESG esg50 in VRF vrf1) in ACI Site 1 to 172.16.32.201 (endpoint in ESG share2 in VRF share) in ACI Site 2.




**Figure 410.** Policy enforcement VRF vrf1 to VRF share, from ACI Site 1 to ACI Site 2

As outlined in the Data Plane verification, the compute leaf at the source site (Site 1 in this flow) performs a VRF switch from VRF vrf1 to VRF share. Following this VRF switch, the policy enforcement aligns with the behavior described in [Use Case 4: Inter-Subnet Communication with Non-stretched BDs Multiple ESGs](#). Specifically, for traffic flowing from ACI Site 1 to ACI Site 2 (from VRF vrf1 to VRF share):

- ACI Site 1 Border Gateway applies policy in VRF share
- ACI Site 2 Compute Leaf applies policy in VRF share

The figure below illustrates the policy enforcement location for traffic from 172.16.32.201 (endpoint in ESG share2 in VRF share) in ACI Site 2 to 192.168.50.11 (endpoint in ESG esg50 in VRF vrf1) in ACI Site 1.





**Figure 411.** Policy enforcement VRF share to VRF vrf1, from ACI Site 2 to ACI Site 1

Similarly, the compute leaf at the source site (Site 2 in this flow) performs a VRF switch from VRF share to VRF vrf1. Following this VRF switch, the policy enforcement aligns with the behavior described in [Use Case 4: Inter-Subnet Communication with Non-stretched BDs Multiple ESGs](#). Specifically, for traffic flowing from ACI Site 2 to ACI Site 1 (from VRF share to VRF vrf1):


- ACI Site 2 Border Gateway applies policy in VRF vrf1
- ACI Site 1 Compute Leaf applies policy in VRF vrf1

## Use Case 11: Inter-VRF Communication (Shared Services) with Shared L3Out

### Use Case Overview

This section covers an inter-VRF communication use case with an L3Out where the source and the destination reside in different VRFs similar to the previous use case. A shared L3Out and its ESG does not have to be in the same tenant with the ESG for endpoints.

The figure below illustrates an example used in this section. VRFs, BDs and ESGs are stretched across sites, and the L3Out is local to ACI Site 1. Although this example shows stretched VRFs, Bridge Domains, and ESGs, only the VRF must be stretched. The BD and ESG may remain local to each site. A Contract is configured between ESG ext-1 in VRF vrf1 and ESG share1 in VRF share. When an endpoint in ESG share1 in ACI Site2 communicate with an external endpoint in ESG ext-1 (100.64.1.0/24), it will go through the L3Out in ACI Site 1.



**Figure 412.** Shared L3Out across ACI Sites


The configuration steps are following:

- Create VRF share, BD bd-share1, stretch the VRF and the BD.
- Create ESG share1 with the normalized pcTag.
- [Leak ACI Site 1 VRF vrf1 external prefix to VRF share.](#)
- Leak BD bd-share1 subnet in VRF share to ACI Site 1 VRF vrf1 L3Out.
- Apply a tenant scope contract between ESG esg1 and ESG ext-1.
- [Enabled “Shared” flag under ESG External Subnet Selector](#) (for external subnet 100.64.1.0/24) in ACI Site 1

Since the first two steps are identical with the previous use case, this section covers the last four steps.

The following figure summarizes the leaked subnet information between VRF vrf1 and VRF share. In this example, the following subnets need to be leaked:


- 100.64.1.0/24 learnt via the L3Out in VRF vrf1 needs to be leaked to VRF share.
- 172.16.31.0/24 in bridge domain bd-share of VRF share must be leaked to VRF vrf1.



**Figure 413.** Leak routes across VRF

### Advertise External Route from L3Out to Remote VRF

This section covers how to leak an external prefix to another VRF. At ACI Site 1, navigate to Networking -> VRFs -> vrf1 -> Inter-VRF Leaked Routes for ESG. Right click and choose “Create Leaked External Prefix”. And follow the wizard to specify the prefix and the destination VRF where the prefix needs to be leaked.



**Figure 414.** Create Leaked External Prefix

Enter 100.64.1.0/24 in the IP field, then click “+” button.

Create Leaked External Prefix

IP: 100.64.1.0/24  
address/optional mask

Description: optional

Greater Than or Equal (Prefix): unspecified

Less Than or Equal (Prefix): unspecified

Tenant and VRF Destinations:

| Tenant Name | VRF Name | Description |
|-------------|----------|-------------|
|-------------|----------|-------------|

Cancel Submit

**Figure 415.** Define 100.64.1.0/24 as leaked external prefix

Choose “bgw” from the Tenant drop-down list, choose “share” from VRF drop-down list then click OK.

Create Tenant and VRF Destination

Tenant and VRF: bgw share  
Tenant VRF

Description: optional

Cancel OK

**Figure 416.** Choose VRF share as destination VRF

Click Submit to finish.

Create Leaked External Prefix

IP: 100.64.1.0/24  
address/optional mask

Description: optional

Greater Than or Equal (Prefix): unspecified

Less Than or Equal (Prefix): unspecified

Tenant and VRF Destinations:

| Tenant Name | VRF Name | Description |
|-------------|----------|-------------|
| bgw         | share    |             |

Cancel Submit


**Figure 417.** Leak External Prefix to destination VRF completion

| IP            | Description | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Target VRF(s) | Is Target VRF Present? |
|---------------|-------------|--------------------------------|-----------------------------|---------------|------------------------|
| 100.64.1.0/24 |             | Unspecified                    | Unspecified                 | bgw/share     | Yes                    |

**Figure 418.** Leak external prefix to different VRF completion

## Advertise Internal Bridge Domain Subnet to L3Out Across VRF

This section covers how to leak an internal subnet to an external network in another VRF.



**Figure 419.** Advertise 172.16.31.0/24 to ACI Site 1 L3Out in VRF vrf1

At ACI Site 1, make sure the subnet 172.16.31.0/24 is leaked from VRF share to VRF vrf1 using Internal Prefixes route leak.

| IP             | Description | Greater Than or Equal (Prefix) | Less Than or Equal (Prefix) | Allow L3Out Advertisement | Configuration Issues |
|----------------|-------------|--------------------------------|-----------------------------|---------------------------|----------------------|
| 172.16.31.0/24 | optional    | unspecified                    | 32                          | True                      |                      |

**Figure 420.** ACI Site 1 Internal Prefixes leak 172.16.31.0/24 to VRF vrf1


A route profile configuration is required at the external EPG to export the internal prefix to L3Out. In this example, the route profile that has a match prefix rule for 172.16.31.0/24 is required on the external EPG under the L3Out in VRF vrf1. After this step, subnet 172.16.31.0/24 is advertised from VRF share to the external router in VRF vrf1 in ACI Site 1.

It is important to note that a given external EPG supports only one Route Control Profile per direction. In [Use Case 7: Transit Routing Across ACI Sites](#), the route map transit-100-68-1 has already been applied in

the export direction under the Route Control Profile associated with the External EPG bgp-ext-epg. Therefore, applying a new export route map in this scenario would replace the existing association and cause transit-100-68-1 to be detached.


Although this use case uses a different route-map named 172-vrf-share, the existing route-map transit-100-68-1 can be reused by adding an additional context to the existing route map.

The following figures show a configuration example for route control profile at the external EPG. Route-map 172-vrf-share is associated to external EPG bgp-ext-epg in ACI Site 1.




**Figure 421.** Apply route profile export direction

Route-map 172-vrf-share is configured with a match prefix rule for 172.16.31.0/24.



**Figure 422.** Route-map to match 172.16.31.0/24 subnet



**Figure 423.** Route Context

Match Rule - 172

Policy

Properties

Match AS Path Regex Terms:

| Name                                                              | Regular Expression | Description |
|-------------------------------------------------------------------|--------------------|-------------|
| No items have been found.<br>Select Actions to create a new item. |                    |             |

Match Prefix:

| IP             | Description | Aggregate | Greater Equal Mask | Less Equal Mask |
|----------------|-------------|-----------|--------------------|-----------------|
| 172.16.31.0/24 |             | False     | 0                  | 0               |

Figure 424. Match rule to match 172.16.31.0/24

## Create and Apply Tenant Scope Contract

On both ACI Sites, create a tenant scope contract named bgw-shared-l3out, apply this contract between ESG share1 and ESG ext-1.




Figure 425. Shared L3Out logical topology

The following screenshots show a contract configuration example.

APIC (site1)

System | Tenants | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | bgw | demo | Fortune | infra

bgw

- Quick Start
- bgw
  - Application Profiles
  - Networks
  - Contracts
    - Standard
      - bgw-shared-l3out

Contract - bgw-shared-l3out

Summary | Topology | Policy

Properties

Name: bgw-shared-l3out

Alias:

Global Alias:

Scope: Tenant

QoS Class: Unspecified

Target DSCP: Unspecified

Description: optional

Annotations: Click to add a new annotation

Subjects:

| Name | Alias | Filters |
|------|-------|---------|
| IP   |       | bgw/ip  |

Figure 426. ACI Site 1 tenant-scope contract

APIC (site1)

System | Tenants | Fabric | Virtual Networking | Admin | Operations | Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | bgw | mgmt | vc9-demo | Inmarket

bgw

- Quick Start
- bgw
  - Application Profiles
  - Application EPGs
  - uSeg EPGs
  - Endpoint Security Groups
  - share1
    - Contracts

Contracts

Contracts | Inherited Contracts | Contracts Via EPG Selectors | Inherited Contracts Via EPG

| Tenant Name             | Tenant Alias | Contract Name    | Contract Type | Provided / Consumed | QoS Class   | State  |
|-------------------------|--------------|------------------|---------------|---------------------|-------------|--------|
| Contract Type: Contract |              |                  |               |                     |             |        |
| bgw                     |              | bgw-shared-l3out | Contract      | Consumed            | Unspecified | Formed |
| bgw                     |              | share-svc        | Contract      | Provided            | Unspecified | Formed |

Figure 427. ACI Site 1 ESG share1 contract consumer




Figure 428. ACI Site 1 ESG ext-1 contract provider




Figure 429. ACI Site 2 tenant-scope contract




Figure 430. ACI Site 2 ESG share1 contract consumer





Figure 431. ACI Site 2 ESG ext-1 contract provider


## Enable Shared flag in ESG External Subnet Selector

The “Shared” flag needs to be enabled at the external subnet selector for the ESG ext-1 otherwise endpoint in VRF share in ACI Site 1 is not allowed to communication to external endpoint in L3Out in ACI Site 1 even with tenant-scope contract applied. Navigate to ESG ext-1 -> Selectors -> Double-click on External subnet.



**Figure 432.** Enable shared flag in external subnet

Once the External subnet setting window open, check Shared and click Submit.



**Figure 433.** Check Shared and Submit

## Control Plane Verification

The external router in ACI Site 1 learns 172.16.31.0/24 that is BD bd-share1 subnet in VRF share.



```

Site1-C8K-1#show ip route bgp
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2, m - OMP
n - NAT, Ni - NAT inside, No - NAT outside, Nd - NAT DIA
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
H - NHRP, G - NHRP registered, g - NHRP registration summary
o - ODR, P - periodic downloaded static route, l - LISP
a - application route
+ - replicated route, % - next hop override, p - overrides from Pfr
& - replicated local route overrides by connected

Gateway of last resort is not set


 8.0.0.0/24 is subnetted, 1 subnets
B    8.8.8.0 [20/0] via 11.0.0.1, 7w0d
100.0.0.0/8 is variably subnetted, 13 subnets, 2 masks
B    100.68.1.0/24 [20/0] via 172.16.161.1, 18:59:18
172.16.0.0/16 is variably subnetted, 7 subnets, 3 masks
B    172.16.31.0/24 [20/0] via 172.16.161.1, 18:59:26
B    192.168.1.0/24 [20/0] via 172.16.161.1, 18:59:26

```


**Figure 434.** External router learns internal BD subnet

## Data Plane Verification


The figure below illustrates the policy enforcement location and VNI translation behavior for traffic from 172.16.31.201 (VRF share) in ACI Site 2 to 100.64.1.10 (VRF vrf1) in ACI Site 1. In this case, ingress leaf performs “VRF switch” also known as VRF re-write for both directions.



**Figure 435.** ACI Site 2 VRF share to ACI Site 1 VRF vrf1 L3Out, ingress leaf performs VRF switch




**Figure 436.** ACI Site 1 VRF vrf1 L3Out to ACI Site 2 VRF share, ingress leaf performs VRF switch




**Figure 437.** Data plane Shared L3Out communication

Ping result from an endpoint in ESG share1 in ACI Site 2 to an external endpoint in VRF vrf1 in ACI Site 1. The packet capture of the ICMP request from EP-2 to ExtEP-1 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF vrf1) is used in the VXLAN header for inter-site data plane forwarding.



**Figure 438.** ICMP request from EP-2 (172.16.31.201) to ExtEP-1 (100.64.1.10)


The packet capture of the ICMP reply from ExtEP-1 to EP-2 confirms that the Layer 3 (VRF) Normalized VNI of the destination VRF (VRF share) is used in the VXLAN header for inter-site data plane forwarding.




**Figure 439.** ICMP reply from ExtEP-1 (100.64.1.10) to EP-2 (172.16.31.201)

## Policy Enforcement

The figure below illustrates the policy enforcement location for traffic between 172.16.31.201 (an endpoint in ESG share1 ACI Site 2 VRF share) and 100.64.1.10 (an external endpoint in ESG ext-1 in ACI Site 1 VRF vrf1). In both directions, after the ingress leaf performs the “VRF switch” policy enforcement is identical to that described in [Use Case 5: North-South Communication Across ACI Sites with Stretched BDs](#)



**Figure 440.** Local endpoint in ACI Site 2 VRF share to external endpoint in ACI Site 1 VRF vrf1



**Figure 441.** External endpoint in ACI Site 1 VRF vrf1 to local endpoint in ACI Site 2 VRF share


ACI Site 2 compute leaf does not apply the policy. Instead, ACI Site 2 Border Gateway applies the policy. ACI Site 1 Border Gateway applies the policy. ACI Site 1 Border Leaf does not apply the policy since the policy was already applied by the Border Gateway. ACI Border Leaf (node-101) does not apply the policy. Instead, Border Gateway applies the policy in the destination VRF. ACI Site 2 Border Gateway does not apply the policy. Instead, ACI Site 2 compute leaf applies the policy in the destination VRF.

## Use Case 12: Service Node Integration

### Use Case Overview


This section explains PBR (Policy Based Redirect) for L4-L7 service integration in an ACI-to-ACI deployment through Border Gateways. For inter-site communication, contracts are applied in both the source and the destination sites, hence service insertion is handled independently within each site.

Each site may connect its own firewall devices, operating in Active/Standby mode, Active/Active mode, or as multiple independent firewalls with symmetric PBR (Policy Based Redirect). Firewall deployment is independent for each site, and the Service Bridge Domain (BD) can be entirely local to the site without requiring deployment on the Border Gateway. This means the Service BD does not need to be stretched or deployed on the Border Gateway to function properly within that site. Consumer and Provider Bridge Domains (BDs) can be either stretched across sites or remain local to each site. It is a valid design option for one site to deploy a firewall while another site operates without one. The site with the firewall can redirect traffic to its local firewall for traffic that is local to that site, for traffic arriving from the remote site, and for traffic destined toward the remote site. However, the remote site that does not have a local firewall cannot redirect traffic to the firewall deployed at the other site. However, for consistent security and policy enforcement, this guide recommends deploying firewalls at both source and destination sites. The Endpoint Security Groups (ESGs) involved in these relationships can be standard ESGs (for example ESG esg1, esg2) or ESGs configured with an external subnet to represent an external network (for example ESG ext-1).



**Figure 442.** Firewall Insertion Topology


Below is a logical diagram with a contract between esg1 and esg2, the expectation is that traffic flow between esg1 and esg2 is redirected to the local firewall in each site independently.



**Figure 443.** Firewall Insertion Logical Diagram

As shown in the figure above, both the consumer and provider are locally connected endpoints. However, as mentioned previously it is also possible for the consumer and provider to be external endpoints; for example, the consumer could be ESG esg1, and the provider could be ESG ext-1.

The following diagram illustrates the traffic flow originating from esg1 in ACI Site 1 to esg2 in ACI Site 2. Incoming traffic arriving from a remote site is always redirected by the Border Gateway in the receiving site.




**Figure 444.** Flow from ACI Site 1 esg1 endpoint to ACI Site 2 esg2 endpoint

Since in the example in figure above the compute leaf in Site 1 does not have the pcTag information of the destination endpoint (EP-2), it forwards the traffic to the Site 1 Border Gateway, which maintains the complete pcTag information for both the source and destination endpoints. Upon receiving the traffic, the Site 1 Border Gateway performs a Policy-Based Redirect (PBR) and redirects the traffic to the Site 1 Firewall for inspection.

- 1a) EP-1 -> Site 1 leaf1 -> Site 1 Spine -> Site 1 Border Gateway -> Site 1 Spine -> Site 1 leaf601 -> Site 1 Firewall
- 1b) Site 1 Firewall -> Site 1 leaf601 -> Site 1 Spine -> Site 1 Border Gateway -> ISN -> Site 2 Border Gateway -> Site 2 Spine -> Site 2 leaf802 -> Site 2 Firewall
- 1c) Site 2 FW -> Site 2 leaf802 -> EP-2

Note: in the specific case where the BD of EP-2 is stretched across sites and also locally deployed on leaf1 in Site 1, it may happen that EP-2 IP information (and associated pcTag) will be learned on leaf1 based on data-plane activity. Under those specific circumstances, the PBR policy could be directly applied on leaf1 and traffic would be optimally redirected to the local firewall. The following diagram illustrates the flow for returning traffic from ESG2 in ACI Site 2 to ESG1 in ACI Site 1.



**Figure 445.** Returning flow from ACI Site 2 esg1 endpoint to ACI Site 1 esg2 endpoint

- 2a) EP-2 -> Site 2 leaf802 -> Site2 Spine -> Site 2 Border Gateway -> Site 2 Spine -> Site leaf802 -> Site 2 Firewall
- 2b) Site2 Firewall -> Site 2 leaf802 -> Site 2 Spine -> Site 2 Border Gateway -> ISN -> Site 1 Border Gateway -> Site 1 Spine -> Site 1 leaf1 -> Site 1 Spine -> Site 1 leaf601 -> Site 1 Firewall
- 2c) Site 1 Firewall -> Site 1 leaf601 -> Site 1 Spine -> Site 1 leaf1 -> EP-1

Note: in the specific case where the BD of EP-1 is stretched across sites and also locally deployed on leaf802 in Site 2, it may happen that EP-1 IP information (and associated pcTag) will be learned on leaf802 based on data-plane activity. Under those specific circumstances, the PBR policy could be directly applied on leaf802 and traffic would be optimally redirected to the local firewall.

The following steps outline the primary configuration on both ACI Sites, assuming that esg1, esg2, and the required contract are already in place.

- Create a Bridge Domain (BD) for the service node, also known as the Service BD.
- Create the Firewall Logical Device.
- Create the Service Graph Template.
- Create the L4-L7 Redirection Policy.
- Deploy the Service Graph using the template.


For more detail information, please refer to this whitepaper:

<https://www.cisco.com/c/en/us/solutions/collateral/data-center-virtualization/application-centric-infrastructure/white-paper-c11-739971.html>

The next section shows a configuration example for both ACI sites.


### Firewall Insertion Configuration Details

In ACI Site 1, the Service BD is configured as Layer 3 with Unicast Routing enabled. The Service BD subnet does not need to be advertised externally or stretched across sites.




**Figure 446.** ACI Site 1 Service BD

For the ACI Site 1 service node, this deployment uses a virtual domain; however, the same principles apply to a physical domain. While this service node is configured using a one-arm interface, a two-arm interface configuration is also supported. Note that for a two-arm service, two separate service BDs need be defined, one for each interface. This example uses one-arm service node.



**Figure 447.** ACI Site 1 Service Node


The “Route Redirect” parameter in the Service Graph Template must be set to “true” as this deployment utilizes PBR.



**Figure 448.** ACI Site 1 Service Graph Template




In this example, the IP SLA frequency is set to 3 seconds, resulting in ACI sending an ICMP probe to the service node every 3 seconds. Based on the Detect Multiplier value of 3, the service node is declared down after three consecutive probe failures.



**Figure 449.** ACI Site 1 IP SLA Monitoring Policy

A Redirect Health Group (Health Group) in Cisco ACI Policy-Based Redirect (PBR) is a logical grouping of PBR destination IP addresses used to track the operational status of service nodes, such as firewalls or load balancers. The health group prevents traffic redirection to a service node that is down, avoiding traffic blackholing. To enable IP SLA monitoring, a Redirect Health Group must be configured. For more details, please refer to the Cisco ACI white paper on optional features available at <https://www.cisco.com/c/en/us/solutions/collateral/data-center-virtualization/application-centric-infrastructure/white-paper-c11-739971.html#Optionalfeatures>



**Figure 450.** ACI Site 1 L4-L7 Redirect Health Group



L4-L7 Policy Based Redirect (also known as PBR policy) specifies where ACI fabric should redirect the traffic by specifying the destination IP and MAC addresses. Since this configuration example uses the IP SLA Monitoring Policy, MAC address configuration is not mandatory.




Figure 451. ACI Site 1 L4-L7 Policy-Based Redirect Policy

To apply the service graph to the contract subject, right click on the graph template and choose “Apply L4-L7 Service Graph Template”.




Figure 452. Apply Service Graph Template

From the menu, choose a consumer ESG, a provider ESG and a contract subject. In this example, choose esg1 as consumer, esg2 as provider and choose esg1-esg2/ip from Existing Contracts subjects.

## Apply L4-L7 Service Graph Template to EPG/ESG(s)

### STEP 1 • Contract

Endpoint Group Type

Group Type: Endpoint Policy Group (EPG) Endpoint Security Group (ESG)

Endpoint Group Configuration

Configure an Intra-Endpoint Contract: ☐

Consumer ESG / External Network: bgw/ap1/esg-esg1 Provider ESG / Internal Network: bgw/ap1/esg-esg2

Contract Information

Contract Type: New Contract Select Existing Contract Subject

Existing Contracts with Subjects: esg1-esg2/ip

Previous Cancel Next


**Figure 453.** Choose ESGs and Contract subjects

Choose a service BD, a Redirect Policy and a Cluster interface for each connector: consumer and provider connector. In this example, choose bd-svc-site1 as the service BD, site1-fw-one-arm as the Redirect Policy and one-arm as the Cluster interface for both connectors.

## Apply L4-L7 Service Graph Template to EPG/ESG(s)

### STEP 2 • Graph

Service Graph Template: bgw/site1-graph




Previous Cancel Finish

**Figure 454.** Consumer connector configuration

## Apply L4-L7 Service Graph Template to EPG/ESG(s)

### STEP 2 • Graph

Service Graph Template: bgw/site1-graph



Previous Cancel Finish

**Figure 455.** Provider connector configuration

Once the configuration is complete, click Finish. A Deployed Graph Instance will appear in the Deploy Graph Instances menu; verify that the status is “Applied” and that no faults are present.




Figure 456. Deployed Graph Instance

As previously noted, service insertion is configured independently across ACI sites. The following screenshots show the corresponding configuration on ACI Site 2.




Figure 457. ACI Site 2 Service BD







Figure 458. ACI Site 2 Service Node




**Figure 459. ACI Site 2 Service Graph Template**




**Figure 460. ACI Site 2 IP SLA Monitoring Policy**




**Figure 461. ACI Site 2 L4-L7 Redirect Health Group**



**Figure 462. ACI Site 2 L4-L7 Policy-Based Redirect**



**Figure 463. Apply Service Graph site2-graph**



**Figure 464. Choose proper ESG and Contract subject**

Apply L4-L7 Service Graph Template to EPG/ESG(s)

#### STEP 2 • Graph

Service Graph Template: bgw/site2-graph

**Consumer**

EPG  
esg1

site2-fw  
N1

**Provider**

EPG  
esg2

**site2-fw Information**

Firewall: routed  
Policy-Based Redirect: true

**Consumer Connector**

Type: General Route Peering

BD: bgw/bd-svc-site2

L3 Destination (VIP): ☒

Redirect Policy: bgw/site2-fw-onearm

Service EPG Policy: select an option

Cluster Interface: onearm

**Provider Connector**

**Figure 465.** ACI Site 2 Consumer connector

Apply L4-L7 Service Graph Template to EPG/ESG(s)

#### STEP 2 • Graph

Service Graph Template: bgw/site2-graph

**Consumer**

EPG  
esg1

site2-fw  
N1

**Provider**

EPG  
esg2

**Service EPG Policy**

select an option

Cluster Interface: onearm

**Provider Connector**

Type: General Route Peering

BD: bgw/bd-svc-site2

L3 Destination (VIP): ☒

Redirect Policy: bgw/site2-fw-onearm

Service EPG Policy: select an option

Cluster Interface: onearm

1. Contract 2. Graph

Previous Cancel **Finish**

**Figure 466.** ACI Site 2 Provider connector click Finish to complete

**APIC (site2)**

System **Tenants** Fabric Virtual Networking Admin Operations Integrations

ALL TENANTS | Add Tenant | Tenant Search: name or descr | common | bgw | infra | queenstown | mgmt

**bgw**

- Quick Start
- bgw
  - Application Profiles
  - Networking
  - Contracts
  - Policies
  - Services
    - L4-L7
      - Service Graph Templates
      - Devices
      - Imported Devices
      - Devices Selection Policies
      - Deployed Graph Instances
        - esg1-esg2-site2-graph-vrf1
    - DNS Server Groups (Beta)


**Deployed Graph Instances**

| Service Graph | Contract  | Contained By         | State   |
|---------------|-----------|----------------------|---------|
| site2-graph   | esg1-esg2 | Private Network vrf1 | Applied |

**Figure 467.** ACI Site 2 Deployed Graph Instance


### Data Plane and Policy Verification

This section focuses on the verification process only for ACI Site 1 as the same principles apply to both ACI sites. The following figure illustrates the topology.




**Figure 468.** Firewall insertion topology example

The initial verification step is to confirm that the deployed graph instance is in “Applied” state without any faults.




**Figure 469.** Deploy Graph Instance in Applied state without any faults



**Figure 470.** Deployed graph instance without faults


The pcTag (class ID) of the service node connector can be verified under the Deployed Graph Instance. Since the service node uses a one-arm interface, both the consumer and provider connectors use the

same class ID. In this example, VLAN 240 is programmed on the ACI leaf interface that connects to the service node that is a virtual firewall running on top of a VMM domain integrated with ACI, and the VLAN is automatically programmed by the APIC. However, if the service node resides in a physical domain, the VLAN must be statically configured as part of the [L4-L7 device configuration](#).



**Figure 471.** ACI Site 1 Service Node connector class ID

Verify that the contract subject within the contract “esg1-esg2” has the right L4-L7 Service Graph attached.



**Figure 472.** ACI Site 1 Contract subject with service graph attached

Verify that the redirect zoning rules are programmed on the leaf switches to which the consumer or the provider endpoints are attached. In this example, 2162688 is the VRF vrf1 VNID, ESG esg1 class ID is 10947 and ESG esg2 class ID is 10948. Although the figure below shows the result for one direction from 10947 to 10948, a zoning-rule for the return direction, from 10948 to 10947, should also exist.

```
bgw-leaf1# show zoning-rule scope 2162688 src-epg 10947 dst-epg 10948
```

| Rule ID | SrcEPG | DstEPG | FilterID | Dir    | operSt  | Scope   | Name          | Action           | Priority      |
|---------|--------|--------|----------|--------|---------|---------|---------------|------------------|---------------|
| 4174    | 10947  | 10948  | 71       | bi-dir | enabled | 2162688 | bgw:esg1-esg2 | redir(destgrp-7) | fully_qual(7) |

**Figure 473.** ACI Site 1 Border Gateway zoning-rule with redirect action



In this example, 192.168.251.11 is the Service Node (Firewall) one-arm interface IP address. Verify that the “operSt” is “enabled”. Note that for inter-site traffic, the Border Gateway is responsible for the policy enforcement. Thus, the zoning-rule and reachability verification should be performed on the Border Gateway switches.

```
bgw-leaf1# show service redir info destination ip 192.168.251.11 vnid 2162688
```

| LEGEND                                |                     |                   |               |                  |               |                 |           |
|---------------------------------------|---------------------|-------------------|---------------|------------------|---------------|-----------------|-----------|
| TL: Threshold(Low)                    | TH: Threshold(High) | HP: HashProfile   | HG: HealthGrp | BAC: Backup-Dest | TRA: Tracking | RES: Resiliency | W: Weight |
| Name                                  | bdVnid              | vMac              | vrf           | operSt           | operStQual    | HG-name         |           |
| dest-[192.168.251.11]-[vxlan-2162688] | vxlan-15728624      | 00:50:56:BF:EC:ED | bgw:vrf1      | <b>enabled</b>   | no-oper-dest  | bgw:site1-HG    |           |

**Figure 474.** Service redirect on Border Gateway

To verify the data plane behavior, initiate ICMP traffic from endpoint 192.168.1.11 (ESG: esg1) in ACI Site 1 to endpoint 192.168.2.201 (ESG: esg2) in ACI Site 2. The expected behavior is that the traffic will be steered through the firewall.

```
cisco@aci-ubu-1:~$ ifconfig ens192
ens192: flags=4163<UP,BROADCAST,RUNNING,MULTICAST> mtu 1500
    inet 192.168.1.11 netmask 255.255.255.0 broadcast 192.168.1.255
    inet6 fe80::250:56ff:febf:7a53 prefixlen 64 scopeid 0x20<link>
    ether 00:50:56:bf:7a:53 txqueuelen 1000 (Ethernet)
    RX packets 9500806 bytes 916865928 (916.8 MB)
    RX errors 0 dropped 377 overruns 0 frame 0
    TX packets 10009224 bytes 955331964 (955.3 MB)
    TX errors 0 dropped 0 overruns 0 carrier 0 collisions 0

cisco@aci-ubu-1:~$
cisco@aci-ubu-1:~$ ping 192.168.2.201
PING 192.168.2.201 (192.168.2.201) 56(84) bytes of data:
64 bytes from 192.168.2.201: icmp_seq=1 ttl=56 time=1.26 ms
64 bytes from 192.168.2.201: icmp_seq=2 ttl=56 time=0.864 ms
64 bytes from 192.168.2.201: icmp_seq=3 ttl=56 time=0.971 ms
64 bytes from 192.168.2.201: icmp_seq=4 ttl=56 time=0.695 ms
64 bytes from 192.168.2.201: icmp_seq=5 ttl=56 time=0.737 ms
64 bytes from 192.168.2.201: icmp_seq=6 ttl=56 time=0.845 ms
```

**Figure 475.** Sending ICMP from 192.168.1.11 to 192.168.2.201

The capture command below is specific to Cisco ASA platforms; syntax for other firewall models may vary. In this example, the firewall is configured with a one-arm interface named “onearm”. As show in the Figure below, traffic is redirected to Site1-Firewall.

```
Site1-Firewall# capture in interface onearm real-time

Warning: using this option with a slow console connection may
result in an excessive amount of non-displayed packets
due to performance limitations.

Use ctrl-c to terminate real-time capture

1: 23:48:33.626066 192.168.1.11 > 192.168.2.201 icmp: echo request
2: 23:48:33.626096 192.168.1.11 > 192.168.2.201 icmp: echo request
3: 23:48:33.626783 192.168.2.201 > 192.168.1.11 icmp: echo reply
4: 23:48:33.626783 192.168.2.201 > 192.168.1.11 icmp: echo reply
5: 23:48:33.737632 192.168.251.254 > 192.168.251.11 icmp: echo request
6: 23:48:33.737785 192.168.251.11 > 192.168.251.254 icmp: echo reply
7: 23:48:33.738105 192.168.251.254 > 192.168.251.11 icmp: echo request
8: 23:48:33.738212 192.168.251.11 > 192.168.251.254 icmp: echo reply
9: 23:48:34.627286 192.168.1.11 > 192.168.2.201 icmp: echo request
10: 23:48:34.627317 192.168.1.11 > 192.168.2.201 icmp: echo request
11: 23:48:34.627820 192.168.2.201 > 192.168.1.11 icmp: echo reply
12: 23:48:34.627836 192.168.2.201 > 192.168.1.11 icmp: echo reply
13: 23:48:35.637402 192.168.1.11 > 192.168.2.201 icmp: echo request
14: 23:48:35.637433 192.168.1.11 > 192.168.2.201 icmp: echo request
15: 23:48:35.637921 192.168.2.201 > 192.168.1.11 icmp: echo reply
16: 23:48:35.637936 192.168.2.201 > 192.168.1.11 icmp: echo reply
```

**Figure 476.** Site 1 Firewall sees traffic in and out

In the Site 1 firewall capture output above, 192.168.251.254 is the service BD SVI that ACI Site 1 uses as the source IP to send continuous ICMP health probes to the firewall at 192.168.254.11, based on the intervals defined in the IP SLA Monitoring Policy.

Since the service graph is also applied in ACI Site 2, traffic is redirected to the Site2 firewall by Site 2 Border Gateway, as demonstrated in the captured traffic below:

```
Site2-Firewall# capture in interface onearm real-time

Warning: using this option with a slow console connection may
         result in an excessive amount of non-displayed packets
         due to performance limitations.

Use ctrl-c to terminate real-time capture

1: 23:53:30.377452      192.168.1.11 > 192.168.2.201 icmp: echo request
2: 23:53:30.377482      192.168.1.11 > 192.168.2.201 icmp: echo request
3: 23:53:30.377757      192.168.2.201 > 192.168.1.11 icmp: echo reply
4: 23:53:30.377772      192.168.2.201 > 192.168.1.11 icmp: echo reply
5: 23:53:31.401483      192.168.1.11 > 192.168.2.201 icmp: echo request
6: 23:53:31.401514      192.168.1.11 > 192.168.2.201 icmp: echo request
7: 23:53:31.401743      192.168.2.201 > 192.168.1.11 icmp: echo reply
8: 23:53:31.401758      192.168.2.201 > 192.168.1.11 icmp: echo reply
9: 23:53:32.275620      192.168.252.254 > 192.168.252.12 icmp: echo request
10: 23:53:32.275849      192.168.252.12 > 192.168.252.254 icmp: echo reply
11: 23:53:32.425515      192.168.1.11 > 192.168.2.201 icmp: echo request
12: 23:53:32.425545      192.168.1.11 > 192.168.2.201 icmp: echo request
13: 23:53:32.425759      192.168.2.201 > 192.168.1.11 icmp: echo reply
14: 23:53:32.425774      192.168.2.201 > 192.168.1.11 icmp: echo reply
15: 23:53:33.449515      192.168.1.11 > 192.168.2.201 icmp: echo request
16: 23:53:33.449546      192.168.1.11 > 192.168.2.201 icmp: echo request
17: 23:53:33.449760      192.168.2.201 > 192.168.1.11 icmp: echo reply
18: 23:53:33.449775      192.168.2.201 > 192.168.1.11 icmp: echo reply
```

**Figure 477.** Site 2 Firewall sees traffic in and out

In the Site 2 firewall capture output above, 192.168.252.254 is the service BD SVI that ACI Site 2 uses as the source IP to send continuous ICMP health probes to the firewall at 192.168.252.12, based on the intervals defined in the IP SLA Monitoring Policy.

## FAQ

Q. Can I connect my endpoints, such as servers or routers, directly to a Border Gateway?

A. At the time of writing up to ACI release 6.2(2), Border Gateway must be a dedicated device, you cannot connect endpoints like server, router to a Border Gateway. The requirement maybe relaxed in the future ACI release.

Q. Can I connect Border Gateways from ACI Site 1 directly to Border Gateways in ACI Site 2 using back-to-back connections?

A. No, it is not supported to use back-to-back connections, the ISN is required to interconnect Border Gateways across site. The requirement maybe relaxed in the future ACI release.

Q. Can I just use EPGs instead of ESGs?

A. No, it is required to use ESGs when extending a logical construct between ACI sites using Border Gateways. ESGs must be used for security group classification for policy enforcement whereas EPGs are used to enable the VLANs on the downlinks for endpoint connectivity.

Q. Is it mandatory to use the same ACI version between two ACI sites?

A. No, there is no version dependency between two ACI Sites.

Q. Can I share an ISN device with other networking functions?

A. Yes, you can share an ISN device with other networking functions. However, it is recommended to use a dedicated VRF for the Inter-Site function between ACI Border Gateways across sites.

Q. If I do not need intra-subnet communication across sites, and all communication is inter-subnet; do I need to stretch the BD across sites?

A. No, you do not need to stretch the BD in this scenario, local BDs should be deployed also on the site's BGWs to ensure EVPN Type-2 prefixes are advertised toward the remote sites.

Q. Can I use vzAny contract instead of specific contract?

A. Yes, you can use vzAny just like in a single ACI site; it represents all ESGs in a VRF and simplifies contract application across multiple sites.

Q. Does the solution support inter-tenant communication?

A. Yes, inter-tenant communication is supported. The use cases for intra-tenant inter-VRF communication are similarly supported in inter-tenant scenarios, enabling flexible policy enforcement and connectivity across tenants.

Document history

| New or Revised Topic | Described in  | Date              |
|----------------------|---------------|-------------------|
| First Release        | This document | September 2, 2026 |

Americas Headquarters  
Cisco Systems, Inc.  
San Jose, CA

Asia Pacific Headquarters  
Cisco Systems (USA) Pte. Ltd.  
Singapore

Europe Headquarters  
Cisco Systems International BV Amsterdam,  
The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at <https://www.cisco.com/go/offices>.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)