



Cisco HyperFlex Drive Compatibility Guide

First Published: 2020-01-31

Last Modified: 2024-01-17

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2020 –2024 Cisco Systems, Inc. All rights reserved.



CONTENTS

[Full Cisco Trademarks with Software License](#) ?

PREFACE

[Communications, Services, Bias-free Language, and Additional Information](#) v

CHAPTER 1

[New and Changed](#) 1

[New and Changed](#) 1

CHAPTER 2

[Overview](#) 3

[Overview](#) 3

CHAPTER 3

[Reading the Tables](#) 5

[Reading the Tables](#) 5

CHAPTER 4

[Drive Compatibility Matrix for Non-SED Nodes](#) 7

[Drive Compatibility Matrix for Non-SED Nodes](#) 7

CHAPTER 5

[Drive Compatibility Matrix for M4 SED Nodes](#) 25

[Drive Compatibility Matrix for M4 SED Nodes](#) 25

CHAPTER 6

[Drive Compatibility Matrix for M5/M6 SED Nodes](#) 29

[Drive Compatibility Matrix for M5/M6 SED Nodes](#) 29



Communications, Services, Bias-free Language, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions and services, visit [Cisco Marketplace](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.

Bias-Free Language

The documentation set for this product strives to use bias-free language. For purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on standards documentation, or language that is used by a referenced third-party product.



CHAPTER 1

New and Changed

- [New and Changed, on page 1](#)

New and Changed

Date	Description
January 2, 2024	Added support for the following: <ul style="list-style-type: none"> • HX-HD12T7KL4KM (5.0) • HX-M2-240G (5.0(2a)) • HX-M2-960G (5.0(2a)) • HX-SD16TBKANK9 (5.0(2a)+Catalog) • HX-SD38TBKANK9 (5.0(2a)+Catalog) • HX-SD76TBKANK9 (5.0(2a)+Catalog) • HX-SD16TKA3X-EP (5.0(2a)+Catalog) • HX-SD19TBM1X-EV (5.0(2a)) • HX-SD240GBM1X-EV (5.0(2a)+Catalog) • HX-SD32TKA3X-EP (5.0(2a)+Catalog) • HX-SD38TBM1X-EV (5.0(2a)) • HX-SD480GBM1X-EV (5.0(2a)) • HX-SD76TBM1X-EV (5.0(2a)) • HX-SD960GBM1X-EV (5.0(2a))
February 7, 2023	Update to show support for HX-SD38T6SB-EV.
January 31, 2023	Added HX-NVMEM6-W1600 (5.0(2b)) for HXAF220C-M5SN; HX-NVMEM6-W1600 (5.0(2b)) for HXAF220C-M6SN HXAF240C-M6SN.

Date	Description
September 13, 2022	Added HX-NVMEM6-W15300 for HXAF220C-M6SN; HXAF240C-M6SN.
July 8, 2022	Updated to add HX-SD960G6S1X-EV, HX-SD19T6S1X-EV, HX-SD38T6S1X-EV, HX-SD76T6S1X-EV.
December 9, 2021	Added support for SED drives qualified for 4.5(2b).
November 10, 2021	Added M6 PID information.
July 29, 2021	Updated to add HX-NVMEM6-W1600 qualified for 220/240 AF.Non-SED. Added example describing incompatible drives. Added Table of Contents.
May 27, 2021	Updated to add Non-SED drives qualified for 240 Full-Depth Hybrid Edge, 240 Full-Depth AF Edge.
April 29, 2021	Updated to add HX-SD16TK3X-EP, HX-SD19TBEM2NK9, HX-SD32TK3X-EP, HX-SD800GK3X-EP qualified for HX 4.5(1a)+Catalog, and HX-SD16TBHMK9 (4.0(2e)).
Jan 6, 2021	Updated to add HX-HD24T10NK9 qualified for HX 4.5(1a) 220 Hybrid and 240 Hybrid M5 SED Nodes.
July 13, 2020	Updated to add HX-SD16T123X-EP interop with HX-SD16TB12S3-EP. Also added new drives qualified for HX 4.0(2c).
April 21, 2020	Updated to add support for 7.6TB SSD on HX Edge configuration.
January 31, 2020	This document was introduced.



CHAPTER 2

Overview

- [Overview, on page 3](#)

Overview

For expansion of existing Cisco Hyperflex cluster it is very important to pay attention to the BOM / Configuration, especially the drives. Note that the estimates created via the Cisco Commerce website (CCW) checks for a valid configuration of the initial cluster. However, when ordering expansion nodes, CCW checks do not work, because CCW does not have any information about the drives previously ordered. This document is intended to communicate the compatibility of drives when expanding the cluster either through addition of new nodes or by adding data drives to existing nodes.



CHAPTER 3

Reading the Tables

- [Reading the Tables, on page 5](#)

Reading the Tables

HyperFlex currently does not support mixing of different server types in the same cluster. Each of the tables shows the compatible drives for a particular server version. The tables are designed to describe the compatible drive PIDS and specify the minimum HXDP release required to expand the cluster.

Table 1: Compatibility Table Example

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)
Drive Function: System Drive (Housekeeping)	
HX-SD120GBKS4-EB (2.5)	HX-SD240G61X-EV (2.6)
HX-SD120GBKS4-EV (1.8)	HX-SD240GM1X-EV (3.5)
HX-SD240GBKS4-EB (2.5)	
HX-SD240GBKS4-EV (1.8)	

Compatible Drives: Compatible drives listed in the same row and outlined in black are compatible with each other. In the Housekeeping example: HX-SD240G61X-EV and HX-SD240GM1X-EV are compatible with each and can be used on the same cluster at the same time. If the node takes more than one drive of this type (which is not the case with system drive), then you can use the mixed PID on the same node as well.

Each HyperFlex node requires several different types of drives to be functional. The drive function is indicated in the first column of the table.

Incompatible Drives: Drives listed in different rows are not compatible with each other. In the Capacity Drive (Data) example: a new node or added capacity drive with a cluster currently using drives HX-SD38TBE1NK9, is not compatible with drives HX-SD38TBHTNK9 or drives HX-SD38T2HTNK9, but is compatible with drive HX-SD38TBEM2NK9 in the same row only.

Table 2: Incompatible Drive Example

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)
Drive Function: System Drive (Housekeeping)	

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)
-	HX-SD38TBE1NK9 (2.6) HX-SD38TBEM2NK9 (4.0(2c))
-	HX-SD38TBHTNK9 (3.5(2a)) HX-SD38T2HTNK9 (4.0(2a))

Minimum HXDP Version: HX-SD240GM1X-EV (3.5) means this 240G Housekeeping drive support was added in HXDP release version 3.5. To expand a cluster with a node containing this drive, you must first upgrade to the minimum release (3.5(2e) in this case). The recommended HXDP release for different configurations can be found in the Recommended Cisco HyperFlex HX Data Platform Software Releases - for Cisco HyperFlex HX-Series Systems.

Compatibility Catalog : This new capability simplifies the introduction of new drives by allowing customers to perform an HX drive catalog-only upgrade to start consuming new drives and models introduced in the future, without requiring a HyperFlex Data Platform upgrade. Please note that you may need to update a separate UCS drive catalog as well. This ESXi feature is supported on PIDs identified with the minimum HXDP version+Catalog.



CHAPTER 4

Drive Compatibility Matrix for Non-SED Nodes

- [Drive Compatibility Matrix for Non-SED Nodes, on page 7](#)

Drive Compatibility Matrix for Non-SED Nodes

For details on how to read the table, see [Reading the Tables](#).

240 LFF

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
This configuration is not supported on the M4 platform.	HX240C-M5L	HX240C-M6L / UCSC-C240-M6L
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (3.0) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB HX-M2-960G (5.0(2a)) HX-M2-960GB
Drive Function: System Drive (Housekeeping)		
n/a	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240G61X-EV (3.0) HX-SD240GM1X-EV (3.5) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2a)) HX-SD480GM1X-EV (4.0(2a))	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240GM1X-EV (5.0(1a))
Drive Function: Capacity Drive (Data)		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
n/a	HX-HD6T7KL4KN (3.0)	HX-HD6T7KL4KM (5.0(1a)) HX-HD6T7KL4KN (5.0(1a))
n/a	HX-HD8T7K4KAN (4.0(2a)) HX-HD8T7KL4KN (3.0)	HX-HD8T7K4KAM (5.0(1a)) HX-HD8T7K4KAN (5.0(1a))
n/a	HX-HD12T7KL4KN (4.0(1a))	HX-HD12T7KL4KM (5.0(1a)) HX-HD12T7KL4KN (5.0(1a))
Drive Function: Cache Drive (Write Log)		
n/a	HX-SD32TKA3X-EP (5.0(2a)+Catalog) HX-SD32TK3X-EP (4.5(1a)+Catalog) HX-SD32T123X-EP (3.0)	HX-SD32TKA3X-EP (5.0(2a)+Catalog) HX-SD32TK3X-EP (5.0(1a))
Drive Function: Staging Drive		
n/a	HX-MSD-32G	-

220 Hybrid

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HX220C-M4S	HX220C-M5SX	HX220C-M6SX / UCSC-C220-M6S
Drive Function: Boot Drive		
HX-SD-32G-S	HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a)) HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6)	HX-M2-960G (5.0(2a)) HX-M2-960GB (5.0(1a)) HX-M2-240G (5.0(2a)) HX-M2-240GB (5.0(1a))
Drive Function: System Drive (Housekeeping)		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-SD240GBKS4-EV (1.8)	HX-SD480GM1X-EV (4.0(2a))	HX-SD480GBM1X-EV (5.0(2a))
HX-SD240GBKS4-EB (2.5)	HX-SD480GBM1X-EV (5.0(2a))	HX-SD480GM1X-EV (5.0(1a))
HX-SD120GBKS4-EV (1.8)	HX-SD480G6I1X-EV (4.0(2a))	HX-SD480G6I1X-EV (5.0(1a))
HX-SD120GBKS4-EB (2.5)	HX-SD240GBM1X-EV (5.0(2a)+Catalog)	HX-SD240GBM1X-EV (5.0(2a)+Catalog)
	HX-SD240GM1X-EV (3.5)	HX-SD240GM1X-EV (5.0(1a))
	HX-SD240G61X-EV (2.6)	
Drive Function: Capacity Drive (Data)		
HX-HD12TB10K12G (1.8)	HX-HD12TB10K12N (2.6)	HX-HD12TB10K12N (5.0(1a))
HX-HD18TB10KS4K (2.6)	HX-HD18TB10K4KN (2.6)	HX-HD18TB10K4KN (5.0(1a))
-	HX-HD24TB10K4KN (4.0)	HX-HD24TB10K4KN (5.0(1a))
Drive Function: Cache Drive (Write Log)		
HX-SD480G12S3-EP (1.8)	HX-SD800GK3X-EP (4.5(1a)+Catalog)	HX-SD800GK3X-EP (5.0(1a))
	HX-SD800G123X-EP (2.6)	HX-SD480G63X-EP (5.0(1a)+Catalog)
	HX-SD480G63X-EP (2.6)	
HX-SD800GSAS3-EP (2.5)	HX-SD800GK3X-EP (4.5(1a)+Catalog)	HX-SD800GK3X-EP (5.0(1a))
	HX-SD800G123X-EP (2.6)	
Drive Function: Staging Drive		
-	HX-MSD-32G (2.6)	-

240 Hybrid

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HX240C-M4SX	HX240C-M5SX	HX240C-M6SX / UCSC-C240-M6S / UCSC-C240-M6SX
Drive Function: Boot Drive		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-SD-32G-S	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB (5.0(1a)) HX-M2-960G (5.0(2a)) HX-M2-960GB (5.0(1a))
Drive Function: System Drive (Housekeeping)		
HX-SD120GBKS4-EB (2.1) HX-SD120GBKS4-EV (1.8) HX-SD240GBKS4-EB (2.1) HX-SD240GBKS4-EV (1.8)	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240G61X-EV (2.6) HX-SD240GM1X-EV (3.5) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2a)) HX-SD480GM1X-EV (4.0(2a))	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240GM1X-EV HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV HX-SD480GM1X-EV
Drive Function: Capacity Drive (Data)		
HX-HD12TB10K12G (1.8)	HX-HD12TB10K12N (2.6)	HX-HD12TB10K12N (5.0(1a))
HX-HD18TB10KS4K (2.6)	HX-HD18TB10K4KN (2.6)	HX-HD18TB10K4KN (5.0(1a))
-	HX-HD24TB10K4KN (4.0)	HX-HD24TB10K4KN (5.0(1a))
Drive Function: Cache Drive (Write Log)		
HX-SD16TB12S3-EP (1.8) HX-SD16TSASS3-EP (2.6)	HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD16T123X-EP (4.0(2c)) HX-SD16T63X-EP (2.6)	HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (5.0(1a))
Drive Function: Staging Drive		
-	HX-MSD-32G	-

220 Hybrid Edge

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HX220C-M4S	HX-E-220M5SX	HX-E-220M6SX / UCSC-C220-M6S

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Boot Drive		
HX-SD-32G-S	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB HX-M2-960G (5.0(2a)) HX-M2-960GB
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EV (1.8) HX-SD240GBKS4-EB (2.5) HX-SD120GBKS4-EB (2.5) HX-SD120GBKS4-EV (1.8) HX-SD240GM1X-EV (3.5)	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240G61X-EV (2.6) HX-SD240GM1X-EV (3.5) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2a)) HX-SD480GM1X-EV (4.0(2a))	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (5.0(1a)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (5.0(1a)) HX-SD480GM1X-EV (5.0(1a))
Drive Function: Capacity Drive (Data)		
HX-HD12TB10K12G (1.8)	HX-HD12TB10K12N (2.6)	HX-HD12TB10K12N (5.0(1a))
HX-HD18TB10KS4K (2.6)	HX-HD18TB10K4KN (2.6)	HX-HD18TB10K4KN (5.0(1a))
-	HX-HD24TB10K4KN (4.0)	HX-HD24TB10K4KN (5.0(1a))
Drive Function: Cache Drive (Write Log)		
HX-SD480G12S3-EP (1.8)	HX-SD480G63X-EP (2.6)	HX-SD480G63X-EP (5.0(1a))
HX-SD800GSAS3-EP (2.5)	HX-SD800GK3X-EP (4.5(1a)+Catalog) HX-SD800G123X-EP (2.6)	HX-SD800GK3X-EP (5.0(1a))
Drive Function: Staging Drive		
-	HX-MSD-32G	-

240 Hybrid Edge

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
This configuration is not supported on the M4 platform.	HX-E-240M5SX	HX-E-240M6SX / UCSC-C240-M6S / UCSC-C240-M6SX
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (4.5(1a)) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.5(1a))	HX-M2-240G (5.0(2a)) HX-M2-240GB (5.0(1a)) HX-M2-960G (5.0(2a)) HX-M2-960GB
Drive Function: System Drive (Housekeeping)		
n/a	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (4.5(1a)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.5(1a)) HX-SD480GM1X-EV (4.5(1a))	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (4.5(1a)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.5(1a)) HX-SD480GM1X-EV (4.5(1a))
Drive Function: Capacity Drive (Data)		
n/a	HX-HD12TB10K12N (4.5(1a))	HX-HD12TB10K12N (5.0(1a))
n/a	HX-HD18TB10K4KN (4.5(1a))	HX-HD18TB10K4KN (5.0(1a))
n/a	HX-HD24TB10K4KN (4.5(1a))	HX-HD24TB10K4KN (5.0(1a))
Drive Function: Cache Drive (Write Log)		
n/a	HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD16T123X-EP (4.5(1a))	HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (5.0(1a))
Drive Function: Staging Drive		
n/a	HX-MSD-32G	-

220 AF Edge

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HXAF220C-M4S	HXAF-E-220M5SX	HXAF-E-220M6SX / UCSC-C220-M6S
Drive Function: Boot Drive		
HX-SD-32G-S	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EB (2.5/2.1)	HX-SD240GBM1X-EV (5.0(2a))	HX-SD240GBM1X-EV (5.0(2a))
HX-SD240GBKS4-EV (2.0)	HX-SD240G61X-EV (2.6)	HX-SD240GM1X-EV
HX-SD120GBKS4-EB (2.5/2.1)	HX-SD240GM1X-EV (3.5)	HX-SD480GBM1X-EV (5.0(2a))
HX-SD120GBKS4-EV (2.0)	HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2a)) HX-SD480GM1X-EV (4.0(2a))	HX-SD480G6I1X-EV HX-SD480GM1X-EV
Drive Function: Capacity Drive (Data)		
HX-SD960GBKS4-EV (2.0)	HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (2.6) HX-SD960G6I1X-EV (3.5.2a) HX-SD960G6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (5.0) HX-SD960G6S1X-EV (5.0.1c) + catalog
	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (5.0.1c) + catalog
HX-SD38TBKS4-EV (2.0)	HX-SD38T6SB-EV (4.0(2c)) HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (2.6) HX-SD38T6I1X-EV (3.5.2a) HX-SD38T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD38T6SB-EV (5.0(2b)) HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (5.0) HX-SD38T6S1X-EV (5.0.1c) + catalog

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
-	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (4.0(2a)) HX-SD76T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (5.0) HX-SD76T6S1X-EV (5.0.1c) + catalog
Drive Function: Cache Drive (Write Log)		
HX-SD400G12S4-EP (2.0) HX-SD800G12S4-EP (2.0)	HX-SD400G12TX-EP (2.6) HX-SD16T123X-EP (3.5.2e, 4.0.1b) HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD800G123X-EP (4.0(2a)) HX-SD800GK3X-EP (4.5(1a)+Catalog)	HX-SD16TK3X-EP (5.0(1a)) HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (5.0(1a)) HX-SD800GK3X-EP (5.0(1a))
Drive Function: Staging Drive		
-	HX-MSD-32G	-

240 AF Edge

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
This configuration is not supported on the M4 platform.	HXAF-E-240M5SX	HXAF-E-240M6SX / UCSC-C240-M6S / UCSC-C240-M6SX
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (4.5(1a)) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.5(1a))	HX-M2-960G (5.0(2a)) HX-M2-960GB (5.0(1a)) HX-M2-240G (5.0(2a)) HX-M2-240GB (5.0(1a))
Drive Function: System Drive (Housekeeping)		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
n/a	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (4.5(1a)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.5(1a)) HX-SD480GM1X-EV (4.5(1a))	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV HX-SD480GM1X-EV
Drive Function: Capacity Drive (Data)		
n/a	HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (2.6) HX-SD960G6I1X-EV (3.5.2a) HX-SD960G6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (5.0) HX-SD960G6S1X-EV (5.0.1c) + catalog
n/a	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (4.0(2a)) HX-SD76T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (5.0) HX-SD76T6S1X-EV (5.0.1c) + catalog
n/a	HX-SD38T6SB-EV (4.0(2c)) HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (2.6) HX-SD38T6I1X-EV (3.5.2a) HX-SD38T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD38T6SB-EV (5.0(2b)) HX-SD38TBM1X-EV (5.0(2a)), HX-SD38T61X-EV (5.0) HX-SD38T6S1X-EV (5.0.1c) + catalog
n/a	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (5.0.1c) + catalog
Drive Function: Cache Drive (Write Log)		
n/a	HX-SD800G123X-EP (4.5(1a)) HX-SD16T123X-EP (4.5(1a)) HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD800GK3X-EP (4.5(1a)+Catalog)	HX-SD16TK3X-EP HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD800GS3X-EP (5.0(2a)) HX-SD800GK3X-EP (5.0(1a))

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Staging Drive		
n/a	HX-MSD-32G	-

240 Hybrid SD

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
This configuration is not supported on the M4 platform.	HXAF240C-M5SD	This configuration is not supported on the M6 platform.
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (4.0(2c)) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2c))	n/a
Drive Function: System Drive (Housekeeping)		
n/a	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (4.0(2c)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2c)) HX-SD480GM1X-EV (4.0(2c))	n/a
Drive Function: Capacity Drive (Data)		
n/a	HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (2.6) HX-SD38T6I1X-EV (3.5.2a) HX-SD38T6S1X-EV (4.5.2c), (5.0.1c) + catalog	n/a
n/a	HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (2.6) HX-SD960G6I1X-EV (3.5.2a) HX-SD960G6S1X-EV (4.5.2c), (5.0.1c) + catalog	n/a

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
n/a	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (4.0(2a)) HX-SD76T6S1X-EV (4.5.2c), (5.0.1c) + catalog	n/a
n/a	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (4.5.2c)(5.0.1c) + catalog	n/a
Drive Function: Cache Drive (Write Log)		
n/a	HX-SD800G123X-EP (4.0(2c)) HX-SD800GK3X-EP (4.5(1a)+Catalog) HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD16T123X-EP (4.0(2c))	
Drive Function: Staging Drive		
n/a	HX-MSD-32G	n/a

240 AF SD

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
This configuration is not supported on the M4 platform.	HX240C-M5SSD	This configuration is not supported on the M6 platform.
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (4.0(2c)) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2c))	n/a
Drive Function: System Drive (Housekeeping)		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
n/a	HX-SD240GBM1X-EV (5.0(2a)) HX-SD240GM1X-EV (4.0(2c)) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G611X-EV (4.0(2c)) HX-SD480GM1X-EV (4.0(2c))	n/a
Drive Function: Capacity Drive (Data)		
n/a	HX-HD12TB10K12N (4.0(2c))	n/a
n/a	HX-HD18TB10K4KN (4.0(2c))	n/a
n/a	HX-HD24TB10K4KN (4.0(2c))	n/a
Drive Function: Cache Drive (Write Log)		
n/a	HX-SD480G63X-EP (4.0(2c))	n/a
Drive Function: Staging Drive		
n/a	HX-MSD-32G	n/a

220AF / 240 AF

Note HX 5.0(2b) supports the ability to handle inter-operability of mixed cache drives on HyperFlex M5 and M6 AF clusters with certain hardware configurations: Existing 375G cluster expansion with 1.6TB; New cluster creation with two-step approach, (1) creation with minimum three 375G and (2) expansion with 1.6TB.

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HXAF220C-M4S	HXAF220C-M5SX	HXAF220C-M6SX (UCSC-C220-M6S)
HXAF240C-M4SX	HXAF240C-M5SX	-
Drive Function: Boot Drive		
HX-SD-32G-S	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB (2.6) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EV (2.0) HX-SD240GBKS4-EB (2.5/2.1) HX-SD120GBKS4-EV (2.0) HX-SD120GBKS4-EB (2.5/2.1)	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240G61X-EV (2.6) HX-SD240GM1X-EV (3.5) HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV (4.0(2a)) HX-SD480GM1X-EV (4.0(2a))	HX-SD240GBM1X-EV (5.0(2a)+Catalog) HX-SD240GM1X-EV HX-SD480GBM1X-EV (5.0(2a)) HX-SD480G6I1X-EV HX-SD480GM1X-EV
Drive Function: Capacity Drive (Data)		
HX-SD38TBKS4-EV (2.0)	HX-SD38T6SB-EV (4.0(2c)) HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (2.6) HX-SD960G6I1X-EV (3.5.2a) HX-SD960G6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD38T6SB-EV (5.0(2b)) HX-SD960GBM1X-EV (5.0(2a)) HX-SD960G61X-EV (5.0) HX-SD960G6S1X-EV (5.0.1c) + catalog
HX-SD960GBKS4-EV (2.0)	HX-SD19TBM1X-EV (5.0(2a)), HX-SD19T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD19TBM1X-EV (5.0(2a)) HX-SD19T6S1X-EV (5.0.1c) + catalog
-	HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (2.6) HX-SD38T6I1X-EV (3.5.2a) HX-SD38T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD38TBM1X-EV (5.0(2a)) HX-SD38T61X-EV (5.0) HX-SD38T6S1X-EV (5.0.1c) + catalog
-	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (4.0(2a)) HX-SD76T6S1X-EV (4.5.2c), (5.0.1c) + catalog	HX-SD76TBM1X-EV (5.0(2a)) HX-SD76T61X-EV (5.0) HX-SD76T6S1X-EV (5.0.1c) + catalog
Drive Function: Cache Drive (Write Log)		
HX-NVMEM4-H1600 (2.5)	HX-NVMEM6-W1600 (4.5(1a)+Catalog) HX-NVMEHW-H1600 (2.6)	HX-NVMEM6-W1600 (5.0(1a))

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-PCI25-40010 (2.5)	HX-NVMEM6-W1600 (4.5(1a)+Catalog) HX-NVMEHW-H1600 (2.6)	HX-NVMEM6-W1600 (5.0(1a))
HX-SD800G12S4-EP (2.0) HX-SD400G12S4-EP (2.0)	HX-SD16T123X-EP (3.5.2e, 4.0.1b) HX-SD16TKA3X-EP (5.0(2a)+Catalog) HX-SD16TK3X-EP (4.5(1a)+Catalog) HX-SD800GK3X-EP (4.5(1a)+Catalog) HX-SD800G123X-EP (4.0(2a)) HX-SD400G12TX-EP (2.6)	HX-SD800GK3X-EP (5.0)
-	HX-NVMEM6-W1600 (5.0(2b)) HX-NVMEXPB-I375 (3.5(2h), 4.0) HX-NVMEXP-I375 (3.0)	HX-NVMEM6-W1600 (5.0(2b)) HX-NVMEXP-I400 (5.0(2b)) HX-NVMEXPB-I375 (5.0(1a))
Drive Function: Staging Drive		
-	HX-MSD-32G	-

220 All NVMe



Note HX 5.0(2b) supports the ability to handle inter-operability of mixed cache drives on HyperFlex M5 and M6 All NVMe clusters with certain hardware configurations: Existing 375G cluster expansion with 1.6TB; New cluster creation with two-step approach, (1) creation with minimum three 375G and (2) expansion with 1.6TB.



Note HX 5.0(1a) supports the ability to handle inter-operability of mixed capacity drives on HyperFlex M5 and M6 clusters with certain variance, on the following hardware configurations: 960 and 1TB (220 All NVMe M6 only), 3.8 and 4TB (220 All NVMe M5 and M6) and 7.6 and 8TB (220 All NVMe M5 & M6).

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	HXAF220C-M6SN / UCSC-C220-M6N
Drive Function: Server PID		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	HXAF220C-M6SN / UCSC-C220-M6N
This configuration is not supported on the M4 platform.	HXAF220C-M5SN	
Drive Function: Boot Drive		
n/a	HX-M2-240G (5.0(2a)) HX-M2-240GB (4.0.1a) HX-M2-960G (5.0(2a)) HX-M2-960GB (4.0(2a))	HX-M2-240G (5.0(2a)) HX-M2-240GB, HX-M2-960G (5.0(2a)) HX-M2-960GB
Drive Function: System Drive (Housekeeping)		
n/a	HX-NVMELW-I500 (4.0) HX-NVME2H-I1000 (4.0.1b)	HX-NVME4-1920 (5.0(2b)) UCS-NVMEI4-I1920 (5.0(1a)) HX-NVME2H-I1000 (5.0(2b))
Drive Function: Capacity Drive (Data)		
n/a	HX-NVMEHW-I1000 (4.0) HX-NVME2H-I1000 (4.0.2a)	HX-NVME2H-I1000 (5.0)
n/a	HX-NVMEHW-I4000 (4.0) HX-NVME2H-I4000 (4.0.2a) HX-NVME4-3840 (5.0(2b))	HX-NVMEI4-I1920 HX-NVME4-1920 (5.0(2b)) HX-NVME4-3840 (5.0(2b))
n/a	HX-NVMEHW-I8000 (4.0(2a)) HX-NVME4-7680 (5.0(2b))	HX-NVME2H-I4000 HX-NVMEI4-I3840 HX-NVME4-3840 (5.0(2b)) HX-NVME4-7680 (5.0(2b))
n/a	-	HX-NVMEHW-I8000 HX-NVMEI4-I7680 HX-NVME4-7680 (5.0(2b)) HX-NVME4-1920 (5.0(2b))
n/a	-	HX-NVMEM6-W15300 (5.0(2a)) HX-NVME4-15360 (5.0(2b) + Catalog)
Drive Function: Cache Drive (Write Log)		

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	HXAF220C-M6SN / UCSC-C220-M6N
n/a	HX-NVMEM6-W1600 (5.0(2b)) HX-NVMEXPB-I375 (4.0) HX-NVMEXP-I375 (4.0)	HX-NVMEM6-W1600 (5.0(2b)) HX-NVMEXP-I400 (5.0(2b)) HX-NVMEXPB-I375 (5.0(1a))
Drive Function: Staging Drive		
n/a	HX-MSD-32G	-

240 All NVMe



Note HX 5.0(2b) supports the ability to handle inter-operability of mixed cache drives on HyperFlex M5 and M6 All NVMe clusters with certain hardware configurations: Existing 375G cluster expansion with 1.6TB; New cluster creation with two-step approach, (1) creation with minimum three 375G and (2) expansion with 1.6TB.

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
This configuration is not supported on the M4 platform.	This configuration is not supported on the M5 platform.	HXAF240C-M6SN / UCSC-C240-M6N / UCSC-C240-M6SN
Drive Function: Boot Drive		
n/a	n/a	HX-M2-240G HX-M2-240GB HX-M2-960G HX-M2-960GB
Drive Function: System Drive (Housekeeping)		
n/a	n/a	UCS-NVMEI4-I1920 HX-NVME4-1920 (5.0(2b)) HX-NVME2H-I1000 (5.0(1a))
Drive Function: Capacity Drive (Data)		
n/a	n/a	HX-NVMEI4-I1920 (5.0(1a)) HX-NVME4-1920 (5.0(2b))
n/a	n/a	HX-NVME4-3840 (5.0(2b)) HX-NVMEI4-I3840 (5.0(1a))

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
n/a	n/a	HX-NVME4-7680 (5.0(2b)) HX-NVMEI4-I7680 (5.0(1a))
n/a	n/a	HX-NVME4-15360 (5.0(2b) + Catalog) HX-NVMEM6-W15300 (5.0(2a))
Drive Function: Cache Drive (Write Log)		
n/a	n/a	HX-NVMEM6-W1600 (5.0(2b)) HX-NVMEXP-I400 (5.0(2b)) HX-NVMEXPB-I375 (5.0(1a))
Drive Function: Staging Drive		
n/a	n/a	-



CHAPTER 5

Drive Compatibility Matrix for M4 SED Nodes

- [Drive Compatibility Matrix for M4 SED Nodes, on page 25](#)

Drive Compatibility Matrix for M4 SED Nodes

For details on how to read the table, see [Reading the Tables](#).



Note This chapter applies to customers running HXDP Release 5.0(x) or earlier.

240 LFF

SED configurations are not supported on M5 and M6.

220 Hybrid

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HX220C-M4S	M4 SED Cluster expansion using M5 SED nodes is not supported at this time.	M4 SED Cluster expansion using M6 SED nodes is not supported at this time.
Drive Function: Boot Drive		
HX-SD-32G-S	n/a	n/a
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EV HX-SD240GBKS4-EB HX-SD120GBKS4-EV HX-SD120GBKS4-EB	n/a	n/a

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Capacity Drive (Data)		
HX-HD12G10K9 (2.1)	n/a	n/a
Drive Function: Cache Drive (Write Log)		
HX-SD800GBEK9 (2.1)	n/a	n/a
Drive Function: Staging Drive		
-	-	-

240 Hybrid

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HX240C-M4SX	M4 SED Cluster expansion using M5 SED nodes is not supported at this time.	M4 SED Cluster expansion using M6 SED nodes is not supported at this time.
Drive Function: Boot Drive		
HX-SD-32G-S	n/a	n/a
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EV HX-SD240GBKS4-EB HX-SD120GBKS4-EV HX-SD120GBKS4-EB	n/a	n/a
Drive Function: Capacity Drive (Data)		
HX-HD12G10K9 (2.1)	n/a	n/a
Drive Function: Cache Drive (Write Log)		
HX-SD16TBK9 (2.1)	n/a	n/a
Drive Function: Staging Drive		
-	n/a	n/a

220 Hybrid Edge

SED configurations are not supported on M5 and M6.

240 Full-Depth Hybrid Edge

SED configurations are not supported on M5 and M6.

220 AF Edge

SED configurations are not supported on M5 and M6.

240 Full-Depth AF Edge

SED configurations are not supported on M5 and M6.

220 AF / 240 AF

Current M4 PID (Min HXDP Version)	M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID		
HXAF240C-M4SX HXAF220C-M4S	M4 SED Cluster expansion using M5 SED nodes is not supported at this time.	M4 SED Cluster expansion using M6 SED nodes is not supported at this time.
Drive Function: Boot Drive		
HX-SD-32G-S	n/a	n/a
Drive Function: System Drive (Housekeeping)		
HX-SD240GBKS4-EV HX-SD240GBKS4-EB HX-SD120GBKS4-EV HX-SD120GBKS4-EB	n/a	n/a
Drive Function: Capacity Drive (Data)		
HX-SD38TBM1K9 (2.5)	n/a	n/a
HX-SD800GBEK9 (2.1)	n/a	n/a
HX-SD960GBM1K9 (2.5)	n/a	n/a
Drive Function: Cache Drive (Write Log)		
HX-SD800GBEK9 (2.1)	n/a	n/a
Drive Function: Staging Drive		
-	n/a	n/a

220 NVMe

SED configurations are not supported on M5 and M6.



CHAPTER 6

Drive Compatibility Matrix for M5/M6 SED Nodes

- [Drive Compatibility Matrix for M5/M6 SED Nodes, on page 29](#)

Drive Compatibility Matrix for M5/M6 SED Nodes

For details on how to read the table, see [Reading the Tables](#).



Note M4 SED Cluster expansion using M5 SED nodes is not supported at this time.

240 LFF

SED configurations are not supported on M5 and M6.

220 Hybrid

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID	
HX220C-M5SX	HX220C-M6SX / UCSC-C220-M6S
Drive Function: Boot Drive	
HX-M2-240G (5.0(2a))	HX-M2-240G (5.0(2a))
HX-M2-240GB (5.0(1a))	HX-M2-240GB (5.0(1a))
HX-M2-960G (5.0(2a))	HX-M2-960G (5.0(2a))
HX-M2-960GB (4.0(2a))	HX-M2-960GB (5.0(1a))
Drive Function: System Drive (Housekeeping)	

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-SD480G611X-EV (4.0(2a))	HX-SD480GM1X-EV (5.0(1a))
HX-SD480GM1X-EV (4.0(2a))	HX-SD480G611X-EV (5.0(1a))
HX-SD240GBM1X-EV (5.0(2a)+Catalog)	HX-SD240GBM1X-EV (5.0(2a)+Catalog)
HX-SD240GM1X-EV (3.5)	HX-SD240GM1X-EV (5.0(1a))
HX-SD240G61X-EV (2.6)	
Drive Function: Capacity Drive (Data)	
HX-HD12T10NK9 (2.6)	HX-HD12T10NK9 (5.0(1a))
HX-HD24T10NK9 (4.5(1a))	HX-HD24T10NK9 (5.0(1a))
Drive Function: Cache Drive (Write Log)	
HX-SD800GBKNK9 (4.5(2b))	HX-SD800GBKNK9 (5.0(1a))
HX-SD800GBHMK9 (4.0)	
HX-SD800GBENK9 (2.6)	
Drive Function: Staging Drive	
HX-MSD-32G	-

240 Hybrid

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID	
HX240C-M5SX	HX240C-M6SX / UCSC-C240-M6S / UCSC-C240-M6SX
Drive Function: Boot Drive	
HX-M2-240G (5.0(2a))	HX-M2-240G (5.0(2a))
HX-M2-240GB (5.0(1a))	HX-M2-240GB (5.0(1a))
HX-M2-960G (5.0(2a))	HX-M2-960G (5.0(2a))
HX-M2-960GB (4.0(2a))	HX-M2-960GB (5.0(1a))
Drive Function: System Drive (Housekeeping)	
HX-SD480G611X-EV (4.0(2a))	HX-SD480GM1X-EV (5.0(1a))
HX-SD480GM1X-EV (4.0(2a))	HX-SD480G611X-EV (5.0(1a))
HX-SD240GBM1X-EV (5.0(2a)+Catalog)	HX-SD240GBM1X-EV (5.0(2a)+Catalog)
HX-SD240GM1X-EV (3.5)	HX-SD240GM1X-EV (5.0(1a))
HX-SD240G61X-EV (2.6)	

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Capacity Drive (Data)	
HX-HD12T10NK9 (2.6)	HX-HD12T10NK9 (5.0(1a))
HX-HD24T10NK9 (4.5(1a))	HX-HD24T10NK9 (5.0(1a))
Drive Function: Cache Drive (Write Log)	
HX-SD16TBKANK9 (5.0(2a)+Catalog)	HX-SD16TBKANK9 (5.0(2a)+Catalog)
HX-SD16TBKKNK9 (4.5(2b))	HX-SD16TBKKNK9 (5.0(1a))
HX-SD16TBHKNK9 (4.0.2e)	
HX-SD16TBENK9 (2.6)	
Drive Function: Staging Drive	
HX-MSD-32G	

220 Hybrid Edge

SED configurations are not supported on M5 and M6.

240 Full-Depth Hybrid Edge

SED configurations are not supported on M5 and M6.

220 AF Edge

SED configurations are not supported on M5 and M6.

240 Full-Depth AF Edge

SED configurations are not supported on M5 and M6.

220 AF / 240 AF

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
Drive Function: Server PID	
HXAF220C-M5SX	HXAF220C-M6SX (UCSC-C220-M6S)
HXAF240C-M5SX	HXAF240C-M6SX (UCSC-C240-M6S / UCSC-C240-M6SX)
Drive Function: Boot Drive	

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-M2-240G (5.0(2a))	HX-M2-240G (5.0(2a))
HX-M2-240GB	HX-M2-240GB
HX-M2-960G (5.0(2a))	HX-M2-960G (5.0(2a))
HX-M2-960GB (4.0(2a))	HX-M2-960GB
Drive Function: System Drive (Housekeeping)	
HX-SD240GBM1X-EV (5.0(2a)+Catalog)	HX-SD240GBM1X-EV (5.0(2a)+Catalog)
HX-SD240G61X-EV (2.6)	HX-SD240GM1X-EV
HX-SD240GM1X-EV (3.5)	HX-SD480G61X-EV (5.0(1a))
HX-SD480G61X-EV (4.0(2a))	HX-SD480GM1X-EV (5.0(1a))
HX-SD480GM1X-EV (4.0(2a))	
Drive Function: Capacity Drive (Data)	
HX-SD76TBKANK9 (5.0(2a)+Catalog)	HX-SD76TBKANK9 (5.0(2a)+Catalog)
HX-SD76TEM2NK9 (5.0(2a)+Catalog) ¹	HX-SD76TEM2NK9 (5.0(2a)+Catalog) ²
HX-SD76TBEM2NK9 (4.0.2c)	HX-SD76TBEM2NK9 (5.0(1a))
HX-SD76TBKNK9 (5.0)	HX-SD76TBKNK9 (5.0(1a))
HX-SD38TBKANK9 (5.0(2a)+Catalog)	HX-SD38TBKANK9 (5.0(2a)+Catalog)
HX-SD38TEM2NK9 (5.0(2a)+Catalog)	HX-SD38TEM2NK9 (5.0(2a)+Catalog)
HX-SD38TBKNK9 (4.5.2b + catalog)	HX-SD38TBKNK9 (5.0(1a))
HX-SD38TBEM2NK9 (4.0(2c))	HX-SD38TBEM2NK9 (5.0(1a))
HX-SD38T2HTNK9 (4.0(2a))	
HX-SD38TBHTNK9 (3.5(2a))	
HX-SD38TBE1NK9 (2.6)"	
HX-SD960GM2NK9 (5.0(2a)+Catalog)	HX-SD960GM2NK9 (5.0(2a)+Catalog)
HX-SD960GBKNK9 (4.5(2a)+catalog)	HX-SD960GBKNK9 (5.0(1a))
HX-SD960GBM2NK9 (4.0(2c))	HX-SD960GBM2NK9 (5.0(1a))
HX-SD960G2HTNK9 (4.0(2a))	
HX-SD960GBHTNK9 (3.5(2a))	
HX-SD960GBE1NK9 (2.6)	
HX-SD19TEM2NK9 (5.0(2a)+Catalog)	-
HX-SD19TBEM2NK9 (4.5(1a)+Catalog)	
Drive Function: Cache Drive (Write Log)	

M5 Expansion PID (Min HXDP Version)	M6 PID (Min HXDP Version)
HX-SD800GBKNK9 (4.5(2b)) HX-SD800GBHNK9 (3.5(2g), 4.0(2a)) HX-SD800GBENK9 (2.6)	HX-SD800GBKNK9 (5.0(1a))
Drive Function: Staging Drive	
HX-MSD-32G (4.5(2b))	-

¹ Some workloads may impact performance by 10-15%.

² Some workloads may impact performance by 10-15%.

220 All NVMe

SED configurations are not supported on M5 and M6.

