



CBQoS MIB Index Enhancements

Last Updated: June 21, 2011

The Class-Based Quality of Service (CBQoS) MIB Index Enhancements feature introduces persistence across all CBQoS MIB indexes including cbQosConfigIndex, cbQosObjectsIndex, and cbQosPolicyIndex.

- [Finding Feature Information, page 1](#)
- [Prerequisites for the CBQoS MIB Index Enhancements, page 1](#)
- [Restrictions for the CBQoS MIB Index Enhancements, page 2](#)
- [Information About the CBQoS MIB Index Enhancements, page 2](#)
- [How to Configure the CBQoS MIB Index Enhancements, page 3](#)
- [Configuration Examples for the CBQoS MIB Index Enhancements, page 5](#)
- [Additional References, page 5](#)
- [Command Reference, page 6](#)
- [Feature Information for the CBQoS MIB Index Enhancements, page 7](#)
- [, page 7](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the Feature Information Table at the end of this document.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Prerequisites for the CBQoS MIB Index Enhancements

- Simple Network Management Protocol (SNMP) must be installed and enabled on the label switch routers (LSRs).
- You must enable ifMIB persistence by issuing the **snmp-server ifindex persist** command. Then issue the **snmp mib persist cbqos** command to enable CBQoS MIB index persistence.

**Note**

If you issue the **snmp mib persist cbqos** command before the **snmp-server ifindex persist** command, you receive a prompt requesting you to enable ifIndex persistence first.

Restrictions for the CBQoS MIB Index Enhancements

If the internal hashing of configuration strings causes too many collisions, NVRAM storage may become tight. You can issue the **more nvram** command to display a new collision file called `cbqos-mib` to help you keep track of the size.

Information About the CBQoS MIB Index Enhancements

- [Feature Overview of the CBQoS MIB Index Enhancements, page 2](#)
- [Benefits of the CBQoS MIB Index Enhancements, page 2](#)

Feature Overview of the CBQoS MIB Index Enhancements

The `cbQosConfigIndex`, `cbQosObjectsIndex`, and `cbQosPolicyIndex` are volatile because when a networking device reboots, the index numbers may change. This happens because system rebooting can cause the order of the Modular QoS CLI (MQC) configuration to differ from the actual configuration order, which is user-driven and unpredictable. As a result, you must read the MIB frequently to extract statistical and configuration information. Therefore, once a reload has occurred, the MIB has to be repopulated to reestablish the indexes to the data stored in the CBQoS MIB.

Traditionally, MIB persistence is handled by Cisco IOS APIs, which save the index and key information to NVRAM. The data is then retrieved and repopulated after reloading. However, this approach does not work well for the current implementation of the `cbQosObjectsIndex` because of the large amount of information that needs to be saved.

An index encoding scheme based on configuration entries instead of operational sequence is being implemented to provide persistent indexes on router reload so that MIB information retains the same set of object values each time that a networking device reboots.

Benefits of the CBQoS MIB Index Enhancements

These enhancements provide a repeatable method for generating MIB indexes so that they do not change between reboots.

The complexity of configuring and correlating statistics objects is reduced, making it easier for network management applications to gather accurate information.

You do not need to make any changes to your Network Management Station (NMS) software since this feature is an infrastructure improvement that is backward compatible with older MIBs.

How to Configure the CBQoS MIB Index Enhancements

- [Enabling Cisco IOS MIB and CBQoS MIB Index Persistence, page 3](#)
- [Verifying CBQoS MIB Index Persistence, page 4](#)

Enabling Cisco IOS MIB and CBQoS MIB Index Persistence

write

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **snmp-server ifindex persist**
4. **snmp mib persist [event | expression | circuit| cbqos]**
5. **end**
6. write mib-data

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	snmp-server ifindex persist Example: Router(config)# snmp-server ifindex persist	Enables Cisco IOS MIB index (ifIndex) persistence.
Step 4	snmp mib persist [event expression circuit cbqos] Example: Router(config)# snmp mib persist cbqos	Enables MIB persistence. <ul style="list-style-type: none"> • The optional event keyword enables Event MIB persistence. • The optional expression keyword enables Expression MIB persistence. • The optional circuit keyword enables Circuit MIB persistence. • The optional cbqos keyword enables CBQoS MIB persistence.

	Command or Action	Purpose
		Note If you have not enabled Cisco IOS MIB index (ifIndex) persistence (Step 3), the following message appears when you issue the snmp mib persist cbqos command: Enable 'snmp-server ifindex persist' for persist cbqos index
Step 5	end Example: Router(config)# end	Returns to privileged EXEC mode.
Step 6	write mib-data Example: write Example: Router# write mib-data Example: Router# write	Saves CBQoS MIB data to NVRAM.

Verifying CBQoS MIB Index Persistence

SUMMARY STEPS

1. enable
2. show running-config include cbqos
3. exit

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	show running-config include cbqos Example: Router# show running-config include cbqos	Displays the configuration information currently running on the router. Note The information should include snmp mib persist cbqos.
Step 3	exit	Returns to user EXEC mode.

	Command or Action	Purpose
	Example: Router# exit	

Configuration Examples for the CBQoS MIB Index Enhancements

- [Example Enabling Cisco IOS MIB and CBQoS MIB Index Persistence, page 5](#)
- [Examples Verifying Cisco IOS MIB and CBQoS MIB Index Persistence, page 5](#)

Example Enabling Cisco IOS MIB and CBQoS MIB Index Persistence

The following example enables Cisco IOS MIB (ifIndex) and CBQoS MIB index persistence:

```
Router# configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)# snmp-server ifindex persist
Router(config)# snmp mib persist cbqos
```

Examples Verifying Cisco IOS MIB and CBQoS MIB Index Persistence

The following examples verify that Cisco IOS MIB (ifIndex) and CBQoS MIB index persistence have been configured:

```
Router# show running-config
| include cbqos
snmp mib persist cbqos
Router# show running-config
| include persist
snmp-server ifindex persist
snmp mib persist cbqos
```

Additional References

The following sections provide references related to the CBQoS MIB Index Enhancements.

Related Documents

Related Topic	Document Title
SNMP commands	<i>Cisco IOS Network Management Command Reference</i>
SNMP configuration tasks, MIB persistence	"Configuring SNMP Support" module

Related Topic	Document Title
Other documentation	For information on using SNMP MIB features, see the appropriate documentation for your network management system.

Standards

Standard	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	--

MIBs

MIB	MIBs Link
CISCO-CLASS-BASED-QOS-MIB, Revision 13 Note The CISCO-CLASS-BASED-QOS-MIB is actually two MIBs: the CISCO-CLASS-BASED-QOS-MIB and the CISCO-CLASS-BASED-QOS-CAPABILITY-MIB.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFC	Title
RFC 2233	The Interfaces Group MIB using SMIV2

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Command Reference

The following commands are introduced or modified in the feature or features documented in this module. For information about these commands, see the *Cisco IOS Quality of Service Solutions Command Reference* at http://www.cisco.com/en/US/docs/ios/qos/command/reference/qos_book.html . For

information about all Cisco IOS commands, use the Command Lookup Tool at <http://tools.cisco.com/Support/CLILookup> or a Cisco IOS master commands list.

- `snmp mib persist`

Feature Information for the CBQoS MIB Index Enhancements

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 1: Feature Information for the CBQoS MIB Index Enhancements

Feature Name	Releases	Feature Information
CBQoS MIB Index Enhancements	12.4(4)T, 12.0(32)S, 12.2(31)SB2	<p>The CBQoS MIB Index Enhancements feature introduces persistence across all CBQoS MIB indexes including <code>cbQosConfigIndex</code>, <code>cbQosObjectsIndex</code>, and <code>cbQosPolicyIndex</code>.</p> <p>In 12.4(4)T, this feature was introduced.</p> <p>In 12.0(32)S, this feature was integrated into the release.</p> <p>In 12.2(31)SB2, support for the Cisco 10000 Series routers and the Cisco 7304 router was introduced.</p>

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.