



Configuring RTP Header Compression

First Published: January 30, 2006

Last Updated: July 23, 2010

Header compression is a mechanism that compresses the IP header in a packet before the packet is transmitted. Header compression reduces network overhead and speeds up the transmission of either Real-Time Transport Protocol (RTP) or Transmission Control Protocol (TCP) packets.

Cisco provides two types of header compression: RTP header compression and TCP header compression. This module describes the concepts and tasks related to configuring RTP header compression.



Note RTP header compression is configured on a per-interface (or subinterface) basis. If you want to configure RTP header compression on a per-class basis, see the “[Configuring Class-Based RTP and TCP Header Compression](#)” module.

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the “[Feature Information for Configuring RTP Header Compression](#)” section on page 22.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.

Contents

- [Prerequisites for Configuring RTP Header Compression, page 2](#)
- [Information About Configuring RTP Header Compression, page 2](#)
- [How to Configure RTP Header Compression, page 5](#)
- [Configuration Examples for RTP Header Compression, page 15](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

■ Prerequisites for Configuring RTP Header Compression

- Additional References, page 18
- Glossary, page 20
- Feature Information for Configuring RTP Header Compression, page 22

Prerequisites for Configuring RTP Header Compression

- Before configuring RTP header compression, read the information in the “[Header Compression](#)” module.
- You must configure RTP header compression on both ends of the network.

Information About Configuring RTP Header Compression

Before configuring RTP header compression, you should understand the following concepts:

- [Configurable RTP Header-Compression Settings, page 2](#)
- [RTP Header-Compression Keywords, page 3](#)
- [Enhanced RTP Header Compression, page 4](#)
- [RTP Header Compression over Satellite Links, page 4](#)

Configurable RTP Header-Compression Settings

With RTP header compression, you can configure the maximum size of the compressed IP header, the maximum time between transmitting full-header packets, and the maximum number of compressed packets between full headers. These settings are configured using the following three commands:

- **ip header-compression max-header**
- **ip header-compression max-time**
- **ip header-compression max-period**

The **ip header-compression max-header** command allows you to define the maximum size of the IP header of a packet to be compressed. Any packet with an IP header that exceeds the maximum size is sent uncompressed.

The **ip header-compression max-time** command allows you to specify the maximum time between transmitting full-header packets, and the **ip header-compression max-period** command allows you to specify the maximum number of compressed packets between full headers. With the **ip header-compression max-time** and **ip header-compression max-period** commands, the full-header packet is transmitted at the specified time period or when the maximum number of packets is reached, respectively. The counters for both the time period and the number of packets sent are reset after the full-header packet is sent.

For more information about these commands, see the [Cisco IOS Quality of Service Solutions Command Reference](#).

RTP Header-Compression Keywords

When you configure RTP header compression, you can specify the circumstances under which the RTP packets are compressed and the format that is used when the packets are compressed. These circumstances and formats are defined by the following keywords:

- **passive**
- **iphc-format**
- **ietf-format**

These keywords (described below) are available with many of the quality of service (QoS) commands used to configure RTP header compression, such as the **ip rtp header-compression** command. For more information about the **ip rtp header-compression** command, these keywords, and the other QoS commands, see the *Cisco IOS Quality of Service Solutions Command Reference*.

The **passive** Keyword

By default, the **ip rtp header-compression** command compresses outgoing RTP traffic. If you specify the **passive** keyword, outgoing RTP traffic is compressed only if *incoming* RTP traffic on the *same* interface is compressed. If you do not specify the **passive** keyword, *all* outgoing RTP traffic is compressed.

The **passive** keyword is ignored on PPP interfaces.

The **iphc-format** Keyword

The **iphc-format** keyword indicates that the IP Header Compression (IPHC) format of header compression will be used. For PPP and HDLC interfaces, when the **iphc-format** keyword is specified, TCP header compression is also enabled. Since both RTP and TCP header compression are enabled, both UDP and TCP packets are compressed.

The **iphc-format** keyword includes checking whether the destination port number is even and is in the ranges of 16,385 to 32,767 (for Cisco audio) or 49,152 to 65,535 (for Cisco video). Valid RTP packets that meet the criteria (that is, the port number is even and is within the specified range) are compressed using the compressed RTP packet format. Otherwise, packets are compressed using the less-efficient compressed non-TCP packet format.

The **iphc-format** keyword is not available for interfaces that use Frame Relay encapsulation.



Note

The header compression format (in this case, IPHC) must be the same at *both* ends of the network. That is, if you specify the **iphc-format** keyword on the local router, you must also specify the **iphc-format** keyword on the remote router.

The **ietf-format** Keyword

The **ietf-format** keyword indicates that the Internet Engineering Task Force (IETF) format of header compression will be used. For HDLC interfaces, the **ietf-format** keyword compresses only UDP packets. For PPP interfaces, when the **ietf-format** keyword is specified, TCP header compression is also enabled. Since both RTP header compression and TCP header compression are enabled, both UDP packets and TCP packets are compressed.

With the **ietf-format** keyword, any even destination port number higher than 1024 can be used. Valid RTP packets that meet the criteria (that is, the port number is even and is higher than 1024) are compressed using the compressed RTP packet format. Otherwise, packets are compressed using the less-efficient compressed non-TCP packet format.

The **ietf-format** keyword is not available for interfaces that use Frame Relay encapsulation.

**Note**

The header compression format (in this case, IETF) must be the same at *both* ends of the network. That is, if you specify the **ietf-format** keyword on the local router, you must also specify the **ietf-format** keyword on the remote router.

Enhanced RTP Header Compression

The Cisco IOS Release 12.3(11)T introduced a feature that enhances the functionality of RTP header compression. This feature is called Enhanced CRTP for Links with High Delay, Packet Loss, and Reordering (ECRTP).

The ECRTP feature is also known as Enhanced RTP Header Compression. It includes modifications and enhancements to RTP header compression to achieve robust operation over unreliable point-to-point links. This is accomplished by repeating updates and sending absolute (uncompressed) values in addition to delta values for selected context parameters.

During compression of an RTP stream, a session context is defined. For each context, the session state is established and shared between the compressor and the decompressor. The context state consists of the full IP/UDP/RTP headers, a few first-order differential values, a link sequence number, a generation number, and a delta encoding table. Once the context state is established, compressed packets may be sent.

RTP header compression was designed for reliable point-to-point links with short delays. It does not perform well over links with a high rate of packet loss, packet reordering, and long delays. Packet loss results in context corruption, and because of long delay, packets are discarded before the context is repaired. To correct the behavior of RTP header compression over such links, several enhancements have been made to the RTP header compression functionality. The enhancements reduce context corruption by changing the way that the compressor updates the context at the decompressor; updates are repeated and include additions to full and differential context parameters.

With these enhancements, RTP header compression performs well over links with packet loss, packet reordering, and long delays.

RTP Header Compression over Satellite Links

The Cisco IOS Release 12.3(2)T introduced a feature called RTP Header Compression over Satellite Links. The RTP Header Compression over Satellite Links feature allows you to use RTP header compression over an asymmetric link (such as a satellite link), where the uplink and downlink connections are on separate interfaces. This feature provides improved system performance by reducing network overhead and speeding up transmission of RTP packets.

Periodic Refreshes of a Compressed Packet Stream

RTP header compression is a mechanism that compresses the IP header in a packet before the packet is transmitted. RTP header compression requires a context status feedback mechanism to recover when the compressed packet stream experiences packet channel loss. If the round-trip time of the packet between the uplink and the downlink is lengthy or if a feedback path does not exist, the chance of loss propagation is greatly increased when a packet is dropped from the link. For instance, if a feedback path does not exist, a compressed packet stream may never recover. This situation presents a need for a configurable option that allows periodic refreshes of the compressed packet stream using full-header packets.

The periodic-refresh Keyword

When you configure header compression, you can configure periodic refreshes of the compressed packet stream using the **periodic-refresh** keyword. The **periodic-refresh** keyword is available with the following commands:

- **ip rtp header-compression**
- **frame-relay ip rtp header-compression**
- **frame-relay map ip rtp header-compression**

For more information about these commands, see the *Cisco IOS Quality of Service Solutions Command Reference*.

Optional Disabling of Context-Status Messages

During header compression, a session context is defined. For each context, the session state is established and shared between the compressor and the decompressor. The context state consists of the full IP/UDP/RTP headers, a few first-order differential values, a link sequence number, a generation number, and a delta encoding table. This information is included in the context-status messages.

You can disable the sending of context-status messages in instances either when the time it takes for the packet to traverse the uplink and the downlink portions of the data path is greater than the refresh period (in which case, the sending of the context-status message would not be useful) or when a feedback path does not exist.

Disabling the context-status messages can be accomplished by using the **ip header-compression disable-feedback** command. For more information about this command, see the *Cisco IOS Quality of Service Solutions Command Reference*.

How to Configure RTP Header Compression

- [Enabling RTP Header Compression on an Interface, page 5](#) (required)
- [Enabling RTP Header Compression on an Interface That Uses Frame Relay Encapsulation, page 7](#) (optional)
- [Enabling Enhanced RTP Header Compression, page 9](#) (optional)
- [Enabling RTP Header Compression over a Satellite Link, page 10](#) (optional)
- [Specifying the Header-Compression Settings, page 11](#) (optional)
- [Changing the Number of Header-Compression Connections, page 13](#) (optional)
- [Displaying Header-Compression Statistics, page 14](#) (optional)

Enabling RTP Header Compression on an Interface

To enable RTP header compression on an interface, perform the following steps.



Note To enable RTP header compression on an interface that uses Frame Relay encapsulation, skip these steps and complete the steps in the “[Enabling RTP Header Compression on an Interface That Uses Frame Relay Encapsulation](#)” section on page 7 instead.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface type number [name-tag]**
4. **encapsulation encapsulation-type**
5. **ip address ip-address mask [secondary]**
6. **ip rtp header-compression [passive | iphc-format | ietf-format] [periodic-refresh]**
7. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	
Step 3	interface type number [name-tag]	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the interface number.
	Example: Router(config)# interface serial0	
Step 4	encapsulation encapsulation-type	Sets the encapsulation method used by the interface. <ul style="list-style-type: none"> • Enter the encapsulation method.
	Example: Router(config-if)# encapsulation ppp	
Step 5	ip address ip-address mask [secondary]	Sets a primary or secondary IP address for an interface. <ul style="list-style-type: none"> • Enter the IP address and mask for the associated IP subnet.
	Example: Router(config-if)# ip address 209.165.200.225 255.255.255.224	
Step 6	ip rtp header-compression [passive iphc-format ietf-format] [periodic-refresh]	Enables RTP header compression.
	Example: Router(config-if)# ip rtp header-compression	
Step 7	end	(Optional) Exits interface configuration mode.
	Example: Router(config-if)# end	

Enabling RTP Header Compression on an Interface That Uses Frame Relay Encapsulation

To enable RTP header compression on an interface that uses Frame Relay encapsulation, perform the following steps.

Restrictions

The encapsulation type is specified by using either the **cisco** or **ietf** keyword of the **frame-relay interface-dlci** command. The **cisco** keyword specifies Cisco proprietary encapsulations, and the **ietf** keyword specifies IETF encapsulations. However, note the following points about these keywords:

- Frame Relay interfaces do not support IETF encapsulations when RTP header compression is enabled. Therefore, the **ietf** keyword is not available for Frame Relay interfaces and is not listed in the command syntax shown below.
- The **cisco** keyword is available for use on point-to-point subinterfaces *only*.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface type number [name-tag]**
4. **encapsulation frame-relay**
5. **ip address ip-address mask [secondary]**
6. **frame-relay interface-dlci dlci [cisco]**
7. **frame-relay ip rtp header-compression [active | passive] [periodic-refresh]**
8. **or**
9. **frame-relay map ip ip-address dlci [broadcast] rtp header-compression [active | passive] [periodic-refresh] [connections number]**
10. **end**

How to Configure RTP Header Compression

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	
Step 3	interface type number [name-tag]	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the interface number.
	Example: Router(config)# interface serial0	
Step 4	encapsulation frame-relay	Enables Frame Relay encapsulation.
	Example: Router(config-if)# encapsulation frame-relay	
Step 5	ip address ip-address mask [secondary]	Sets a primary or secondary IP address for an interface. <ul style="list-style-type: none"> • Enter the IP address and mask for the associated IP subnet.
	Example: Router(config-if)# ip address 209.165.200.225 255.255.255.224	
Step 6	frame-relay interface-dlci dlci [cisco]	Assigns a data-link connection identifier (DLCI) to a specified Frame Relay interface on the router.
	Example: Router(config-if)# frame-relay interface-dlci 20	
Step 7	frame-relay ip rtp header-compression [active passive] [periodic-refresh]	Enables RTP header compression for all Frame Relay maps on a physical interface.
	Example: Router(config-if)# frame-relay ip rtp header-compression	
	or	
	frame-relay map ip ip-address dlci [broadcast] rtp header-compression [active passive] [periodic-refresh] [connections number]	Assigns to an IP map header-compression characteristics that differ from the compression characteristics of the interface with which the IP map is associated. <ul style="list-style-type: none"> • Enter the IP address, DLCI number, and any optional keywords and arguments.
	Example: Router(config-if)# frame-relay map ip 10.108.175.220 180 rtp header-compression periodic-refresh	
Step 8	end	(Optional) Exits interface configuration mode.
	Example: Router(config-if)# end	

Enabling Enhanced RTP Header Compression

The Enhanced RTP Header Compression feature (also known as EC RTP) includes modifications and enhancements to RTP header compression to achieve robust operation over unreliable point-to-point links. Enhanced RTP header compression is intended for use on networks subject to high rates of packet loss, packet reordering, and long delays. For more information about Enhanced RTP header compression, see the “[Enhanced RTP Header Compression](#)” section on page 4.

To enable enhanced RTP header compression, perform the following steps.

Prerequisites

- Configure a serial link using HDLC encapsulation or configure an interface using PPP encapsulation.
- Ensure that RTP header compression is enabled on the interface. See the “[Enabling RTP Header Compression on an Interface](#)” section on page 5.

Restrictions

Enhanced RTP header compression is not supported on interfaces that use Frame Relay encapsulation.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface *type number [name-tag]***
4. **encapsulation *encapsulation-type***
5. **ip address *ip-address mask [secondary]***
6. **ip rtp header-compression [*passive | iphc-format | ietf-format*] [*periodic-refresh*]**
7. **ip header-compression recoverable-loss {*dynamic | packet-drops*}**
8. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none">• Enter your password if prompted.
	Example: Router> enable	
Step 2	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	

Command or Action	Purpose
Step 3 <code>interface type number [name-tag]</code> Example: Router(config)# interface serial0	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none">• Enter the interface type and the interface number.
Step 4 <code>encapsulation encapsulation-type</code> Example: Router(config-if)# encapsulation ppp	Sets the encapsulation method used on the interface. <ul style="list-style-type: none">• Enter the encapsulation method.
Step 5 <code>ip address ip-address mask [secondary]</code> Example: Router(config-if)# ip address 209.165.200.225 255.255.255.224	Sets a primary or secondary IP address for an interface. <ul style="list-style-type: none">• Enter the IP address and mask for the associated IP subnet.
Step 6 <code>ip rtp header-compression [passive iphc-format ietf-format] [periodic-refresh]</code> Example: Router(config-if)# ip rtp header-compression ietf-format	Enables RTP header compression.
Step 7 <code>ip header-compression recoverable-loss {dynamic packet-drops}</code> Example: Router(config-if)# ip header-compression recoverable-loss dynamic	Enables EC RTP on an interface. Note Enter the dynamic keyword to enable dynamic packet loss recovery, or enter the <i>packet-drops</i> argument to specify the maximum number of consecutive packet drops that are acceptable.
Step 8 <code>end</code> Example: Router(config-if)# end	(Optional) Exits interface configuration mode.

Enabling RTP Header Compression over a Satellite Link

To enable RTP header compression over a satellite link, perform the following steps.

SUMMARY STEPS

1. `enable`
2. `configure terminal`
3. `interface type number [name-tag]`
4. `ip address ip-address mask [secondary]`
5. `ip rtp header-compression [passive | iphc-format | ietf-format] [periodic-refresh]`
6. `ip header-compression disable-feedback`
7. `end`

DETAILED STEPS

	Command or Action	Purpose
Step 1	<code>enable</code>	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	<code>configure terminal</code>	Enters global configuration mode.
	Example: Router# configure terminal	
Step 3	<code>interface type number [name-tag]</code>	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the interface number.
	Example: Router(config)# interface serial0	
Step 4	<code>ip address ip-address mask [secondary]</code>	Sets a primary or secondary IP address for an interface. <ul style="list-style-type: none"> • Enter the IP address and mask for the associated IP subnet.
	Example: Router(config-if)# ip address 209.165.200.225 255.255.255.224	
Step 5	<code>ip rtp header-compression [passive iphc-format ietf-format] [periodic-refresh]</code>	Enables RTP header compression. Note For RTP header compression over a satellite link, use the periodic-refresh keyword.
	Example: Router(config-if)# ip rtp header-compression ietf-format periodic-refresh	
Step 6	<code>ip header-compression disable-feedback</code>	(Optional) Disables the context status feedback messages from the interface or link.
	Example: Router(config-if)# ip header-compression disable-feedback	
Step 7	<code>end</code>	(Optional) Exits interface configuration mode.
	Example: Router(config-if)# end	

Specifying the Header-Compression Settings

With RTP header compression, you can configure the maximum size of the compressed IP header, the time period for an automatic resend of full-header packets, and the number of packets transmitted before a new full-header packet is sent.

To specify these header-compression settings, perform the following steps.

SUMMARY STEPS

1. `enable`
2. `configure terminal`

How to Configure RTP Header Compression

3. **interface type number [name-tag]**
4. **ip header-compression max-header max-header-size**
or
ip header-compression max-time length-of-time
or
ip header-compression max-period number-of-packets
5. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	interface type number [name-tag] Example: Router(config)# interface serial0	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the interface number.
Step 4	ip header-compression max-header max-header-size Example: Router(config-if)# ip header-compression max-header 100	Specifies the maximum size of the compressed IP header. <ul style="list-style-type: none"> • Enter the maximum size of the compressed IP header, in bytes.
	or ip header-compression max-time length-of-time Example: Router(config-if)# ip header-compression max-time 30	Specifies the maximum amount of time to wait before the compressed IP header is refreshed. <ul style="list-style-type: none"> • Enter the amount of time, in seconds.
	or ip header-compression max-period number-of-packets Example: Router(config-if)# ip header-compression max-period 160	Specifies the maximum number of compressed packets between full headers. <ul style="list-style-type: none"> • Enter the maximum number of compressed packets between full headers.
Step 5	end Example: Router(config-if)# end	(Optional) Exits interface configuration mode.

Changing the Number of Header-Compression Connections

For PPP and HDLC interfaces, the default is 16 compression connections. For interfaces that use Frame Relay encapsulation, the default is 256 compression connections.

To change the default number of header-compression connections, perform the following steps.

Implications of Changing the Number of Header-Compression Connections

Each header-compression connection sets up a compression cache entry, so you are in effect specifying the maximum number of cache entries and the size of the cache. Too few cache entries for the specified interface can lead to degraded performance, and too many cache entries can lead to wasted memory. Choose the number of header-compression connections according to the network requirements.

Restrictions

Header-Compression Connections on HDLC and Frame Relay Interfaces

For HDLC interfaces and Frame Relay interfaces (that is, interfaces that use Frame Relay encapsulation), the number of header-compression connections on *both sides* of the network must match. That is, the number configured for use on the local router must match the number configured for use on the remote router.

Header-Compression Connections on PPP Interfaces

For PPP interfaces, if the header-compression connection numbers on both sides of the network do not match, the number used is “autonegotiated.” That is, any mismatch in the number of header-compression connections between the local router and the remote router will be automatically negotiated to the lower of the two numbers. For example, if the local router is configured to use 128 header-compression connections, and the remote router is configured to use 64 header-compression connections, the negotiated number will be 64.



Note This autonegotiation function applies to PPP interfaces *only*. For HDLC interfaces and interfaces that use Frame Relay encapsulation, no autonegotiation occurs.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface type number [name-tag]**
4. **ip rtp compression-connections number**
or
frame-relay ip rtp compression-connections number
5. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	
Step 3	interface type number [name-tag]	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the interface number.
	Example: Router(config)# interface serial0	
Step 4	ip rtp compression-connections number	Specifies the total number of RTP header-compression connections that can exist on an interface. <ul style="list-style-type: none"> • Enter the number of compression connections. Note This command can be used for PPP interfaces, HDLC interfaces, or interfaces that use Frame Relay encapsulation.
	Example: Router(config-if)# ip rtp compression-connections 150	
or		
	frame-relay ip rtp compression-connections number	Specifies the maximum number of RTP header-compression connections that can exist on a Frame Relay interface (that is, an interface using Frame Relay encapsulation). <ul style="list-style-type: none"> • Enter the number of compression connections. Note This command can be used for interfaces that use Frame Relay encapsulation only.
Step 5	end	(Optional) Exits interface configuration mode.
	Example: Router(config-if)# end	

Displaying Header-Compression Statistics

You can display header-compression statistics, such as the number of packets sent, received, and compressed, by using either the **show ip rtp header-compression** command or the **show frame-relay ip rtp header-compression** command.

To display header-compression statistics, perform the following steps.

SUMMARY STEPS

1. **enable**
2. **show ip rtp header-compression [interface-type interface-number] [detail]**
or

show frame-relay ip rtp header-compression [interface type number]

3. **end**

DETAILED STEPS

Command or Action	Purpose
Step 1 enable Example: Router> enable	Enables privileged EXEC mode. • Enter your password if prompted.
Step 2 show ip rtp header-compression [interface-type interface-number] [detail] Example: Router# show ip rtp header-compression	Displays RTP header-compression statistics for one or all interfaces.
or	
show frame-relay ip rtp header-compression [interface type number] Example: Router# show frame-relay ip rtp header-compression	Displays Frame Relay RTP header-compression statistics for one or all interfaces.
Step 3 end Example: Router# end	(Optional) Exits privileged EXEC mode.

Configuration Examples for RTP Header Compression

This section provides the following configuration examples:

- [Example: Enabling RTP Header Compression on an Interface, page 16](#)
- [Example: Enabling RTP Header Compression on an Interface That Uses Frame Relay Encapsulation, page 16](#)
- [Example: Enabling Enhanced RTP Header Compression, page 16](#)
- [Example: Enabling RTP Header Compression over a Satellite Link, page 17](#)
- [Example: Specifying the Header-Compression Settings, page 17](#)
- [Example: Changing the Number of Header-Compression Connections, page 17](#)
- [Example: Displaying Header-Compression Statistic, page 17](#)

Example: Enabling RTP Header Compression on an Interface

In the following example, RTP header compression is enabled on serial interface 0.

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# encapsulation ppp
Router(config-if)# ip address 209.165.200.225 255.255.255.224
Router(config-if)# ip rtp header-compression
Router(config-if)# end
```

Example: Enabling RTP Header Compression on an Interface That Uses Frame Relay Encapsulation

In the following example, RTP header compression is enabled on serial interface 0. Frame Relay encapsulation has been enabled on this interface by using the **encapsulation frame-relay** command.

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# encapsulation frame-relay
Router(config-if)# ip address 209.165.200.225 255.255.255.224
Router(config-if)# frame-relay interface-dlci 20
Router(config-if)# frame-relay ip rtp header-compression
Router(config-if)# end
```

Example: Enabling Enhanced RTP Header Compression

In the following example, ECRTP is enabled on serial interface 0. PPP encapsulation is enabled on the interface (a prerequisite for configuring ECRTP on a serial interface). Also, dynamic loss recovery has been specified by using the **dynamic** keyword of the **ip header-compression recoverable-loss** command.

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# encapsulation ppp
Router(config-if)# ip address 209.165.200.225 255.255.255.224
Router(config-if)# ip rtp header-compression ietf-format
Router(config-if)# ip header-compression recoverable-loss dynamic
Router(config-if)# end
```

Example: Enabling RTP Header Compression over a Satellite Link

In the following example, RTP header compression is enabled on the serial interface 0. In this example, serial interface 0 is a satellite link in the network topology. The **periodic-refresh** keyword has been specified, which means that the compressed IP header will be refreshed periodically. Also, the context-status messages have been turned off (disabled).

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# ip address 209.165.200.225 255.255.255.224
Router(config-if)# ip rtp header-compression ietf-format periodic-refresh
Router(config-if)# ip header-compression disable-feedback
Router(config-if)# end
```

Example: Specifying the Header-Compression Settings

In the following example, the maximum size of the compressed IP header (100 bytes) has been specified by using the **ip header-compression max-header** command.

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# ip header-compression max-header 100
Router(config-if)# end
```

Example: Changing the Number of Header-Compression Connections

In the following example, the number of header-compression connections has been changed to 150 by using the **ip rtp compression-connections** command.

```
Router> enable
Router# configure terminal
Router(config)# interface serial0
Router(config-if)# ip rtp compression-connections 150
Router(config-if)# end
```

Example: Displaying Header-Compression Statistic

You can use the **show ip rtp header-compression** command to display header-compression statistics such as the number of packets received, sent, and compressed. The following is sample output from the **show ip rtp header-compression** command. In this example, EC RTP has been enabled on serial interface 0.

```
Router# show ip rtp header-compression serial0

RTP/UDP/IP header compression statistics:
Interface Serial0 (compression on, IETF, EC RTP)
    Rcvd: 1473 total, 1452 compressed, 0 errors, 0 status msgs
          0 dropped, 0 buffer copies, 0 buffer failures
    Sent: 1234 total, 1216 compressed, 0 status msgs, 379 not predicted
          41995 bytes saved, 24755 bytes sent
          2.69 efficiency improvement factor
```

■ Additional References

```
Connect: 16 rx slots, 16 tx slots,
6 misses, 0 collisions, 0 negative cache hits, 13 free contexts
99% hit ratio, five minute miss rate 0 misses/sec, 0 max
```

Additional References

The following sections provide references related to configuring RTP header compression.

Related Documents

Related Topic	Document Title
Cisco IOS commands	Cisco IOS Master Commands List, All Releases
QoS commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples	Cisco IOS Quality of Service Solutions Command Reference
Frame Relay	“Frame Relay Queueing and Fragmentation at the Interface” module
Header compression overview	“Header Compression” module
TCP header compression	“Configuring TCP Header Compression” module
Class-based RTP and TCP header compression	“Configuring Class-Based RTP and TCP Header Compression” module
IPHC profiles and header compression	“Configuring Header Compression Using IPHC Profiles” module

Standards

Standard	Title
No new or modified standards are supported, and support for existing standards has not been modified.	—

MIBs

MIB	MIBs Link
No new or modified MIBs are supported, and support for existing MIBs has not been modified.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFC	Title
RFC 2507	<i>IP Header Compression</i>
RFC 2508	<i>Compressing IP/UDP/RTP Headers for Low-Speed Serial Links</i>
RFC 3544	<i>IP Header Compression over PPP</i>
RFC 3545	<i>Enhanced Compressed RTP (CRTP) for Links with High Delay, Packet Loss and Reordering</i>

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Glossary

compression—The running of a data set through an algorithm that reduces the space required to store the data set or the bandwidth required to transmit the data set.

context—The state that the compressor uses to compress a header and that the decompressor uses to decompress a header. The context is the uncompressed version of the last header sent and includes other information used to compress and decompress the packet.

context-state packet—A special packet sent from the decompressor to the compressor to communicate a list of (TCP or NON_TCP/RTP) context identifiers (CIDs) for which synchronization has been lost. This packet is sent only over a single link, so it requires no IP header.

DLCI—data-link connection identifier. A value that specifies a permanent virtual circuit (PVC) or switched virtual circuit (SVC) in a Frame Relay network. In the basic Frame Relay specification, DLCIs are locally significant (connected devices might use different values to specify the same connection). In the Local Management Interface (LMI) extended specification, DLCIs are globally significant (DLCIs specify individual end devices).

ECRTP—Enhanced Compressed Real-Time Transport Protocol. A compression protocol that is designed for unreliable point-to-point links with long delays.

encapsulation—A method of wrapping data in a particular protocol header. For example, Ethernet data is wrapped in a specific Ethernet header before network transit. Also, when dissimilar networks are bridged, the entire frame from one network is simply placed in the header used by the data link layer protocol of the other network.

full header (header refresh)—An uncompressed header that updates or refreshes the context for a packet stream. It carries a CID that will be used to identify the context. Full headers for non-TCP packet streams also carry the generation of the context that they update or refresh.

HDLC—High-Level Data Link Control. A bit-oriented synchronous data link layer protocol developed by the International Organization for Standardization (ISO). Derived from Synchronous Data Link Control (SDLC), HDLC specifies a data encapsulation method on synchronous serial links using frame characters and checksums.

header—A chain of subheaders.

IETF—Internet Engineering Task Force. A task force that consists of over 80 working groups responsible for developing Internet standards.

IPHC—IP Header Compression. A protocol capable of compressing both TCP and UDP headers.

ISDN—Integrated Services Digital Network. A communication protocol offered by telephone companies that permits telephone networks to carry data, voice, and other source traffic.

lossy serial links—Links in a network that are prone to lose packets.

packet stream—The sequence of packets whose headers are similar and share context. For example, headers in an RTP packet stream have the same source and final destination address and the same port numbers in the RTP header.

PPP—Point-to-Point Protocol. A protocol that provides router-to-router and host-to-network connections over synchronous and asynchronous circuits.

regular header—A normal, uncompressed header. A regular header does not carry a context identifier (CID) or generation association.

RTP—Real-Time Transport Protocol. A protocol that is designed to provide end-to-end network transport functions for applications that transmit real-time data, such as audio, video, or simulation data, over unicast or multicast network services. RTP provides such services as payload type identification, sequence numbering, timestamping, and delivery monitoring to real-time applications.

subheader—An IPv6 base header, an IPv6 extension header, an IPv4 header, a UDP header, an RTP header, or a TCP header.

Feature Information for Configuring RTP Header Compression

lists the release history for this feature.

Not all commands may be available in your Cisco IOS software release. For release information about a specific command, see the command reference documentation.

For information on a feature in this technology that is not documented here, see the “[Header-Compression Features Roadmap](#)” module.

Cisco IOS software images are specific to a Cisco IOS software release, a feature set, and a platform. Use Cisco Feature Navigator to find information about platform support and software image support. Cisco Feature Navigator enables you to determine which Cisco IOS and Catalyst OS software images support a specific software release, feature set, or platform. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.



Note

lists only the Cisco IOS software release that introduced support for a given feature in a given Cisco IOS software release train. Unless noted otherwise, subsequent releases of that Cisco IOS software release train also support that feature.

Table 1 **Feature Information for Configuring RTP Header Compression**

Feature Name	Releases	Feature Information
RTP Header Compression over Satellite Links	12.3(2)T	<p>The RTP Header Compression over Satellite Links feature allows customers to use RTP header compression over an asymmetric link (such as a satellite link), where the uplink and downlink connections are on separate interfaces.</p> <p>The following sections provide information about this feature:</p> <ul style="list-style-type: none"> • RTP Header Compression over Satellite Links, page 4 • Enabling RTP Header Compression over a Satellite Link, page 10

Table 1 Feature Information for Configuring RTP Header Compression (continued)

Feature Name	Releases	Feature Information
Enhanced CRTP for Links with High Delay, Packet Loss and Reordering	12.3(11)T	<p>The Enhanced Compressed Real-Time Transport Protocol (ECRTP) for Links with High Delay, Packet Loss, and Reordering feature includes modifications and enhancements to CRTP to achieve robust operation over unreliable point-to-point links. This is accomplished by repeating updates and sending absolute (uncompressed) values in addition to delta values for selected context parameters.</p> <p>The following sections provide information about this feature:</p> <ul style="list-style-type: none"> • Enhanced RTP Header Compression, page 4 • Enabling Enhanced RTP Header Compression, page 9
RTP Header Compression RTP Header Compression over Satellite Links	15.0(1)S	The RTP Header Compression and RTP Header Compression over Satellite Links features were integrated into the Cisco IOS Release 15.0(1)S release.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

© 2007—2010 Cisco Systems, Inc. All rights reserved.

■ Feature Information for Configuring RTP Header Compression