

Telnet Messages

This chapter describes unnumbered messages issued to the client by Server Telnet.

Server Telnet Messages

This section includes the messages that are issued by Server Telnet.

Command Not Supported

Explanation There is no support for the command name entered, or the support is not properly defined in the Cisco IOS for S/390 configuration.

Recommended Action Enter the proper command name, or consult with your System Administrator to resolve the issue.

Enter Command or HELP

Explanation This is the main user prompt issued by Server Telnet.

Recommended Action In response, enter the name for a command, service, or VTAM application supported by the Server Telnet component of Cisco IOS for S/390. Alternatively, enter HELP, for guidance.

Operator Forced Logout

Explanation Cisco IOS for S/390 has terminated, either abnormally or normally, in response to an MVS operator STOP command.

Recommended Action Await restart of Cisco IOS for S/390, and then resume working.

Password Not Authorized

Explanation The password entered does not match the user ID entered.

Recommended Action Use a proper combination of user ID and password.

Requested Command Cannot Be Serviced

Explanation The requested service could not be executed because its supporting module could not be found or loaded correctly.

Recommended Action Report the matter to your System Administrator for resolution.

Requested Service Restricted

Explanation This message reports that the requested service is restricted and access will depend on your user ID and password.

Recommended Action In response to subsequent prompts, enter your user ID and password.

prodid Server Telnet (*hostid*) *timestamp*

Explanation This is the sign on banner for the Server Telnet component of Cisco IOS for S/390. *prodid* identifies the version of Cisco IOS for S/390 to which you have connected. *hostid* is the domain name (host name on the TCP/IP network) for this instance of Cisco IOS for S/390. *timestamp* reports the date and time the connection was established.

Server Telnet User *uid* Logged Out

Explanation This message reports that the user ID *uid* has been logged out. This message appears after a service has been executed or a change of user ID is changing.

Service Completed Abnormally

Explanation The module providing the service terminated abnormally.

Recommended Action Report the failure to your System Administrator for resolution.

Translate Table Cannot Be Loaded

Explanation The translate table specified by the TRANTBL parameter on the TELNET or APPL statement cannot be found or cannot be loaded properly. Consequently the service requested could not be executed.

Recommended Action Have your System Administrator correct the Cisco IOS for S/390 configuration or make available the proper translate table load module.

Userid is Not Defined To the Security System

Explanation An unknown user ID has been entered for access to a restricted service.

Recommended Action Enter a user ID and password that is authorized for the service.