



DHCP Commands



Note All commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 540 Series Router that is introduced from Cisco IOS XR Release 6.3.2. References to earlier releases in Command History tables apply to only the Cisco NCS 5500 Series Router.



- Note**
- Starting with Cisco IOS XR Release 6.6.25, all commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 560 Series Routers.
 - Starting with Cisco IOS XR Release 6.3.2, all commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 540 Series Router.
 - References to releases before Cisco IOS XR Release 6.3.2 apply to only the Cisco NCS 5500 Series Router.
 - Cisco IOS XR Software Release 7.0.1 specific updates are not applicable for the following variants of Cisco NCS 540 Series Routers:
 - N540-28Z4C-SYS-A
 - N540-28Z4C-SYS-D
 - N540X-16Z4G8Q2C-A
 - N540X-16Z4G8Q2C-D
 - N540-12Z20G-SYS-A
 - N540-12Z20G-SYS-D
 - N540X-12Z16G-SYS-A
 - N540X-12Z16G-SYS-D

This chapter describes the commands used to configure and monitor the Direct Host Control Protocol (DHCP) on Cisco NCS 5500 Series routers.

For detailed information about ARP concepts, configuration tasks, and examples, refer to the *IP Addresses and Services Configuration Guide for Cisco NCS 5500 Series Routers*, *IP Addresses and Services Configuration Guide for Cisco NCS 540 Series Routers*, and *IP Addresses and Services Configuration Guide for Cisco NCS 560 Series Routers*.

- [clear dhcp ipv4 client](#), on page 3
- [clear dhcp ipv4 client statistics](#), on page 4
- [clear dhcp ipv4 server binding](#), on page 5
- [clear dhcp ipv4 server statistics](#), on page 6
- [clear dhcp ipv6 relay binding](#), on page 7
- [clear dhcp ipv6 proxy binding](#), on page 9
- [clear dhcp ipv6 relay statistics](#), on page 10
- [client-mac-mismatch](#), on page 10
- [default-router](#), on page 11
- [dhcp ipv4](#) , on page 12
- [dhcp ipv6](#), on page 13
- [dns-server](#), on page 14
- [domain-name](#), on page 14
- [duplicate-mac-allowed](#), on page 15
- [giaddr policy](#), on page 17
- [helper-address](#), on page 18
- [helper-address \(ipv6\)](#), on page 19
- [hop-count-seed](#), on page 21
- [iana-route-add](#), on page 22
- [lease \(DHCPv4 Server\)](#), on page 22
- [limit lease](#), on page 23
- [netbios-name-server](#), on page 24
- [netbios-node-type](#), on page 25
- [option](#), on page 26
- [pool](#), on page 27
- [profile \(DHCP\)](#), on page 28
- [relay information authenticate](#), on page 30
- [relay information check](#) , on page 32
- [relay information option](#) , on page 33
- [relay information option allow-untrusted](#) , on page 34
- [secure-arp](#), on page 35
- [show dhcp ipv4 client](#), on page 36
- [show dhcp ipv4 client statistics](#), on page 38
- [show dhcp ipv4 proxy interface](#), on page 39
- [show dhcp ipv4 proxy statistics](#), on page 40
- [show dhcp ipv4 relay profile](#), on page 41
- [show dhcp ipv4 relay profile name](#), on page 42
- [show dhcp ipv4 relay statistics](#), on page 43
- [show dhcp ipv4 server binding](#), on page 44
- [show dhcp ipv4 server disconnect-history](#), on page 46
- [show dhcp ipv4 server interface](#), on page 47
- [show dhcp ipv4 server profile](#), on page 48

- [show dhcp ipv4 server statistics](#), on page 49
- [show dhcp ipv6 database](#), on page 50
- [show dhcp ipv6 proxy](#), on page 52
- [show dhcp ipv6 proxy binding](#), on page 53
- [show dhcp ipv6 proxy interface](#), on page 54
- [show dhcp ipv6 server](#), on page 55
- [show dhcp vrf ipv4 server statistics](#), on page 56
- [show tech support dhcp ipv4 client](#), on page 58
- [trust relay-reply](#), on page 59

clear dhcp ipv4 client

To clear the DHCP client binding information configured on a given interface and set the binding information again, use the **clear dhcp ipv4 client** command in XR EXEC mode.

clear dhcp ipv4 client *interface-name interface-number*

Syntax Description

interface-name Specifies DHCP IPv4 client enabled interface name.

interface-number Specifies DHCP IPv4 client enabled interface number.

Command Default

No default behavior or values

Command Modes

XR EXEC mode

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

Use the **clear dhcp ipv4 client** command to clear the DHCP client binding information for the specified interface.

Task ID

Task ID	Operations
IP-Services	Execution

Examples

The following example shows how to clear the DHCP client binding information:

```
Router# clear dhcp ipv4 client mgmtEth 0/0/CPU0/0
Fri Jun  6 08:24:14.558 UTC
RP/0/0/CPU0:ios#show dhcp ipv4 client
Fri Jun  6 08:24:17.377 UTC
```

Interface name	IP Address	Binding State	Lease Time Rem
MgmtEth0/0/CPU0/0	11.11.11.5	BOUND	3598 secs (00:59:58)

```
RP/0/0/CPU0:ios#show dhcp ipv4 client mgmtEth 0/0/CPU0/0 statistics
```

```

Fri Jun  6 08:24:19.397 UTC

Client Interface name      : MgmtEth0/0/CPU0/0
-----
      CLIENT COUNTER(s)    |      VALUE
-----
Num discovers sent        :          1
Num requests sent         :          1
Num releases sent         :          1
Num offers received       :          1
Num acks received         :          1
-----

```

clear dhcp ipv4 client statistics

To clear DHCP client binding statistics information for a given interface, use the **clear dhcp ipv4 client statistics** command in XR EXEC mode.

clear dhcp ipv4 client <interface-name> interface-number **statistics**

Syntax Description	<i>interface-name</i>	Specifies DHCP IPv4 client enabled interface name.
	<i>interface-number</i>	Specifies DHCP IPv4 client enabled interface number.
	statistics	Clears DHCP IPv4 statistical information for the specified interface.

Command Default No default behavior or values

Command Modes XR EXEC mode

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines Use the **clear dhcp ipv4 client statistics** command to clear the DHCP client binding statistics information for the specified interface.

Task ID	Task ID	Operations
	IP-Services	Execution

Examples The following example shows how to clear the DHCP client binding statistics information:

```

RP/0/0/CPU0:ios#show dhcp ipv4 client mgmtEth 0/0/CPU0/0 statistics
Fri Jun  6 08:23:04.822 UTC

Client Interface name      : MgmtEth0/0/CPU0/0
-----

```

```

      CLIENT COUNTER(s)      |      VALUE
-----
Num discovers sent          :          11
Num requests sent           :           3
Num releases sent           :           2
Num offers received         :           3
Num acks received           :           3
-----

```

```

RP/0/0/CPU0:ios#clear dhcp ipv4 client mgmtEth 0/0/CPU0/0 statistics
Fri Jun  6 08:23:11.852 UTC
RP/0/0/CPU0:ios#show dhcp ipv4 client mgmtEth 0/0/CPU0/0 statistics
Fri Jun  6 08:23:13.682 UTC

```

```
Client Interface name      : MgmtEth0/0/CPU0/0
```

```

      CLIENT COUNTER(s)      |      VALUE
-----

```

```

RP/0/0/CPU0:ios#show dhcp ipv4 client
Fri Jun  6 08:23:16.862 UTC

```

```

      Interface name      IP Address      Binding State      Lease Time Rem
-----
MgmtEth0/0/CPU0/0      11.11.11.5      BOUND      3562 secs (00:59:22)

```

Related Commands

Commands	Description
show dhcp ipv4 client	This command displays DHCP IPv4 client information.
clear dhcp ipv4 proxy statistics	This command clears DHCP proxy binding statistics information for a given interface.
clear dhcp ipv4 proxy statistics	This command clears DHCP server binding statistics information for a given interface.

clear dhcp ipv4 server binding

To clear all client bindings in server, use the **clear dhcp ipv4 server binding** command in XR EXEC mode.

clear dhcp ipv4 server binding [*location node-ID*] [*interface type interface-path-ID*] [*mac-address address*]

Syntax Description

location node-ID	Clears detailed client binding information for a specified node.
-------------------------	--

interface <i>type</i> <i>interface-path-ID</i>	<p>Clears client binding by interface.</p> <p>Specifies the interface type. For more information, use the question mark (?) online help function.</p> <p>Physical interface or virtual interface. Use the show interfaces command to see a list of all interfaces currently configured on the router.</p> <p>Note For more information about the syntax for the router, use the question mark (?) online help function.</p>
mac-address <i>address</i>	Clears detailed client binding information per mac-address.

Command Default

None

Command Modes

XR EXEC mode

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	execute

Example

This is a sample output from the **clear dhcp ipv4 server binding** command:

```
Router# clear dhcp ipv4 server binding
```

Related Commands

Command	Description
clear dhcp ipv4 server statistics, on page 6	Clears DHCP server statistics.

clear dhcp ipv4 server statistics

To clear DHCP server statistics, use the **clear dhcp ipv4 server statistics** command in XR EXEC mode.

clear dhcp ipv4 server statistics [**[raw [all] [location node-ID]]**]

Syntax Description

raw	Clears debug statistics.
all	Clears debug statistics for base mode.

include-zeroes	Clears debug statistics that are zero.
location <i>node-ID</i>	Clears DHCP server statistics information for a specified node.

Command Default

None

Command Modes

XR EXEC mode

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	execute
root-system	read, write

Example

This is a sample output from the **clear dhcp ipv4 server statistics** command:

```
Router# clear dhcp ipv4 server statistics
```

Related Commands

Command	Description
clear dhcp ipv4 server binding, on page 5	Clears all client bindings in server.

clear dhcp ipv6 relay binding

To clear DHCPv6 relay binding, use the **clear dhcp ipv6 relay binding** command in XR EXEC mode.

```
clear dhcp ipv6 relay binding [client-duid client-duid-number ] [interface type interface-path-id]  
[vrf vrf-name] [location node-id]
```

Syntax Description	client-duid <i>client-duid-number</i>	(Optional) Clears DHCPv6 relay client binding information. The argument <i>client-duid-number</i> is the client's DHCP Unique Identifier (DUID) number. Note Use the show dhcp ipv6 relay binding command to see the client DUID number.
	interface <i>type interface-path-id</i>	(Optional) Clears DHCPv6 relay client binding information for an interface. Specifies a physical interface or a virtual interface. Note Use the show interfaces command to see a list of all possible interfaces currently configured on the router.
	vrf <i>vrf-name</i>	(Optional) Clears DHCPv6 relay client binding information for a VPN routing and forwarding (VRF) instance.
	location <i>node-id</i>	(Optional) Clears DHCPv6 relay client binding information for a specified node. The <i>node-id</i> argument is entered in the <i>rack/slot/module</i> notation.
Command Default	None.	
Command Modes	XR EXEC mode	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	execute

Task ID	Operation
root-system	read, write

This example shows how to clear DHCPv6 relay binding:

```
Router# clear dhcp ipv6 relay binding
```

clear dhcp ipv6 proxy binding

To clear Dynamic Host Configuration Protocol (DHCP) relay bindings for prefix delegation, use the **clear dhcp ipv6 proxy binding** command in XR EXEC mode.

clear dhcp ipv6 proxy binding {*client-duid* | *interface* | *location*}

Syntax Description	<i>client-duid</i>	Specifies the DHCP unique identifier.
	<i>interface</i>	Specifies the interface.
	<i>location</i>	Specifies the node location.

Command Default	No default behavior or values
-----------------	-------------------------------

Command Modes	XR EXEC mode
---------------	--------------

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
------------------	--

Task ID	Task ID	Operation
	ip-services	execute

Example

This is a sample output from the **clear dhcp ipv6 proxy binding** command:

```
Router# clear dhcp ipv6 proxy binding
```

Related Commands	Command	Description
	show dhcp ipv6 proxy binding, on page 53	Displays Dynamic Host Configuration Protocol (DHCP) relay bindings for prefix delegation.

clear dhcp ipv6 relay statistics

To clear DHCPv6 relay statistics, use the **clear dhcp ipv6 relay statistics** command in XR EXEC mode.

clear dhcp ipv6 relay statistics [**vrf** *vrf-name*][**location** *node-id*][**debug** {*all* | *location*}]

Syntax Description	vrf <i>vrf-name</i>	(Optional) Clears DHCPv6 relay statistics information for a VPN routing and forwarding (VRF) instance.
	location <i>node-id</i>	(Optional) Clears DHCPv6 relay statistics information for a specified node. The <i>node-id</i> argument is entered in the <i>rack/slot/module</i> notation.
	debug	(Optional) Clears DHCPv6 relay statistics information for base mode or a specified location.
	{ <i>all</i> <i>location</i> } <i>node-id</i>	

Command Default None.

Command Modes XR EXEC mode

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operation
	ip-services	execute
	root-system	read, write

This example shows how to clear DHCPv6 relay statistics:

```
Router# clear dhcp ipv6 relay statistics
```

client-mac-mismatch

To enable DHCP MAC address verification.

client-mac-mismatch action drop

Syntax Description	action	Specifies an action for the router when the DHCP MAC address is not a match.
	drop	Drops the packet with the mismatched DHCP MAC address.
Command Default	None	
Command Modes	DHCP Relay Profile Configuration Mode	
Command History	Release	Modification
	Release 6.3.2	This command was introduced.
Usage Guidelines	Enables MAC address verification. If MAC address in the DHCPv4 protocol header does not match the L2 header source MAC address in the DHCPv4 relay profile, the frame is dropped.	

Example

Use the following example to configure DHCP MAC address verification.

```
Router# configure

Router(config)# dhcp ipv4
/* Configures DHCP for IPv4 and enters the DHCPv4 configuration submode. */

Router(config-dhcpv4)# profile client relay
/* Enables DHCP relay profile */

Router(config-dhcpv4)# client-mac-mismatch action drop
/* Enables MAC address verification. If MAC address in the DHCPv4 protocol header does not
match the L2 header source MAC address in the DHCPv4 relay profile,
the frame is dropped */

Router(config-dhcpv4-relay-profile)# commit

Router(config-dhcpv4-relay-profile)# exit
```

default-router

To configure the default-router, use the **default-router** command in the DHCPv4 server profile sub-mode. To deconfigure the name of the default-router or the IP address, use the **no** form of this command.

default-router *address1address2...address8*
no default-router *address1address2...address8*

Syntax Description	<i>address1address2...address8</i>	Name of the router or IP address. Upto 8 routers can be configured.
Command Default	None	

Command Modes	DHCPv4 Server Profile	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read, write

Example

This is a sample output from the **default-router** command:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
Router(config-dhcpv4-server-profile)# default-router 10.20.1.2
```

dhcp ipv4

To enable Dynamic Host Configuration Protocol (DHCP) for IPv4 and to enter DHCP IPv4 configuration mode, use the **dhcp ipv4** command in Global Configuration mode. To disable DHCP for IPv4 and exit the DHCP IPv4 configuration mode, use the **no** form of this command.

dhcp ipv4
no dhcp ipv4

Syntax Description	This command has no keywords or arguments.	
Command Modes	None	
Command Modes	Global Configuration mode	
Command History	Release	Modification
	Release 6.1.2	This command was introduced.
Usage Guidelines	Use the dhcp ipv4 command to enter DHCP IPv4 configuration mode.	

Task ID	Task ID	Operations
	ip-services	read, write

Examples

This example shows how to enable DHCP for IPv4:

```
RP0/CPU0:Router# dhcp ipv4
RP0/CPU0:Router# (config-dhcpv4) #
```

dhcp ipv6

To enable Dynamic Host Configuration Protocol (DHCP) for IPv6 and to enter DHCP IPv6 configuration mode, use the **dhcp ipv6** command in XR Config mode. To disable the DHCP for IPv6, use the **no** form of this command.

dhcp ipv6

Syntax Description	This command has no keywords or arguments.	
Command Modes	XR Config mode	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	Use the dhcp ipv6 command to enter DHCP IPv6 configuration mode.	
Task ID	Task ID	Operations
	ip-services	read, write
Examples	This example shows how to enable DHCP for IPv6:	
	<pre>Router(config)# dhcp ipv6 Router(config-dhcpv6) #</pre>	

dns-server

To configure the Domain Name System (DNS) servers, use the **dns-server** command in DHCPv4 server profile configuration and DHCPv4 server profile class sub-mode. To remove the DNS servers use the no form of this command.

dns-server *address1 address2address8*
no dns-server *address1 address2.....address8*

Syntax Description	<i>address1</i> , <i>address2...address8</i>		Specifies the server IPv4 address. Upto 8 server addresses can be configured. The servers are listed in order of preference <i>address1</i> is the most preferred server, <i>address2</i> is the next most preferred server, and so on.
Command Default	None.		
Command Modes	DHCPv4 Server Profile DHCPv4 Server Profile Class Sub-mode		
Command History	Release	Modification	
	Release 6.0.1	This command was introduced.	
Usage Guidelines	No specific guidelines impact the use of this command.		
Task ID	Task ID	Operation	
	ip-services	read, write	

This example shows how to configure DNS server address:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
Router(config-dhcpv4-server-profile)# dns-server 192.168.155.9
```

domain-name

To configure domain name that DHCP clients will use to resolve DNS names, use the **domain-name** command in DHCP IPv4 server profile configuration mode.

domain-name *domain-name*

Syntax Description	<i>domain-name</i> Specify DHCP server domain name for the client.				
Command Default	None				
Command Modes	DHCP IPv4 Server Profile configuration DHCP IPv4 Server Profile Class sub-mode				
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>Release 6.0.1</td><td>This command was introduced.</td></tr> </table>	Release	Modification	Release 6.0.1	This command was introduced.
Release	Modification				
Release 6.0.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table> <tr> <th>Task ID</th><th>Operation</th></tr> <tr> <td>ip-services</td><td>read, write</td></tr> </table>	Task ID	Operation	ip-services	read, write
Task ID	Operation				
ip-services	read, write				

This example shows how to define cisco.com as domain name for DHCP server:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
Router(config-dhcpv4-server-profile)# domain-name cisco.com
```

duplicate-mac-allowed

To allow duplicate client MAC addresses across different VLANs and interfaces, use the **duplicate-mac-allowed** command in the DHCP IPv4 configuration mode. To disallow duplicate client MAC addresses, use the **no** form of this command.

duplicate-mac-allowed [{**exclude-vlan** | **include-giaddr**}]

Syntax Description	<table> <tr> <td>exclude-vlan</td><td>Excludes VLANs from the client key; only MAC address and interface form the client key.</td></tr> <tr> <td>include-giaddr</td><td>Enables support for duplicate sessions having the same MAC address but different <i>gi-address</i> values, mainly in the case of routed sessions.</td></tr> </table>	exclude-vlan	Excludes VLANs from the client key; only MAC address and interface form the client key.	include-giaddr	Enables support for duplicate sessions having the same MAC address but different <i>gi-address</i> values, mainly in the case of routed sessions.
exclude-vlan	Excludes VLANs from the client key; only MAC address and interface form the client key.				
include-giaddr	Enables support for duplicate sessions having the same MAC address but different <i>gi-address</i> values, mainly in the case of routed sessions.				
Command Default	By default, duplicate MAC address support is disabled.				
Command Modes	DHCP IPv4 configuration				

Command History	Release	Modification
	Release 6.3.2	Modified the command to include include-giaddr option as part of DHCP L3 snooping feature in BNG.
	Release 6.1.2	This command was introduced in BNG, with an addition of exclude-vlan option to exclude VLANs from the client key.

Usage Guidelines

You can enable duplicate MAC addresses on relay, proxy, server, and snoop DHCP modes.

Do not enable the **duplicate-mac-allowed** command for mobile subscribers.

With **exclude-vlan** option enabled, both inner and outer VLANs get excluded. You cannot exclude just one of them.

The **include-giaddr** option is used for DHCP L3 snooping feature in BNG. It is supported only on Cisco IOS XR 64-bit operating system.

Task ID

Task ID	Operation
ip-services	read, write

Example

This examples shows how to allow duplicate client MAC addresses across different VLANs and interfaces, using the **duplicate-mac-allowed** command:

```
Router# configure
Router(config)# dhcp ipv4
Router(config-dhcpv4)# duplicate-mac-allowed exclude-vlan
```

This examples shows how to enable support for duplicate sessions having the same MAC address but different *gi-address* values, for DHCP L3 snooping in BNG:

Related Commands

Command	Description
dhcp ipv4 , on page 12	Enables Dynamic Host Configuration Protocol (DHCP) for IPv4 and enters DHCP IPv4 configuration mode.

giaddr policy

To configure how Dynamic Host Configuration Protocol (DHCP) IPv4 Relay processes BOOTREQUEST packets that already contain a nonzero giaddr attribute, use the **giaddr policy** command in DHCP IPv4 profile relay configuration submode. To restore the default giaddr policy, use the **no** form of this command.

```
giaddr policy {replace | drop}
no giaddr policy {replace | drop}
```

Syntax Description

replace	Replaces the existing giaddr value with a value that it generates.
drop	Drops the packet that has an existing nonzero giaddr value.

Command Default

DHCP IPv4 relay retains the existing nonzero giaddr value in the DHCP IPv4 packet received from a client value.

Command Modes

DHCP IPv4 profile relay configuration
DHCP IPv4 profile proxy configuration

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

The **giaddr policy** command affects only the packets that are received from a DHCP IPv4 client that have a nonzero giaddr attribute.

Task ID

Task ID	Operations
ip-services	read, write

Examples

The following example shows how to use the **giaddr policy** command:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile client relay
Router(config-dhcpv4-relay-profile)# giaddr policy drop
```

Related Commands

Command	Description
dhcp ipv4 , on page 12	Enables DHCP for IPv4 and enters DHCP IPv4 configuration mode.

Command	Description
helper-address, on page 18	Configures the DHCP relay agent to relay packets to a specific DHCP Server.
interface (relay profile)	Specifies a relay profile on an interface.
profile (DHCP), on page 28	Configures a relay profile for the DHCP IPv4 component.
relay information check , on page 32	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
relay information option , on page 33	Enables the system to insert a DHCP relay agent information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option allow-untrusted , on page 34	Configures the DHCP component to not drop BOOTREQUEST messages that have the relay information option set and the giaddr set to zero.
relay information policy	Configures how a relay agent processes BOOTREQUEST messages that already contain a relay information option.

helper-address

To configure the Dynamic Host Configuration Protocol (DHCP) IPv4 relay agent to relay DHCP packets to a specific DHCP server, use the **helper-address** command in an DHCP IPv4 relay profile configuration mode. Use the **no** form of this command to clear the address.

helper-address [**vrf** *vrf-name*] [*address*] [**giaddr** *gateway-address*]
no helper-address [**vrf** *vrf-name*] [*address*] [**giaddr** *gateway-address*]

Syntax Description	<i>vrf-name</i>	(Optional) Specifies the name of a particular VRF.
	<i>address</i>	IPv4 in four part, dotted decimal format.
	giaddr <i>gateway-address</i>	(Optional) Specifies the gateway address to use in packets relayed to server. This keyword is applicable for IPv4 helper address.
Command Default	Helper address is not configured.	
Command Modes	DHCP IPv4 relay profile configuration	
Command History	Release	Modification
	Release 6.1.2	This command was introduced.
Usage Guidelines	A maximum of upto eight helper addresses can be configured.	

Task ID	Task ID	Operations
	ip-services	read, write

Examples

This example shows how to set the helper-address for a VRF using the **helper address** command in DHCP IPv4 relay profile class configuration mode:

```
RP/0/CPU0:router(config)# dhcp ipv4
RP/0/CPU0:router(config-dhcpv4)# profile profile1 relay
RP/0/CPU0:router(config-dhcpv4-relay-profile)# helper-address vrf my-server-vrf 10.1.1.1
```

Related Commands	Command	Description
	dhcp ipv4	Enables Dynamic Host Configuration Protocol (DHCP) for IPv4 and enters DHCP IPv4 configuration mode.
	relay information check	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
	relay information option	Enables the system to insert a DHCP relay agent information option in forwarded BOOTREQUEST messages to a DHCP server.
	relay information option allow-untrusted	Configures the DHCP component to not drop BOOTREQUEST messages that have the relay information option set and the giaddr set to zero.

helper-address (ipv6)

To configure the Dynamic Host Configuration Protocol (DHCP) IPv6 relay agent for prefix delegation to relay DHCP packets to a specific DHCP server, use the **helper-address** command in the DHCP IPv6 profile configuration submenu. Use the **no** form of this command to clear the address.

helper-address *ipv6-address* [**interface** *type interface-path-id*]
no helper-address *ipv6-address* [**interface** *type interface-path-id*]

Syntax Description	<i>ipv6-address</i>	The IPv6 address assigned to the interface. This argument must be in the form documented in RFC 2373 where the address is specified in hexadecimal format using 16-bit values between colons.
	interface <i>type</i>	Interface type. For more information, use the question mark (?) online help function.

interface-path-id

(Optional) Either a physical interface instance or a virtual interface instance as follows:

- Physical interface instance. Naming notation is *rack/slot/module/port* and a slash between value *s* is required as part of the notation.
 - *rack*: Chassis number of the rack.
 - *slot*: Physical slot number of the modular services card or line card.
 - *module*: Module number. A physical layer interface module (PLIM) is always 0.
 - *port*: Physical port number of the interface.

Note In references to a Management Ethernet interface located on a route processor card, the physical slot number is alphanumeric (RSP0) and the module is CPU0. Example: interface MgmtEth0/RSP0/CPU0/0.

- Virtual interface instance. Number range varies depending on interface type.

For more information about the syntax for the router, use the question mark (?) online help function.

Command Default

No default behavior or values

Command Modes

DHCP IPv6 profile configuration

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read, write

Example

This is a sample output that shows how to set the helper-address using the **helper-address** command

```
Router# config
Router(config)# dhcp ipv6
```

```
Router(config-dhcpv6)# profile p1 proxy
Router(config-dhcpv6-profile)# helper-address 2001:db8::3 GigabitEthernet 0/2/0/0
```

Related Commands

Command	Description
dhcp ipv6, on page 13	Enables Dynamic Host Configuration Protocol (DHCP) for IPv6.

hop-count-seed

To configure the hop-count in relay-forward message for a DHCP relay agent as zero, use the `hop-count-seed` command in the DHCP IPv6 configuration mode. By default, hop-count in relay-forward message for DHCP relay agents is set to one.

hop-count-seed
no hop-count-seed

Syntax Description

This command has no keywords or arguments.

Command Default

If this command is not configured, by default, hop-count in relay-forward message for DHCP relay agents is set to one.

Command Modes

DHCP IPv6 configuration

Command History

Release	Modification
Release 7.0.1	This command was introduced.

Usage Guidelines

Use this command only on routers that are configured as DHCP relay agents. You can only configure this command in the DHCP IPv6 mode and not on DHCP IPv4 mode.

Task ID

Task ID	Operations
ip-services	read, write

The following is an example of the **hop-seed-count** command:

```
Router# config
Router(config)# dhcp ipv6
Router(dhcp-ipv6)# hop-count-seed
```

iana-route-add

To enable route addition for identity association for non temporary address (IANA), use the **iana-route-add** command in DHCPv6 relay profile configuration submode. To disable route addition to IANA, use the **no** form of this command.

iana-route-add
no iana-route-add

Syntax Description	This command has no keywords or arguments.
Command Default	Disabled.
Command Modes	DHCP IPv6 relay profile configuration submode

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines	The DHCPv6 relay is capable of installing routes for multiple identity association for prefix delegation (IAPD) options within a DHCPv6 message. The route addition for IAPD is enabled by default. The DHCPv6 relay is capable of installing routes for IANA as well, but this feature is disabled by default. Users can enable the route addition to IANA feature by using iana-route-add command in DHCPv6 relay profile configuration submode.
-------------------------	---

Task ID	Task ID	Operation
	ip-services	read, write

Example

This example shows how to enable route addition to IANA:

```
Router# config
Router(config)# dhcp ipv6
Router(config-dhcpv6)# profile client relay
Router(config-dhcpv6-relay-profile)# iana-route-add
```

lease (DHCPv4 Server)

To configure the lease for an IP address assigned from the pool, use the **lease** command in the DHCPv4 server profile submode. To deconfigure, use the **no** form of this command.

lease { **infinite** | *days* }
no lease { **infinite** | *days* }

Syntax Description	infinite Configures an infinite lease.
---------------------------	---

<i>days</i>	Configures lease for the specified number of days. The number of days can range from 0 to 365.
-------------	--

Command Default

None

Command Modes

DHCPv4 Server Profile

Command History

Release	Modification
Release 6.1.2	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read, write

ExampleThis is a sample output from the **lease** command:

```
Router# config
Router#(config)# dhcp ipv4
Router#(config-dhcpv4)# profile P1 server
Router#(config-dhcpv4-server-profile)# lease infinite
```

limit lease

To configure the limit on a lease per-circuit-id, per-interface, or per-remote-id, use the **limit lease** command in the DHCPv4 server profile submode. To deconfigure, use the **no** form of this command.

limit lease {**per-circuit-id** | **per-interface** | **per-remote-id**} *value*
no limit lease {**per-circuit-id** | **per-interface** | **per-remote-id**} *value*

Syntax Description

per-circuit-id	Inserts the limit lease type circuit-id.
per-interface	Inserts the limit lease type interface.
per-remote-id	Inserts the limit lease type remote-id.
<i>value</i>	Value of limit lease count. Range is from 1 to 240000.

Command Default

None

Command Modes

DHCPv4 Server Profile

Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read, write

Example

This is a sample output from the **limit lease** command:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile P1 server
Router(config-dhcpv4-server-profile)# limit lease per-circuit-id 23
```

netbios-name-server

To configure net bios name servers, use the **netbios-name-server** command in the DHCPv4 server profile submode. To deconfigure, use the **no** form of this command.

netbios-name server *address1address2...address8*
no netbios-name server *address1address2...address8*

Syntax Description	<i>address1address2...address8</i> Name of the server or IP address.	
Command Default	None	
Command Modes	DHCPv4 Server Profile	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read, write

Example

This is a sample configuration for the **netbios-name-server** command:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
Router(config-dhcpv4-server-profile)# netbios-name-server 10.20.3.5
```

netbios-node-type

To configure the type of net bios node, use the **netbios-node-type** command in the DHCPv4 server profile submode. To deconfigure, use the **no** form of this command.

netbios-node-type { *number* | *b-node* | *h-node* | *m-node* | *p-node* }

Syntax Description	<table> <tr> <td><i>number</i></td><td>Hexadecimal number.</td></tr> <tr> <td><i>b-node</i></td><td>broadcast node.</td></tr> <tr> <td><i>h-node</i></td><td>hybrid node.</td></tr> <tr> <td><i>m-node</i></td><td>mixed node.</td></tr> <tr> <td><i>p-node</i></td><td>peer-to-peer node.</td></tr> </table>	<i>number</i>	Hexadecimal number.	<i>b-node</i>	broadcast node.	<i>h-node</i>	hybrid node.	<i>m-node</i>	mixed node.	<i>p-node</i>	peer-to-peer node.
<i>number</i>	Hexadecimal number.										
<i>b-node</i>	broadcast node.										
<i>h-node</i>	hybrid node.										
<i>m-node</i>	mixed node.										
<i>p-node</i>	peer-to-peer node.										
Command Default	None										
Command Modes	DHCPv4 Server Profile										
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>Release 6.0.1</td><td>This command was introduced.</td></tr> </table>	Release	Modification	Release 6.0.1	This command was introduced.						
Release	Modification										
Release 6.0.1	This command was introduced.										
Usage Guidelines	No manually configured prefix delegations exist.										
Task ID	<table> <tr> <th>Task ID</th><th>Operation</th></tr> <tr> <td>ip-services</td><td>read, write</td></tr> </table>	Task ID	Operation	ip-services	read, write						
Task ID	Operation										
ip-services	read, write										

Example

This is a sample output from the **bootfile** command:

```
RP/0/RP0/CPU0:router# config
RP/0/RP0/CPU0:router(config)# dhcp ipv4
RP/0/RP0/CPU0:router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
RP/0/RP0/CPU0:router(config-dhcpv4-server-profile)# netbios-node-type p-node
```

option

To configure the DHCP option code, use the **option** command in the DHCPv4 server profile submode. To deconfigure, use the **no** form of this command.

The DHCP options which are not commonly used are configured in a raw format using **option** command.

```
option option-code{ascii string | hex string | ip address}
no option option-code{ascii string | hex string | ip address}
```

Syntax Description

<i>option-code</i>	Specifies the DHCP option code.
<i>ascii string</i>	Specifies the data as an NVT ASCII string.
<i>hex string</i>	Specifies the data as a hex string.
<i>ip address</i>	Specifies the hostname or the IP Address.

Command Default

None

Command Modes

DHCPv4 Server Profile
DHCPv4 Server Profile Class Sub-mode

Command History

Release	Modification
Release 6.1.2	This command was introduced.

Usage Guidelines

DHCP server profile class sub-mode supports configuring DHCP options except few that are listed in the table below:

Table 1: Not Supported DHCP Options under DHCPv4 Server Profile Class Sub-mode

Pad	10
Hostname	12
Requested Address	50
Over Load	52
Message Type	53
Server Identifier	54

Renewal Time	58
Rebind Time	59
Client Identifier	61
Relay Information	82
End	255

Task ID**Task ID Operation**

ip-services read,
write

Example

This is a sample output from the **option** command:

```
Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile DHCP_SERVER_PROFILE server
Router(config-dhcpv4-server-profile)# option 23 ip 10.20.34.56
Router(config-dhcpv4-server-profile)# option 16 hex 20187634
Router(config-dhcpv4-server-profile)# option 17 ascii /users/cisco/
```

pool

To enable distributed address pool service on IPv4 or IPv6 profile and to enter the pool IPv4 or IPv6 configuration submode, use the **pool ipv4** or **pool ipv6** command in the Global Configuration mode. To disable this feature, use the **no** form of this command.

```
pool { [ipv4 pool-name { address-range | exclude | network utilization-mark } ] | [ipv6 { address-range | |
exclude | | network | prefix-length | prefix-range | utilization-mark } ] [vrf { [all ipv6
ipv6-pool-name] | [vrf-name { [ipv4 ipv4-pool-name { address-range | exclude | network utilization-mark } ]
| [ipv6 ipv6-pool-name { address-range | exclude | network prefix-length prefix-range utilization-mark } } ] } ] } ] }
no pool ipv4
```

Syntax Description

<i>address-range</i>	Specifies the address-range of the pool.
exclude	Specifies the address to be excluded from the pool.
network	Specifies the network of the pool.
<i>utilization-mark</i>	Specifies the utilization-mark of the pool.
<i>prefix-length</i>	Specifies the prefix-length to be used for the pool.
<i>prefix-range</i>	Specifies the prefix-range to be used for the pool.

Command Default None

Command Modes Global Configuration

Command History	Release	Modification
	Release 6.1.2	This command was introduced.

Usage Guidelines Use the **pool ipv4** command to enter IPv4 pool configuration submode.

Task ID	Task ID	Operation
	ip-services	read, write

This is an example of configuring the **pool ipv4** command in the Global Configuration mode:

```
Router# configure
Router(config)# pool ipv4 pool1
Router(config-pool-ipv4)# address-range 10.10.10.1 10.10.10.254
```

Related Commands	Commands	Description
	pool vrf	Enables distributed address pool service on vrf, ipv4, and ipv6.
	exclude	Specifies a range of IP addresses that distributed address pool service should not assign to clients.
	address-range	Specifies a range of IP addresses.

profile (DHCP)

To configure a DHCP relay profile, DHCP snooping profile, DHCP base profile or a DHCP proxy profile for the Dynamic Host Configuration Protocol (DHCP) IPv4 or IPv6 component and to enter the profile mode, use the **profile** command in DHCP IPv4 or DHCP IPv6 configuration mode. To disable this feature and exit the profile mode, use the **no** form of this command.

profile *name* **relay**
no profile *name* **relay**

Syntax Description	<i>name</i>	Name that uniquely identifies the relay or snoop profile.
--------------------	-------------	---

relay

Configures a DHCP relay profile. A DHCP relay agent is a host that forwards DHCP packets between clients and servers. When the clients and servers are not on the same physical subnet, the relay agents are used to forward requests and replies between them.

A DHCP relay agent is any host that forwards DHCP packets between clients and servers. Relay agents are used to forward requests and replies between clients and servers when they are not on the same physical subnet. Relay agent forwarding is distinct from the normal forwarding of an IP router, where IP datagrams are switched between networks rather transparently. By contrast, relay agents receive DHCP messages and then generate a new DHCP message to send out on another interface. The relay agent sets the gateway IP address (giaddr field of the DHCP packet) and, if configured, adds the relay agent information option (option82) in the packet and forwards it to the DHCP server. The reply from the server is forwarded back to the client after removing option 82.

Command Default

None

Command Modes

DHCP IPv4 configuration

DHCP IPv6 configuration

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operations
ip-services	read, write

Examples

This example shows how to use the **profile** command to configure DHCP IPv6 relay profile:

```
RP/0/RP0/CPU0:router(config)# dhcp ipv6
RP/0/RP0/CPU0:router(config-dhcpv6)# profile client relay
RP/0/RP0/CPU0:router(config-dhcpv6-relay-profile)#
```

This example shows how to use the **profile** command to configure DHCP IPv4 relay profile:

```
RP/0/RP0/CPU0:router(config)# dhcp ipv4
RP/0/RP0/CPU0:router(config-dhcpv4)# profile client relay
RP/0/RP0/CPU0:router(config-dhcpv4-relay-profile)#
```

relay information authenticate

To specify relay agent information option to the policy plane for authentication purposes, use the **relay information authenticate** command in the DHCP IPv4 proxy profile configuration mode. To disable the relay option, use the **no** form of this command.

relay information authenticate {received | inserted}

Syntax Description

received Authenticate using received relay agent information option.

inserted Authenticate using inserted relay agent information option.

Command Default

None

Command Modes

DHCP IPv4 proxy profile configuration

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operations
ip-services	read, write

Examples

This example shows how to specify the received relay agent information option for authentication using the **relay information authenticate** command in DHCP IPv4 proxy profile configuration mode:

```

Router# config
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile myprofile proxy
Router(config-dhcpv4-proxy-profile)# relay information authenticate received

```

Related Commands

Command	Description
dhcp ipv4	Enables Dynamic Host Configuration Protocol (DHCP) for IPv4 and enters DHCP IPv4 configuration mode.
relay information check	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
relay information option	Enables the system to insert a DHCP relay agent information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option allow-untrusted	Configures the DHCP component to not drop BOOTREQUEST messages that have the relay information option set and the giaddr set to zero.
relay information option circuit-id	Enables the system to insert a circuit-id information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option remote-id	Enables the system to insert a remote-id information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option vpn	Enables the system to insert vpn information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option vpn-mode	Enables the system to insert a vpn-mode information option in forwarded BOOTREQUEST messages to a DHCP server.

Command	Description
relay information policy	Configures how a relay agent processes BOOTREQUEST messages that already contain a relay information option.

relay information check

To configure a Dynamic Host Configuration Protocol (DHCP) IPv4 Relay to validate the relay agent information option in forwarded BOOTREPLY messages, use the **relay information check** command in DHCP IPv4 relay profile configuration submode. To disable this feature, use the **no** form of this command.

relay information check
no relay information check

Syntax Description	This command has no keywords or arguments.						
Command Default	DHCP validates the relay agent information option.						
Command Modes	DHCP IPv4 relay profile configuration						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>Release 6.1.2</td><td>This command was introduced.</td></tr> </table>	Release	Modification	Release 6.1.2	This command was introduced.		
Release	Modification						
Release 6.1.2	This command was introduced.						
Usage Guidelines	No specific guidelines impact the use of this command.						
Task ID	<table> <tr> <th>Task ID</th><th>Operations</th></tr> <tr> <td>ip-services</td><td>read, write</td></tr> <tr> <td>basic-services</td><td>read, write</td></tr> </table>	Task ID	Operations	ip-services	read, write	basic-services	read, write
Task ID	Operations						
ip-services	read, write						
basic-services	read, write						

This example shows how to use the **relay information check** command:

```
RP/0/CPU0:router# config
RP/0/CPU0:router(config)# dhcp ipv4
RP/0/CPU0:router(config-dhcpv4)# profile client relay
RP/0/CPU0:router(config-dhcpv4-relay-profile)# relay information check
```

Related Commands	Command	Description
	dhcp ipv4	Enables Dynamic Host Configuration Protocol (DHCP) for IPv4 and enters DHCP IPv4 configuration mode.

Command	Description
helper-address	Configures the DHCP relay agent to relay packets to a specific DHCP Server.
relay information check	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
relay information option	Enables the system to insert a DHCP relay agent information option in forwarded BOOTREQUEST messages to a DHCP server.
relay information option allow-untrusted	Configures the DHCP component to not drop BOOTREQUEST messages that have the relay information option set and the giaddr set to zero.

relay information option

To configure Dynamic Host Configuration Protocol (DHCP) IPv4 relay to insert relay agent information option in forwarded BOOTREQUEST messages to a DHCP server, use the **relay information option** command in DHCP IPv4 relay profile relay configuration. To disable inserting relay information into forwarded BOOTREQUEST messages, use the **no** form of this command.

relay information option
no relay information option

Syntax Description This command has no keywords or arguments.

Command Default None

Command Modes DHCP IPv4
 relay
 profile
 configuration

Command History	Release	Modification
	Release 6.1.2	This command was introduced.

Usage Guidelines The **relay information option** command automatically adds the circuit identifier suboption and the remote ID suboption to the DHCP relay agent information option.

The **relay information option** command enables a DHCP server to identify the user (for example, cable access router) sending the request and initiate appropriate action based on this information. By default, DHCP does not insert relay information.

The upstream DHCP server or DHCP relay interface must be configured to accept this type of packet using the **relay information option allow-untrusted** configuration. This configuration prevents the server or relay from dropping the DHCP message.

Task ID	Task ID	Operations
	ip-services	read, write
	basic-services	read, write

This example shows how to use the **relay information option** command:

```
RP/0/CPU0:router# config
RP/0/CPU0:router(config)# dhcp ipv4
RP/0/CPU0:router(config-dhcpv4)# profile client relay
RP/0/CPU0:router(config-dhcpv4-relay-profile)# relay information option
```

Related Commands	Command	Description
	dhcp ipv4	Enables DHCP for IPv4 and enters DHCP IPv4 configuration mode.
	helper-address	Configures the DHCP relay agent to relay packets to a specific DHCP Server.
	relay information check	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
	relay information option allow-untrusted	Configures the DHCP component to not drop BOOTREQUEST messages that have the relay information option set and the giaddr set to zero.

relay information option allow-untrusted

To configure the Dynamic Host Configuration Protocol (DHCP) IPv4 relay not to drop discard BOOTREQUEST packets that have the relay information option set and the giaddr set to zero, use the **relay information option allow-untrusted** command in DHCP IPv4 relay profile configuration submode. To restore the default behavior, which is to discard the BOOTREQUEST packets that have the relay information option and set the giaddr set to zero, use the **no** form of this command.

relay information option allow-untrusted
no relay information option allow-untrusted

Syntax Description	This command has no keywords or arguments.
Command Default	The packet is dropped if the relay information is set and the giaddr is set to zero.
Command Modes	DHCP IPv4 relay profile

configuration

Command History

Release	Modification
Release 6.1.2	This command was introduced.

Usage Guidelines

According to RFC 3046, relay agent receiving a DHCP packet from an untrusted circuit with giaddr set to zero but with a relay agent information option already present in the packet shall discard the packet and increment an error count. This configuration prevents relay from dropping the DHCP message.

Task ID

Task ID	Operations
ip-services	read, write
basic-services	read, write

Examples

This example shows how to use the **relay information option allow-untrusted** command:

```
RP/0/CPU0:router# config
RP/0/CPU0:router(config)# dhcp ipv4
RP/0/CPU0:router(config-dhcpv4)# profile client relay
RP/0/CPU0:router(config-dhcpv4-relay-profile)# relay information option allow-untrusted
```

Related Commands

Command	Description
dhcp ipv4	Enables Dynamic Host Configuration Protocol (DHCP) for IPv4 and enters DHCP IPv4 configuration mode.
helper-address	Configures the DHCP relay agent to relay packets to a specific DHCP Server.
relay information check	Configures a DHCP server to validate the relay agent information option in forwarded BOOTREPLY messages.
relay information option	Enables the system to insert a DHCP relay agent information option in forwarded BOOTREQUEST messages to a DHCP server.

secure-arp

To allow DHCP to add an ARP cache entry when DHCP assigns an IP address to a client in IP subscriber sessions, use the **secure-arp** command in DHCP IPv4 profile proxy configuration or DHCP IPv4 server profile mode. To disallow DHCP to add an ARP cache entry when DHCP assigns an IP address to a client, use the **no** form of this command.

secure-arp
no secure-arp

Syntax Description	This command has no keywords or arguments.	
Command Default	By default, secure ARP support is disabled.	
Command Modes	DHCP IPv4 proxy profile configuration DHCP IPv4 Server Profile	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	<p>In standalone DHCP sessions, the DHCP server adds an ARP entry when it assigns an IP address to a client. However, for IP subscriber sessions, DHCP server does not add an ARP entry. Although ARP establishes correspondences between network addresses, an untrusted device can spoof IP an address not assigned to it posing a security threat for IP subscriber sessions.</p> <p>Secure ARP allows DHCP to add an ARP cache entry when DHCP assigns an IP address to a client in IP subscriber sessions. This is to prevent untrusted devices from spoofing IP addresses not assigned to them. Secure ARP is disabled by default.</p>	
Task ID	Task ID	Operation
	ip-services	read, write

Example

This examples shows how to allow DHCP to add an ARP cache entry when DHCP assigns an IP address to a client using the **secure-arp** command in DHCP IPv4 server profile configuration:

```
Router# configure
Router(config)# dhcp ipv4
Router(config-dhcpv4)# profile profile1 server
Router(config-dhcpv4-server-profile)# secure-arp
Router(config-dhcpv4-server-profile)#
```

show dhcp ipv4 client

To display DHCP client binding information, use the **show dhcp ipv4 client** command in XR EXEC mode.

show dhcp ipv4 client <interfaceName> [**detail**] [**debug**]

Syntax Description	interfaceName Displays the DHCP IPv4 address of the specified interface.
	detail (Optional) Specifies detailed results.

debug (Optional) Displays internal debugging information.

Command Default No default behavior or values

Command Modes XR EXEC mode

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines Use the **show dhcp ipv4 client** command to display the DHCP IPv4 for the specified client.

Task ID	Task ID	Operations
	IP-Services	read

Examples

The following example shows how to display DHCP IPv4 binding information:

```
Router# show dhcp ipv4 client
Mon May 6 16:35:32.581 UTC
```

Interface name Time Rem	IP Address	Binding State	Lease
-----	-----	-----	
MgmtEth0_0_CPU0_0 (00:28:08)	192.168.190.130	BOUND	1688 secs

```
Router#
Router# show dhcp ipv4 client binding ?
  MgmtEth      Ethernet/IEEE 802.3 interface(s)
  detail       Show detailed client binding information
  |            Output Modifiers
  <cr>
Router# show dhcp ipv4 client detail
Mon May 6 16:35:56.579 UTC
```

```
-----
Client Interface name      : MgmtEth0_0_CPU0_0
Client Interface handle    : 0x1280
Client Interface VRF name  : default
Client ChAddr              : 000c.292f.950e
Client ID                  : MgmtEth0_0_CPU0_0
Client State               : BOUND
Client IP Address (Dhcp)   : 192.168.190.130
Client IP Address Mask     : 255.255.255.0
Client Lease Time Allocated : 1800 secs (00:30:00)
Client Lease Time Remaining : 1664 secs (00:27:44)
Client Selected Server Addr : 192.168.190.254
-----
```

```
Router#
Router# show dhcp ipv4 client binding detail ?
  MgmtEth      Ethernet/IEEE 802.3 interface(s)
  debug        Show detailed debug level client binding information
  |            Output Modifiers
```

show dhcp ipv4 client statistics

```

<cr>
Router# show dhcp ipv4 client detail debug
Mon May 6 16:36:43.836 UTC

-----
Client Interface name      : MgmtEth0_0_CPU0_0
Client Interface handle    : 0x1280
Client Interface VRF name  : default
Client ChAddr             : 000c.292f.950e
Client ID                  : MgmtEth0_0_CPU0_0
Client State               : BOUND
Client IP Address (Dhcp)   : 192.168.190.130
Client IP Address Mask     : 255.255.255.0
Client Lease Time Allocated : 1800 secs (00:30:00)
Client Lease Time Remaining : 1617 secs (00:26:57)
Client Selected Server Addr : 192.168.190.254
Client Interface VRF id    : 0x60000000
Client Interface VRF Table id : 0xe0000000
Client XID                 : 0xa7f
Client Timers Running      : 0x2 (T1_RENEW_TIMER)
Client Renew Time Allocated : 900 secs (00:15:00)
Client Renew Time Adjusted  : 900 secs (00:15:00)
Client Rebind Time Allocated : 1575 secs (00:26:15)
Client Rebind Time Adjusted  : 1575 secs (00:26:15)
Client Checkpoint object id : 0x80002fd8
Client IPv4 MA configured   : TRUE
-----

```

```

Router#
Router# show dhcp ipv4 client mgmtEth 0/0/CPU0/0
Mon May 6 16:49:54.382 UTC

```

Interface name	IP Address	Binding State	Lease Time Rem
MgmtEth0_0_CPU0_0	192.168.190.130	BOUND	1727 secs (00:28:47)

RP/0/0/CPU0:ios#

show dhcp ipv4 client statistics

To display DHCP client statistical information, use the **show dhcp ipv4 client statistics** command in XR EXEC mode.

show dhcp ipv4 client *interfaceName* *interface-number* **statistics**

Syntax Description	interfaceName	Displays the DHCP IPv4 statistical information of the specified interface.
	statistics	Applies a statistics template and enable statistics collection.
Command Default	No default behavior or values	
Command Modes	XR EXEC mode	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines

Use the **show dhcp ipv4 client statistics** command to display the DHCP IPv4 statistical information for the specified client.

Task ID**Task ID Operations**

IP-Services read

Examples

The following example shows how to display the DHCP IPv4 statistics information:

```
RP/0/0/CPU0:ios#show dhcp ipv4 client binding mgmtEth 0/0/CPU0/0 statistics
Mon May 6 16:49:46.402 UTC
```

```
-----
Client Interface name      : MgmtEth0_0_CPU0_0
Client State               : BOUND
-----
```

TOTAL STATISTICS

```
-----
DISCOVERS SENT           : 1
OFFERS SENT              : 1
OFFERS RECEIVED          : 1
ACKS RECEIVED            : 1
RELEASE SENT             : 1
RESYNC SENT TO IM        : 1
IPV4_MA CFG SENT         : 1
IPV4_MA CFG SUCCESS      : 1
INIT TIMER STARTED       : x
T1-RENEW TIMER STARTED   : x
T2_REBIND TIMER STARTED  : x
LEASE TIMER STARTED      : x
INIT TIMER STOPPED       : x
T1-RENEW TIMER STOPPED   : x
T2_REBIND TIMER STOPPED  : x
LEASE TIMER STOPPED      : x
-----
```

ERROR COUNTERS

```
-----
OFFERS IGNORED           : 1
ACK IGNORED              : 1
DECLINE SENT             : 1
NACK RECEIVED            : 1
INVALID OFFERS RECEIVED  : 1
INVALID ACKS RECEIVED    : 1
IPV4_MA CFG FAILED       : 0
IPV4_MA CFG FAILED REASON : "... "
IM RESYNC ERROR REASON   : "... "
```

show dhcp ipv4 proxy interface

To display the proxy interface information for Dynamic Host Configuration Protocol (DHCP) IPv4, use the **show dhcp ipv4 proxy interface** command in XR EXEC mode.

```
show dhcp ipv4 proxy interface [interface-type interface-name] [detail]
```

Syntax Description	<i>interface-type</i>	Type of the proxy interface.
	<i>interface-name</i>	Name of the proxy interface.
	detail	Displays the detailed information of proxy interface.
Command Default	None	
Command Modes	XR EXEC mode	
Command History	Release	Modification
	Release 6.0.1	This command was supported for BNG.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read

This is a sample output from the **show dhcp ipv4 proxy interface** command:

```
Router# show dhcp ipv4 proxy interface bundle-Ether 70.16 detail
Sat Jan  5 14:25:53.484 UTC

Interface:          Bundle-Ether70.16
VRF:                default
Mode:               Proxy
Profile Name:       proxy1
Lease Limit:        per circuit id from AAA 2

Lease Count Details:
Circuit id from AAA                                Count
c2                                                  1
```

This table describes the significant fields shown in the display.

Table 2: show dhcp ipv4 proxy interface Command Field Descriptions

Field	Description
Lease Limit	Specifies the lease limit value sent from AAA server.
Count	Specifies the number of sessions on the router having the specific Circuit-ID received from the AAA server.

show dhcp ipv4 proxy statistics

To display DHCP proxy statistics, use the **show dhcp ipv4 proxy statistics** command in EXEC mode.

show dhcp ipv4 proxy statistics {raw | include-zeroes | details}

Syntax Description	raw	Displays debug statistics.
	include-zeroes	Displays debug statistics that are zero.
	details	Displays DHCP server statistics details.

Command Default None.

Command Modes EXEC

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 proxy statistics** command:

```
RP/0/CPU0:router# show dhcp ipv4 proxy statistics
      VRF      |  RX  |  TX  |  DR  |
-----|-----|-----|-----|
      default  |    0  |    0  |    0  |
```

Related Commands	Command	Description
	show dhcp ipv4 server binding	Displays DHCP client bindings for server.
	show dhcp ipv4 server profile	Displays DHCP server profile information.

show dhcp ipv4 relay profile

To display Dynamic Host Configuration Protocol (DHCP) relay agent status, use the **show dhcp ipv4 relay profile** command in EXEC mode.

show dhcp ipv4 relay profile

Syntax Description This command has no keywords or arguments.

Command Default No default behavior or values

Command Modes EXEC mode

Command History	Release	Modification
	Release 6.1.2	This command was introduced.

Usage Guidelines This command displays the relay profiles created for DHCP IPv4.

Task ID	Task ID	Operations
	ip-services	read

Examples The following is sample output from the **show dhcp ipv4 relay profile** command:

```
Router# show dhcp ipv4 relay profile

DHCP IPv4 Relay Profiles
-----
r1
r2
```

Related Commands	Command	Description
	show dhcp ipv4 relay profile name	Displays Dynamic Host Configuration Protocol (DHCP) relay agent status, specific to a relay profile.

show dhcp ipv4 relay profile name

To display Dynamic Host Configuration Protocol (DHCP) relay agent status, specific to a relay profile, use the **show dhcp ipv4 relay profile name** command in EXEC mode.

show dhcp ipv4 relay profile [**name** *profile-name*]

Syntax Description	name <i>profile-name</i> (Optional)	Name that uniquely identifies the relay profile.
--------------------	--	--

Command Default If *name* is not specified, displays a list of configured DHCP profile names.
No default behavior or values

Command Modes EXEC mode

Command History	Release	Modification
	Release 6.1.2	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	ip-services	read

Examples The following is sample output from the **show dhcp ipv4 relay profile name** command:

```
Router# show dhcp ipv4 relay profile name r1

DHCP IPv4 Relay Profile r1:

Helper Addresses:
10.10.10.1, vrf default
Information Option: Disabled
Information Option Allow Untrusted: Disabled
Information Option Policy: Replace
Information Option Check: Disabled
Giaddr Policy: Keep
Broadcast-flag Policy: Ignore

VRF References:
default
Interface References:
FINT0_RP0_CPU0
MgmtEth0_RP0_CPU0_0
```

show dhcp ipv4 relay statistics

To display the Dynamic Host Configuration Protocol (DHCP) IPv4 relay agent packet statistics information for VPN routing and forwarding (VRF) instances, use the **show dhcp ipv4 relay statistics** command in EXEC mode.

show dhcp [vrf {vrf-name | default}] ipv4 relay statistics

Syntax Description	vrf <i>vrf-name</i>	(Optional) Name that uniquely identifies the VRF.
	default	(Optional) Displays the relay statistics information for the default VRF.

Command Default No default behavior or values

Command Modes EXEC mode

Command History	Release	Modification
	Release 6.1.2	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID

Task ID Operations

ip-services read

Examples

The following is sample output from the **show dhcp ipv4 relay statistics** command when none of the optional keywords or arguments are used command :

```
Router# show dhcp ipv4 relay statistics
```

VRF	RX	TX	DR
default	0	0	0

The following is sample output from the show dhcp ipv4 relay statistics command using the **vrf** and **default** keywords:

```
Router# show dhcp vrf default ipv4 relay statistics
```

```
01 Sep 6 07:10:35.873 UTC
```

```
DHCP IPv4 Relay Statistics for VRF default:
```

TYPE	RECEIVE	TRANSMIT	DROP
DISCOVER	0	0	0
OFFER	0	0	0
REQUEST	0	0	0
DECLINE	0	0	0
ACK	0	0	0
NAK	0	0	0
RELEASE	0	0	0
INFORM	0	0	0
LEASEQUERY	0	0	0
LEASEUNASSIGNED	0	0	0
LEASEUNKNOWN	0	0	0
LEASEACTIVE	0	0	0
BOOTP-REQUEST	0	0	0
BOOTP-REPLY	0	0	0
BOOTP-INVALID	0	0	0

show dhcp ipv4 server binding

To display DHCP client bindings for server, use the **show dhcp ipv4 server binding** command in EXEC mode.

show dhcp ipv4 server binding { **detail** | **location** *node-ID* | **interface** *type interface-path-ID* | **vrf** *vrf-name* | **ip-address** *address* | **mac-address** *address* | **srg** | **srg-master** | **srg-slave** | **summary** }

Syntax Description

detail	Displays detailed client binding information for all clients.
location <i>node-ID</i>	Displays detailed client binding information for a specified node.

interface <i>type interface-path-ID</i>	Displays client binding by interface. Specifies the interface type. For more information, use the question mark (?) online help function. Physical interface or virtual interface. Use the show interfaces command to see a list of all interfaces currently configured on the router. Note For more information about the syntax for the router, use the question mark (?) online help function.
vrf <i>vrf-name</i>	Displays client binding by vrf name.
ip-address <i>address</i>	Displays detailed client binding information per IP address or mac-address.
mac-address <i>address</i>	Displays detailed client binding information per mac-address.
srg	Displays client binding by SRG group.
srg-master	Displays client binding by SRG master.
srg-slave	Displays client binding by SRG slave.

Command Default	None.
------------------------	-------

Command Modes	EXEC
----------------------	------

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 server binding** command:

```
Router# show dhcp ipv4 server binding detail
```

```
Thu Aug 1 11:37:34.784 IST
MAC Address:          ca01.4b16.0000
VRF:                  default
IP Address:           10.10.10.7
Server IP Address:    10.10.10.2
ReceivedCircuit ID:   -
InsertedCircuit ID:   -
ReceivedRemote ID:    -
InsertedRemote ID:    -
ReceivedVSISO:        -
```

show dhcp ipv4 server disconnect-history

```

Auth. on received relay info:TRUE
ParamRequestOption:      -
SavedOptions:            -
Profile:                 TEST
Selected Profile:        TEST
State:                   BOUND
Lease:                   1800 secs (00:30:00)
Lease remaining:         1744 secs (00:29:04)
Client ID:
0x00-0x63-0x69-0x73-0x63-0x6F-0x2D-0x63-0x61-0x30-0x31-0x2E-0x34-0x62-0x31-0x36-0x2E-0x30-0x30-0x30-0x2D-0x50-0x6F-0x31-0x30-0x2E-0x31
Access Interface:        Bundle-Ether10.1
Access VRF:               default
VLAN Id:                 100
Subscriber Label:        0x41
Subscriber Interface:     Bundle-Ether10.1.ip2
Srg State:               NONE
Srg Group Id:            0
Event History:
Session Start:           Aug  1 10:38:05.426
PACKET_DISCOVER          :      0.001s
DPM_SUCCESS              :      0.114s
DAPS_SUCCESS             :      0.118s
PACKET_REQUEST           :      0.818s
LEASE_DPM_SUCCESS        :      1.181s
OTHER                    :      45.005s

```

Related Commands

Command	Description
show dhcp ipv4 server profile	Displays DHCP server profile information.
show dhcp ipv4 server statistics	Display DHCP server statistics.

show dhcp ipv4 server disconnect-history

To display DHCP server profile information with ipv4 binding for disconnect history, use the **show dhcp ipv4 server interface** command in EXEC mode.

show dhcp ipv4 server interface {detail | location | mac-address}

Syntax Description

detail	Displays detailed DHCP server profile information for server.
location	Displays detailed DHCP server profile information for node location.
mac-address	Displays detailed DHCP server profile information for client disconnect history information.

Command Default

None.

Command Modes

EXEC

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID**Task ID Operation**

ip-services read

Example

This is a sample output from the **show dhcp ipv4 server interface** command:

```
RP/0/0/CPU0:ios#show dhcp ipv4 server disconnect-history
Thu Aug 15 16:24:51.736 IST
Codes: Amb - Ambiguous VLAN, B - Base, R - Relay, P - Proxy,
       SR - Server, S - Snoop, C - Client, INV - Invalid
       CID - Circuit Id, RID - Remote Id, INTF - Interface
```

```
Interface                               Mode Profile Name                               Amb Lease Limit
-----
```

show dhcp ipv4 server interface

To display DHCP server profile information with ipv4 binding for interfaces, use the **show dhcp ipv4 server interface** command in EXEC mode.

show dhcp ipv4 server interface { **Bundle-Ether** | **FastEthernet** | **FiftyGigE** | **FortyGigE** | **GigabitEthernet** | **HundredGigE** | **MgmtEth** | **PW-Ether** | **TenGigE** | **TwentyFiveGigE** }

Syntax Description

BVI	Displays Bridge-Group Virtual Interface.
Bundle-Ether	Displays aAggregated Ethernet interface(s).
FastEthernet	Displays detailed DHCP server profile information for FastEthernet/IEEE 802.3 interface(s).
FiftyGigE	Displays detailed DHCP server profile information for FiftyGigabitEthernet/IEEE 802.3 interface(s).
FortyGigE	Displays detailed DHCP server profile information for FortyGigabitEthernet/IEEE 802.3 interface(s).
GigabitEthernet	Displays detailed DHCP server profile information for GigabitEthernet/IEEE 802.3 interface(s).
HundredGigE	Displays detailed DHCP server profile information for HundredGigabitEthernet/IEEE 802.3 interface(s).
MgmtEth	Displays detailed DHCP server profile information for Ethernet/IEEE 802.3 interface(s).
PW-Ether	Displays detailed DHCP server profile information for PWHE ethernet interface.

TenGigE	Displays detailed DHCP server profile information for TenGigabitEthernet/IEEE 802.3 interface(s).
----------------	---

TwentyFiveGigE	Displays detailed DHCP server profile information for TwentyFiveGigabitethernet/IEEE 802.3 interface(s).
-----------------------	--

Command Default	None.
------------------------	-------

Command Modes	EXEC
----------------------	------

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 server interface** command:

```
RP/0/0/CPU0:ios#show dhcp ipv4 server interface
Thu Aug 15 16:24:51.736 IST
Codes: Amb - Ambiguous VLAN, B - Base, R - Relay, P - Proxy,
       SR - Server, S - Snoop, C - Client, INV - Invalid
       CID - Circuit Id, RID - Remote Id, INTF - Interface

Interface                Mode Profile Name                Amb Lease Limit
-----
```

show dhcp ipv4 server profile

To display DHCP server profile information with ipv4 binding, use the **show dhcp ipv4 server profile** command in EXEC mode.

show dhcp ipv4 server profile name *profile-name* [**location** *node-ID*]

Syntax Description	<i>profile-name</i>	Name of the profile.
	location <i>node-ID</i>	Displays detailed DHCP server profile information for a specified node.

Command Default	None.
------------------------	-------

Command Modes	EXEC
----------------------	------

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 server profile** command:

```
Router# show dhcp ipv4 server profile name foo

Profile:    foo
VRF References:
Interface References: GigabitEthernet0/2/0/0
```

Related Commands	Command	Description
	show dhcp ipv4 server binding	Displays DHCP client bindings for server.
	show dhcp ipv4 server statistics	Displays DHCP server statistics.
	show dhcp ipv4 server interface	Displays DHCP client bindings for server with respect to interfaces.
	show dhcp ipv4 server disconnect-history	

show dhcp ipv4 server statistics

To display DHCP server statistics, use the **show dhcp ipv4 server statistics** command in EXEC mode.

show dhcp ipv4 server statistics [**raw** { [**all**] [**include-zeroes**] [**location** *node-ID*] }]

Syntax Description	raw	Displays debug statistics.
	all	Displays debug statistics for base mode.
	include-zeroes	Displays debug statistics that are zero.
	location <i>node-ID</i>	Displays DHCP server statistics information for a specified node.

Command Default	None.	
Command Modes	EXEC	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 server statistics** command:

```
Router# show dhcp ipv4 server statistics
      VRF      |      RX      |      TX      |      DR      |
-----
      default  |             0 |             0 |             0 |
```

Related Commands

Command	Description
show dhcp ipv4 server binding	Displays DHCP client bindings for server.
show dhcp ipv4 server profile	Displays DHCP server profile information.
show dhcp ipv4 server interface	Displays DHCP server profile information for interface.
show dhcp ipv4 server disconnect-history	Displays DHCP server profile information with respect to disconnect-history.

show dhcp ipv6 database

To display the Dynamic Host Configuration Protocol (DHCP) for IPv6 binding database information, use the **show dhcp ipv6 database** command in XR EXEC mode.

show dhcp ipv6 database [*agent-URL*] [**location** *location*]

Syntax Description	<i>agent-URL</i>	(Optional) Flash, NVRAM, FTP, TFTP, or Remote Copy Protocol (RCP) uniform resource locator.
---------------------------	------------------	---

location	Displays the database information of the DHCPv6 node.
<i>location</i>	Name of the DHCPv6 node.

Command Default

None

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

Each permanent storage to which the binding database is saved is called the *database agent*. An agent can be configured using the **dhcp ipv6 database** command. Supported database agents include FTP and TFTP servers, RCP, Flash file system, and NVRAM.

The **show dhcp ipv6 database** command displays DHCP for IPv6 binding database agent information. If the *agent-URL* argument is specified, only the specified agent is displayed. If the *agent-URL* argument is not specified, all database agents are shown.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read

Examples

This is a sample output from the **show dhcp ipv6 database** command:

```
Router# show dhcp ipv6 database location 0/0/CPU0
```

```
Database:
Current file version:          1
Full file:
  write interval:              5 minutes
  last file name:              /disk0:/dhcp/dhcpv6_srpb_0_odd
  last write time:             Feb-27-2013-11:45:06
  write count:                 5
  failed write count:          0
  record count:                0
  last write error:            -
  last write error timestamp:   -
Incremental file:
  write interval:              2 minutes
  last file name:              /disk0:/dhcp/dhcpv6_srpb_0_odd_inc
  last write time:             Feb-27-2013-11:49:06
  write count:                 10
  failed write count:          0
  record count:                0
  last write error:            -
  last write error timestamp:   -
```

Related Commands	Command	Description
	show dhcp ipv6 database full-write-interval	This command displays DHCP for IPv6 binding database information at full file write interval. The default interval is 10 minutes.
	show dhcp ipv6 database incremental-write-interval	This command displays DHCP for IPv6 binding database information at incremental file write interval. The default interval is 1 minute.
	show dhcp ipv6 database proxy	This command enable DHCP proxy binding database storage to file system.
	show dhcp ipv6 database relay	This command enables DHCP relay binding database storage to file system.
	show dhcp ipv6 database server	This command enables DHCP server binding database storage to file system.

show dhcp ipv6 proxy

To display DHCP proxy profile information with ipv6 binding, use the **show dhcp ipv6 profile** command in EXEC mode.

show dhcp ipv6 proxy{**binding** | **disconnect-history** | **interface** | **profile** | **statistics**}

Syntax Description	binding	Displays client bindings for the proxy.
	disconnect-history	Displays disconnect history for the proxy.
	interface	Displays proxy interface information.
	profile	Displays proxy profile information.
	statistics	Displays proxy statistics.

Command Default None.

Command Modes EXEC

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 proxy** command:

```
Router# show dhcp ipv4 proxy name foo

Profile:    foo
VRF References:
Interface References: GigabitEthernet0/2/0/0
```

show dhcp ipv6 proxy binding

To display the client bindings for Dynamic Host Configuration Protocol (DHCP) proxy, use the **show dhcp ipv6 proxy binding** command in XR EXEC mode.

show dhcp ipv6 proxy binding{**detail** | **duid** | **interface** | **interface-id** | **location** | **mac-address** | **remote-id** | **srg** | **srg-master** | **srg-slave** | **state** | **summary** | **vrf**}

Syntax Description		
detail		Displays detailed bindings for proxy.
duid		Displays client bindings for DUID.
interface		Displays client bindings by Interface.
interface-id		Displays client bindings by Interface ID.
location		Specifies the node location.
mac-address		Displays detailed client binding information.
remote-id		Displays client binding by Remote ID.
srg		Displays client Bbnding by SRG group.
srg-master		Displays client Bbnding by SRG master.
srg-slave		Displays client Bbnding by SRG slave.
summary		Displays summary bindings for proxy.
vrf		Displays client bindings by VRF name.

Command Default	None
------------------------	------

Command Modes	XR EXEC mode
----------------------	--------------

Command History	Release	Modification
	Release 6.0.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operation
	ip-services	read

This is a sample output from the **show dhcp ipv6 proxy binding** command:

```
Router# show dhcp ipv6 proxy binding
```

```
Summary:
  Total number of Proxy bindings = 1
Prefix: 2001::/60 (Gi0/0/0/1)
  DUID: 00030001ca004a2d0000
  IAID: 00020001
  lifetime: 2592000
  expiration: Nov 25 2010 16:47
```

```
Router# show dhcp ipv6 proxy binding summary
```

```
Total number of clients: 2
```

STATE	COUNT	
	IA-NA	IA-PD
INIT	0	0
SUB VALIDATING	0	0
ADDR/PREFIX ALLOCATING	0	0
REQUESTING	0	0
SESSION RESP PENDING	2	0
ROUTE UPDATING	0	0
BOUND	0	0

show dhcp ipv6 proxy interface

To display the proxy interface information for Dynamic Host Configuration Protocol (DHCP), use the **show dhcp ipv6 proxy interface** command in XR EXEC mode.

show dhcp ipv6 proxy interface *{typeinterface-path-id}* **{locationlocation}**

Syntax Description	type	Interface type. For more information, use the question mark (?) online help function.
--------------------	------	---

interface-path-id Physical interface or virtual interface.

Note Use the **show interfaces** command to see a list of all interfaces currently configured on the router.

For more information about the syntax for the router, use the question mark (?) online help function.

location Displays the node location by Interface.

location Displays the fully qualified location specification of an interface.

Command Default

None

Command Modes

XR EXEC mode

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read

This is a sample output from the **show dhcp ipv6 proxy interface** command:

```
Router# show dhcp ipv6 proxy interface
```

```
Tue Sep  4 19:14:54.056 UTC
```

```
Codes: Amb - Ambiguous VLAN, B - Base, R - Relay, P - Proxy,
        SR - Server, S - Snoop, C - Client, INV - Invalid
        CID - Circuit Id, RID - Remote Id, INTF - Interface
```

Interface	Mode	Profile Name	Amb	Lease	Limit
BE1.100	P	pxyl	No	None	
BE1.200	P	pxyl	No	None	
BE1.250	P	pxyl	Yes	None	
BE1.400	P	pxyl	Yes	None	

show dhcp ipv6 server

To display DHCP server profile information with ipv6 binding, use the **show dhcp ipv6 server profile** command in EXEC mode.

show dhcp ipv6 server { | **binding** | **disconnect-history** | **interface** | **profile** | **statistics** }

Syntax Description	binding	Displays client bindings for the server.
	disconnect-history	Displays disconnect history for the server.
	interface	Displays server interface information.
	profile	Displays server profile information.
	statistics	Displays server statistics.
Command Default	None.	
Command Modes	EXEC	
Command History	Release	Modification
	Release 6.0.1	This command was introduced.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operation
	ip-services	read

Example

This is a sample output from the **show dhcp ipv4 server profile** command:

```
Router# show dhcp ipv4 server profile name foo

Profile:    foo
VRF References:
Interface References: GigabitEthernet0/2/0/0
```

show dhcp vrf ipv4 server statistics

To display DHCP server statistics for the default vrf or a specific vrf, use the **show dhcp vrf ipv4 server statistics** command in XR EXEC mode.

show dhcp vrf { **default** | *vrf-name* } [**location** *node-ID*]

Syntax Description	default	Display DHCP server statistics for the default vrf.
---------------------------	----------------	---

<i>vrf-name</i>	Display DHCP server statistics for a specific vrf.
location <i>node-ID</i>	Displays DHCP server statistics information for a specified node.

Command Default

None

Command Modes

XR EXEC mode

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read

Example

This is a sample output from the **show dhcp vrf default ipv4 server statistics** command:

```
Router# show dhcp vrf default ipv4 server statistics
Thu Aug 1 11:41:48.255 IST
```

DHCP IPv4 Proxy/Server Statistics for VRF default:

TYPE	RECEIVE	TRANSMIT	DROP
DISCOVER	5	0	0
OFFER	0	3	0
REQUEST	15	0	0
DECLINE	0	0	0
ACK	0	15	0
NAK	0	0	0
RELEASE	0	0	0
INFORM	0	0	0
LEASEQUERY	0	0	0
LEASEUNASSIGNED	0	0	0
LEASEUNKNOWN	0	0	0
LEASEACTIVE	0	0	0
BOOTP-REQUEST	0	0	0
BOOTP-REPLY	0	0	0

RP/0/0/CPU0:server#

show tech support dhcp ipv4 client

To retrieve the DHCP client show tech support information, use the **show tech dhcp ipv4 client** command in XR EXEC mode.

show tech-support dhcp ipv4 client <show-tech-options>

Syntax Description	show-tech-options Displays the DHCP IPv4 client show tech-support options.				
Command Default	No default behavior or values				
Command Modes	XR EXEC mode				
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>Release 6.0.1</td><td>This command was introduced.</td></tr> </table>	Release	Modification	Release 6.0.1	This command was introduced.
Release	Modification				
Release 6.0.1	This command was introduced.				
Usage Guidelines	Use the show tech-support dhcp ipv4 client command to retrieve the DHCP show-tech options for the specified interface.				
Task ID	<table> <tr> <th>Task ID</th><th>Operations</th></tr> <tr> <td>IP-Services</td><td>Execution</td></tr> </table>	Task ID	Operations	IP-Services	Execution
Task ID	Operations				
IP-Services	Execution				
Examples	The following example shows how to clear the DHCP client binding statistics information:				

```

Router# show tech-support dhcp ipv4 client ?
  file      Specify a valid file name (e.g. disk0:tmp.log) (cisco-support)
  terminal  Send output to terminal(cisco-support)
Router# show tech-support dhcp ipv4 client file ?
  WORD      Send to file
  bootflash: Send to bootflash: file system(cisco-support)
  disk0:     Send to disk0: file system(cisco-support)
  disk0a:    Send to disk0a: file system(cisco-support)
  disk1:     Send to disk1: file system(cisco-support)
  disk1a:    Send to disk1a: file system(cisco-support)
  ftp:       Send to ftp: file system(cisco-support)
  nvram:     Send to nvram: file system(cisco-support)
  rcv:       Send to rcv: file system(cisco-support)
  tftp:      Send to tftp: file system(cisco-support)
Router# show tech-support dhcp ipv4 client file disk0?
WORD disk0: disk0a:
Router# show tech-support dhcp ipv4 client file disk0:/dhcpv4-client-showtech.tgz
Fri Jun  6 08:25:24.793 UTC
Router# dir disk0:
Fri Jun  6 08:25:47.321 UTC

Directory of disk0:

 2          drwx  1024          Thu Mar 13 06:12:03 2014  .boot
...
```

```

3          -rw-  83337      Fri Jun  6 08:25:26 2014  dhcpv4-client-showtech.tgz

1911537664 bytes total (1838081024 bytes free)
Router#

```

Related Commands

show dhcp ipv4 client statistics	Displays the statistics of the DHCP client.
show tech support dhcp ipv4 server	Displays the tech support for DHCP ipv4 server profile.
show tech support dhcp ipv4 proxy	Displays the tech support for DHCP ipv4 proxy profile.
show tech support dhcp ipv4 relay	Displays the tech support for DHCP ipv4 relay profile.
show tech support dhcp ipv6 server	Displays the tech support for DHCP ipv6 server profile.
show tech support dhcp ipv6 proxy	Displays the tech support for DHCP ipv6 proxy profile.
show tech support dhcp ipv6 relay	Displays the tech support for DHCP ipv6 relay profile.

trust relay-reply

To configure a DHCP IPv6 profile to enable processing relay-replies, use the **trust relay-reply** command in DHCP IPv6 profile configuration mode. To restore the interface to the default behavior, use the **no** form of the command.

trust relay-reply
no trust relay-reply

This command has no keywords or arguments.

Command Default

By default, all interfaces are trusted.

Command Modes

DHCP IPv6 profile configuration

Command History

Release	Modification
Release 6.0.1	This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operation
ip-services	read, write

Example

```
Router# configure
Router(config)# dhcp ipv6
Router(config-dhcpv6)# profile downstream proxy
Router(config-dhcpv6-profile)# helper-address ff05::1:3
Router(config-dhcpv6-profile)# exit
Router(config-dhcpv6)# profile upstream proxy
Router(config-dhcpv6-profile)# trust relay-reply
```

Related Commands

Command	Description
helper-address (ipv6), on page 19	Configures the Dynamic Host Configuration Protocol (DHCP) IPv6 relay agent for prefix delegation.