

Release Notes for Cisco NCS 560 Series Routers, Cisco IOS XR Release 7.3.2

First Published: 2021-10-15

Network Convergence System 560 Series Routers



- Note** Explore the [Content Hub](#), the all new portal that offers an enhanced product documentation experience.
- Use faceted search to locate content that is most relevant to you.
 - Create customized PDFs for ready reference.
 - Benefit from context-based recommendations.

Get started with the Content Hub at content.cisco.com to craft a personalized documentation experience. Do provide feedback about your experience with the Content Hub.



- Note** Cisco IOS XR Release 7.3.2 is an Extended Maintenance Release of [Cisco IOS XR Release 7.3.1](#) for Cisco NCS 560 Series routers. For more details on the Cisco IOS XR release model and associated support, see [Guidelines for Cisco IOS XR Software](#).

What's New in Cisco IOS XR Release 7.3.2

Feature	Description
System Setup	
FPD Auto Upgrade	This functionality enables automatic upgrade and reload for field-programmable devices (FPDs) whenever the Cisco IOS XR image has a newer FPD version. This functionality upgrades all route processor FPDs simultaneously while displaying upgrade triggers on the console.
System Security	
SSH Port Forwarding	With this feature enabled, the SSH client on a local host forwards the traffic coming on a given port to the specified host and port on a remote server, through an encrypted SSH channel. Legacy applications that do not otherwise support data encryption can leverage this functionality to ensure network security and confidentiality to the traffic that is sent to remote application servers. This feature introduces the ssh server port-forwarding local command.

Feature	Description
BGP	
BGP PIC: Export of Backup Path Agnostic to its Multipath Eligibility	Prior to this release, you could only import the backup paths of a prefix to the respective VRFs only when the backup paths are multipath eligible. For backup paths to be multipath eligible, all the following attributes in the backup paths must be the same: weight, local preference, autonomous system path, origin code, Multi Exit Discriminator (MED), and Interior Gateway Protocol (iGP) distance. Also, the next hop router for each multipath must be different. This feature introduces flexibility to allow the import of backup paths to the VRF even if the said attributes are not the same.
Programmability	
Cisco IOS XR mpls-ping-act and Cisco IOS XR mpls-traceroute-act YANG data model	This feature introduces the Cisco-IOS-XR-mpls-ping-act and Cisco-IOS-XR-mpls-traceroute-act YANG data models to accommodate OAM RPCs for MPLS and SR-MPLS. You can access these Cisco IOS XR native data models from the Github repository.
Routing	
Fast Path - Graceful Conflict Identification or Resolution for Encapsulation-ID	
Segment Routing	
Autoroute Include	This feature allows you to steer specific IGP (IS-IS, OSPF) prefixes, or all prefixes, over non-shortest paths and to divert the traffic for those prefixes on to an SR-TE policy.
SRv6/MPLS L3 Service Interworking Gateway (SRv6 Micro-SID)	This feature enables you to extend L3 services between MPLS and SRv6 domains by providing service continuity on the control plane and data plane. This feature allows for SRv6 L3VPN domains to interwork with existing MPLS L3VPN domains. The feature also allows a way to migrate from MPLS L3VPN to SRv6 L3VPN.
SRv6/MPLS Dual-Connected PE (SRv6 Micro SID)	This feature allows a PE router to support IPv4 L3VPN services for a given VRF with both MPLS and SRv6. This is MPLS and SRv6 L3VPNv4 co-existence scenario and is sometimes referred to as dual-connected PE.
BGP-LU Inter-AS Option-C Interworking with LDP and IGP SR-MPLS using Proxy BGP-SR	This feature extends the current Proxy BGP-SR functionality by allowing the BGP-LU ASBR router with Proxy BGP-SR configured to also interconnect attached LDP domains. The Proxy BGP-SR feature allows interconnection of IGP SR-MPLS domains and legacy domains via BGP-LU Inter-AS option-C. It provides a prefix-to-SID mapping for BGP-LU prefixes that are learned without a Prefix-SID.
L3VPN BGP PIC over SR-TE	This feature provides BGP PIC support for L3VPN over SR policies. BGP PIC provides fast convergence when traffic switches from a primary path to a backup path. BGP PIC over SR-TE is supported when both primary and backup paths each resolve into the BSID of an SR policy.

Feature	Description
SR-TE BGP Soft Next-Hop Validation For ODN Policies	<p>This feature addresses BGP Next-Hop reachability issues through BGP Next-Hop soft validation, and also enhances BGP best path selection.</p> <ul style="list-style-type: none"> • nexthop validation color-extcomm disable • nexthop validation color-extcomm sr-policy • bgp bestpath igp-metric sr-policy
SR-TE PCE Groups	<p>This feature allows an SR policy to be delegated to a set of PCE servers configured under a PCE group. Multiple PCE groups can be configured to allow SR policies on the same head-end to be delegated to different sets of PCEs.</p> <p>With this functionality, an operator can designate sets of PCEs for various purposes, such as PCE-per-service-type or PCE-per-wholesale-customers.</p>
SR-PCE: North-Bound API for SRv6 and Flexible Algorithm in Cisco Optimization Engine (COE) v3.0 release	<p>The SR-PCE provides a north-bound HTTP-based API to allow communication between SR-PCE and external clients and applications. The Cisco Crosswork Optimization Engine is an application that leverages the SR-PCE.</p> <p>This release adds support for the following:</p> <ul style="list-style-type: none"> • Reporting of Flexible Algorithm participation and definitions • SRv6 topology information (nodes, links, Node uSIDs and Adj uSIDs) • SRv6 uSID list and uB6 SIDs allocated for a policy <p>For more information, refer to the Cisco Crosswork Optimization Engine User Guides.</p>
IP Endpoint Delay Measurement and Liveness Monitoring	<p>This feature measures the end-to-end delay and monitors liveness of a specified IP endpoint node, including VRF-aware (awareness of multiple customers belonging to different VRFs).</p> <p>This feature is supported on IPv4, IPv6, and MPLS data planes.</p>
OSPF: Microloop Avoidance for Flexible Algorithm	<p>This feature extends the current OSPF Flexible Algorithm functionality to support Microloop Avoidance.</p>

Feature	Description
SRv6TE Phase1: PCC/PCE (PCEPv6) uSID Introduction - PCE Delegated, Constraints: Disjoint, affinity, Metric: IGP, TE, Latency, L3 Services ODN/AS	<p>This feature brings the Segment Routing Traffic Engineering features to the SRv6 data plane.</p> <p>This release supports the following features:</p> <ul style="list-style-type: none"> • SRv6-TE with SRv6 micro-SIDs (uSIDs) • SRv6 policies • Manual SRv6 policies • On-Demand SRv6 policies - SR On-Demand Next-Hop (SR-ODN) • Automated steering for Layer 3-based BGP services (IPv4 L3VPN, IPv6 L3VPN, IPv4 BGP global, IPv6 BGP global) • SRv6-aware Path Computation Element (PCE) • PCEPv6 • Path computation optimization objectives (TE, IGP, latency) • Path computation constraints (affinity, disjointness)

Restrictions and Limitations on the Cisco NCS 560 Series Router

- The standby RP may get into 'NOT_READY' state intermittently due to some network churn, though the corresponding VM is up and running. But this is a transient state and shows that some data aren't in sync between active and standby due to the network churn. After both active and standby are in sync with respect to all the parameters, then the standby RP comes into 'READY' state.
- Unlabeled BGP PIC EDGE for global prefixes is not supported.

Caveats

This section describes open and resolved severity 1 and 2 caveats and select severity 3 caveats:

- The “Open Caveats” sections list open caveats that apply to the current release and may apply to previous releases. A caveat that is open for a prior release and is still unresolved applies to all future releases until it is resolved.
- The “Resolved Caveats” sections list caveats resolved in a specific release, but open in previous releases.

The bug IDs are sorted alphanumerically.



Note The Caveats section includes the bug ID and a short description of the bug. For details on the symptoms, conditions, and workaround for a specific caveat you must use the Bug Search Tool.

Cisco IOS XR Caveats Release 7.3.2

Caveat ID Number	Description
CSCvy13197	Telemetry Syslog events are not received by telemetry client.

Bug Search Tool

Use the [Cisco Bug Search Tool](#) to access open and resolved bugs for a release.

The tool allows you to search for a specific bug ID, or for all bugs specific to a product and a release.

Supported Packages and System Requirements

For more information on system upgrade and package installation process, see [Perform System Upgrade and Install Feature Packages](#).

For a complete list of supported optics, hardware and ordering information, see the [Cisco NCS 560 Series Routers Interface Modules Data Sheet](#) and [Cisco Network Convergence System 560-4 Router Data Sheet](#).

To install the Cisco NCS 560 Series Routers, see [Cisco N560-RSP4 and Cisco N560-RSP4-E Route Processor Hardware Installation Guide](#) and [Cisco NCS 560-4 Router Hardware Installation Guide](#).

Release 7.3.2 Packages

This following table lists the supported packages and their corresponding file names.

Table 1: Release 7.3.2 Packages for Cisco NCS 560 Series Router

Composite Package		
Feature Set	Filename	Description
Cisco IOS XR IP Unicast Routing Core Bundle	ncs560-mini-x-7.3.2.iso	Contains base image contents that includes: <ul style="list-style-type: none"> • Host operating system • System Admin boot image • IOS XR boot image • BGP packages • OS • Admin • Base • Forwarding • Modular Services Card • Routing • SNMP Agent • Alarm Correlation
Cisco IOS XR Manageability Package	ncs560-mgbl-2.0.0.0-r732.x86_64.rpm	Telemetry, Extensible Markup Language (XML), Parser, and HTTP server packages, NETCONF, YANG Models, gRPC.
Cisco IOS XR OSPF package	ncs560-ospf-2.0.0.0-r732.x86_64.rpm	Supports OSPF
Cisco IOS XR Security Package	ncs560-k9sec-2.0.0.0-r732.x86_64.rpm	Support for Encryption, Decryption, Secure Shell (SSH), Secure Socket Layer (SSL), and Public-key infrastructure (PKI)
Multicast Package	ncs560-mcast-2.0.0.0-r732.x86_64.rpm	Supports Multicast Supports Automatic Multicast Tunneling (AMT), IGMP Multicast Listener Discovery (MLD), Multicast Label Distribution Protocol (MLDP), Multicast Source Discovery Protocol (MSDP) and PIM.

Composite Package		
Feature Set	Filename	Description
Cisco IOS XR ISIS package	ncs560-isis-2.0.0.0-r732.x86_64.rpm	Supports Intermediate System to Intermediate System (IS-IS).
Cisco IOS XR USB Boot Package	ncs560-usb_boot-7.3.2.zip	Supports Cisco IOS XR USB Boot Package
Cisco IOS XR MPLS Package	ncs560-mpls-1.0.0.0-r732.x86_64.rpm ncs560-mpls-te-rsvp-2.0.0.0-r732.x86_64.rpm	Supports MPLS and MPLS Traffic Engineering (MPLS-TE) RPM. Label Distribution Protocol (LDP), MPLS Forwarding, MPLS Operations, Administration, and Maintenance (OAM), Link Manager Protocol (LMP), Optical User Network Interface (OUNI) and Layer-3 VPN. Cisco IOS XR MPLS-TE and RSVP Package MPLS Traffic Engineering (MPLS-TE) and Resource Reservation Protocol (RSVP).
Cisco IOS XR LI Package	ncs560-li-1.0.0.0-r732.x86_64.rpm	Lawful Intercept
Cisco IOS XR EIGRP Package	ncs560-eigrp-1.0.0.0-r732.x86_64.rpm	(Optional) Includes EIGRP protocol support software

Determine Software Version

Log in to the router and enter the **show version** command.

```
RP/0/RP0/CPU0:R3_PE3_RSP4#show version
Fri Oct 15 13:23:14.591 IST
Cisco IOS XR Software, Version 7.3.2
Copyright (c) 2013-2021 by Cisco Systems, Inc.

Build Information:
  Built By      : ingunawa
  Built On     : Wed Oct 13 20:37:50 PDT 2021
  Built Host   : iox-ucs-024
  Workspace    : /auto/srcarchive17/prod/7.3.2/ncs560/ws
  Version     : 7.3.2
  Location    : /opt/cisco/XR/packages/
  Label      : 7.3.2

cisco NCS-560 () processor
System uptime is 12 hours 58 minutes
```

Determine Firmware Support

Log in to the router and enter the **show fpd package** and **show hw-module fpd** commands.

Determine Firmware Support

```
RP/0/RP0/CPU0:RSP4-PE4#sh fpd package
Fri Oct 15 13:23:20.682 IST
```

```
=====
```

Field Programmable Device Package					
Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
A900-IMA8CS1Z-CC	IMFPGA	YES	1.102	1.102	0.0
A900-IMA8CS1Z-M	IMFPGA	YES	1.102	1.102	0.0
A900-IMA8Z	IMFPGA	YES	17.05	17.05	0.0
A900-IMA8Z-CC	IMFPGA	YES	17.05	17.05	0.0
A900-IMA8Z-L	IMFPGA	YES	1.49	1.49	0.0
A900-PWR1200-A	DCA-PrimMCU (A)	NO	0.11	0.11	0.0
	DCA-SecMCU (A)	NO	1.04	1.04	0.0
A900-PWR1200-D	LIT-PrimMCU (A)	NO	2.04	0.04	0.0
	LIT-SecMCU (A)	NO	1.23	1.23	0.0
A907-FAN-E	PSOC (A)	NO	1.65	1.65	0.0
	PSOC (A)	NO	1.66	1.66	0.4
N560-4-FAN-H	PSOC (A)	NO	177.02	177.02	0.0
N560-4-FAN-H-CC	PSOC (A)	NO	177.02	177.02	0.0
N560-4-PWR-FAN	PSOC (A)	NO	177.08	177.08	0.0
N560-4-PWR-FAN-CC	PSOC (A)	NO	177.08	177.08	0.0
N560-4-RSP4	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
N560-4-RSP4-CC	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
N560-4-RSP4E	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
N560-4-RSP4E-CC	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
N560-FAN-H	PSOC (A)	NO	2.02	2.02	0.0
N560-IMA-8Q/4L	IMFPGA	YES	1.08	1.08	0.0
N560-IMA1W	CFP2-D-DCO	NO	38.2739	38.2739	0.0
	CFP2-DE-DCO	NO	38.2739	38.2739	0.0
	CFP2-DET-DCO	NO	38.2739	38.2739	0.0

```
=====
```


	CFP2-DETS-DCO	NO	38.2739	38.2739	0.0
	CFP2-DS-DCO	NO	38.2739	38.2739	0.0
	CFP2-DS100-DCO	NO	38.2739	38.2739	0.0
	IMFPGA	YES	1.28	1.28	0.0
N560-IMA2C	IMFPGA	YES	5.07	5.07	0.0
N560-IMA2C-CC	IMFPGA	YES	5.07	5.07	0.0
N560-IMA2C-DD	IMFPGA	YES	1.28	1.28	0.0
N560-IMA2C-L	IMFPGA	YES	1.28	1.28	0.0
N560-PWR1200-D-E	QCS-PrimMCU (A)	NO	1.82	1.82	0.0
	QCS-SecMCU (A)	NO	1.84	1.84	0.0
N560-RSP4	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
N560-RSP4-E	ADM (A)	NO	1.06	1.06	0.0
	IOFPGA (A)	YES	0.64	0.64	0.0
	PRIMARY-BIOS (A)	YES	0.21	0.21	0.0
	SATA (A)	NO	2.10	2.10	0.0
NCS4200-1T16G-PS	IMFPGA	YES	1.102	1.102	0.0
NCS4200-2H-PQ	IMFPGA	YES	5.07	5.07	0.0
NCS4200-8T-PS	IMFPGA	YES	17.05	17.05	0.0

RP/0/RP0/CPU0:RSP4-PE4#sh hw-module location all fpd
Fri Oct 15 13:23:33.939 IST

Auto-upgrade:Enabled

Location	Card type	HWver	FPD device	ATR Status	FPD Versions	
					Running	Programd
0/0	A900-IMA8CS1Z-M	0.0	IMFPGA	CURRENT	1.102	1.102
0/2	A900-IMA8CS1Z-M	0.0	IMFPGA	CURRENT	1.102	1.102
0/4	A900-IMA8Z	0.0	IMFPGA	CURRENT	17.05	17.05
0/5	A900-IMA8Z	0.0	IMFPGA	CURRENT	17.05	17.05
0/7	N560-IMA2C	0.0	IMFPGA	CURRENT	5.11	5.11
0/9	N560-IMA2C-DD	0.0	IMFPGA	CURRENT	1.28	1.28
0/10	A900-IMA8Z-L	0.0	IMFPGA	CURRENT	1.49	1.49
0/RP0	N560-RSP4-E	0.0	ADM	CURRENT	1.06	1.06
0/RP0	N560-RSP4-E	0.0	IOFPGA	CURRENT	0.64	0.64
0/RP0	N560-RSP4-E	0.0	PRIMARY-BIOS	CURRENT	0.21	0.21
0/RP0	N560-RSP4-E	0.0	SATA	CURRENT	2.10	2.10
0/RP1	N560-RSP4-E	0.0	ADM	CURRENT	1.06	1.06
0/RP1	N560-RSP4-E	0.0	IOFPGA	CURRENT	0.64	0.64
0/RP1	N560-RSP4-E	0.0	PRIMARY-BIOS	CURRENT	0.21	0.21
0/RP1	N560-RSP4-E	0.0	SATA	CURRENT	2.10	2.10
0/FT0	N560-FAN-H	1.0	PSOC	CURRENT	2.02	2.02

Other Important Information

Supported Transceiver Modules

For more information on the supported transceiver modules, see [Transceiver Module Group \(TMG\) Compatibility Matrix](#). In the **Begin your Search** search box, enter the keyword NCS560 and click **Enter**.

Upgrading Cisco IOS XR Software

Cisco IOS XR Software is installed and activated from modular packages, allowing specific features or software patches to be installed, upgraded, or downgraded without affecting unrelated processes. Software packages can be upgraded or downgraded on all supported card types, or on a single card (node).

The upgrade document for Cisco NCS 560 router is available along with the software image in *NCS560_Upgrade_MOP_7.3.2.tar* file.

Use user-class Option 'xr-config' Instead Of 'exr-config' To Provision ZTP

In Cisco IOS XR Release 7.3.1 and earlier, the system accepts the device sending **user-class = "exr-config"**; however starting Cisco IOS XR Release 7.3.2 and later, you must use only **user-class = "xr-config"**.

In Cisco IOS XR Release 7.3.2 and later, use:

```
host cisco-rp0 {
  hardware ethernet e4:c7:22:be:10:ba;
  fixed-address 172.30.12.54;
  if exists user-class and option user-class = "iPXE" {
    filename = "http://172.30.0.22/boot.ipxe";
  } elseif exists user-class and option user-class = "xr-config" {
    filename = "http://172.30.0.22/scripts/cisco-rp0_ztp.sh";
  }
}
```

Additional References

Supported MIBs

The Cisco NCS 5500 MIB support list is also applicable to the Cisco NCS 560 Series Routers. For the list of supported MIBs, see the [Cisco NCS5500 MIB Support List](#).

Full Cisco Trademarks with Software License

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2021 Cisco Systems, Inc. All rights reserved.