



Installing the ISO on the Appliance

The appliance is shipped with the software version pre-installed. You do not have to perform these steps during the initial installation of the appliance. However in case you need to re-image the appliance, you can install the software from the ISO file.

To reduce the installation time, choose **Admin > Network > Network Settings** in the CIMC interface and check the **Auto Negotiation** check box.

Before You Begin

Download the ISO file [PI-APL-3.2.0.0.258-1-K9.iso](#) from [cisco.com](#) and verify file integrity using the checksum values listed for it on [cisco.com](#).

You can verify the Cisco Signature for the ISO image with the following steps:

1. Download [PI-APL-3.2.0.0.258-1-K9.iso](#), [CiscoPI3.2.pem](#) and [PI-APL-3.2.0.0.258-1-K9.iso.signature](#).
2. Copy these file to any Linux server and enter the following command.

```
openssl dgst -sha512 -verify CiscoPI3.2.pem -signature  
PI-APL-3.2.0.0.258-1-K9.iso.signature PI-APL-3.2.0.0.258-1-K9.iso
```

The result will be shown as “Verified”.



Note

Ensure no storage devices are connected to the USB port of the appliance before upgrading or installing the ISO image. The installation fails if a USB storage device is connected to the USB port of the appliance as the installer selects the USB storage device.

- Step 1** Connect to the console using one of the options mentioned in [Connecting to the Console](#).
- Step 2** Mount ISO using any one of the mounting options. See [DVD Mount Options](#) for more details.
- Step 3** Reboot the appliance by pressing the power switch or select **Power > Reset System(Warm Boot)** if you are using vKVM to restart.
- Step 4** After the appliance reboots, press **F6** to enter the boot option.
- Step 5** Select one of the DVD mount option with the Cisco Prime Infrastructure 3.2 software image. See [DVD Mount Options](#) for more information.

```

Please select boot device:

(Bus 05 Dev 00)PCI RAID Adapter
Cisco vKVM-Mapped vHDD1.22
Cisco vKVM-Mapped vFDD1.22
Cisco CIMC-Mapped vHDD1.22
HL-DT-STDVDRAM GP70NS50 1.00
Cisco vKVM-Mapped vDVD1.22
Cisco CIMC-Mapped vDVD1.22
UEFI: BUILT-IN EFI Shell
Enter Setup

↑ and ↓ to move selection
ENTER to select boot device
ESC to boot using defaults

```

Step 6 From the available boot options, enter **1** or **2**.

1—Prime Infrastructure System Installation (Keyboard/Monitor) if you are connected through the VGA port

2—Prime Infrastructure System Installation (Serial Console) if you are connected through the serial port. See [Connecting to the Console Using Serial Over LAN](#) for more information.

```

Welcome to Cisco Prime Infrastructure

To boot from hard disk, press <Enter>.

Available boot options:

[1] Prime Infrastructure System Installation (Keyboard/Monitor)
[2] Prime Infrastructure System Installation (Serial Console)
[3] Recover administrator password. (Keyboard/Monitor)
[4] Recover administrator password. (Serial Console)
<Enter> Boot existing OS from Hard Disk.

Enter boot option and press <return>.

boot:

```

The time taken to deploy the image will depend on the network speed.

Step 7 Enter **setup** at the login prompt when prompted to initiate the installation.

See *Installation Options* section (Step 3 onwards) in [Cisco Prime Infrastructure 3.2 Quick Start Guide](#) for more information about installing the software.

Managing the Appliance Using CIMC

You can connect to the vKVM console by launching the CIMC and log in using your username and password configured in [Setting Up the Appliance](#). Using the vKVM console you can do the following:

- Remotely power on or off the server.
- Monitor the server and disk status.
- Change the BIOS settings.



Note Cisco Prime Infrastructure 3.2 Physical Appliance ISO image is supported till the latest firmware version 3.0 (3a).

- Launch a virtual console on the appliance.
- Mount *iso* files as virtual DVD drives.
- Other server management function.



Note If there are additional slots configured with JBOD, the upgrade will fail, hence ensure that you set the status of additional slots to be “Unconfigured Good”.

See [Cisco Integrated Management Controller](#) documentation for more information.

Monitoring the Appliance

After you have installed the Prime Infrastructure software, you can monitor the appliance by choosing **Administration > Settings > Appliance**. Prime Infrastructure generates an alarm if any hardware failures are detected. See [Cisco UCS C-Series Servers Integrated Management Controller GUI Configuration Guide](#) for more information.

