



Supported Devices Table for Cisco Prime Unified Provisioning Manager 9.0

The following tables and section list the devices and software supported by Cisco Prime Unified Provisioning Manager (Provisioning Manager) 9.0:

- [Table 1, Supported Call Processors and Unified Message Processors](#)
- [Table 2, IP Phones](#)
- [Software Supported by Provisioning Manager 9.0](#)



Devices Supported by Provisioning Manager 9.0

Table 1 Supported Call Processors and Unified Message Processors

Device	Versions Supported	Versions Tested
Cisco Unified Communications Manager ¹ and Session Management Edition	4.1(3), 4.2(1), 4.2(3), 4.3(2), 5.1(2), 5.1(3), 6.0(1), 6.1(1), 6.1(2), 6.1(3), 6.1(4), 6.1(5), 7.0(1), 7.0(2), 7.1(2), 7.1(3), 7.1(5), 8.0(1), 8.0(2), 8.0(3), 8.5(1), 8.6(1), 8.6(2), 9.0(1), and 9.1(1) ²	4.1(3)SR3b, 4.1(3)SR4d, 4.1(3)SR5b, 4.1(3)SR5d, 4.1(3)SR7, 4.2(1)SR1a, 4.2(1)SR1b, 4.2(3)SR1, 4.2(3)SR2, 4.2(3)SR3, 4.2(3)SR3a, 4.3.2.2.49, 4.3(2)SR1a, 4.3(2)SR1c, 4.3(2)SR2, 5.1.2.1000-11, 5.1.2.3000-2, 5.1.3.1000-12, 5.1.3.3000-5, 5.1.3.5000-3, 6.0.1.2000-4, 6.0.1.3000-7, 6.1.1.1000-1, 6.1.1.3000-2, 6.1.2.1000-13, 6.1.3.1000-16, 6.1.4.1000-7, 6.1.5.10000-10, 7.0.1.11000-2, 7.0.1.11001-8, 7.0.2.10000-18, 7.0.2.20000-5, 7.1.2.20000-2, 7.1.3.10000-11, 7.1.5.10000-3, 8.0.1.10000-14, 8.0.1.10000-40, 8.0.2.10000-7, 8.0.2.10000-22, 8.0.2.10000-24, 8.0.3.11002-1, 8.5.1.10000-26, 8.6.1.10000-43, 8.6.2.20000-2, and 9.0.1.10000-35
Cisco Unified Communications Manager Business Edition ³	Cisco Business Edition 5000, Cisco Business Edition 6000	Cisco Business Edition 5000, Cisco Business Edition 6000
Cisco Unified Communications Manager Express	4.0, 4.1, 4.2, 7.0, 7.1, 8.0, 8.5, and 8.6	4.0, 4.1, 4.2, 7.0, 7.0(1), 7.1, 8.0, 8.5, and 8.6
Cisco Unity ⁴	4.0, 4.1, 4.2, 5.0, 7.0, and 8.0	4.0, 4.1, 4.2, 5.0, 7.0, and 8.0
Cisco Unity Connection	2.0(1), 2.1, 7.0, 7.1(2), 7.1(3) ⁵ , 8.0, 8.0(1), 8.0(2), 8.5(1), 8.6(1), 8.6(2), and 9.0(1)	2.0.0.297, 2.1.0.9901-359, 7.0.1.10000-323, 7.1.2.10000-139, 7.1.3.10000-68, 8.0.0.38000-176, 8.0.2.10000-11, 8.0.2.10000-12, 8.5.1.10000-206, 8.6.1.10000-109, 8.6.2.20000-76, and 9.0.1.10000-209
Cisco Unity Express ⁶	2.3(1), 3.0, 3.1, 3.2, 7.0, 7.1, 8.0, 8.5, and 8.6	2.3.1, 3.0, 3.1, 7.0(1), 7.1, 8.0, 8.5, and 8.6
Cisco Unified Presence	8.0, 8.5(1), 8.6(1), 8.6(2), and 9.0(1)	8.0, 8.5.1.10000-35, 8.6.0.97021-20, 8.6.2.10000-44, and 9.0.1.10000-22

1. Cisco Unified Communications Manager 4.1(3), 4.2(1), 4.2(3), and 4.3(2) do not support SIP phones. Provisioning Manager can only provision SCCP phones for these versions.
2. When you add the Cisco Unified Communications Manager 9.1(1) device to Prime Collaboration Provisioning, you must specify the Cisco Unified Communications Manager version as 9.0.
3. Cisco Business Edition 3000 is not supported.
4. Unity High Availability configuration is not supported in Provisioning Manager.
5. Provisioning Manager supports Cisco Unity Connection 7.1(5) in the backward compatibility mode. However, it is supported only when added as Unity Connection 7.1(3).
6. Following are the supported Cisco Unity Express modules: ISM-SRE, SM-SRE, NME-CUE, NM-CUE-EC, NM-CUE, AIM-CUE, and AIM2-CUE.

**Note**

Provisioning Manager supports the Infra products of the Cisco Voice Gateway device types, VG224, VG204, and VG202.

IP Phones Supported by Provisioning Manager

Table 2 lists the phones that are supported by Provisioning Manager. Some phones may be available only for certain releases of Cisco Unified Communications Manager or Cisco Unified Communications Manager express.

Table 2 IP Phones

Device	Series
Blackberry MVS Client	—
Cisco ATA 180 Series Analog Telephone Adaptors	ATA 186 ATA 187 ^{1, 4}
Cisco Cius ^{1, 4}	—
Cisco Dual Mode for Android ^{1, 4}	—
Cisco Dual Mode for Blackberry ^{1, 2}	—
Cisco Dual Mode for iPhone ¹	—
Cisco IP Communicator	2.0, 2.1, and 7.0
Cisco IP Video Phone	E20 ^{1, 3}
	EX60 ^{1, 3}
	EX90 ^{1, 3}
Cisco Unified IP Phones 6900 Series	6901
	6911
	6921
	6941
	6945 ⁴
	6961

Table 2 IP Phones (continued)

Device	Series
Cisco Unified IP Phones 7900 Series	7902G
	7905G
	7906G
	7910G
	7911G
	7912G
	7926G
	7931G
	7940G
	7941G
	7941G-GE
	7942G
	7945G
	7960G
	7961G
	7961G-GE
	7962G
	7965G
	7970G
	7971G-GE
7975G	
7985G	
Cisco Unified IP Phones 8900 Series	8961 ⁵
	8941
	8945
Cisco Unified IP Phones 3900 Series	3905
Cisco Unified IP Phones 7900 Wireless Series	7920
	7921G
	7925G ⁶
Cisco Unified IP Conference Station	7935
	7936
	7937G
Cisco Unified IP Phone Expansion Modules	7914
	7915
	7916

Table 2 **IP Phones (continued)**

Device	Series
Cisco Unified IP Phones 9900 Series	9951 ⁴
	9971
Cisco IP Phones 12 Series	12 S
	12 SP
	12 SP+
Cisco IP Phones 30 Series	30 SP+
	30 VIP
Cisco Unified Client Services Framework ⁷	—
Cisco Unified Personal Communicator	1.1 ⁸ , 1.2 ⁹ , and 2.0
CTI Port	—
Nokia S60 ¹	—
Third-party SIP Device (Advanced) ^{10, 11}	—
Third-party SIP Device (Basic) ^{9, 10}	—

- After an upgrade, this phone cannot be ordered by default. You must associate the new phone types to the appropriate subscriber roles in the desired Domains. You can do so using the Subscriber Role Configuration page (**Advanced Setup > Policies > Subscriber Roles**). For information on associating phones to a subscriber role, see [User Guide for Cisco Prime Unified Provisioning Manager 9.0](#).
- Supported on Cisco Unified Communications Manager 5.x and above.
- Supported on Cisco Unified Communications Manager 8.5 and above.
- Cisco IP Phone 6945 is supported on Cisco Unified Communications Manager 8.5 and greater.
- Supported on Cisco Unified Communications Manager 8.0(1) and above.
- Cisco Unified IP Phone 7925 is supported on Cisco Unified Communications Manager 6.1(3) and above. Also, the phone will not be associated to a subscriber role, you must associate it through the Subscriber Role Configuration page (**Advanced Setup > Policies > Subscriber Roles**). For information on associating phones to a subscriber role, see [User Guide for Cisco Prime Unified Provisioning Manager 9.0](#).
- Cisco Unified Client Services Framework is supported on Cisco Unified Communications Manager 6.1(4) and later.
- Cisco Unified Personal Communicator 1.1 is supported on Cisco Unified Communications Manager 5.1(2) and 6.0(1).
- Cisco Unified Personal Communicator 1.2 is supported on Cisco Unified Communications Manager 6.0(1).
- Third-party SIP Device is supported on Cisco Unified Communications Manager 5.x and later.
- For Third-party SIP Devices, Provisioning Manager supports only the following provisioning attributes: AAR Calling Search Space, Calling Search Space, Common Device Configuration, Device Description, Device Pool, Device Security Profile, Media Resource Group List, MLPP Domain, Owner User ID, and Retro Video Call as Audio (supported only for Advanced).

Software Supported by Provisioning Manager 9.0

The following is a list of the software supported by and interoperable with Provisioning Manager 9.0:

- Cisco Prime Unified Operations Manager
- Cisco Prime Unified Service Monitor
- Cisco Prime Unified Service Statistics Manager
- The following VMware products:
 - ESX Server 3i version 3.5
 - ESX Server 3.5
 - ESXi Server 4.0 and 4.1

- ESXi Server 5.0
- Cisco Secure Access Control Server (ACS) 4.2
- Lightweight Directory Access Protocol (LDAP) server—Microsoft AD 2000, 2003, 2008, and 2010
- Win32 OpenSSL 1.0.0g

Coresident Guidelines

For information on coresident guidelines, see the *Installation Guide for Cisco Prime Unified Operations Manager 9.0* on Cisco.com.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

© 2012–2013 Cisco Systems, Inc. All rights reserved.