



# Cisco Nexus Data Broker Release Notes, Release 3.2.3

This document describes the features, system requirements, limitations, and caveats in the Cisco Nexus Data Broker Release 3.2.3.

## Online History Change

Date	Description
August 21, 2017	Updated the release notes for bug fixes.
June 19, 2017	Created the release notes for Cisco Nexus Data Broker Release 3.2.3.

## Table of Contents

<b>Introduction</b> .....	<b>2</b>
<b>Features</b> .....	<b>2</b>
<b>Supported Deployment Mode</b> .....	<b>4</b>
<b>Supported NX-OS Versions</b> .....	<b>4</b>
<b>New Features</b> .....	<b>4</b>
<b>Open and Resolved Bugs</b> .....	<b>5</b>
<b>Usage Guidelines</b> .....	<b>6</b>
<b>Limitations</b> .....	<b>7</b>
<b>Device Support Matrix</b> .....	<b>7</b>
<b>Scale Information</b> .....	<b>8</b>
<b>System Requirements</b> .....	<b>8</b>
<b>Supported Web Browsers</b> .....	<b>8</b>
<b>Upgrading to Release 3.2.3</b> .....	<b>8</b>
<b>Related Documentation</b> .....	<b>9</b>
<b>Obtaining Documentation and Submitting a Service Request</b> .....	<b>9</b>

## Introduction

Visibility into application traffic has traditionally been important for infrastructure operations to maintain security, troubleshooting, and compliance, and to perform resource planning. With the technological advances and growth in cloud-based applications, it has become imperative to gain increased visibility into the network traffic. Traditional approaches to gain visibility into network traffic are expensive and rigid, making it difficult for managers of large-scale deployments.

Cisco Nexus Data Broker with Cisco Nexus Switches provides a software-defined, programmable solution to aggregate copies of network traffic using SPAN or network taps for monitoring and visibility. As opposed to traditional network taps and monitoring solutions, this packet-brokering approach offers a simple, scalable and cost-effective solution well-suited for customers who need to monitor higher-volume and business-critical traffic for efficient use of security, compliance, and application performance monitoring tools.

Cisco Nexus Data Broker also provides management support for multiple disjointed Cisco Nexus Data Broker networks. You can manage multiple Cisco Nexus Data Broker topologies that may be disjointed using the same application instance. For example, if you have five data centers and want to deploy an independent Cisco Nexus Data Broker solution for each data center, you can manage all five independent deployments using a single application instance by creating a logical partition (network slice) for each monitored network.

Note: SPAN session which includes Production Switch and APIC configurations are not supported in Embedded Nexus Data Broker.

## Features

Cisco Nexus Data Broker 3.2.3 provides the features from the previous Cisco Nexus Data Broker releases listed below. For a list of newly added features specific to this release, see *New Features*:

- Cisco NDB Embedded installation support for NXOS I5(1) release on Cisco Nexus 9000 switches.
- IPv6 addressing support for Centralized NDB in standalone and HA mode.
- Support for entry of a VLAN range when creating a filter.
- Ability to clone filters and connections.
- Configure multiple ports for Edge span and Edge tap.
- Ability to assign multiple filters to a connection.
- Ability to configure both allow and deny filters for the same connection.
- Enable time stamp tagging using PTP on Cisco Nexus 3500 Series switches.
- Display flow and port statistics for devices in the Cisco Nexus Data Broker main user interface.
- Display flow statistics per connection and for each device within the connection.
- Inter-switch link (ISL) utilization information available in the topology diagram and in the connection path.
- Enable packet truncation on input ports on Cisco Nexus 3500 Series switches.
- Scalable topology for Test Access Point (TAP) and Switched Port Analyzer (SPAN) port aggregation.
  - Support for Cisco Nexus 3000 Series switches
  - Cisco Nexus 3100 Series switches
  - Cisco Nexus 3200 Series switches
  - Cisco Nexus 3500 Series switches
  - Cisco Nexus 9000 Series switches

## Features

- QinQ to tag input source TAP and SPAN ports.
- Symmetric load balancing.
- Support for MPLS tag stripping.
- Connections matching monitoring traffic based on Layer 1 through Layer 4 information.
- Support for Layer 7 filtering for HTTP traffic.
- The ability to replicate and forward traffic to multiple monitoring tools.
- Reaction to changes in the TAP/SPAN aggregation network.
- Security features, such as role-based access control (RBAC), and integration with an external Active Directory (AD) using RADIUS or TACACS for authentication, authorization, and accounting (AAA).
- End-to-end path visibility, including both port and flow level statistics for troubleshooting.
- Robust Representational State Transfer (REST) API and a web-based GUI for all functions.
- Support for Cisco Plug-in for OpenFlow, version 1.0.
- Device addition using Device name.
- Inline monitoring and redirection for security use cases.
- Limit Local Authentication Fallback.

The following features require NX-OS 7.0(3)4(1) or later:

- Configure matching on HTTP methods and redirect traffic based on that with NX-API.
- MPLS tag stripping on the following:
  - Cisco Nexus 3100 Series switches
  - Cisco Nexus 3200 Series switches
  - Cisco Nexus 9000 Series switches
- OpenFlow mode of support for Cisco Nexus 9300 Series switches
- Q-in-Q on the following:
  - Cisco Nexus 3000 Series switches
  - Cisco Nexus 3100 Series switches
  - Cisco Nexus 3200 Series switches
  - Cisco Nexus 9000 Series switches

Cisco Nexus Data Broker enables you to:

- Classify SPAN and TAP ports.
- Add monitoring devices to capture network traffic.
- Filter which traffic should be monitored.
- Redirect packets from a single or multiple SPAN or TAP ports to multiple monitoring devices through delivery ports.
- Restrict which users can view and modify the monitoring system.

## Supported Deployment Mode

Cisco Nexus Data Broker 3.2.3 patch release is available only for embedded mode of deployments.

## Supported NX-OS Versions

NX-OS Releases supported in OpenFlow mode:

- 6.0(2)U6(X) and later on the following:
  - Cisco Nexus 3000 Series switches
  - Cisco Nexus 3100 Series switches
- 6.0(2)A6(5a) and later on the following:
  - Cisco Nexus 3500 Series switches
- 7.0(3)I4(1) and later on Cisco Nexus 9000 Series switches
- 7.0(3)I4(1) and later on the following:
  - Cisco Nexus 3200 Series switches
  - Cisco Nexus 9300 Series switches
- 7.0(3)I5(1) and later on Cisco Nexus 9200 Series switches
- 7.0(3)I5(1) and later on Cisco Nexus 9300-EX Series switches

NX-OS Versions supported in NX-API mode:

- 7.0(3)I4(1) and later on the following:
  - Cisco Nexus 9000 Series switches
  - Cisco Nexus 3200 Series switches
  - Cisco Nexus 3100 Series switches
  - Cisco Nexus 9300 Series switches
  - Cisco Nexus 9500 Series switches
- 7.0(3)I5(1) and later on the following:
  - Cisco Nexus 9200 Series switches
  - Cisco Nexus 9300-EX Series switches

## New Features

No new features are introduced in Cisco Nexus Data Broker, release 3.2.3.

## Open and Resolved Bugs

The open and resolved bugs for this release are accessible through the [Cisco Bug Search Tool](#). This web-based tool provides you with access to the Cisco bug tracking system, which maintains information about bugs and vulnerabilities in this product and other Cisco hardware and software products.

**Note:** You must have a Cisco.com account to log in and access the Cisco Bug Search Tool. If you do not have one, you can [register for an account](#).

For more information about the Cisco Bug Search Tool, see the [Bug Search Tool Help & FAQ](#).

This section includes the following topics:

- Resolved Bugs in this Release
- Open Bugs for this Release

## Resolved Bugs in this Release

[Table 1](#) lists the descriptions of resolved caveats in Cisco Nexus Data Broker Release 3.2.3. You can use the bug ID to search the [Cisco Bug Search Tool](#) for details about the bug.

**Table 1 Resolved Bugs in Cisco Nexus Data Broker Release 3.2.3**

Bug ID	Description
<a href="#">CSCve77675</a>	Embedded NDB: Web UI not accessible - 404 Not Found.
<a href="#">CSCvd52879</a>	Second redirection fails to install, if the filter, priority, and service node configuration is similar to the first redirection.
<a href="#">CSCvc46460</a>	APIC SPAN sessions do not handle special characters for EPG.
<a href="#">CSCvc75805</a>	IPv6 filter does not appear in redirection list.
<a href="#">CSCvc75814</a>	NXAPI functionality is not present in topology for Aux and redirections fails after reloading the device.
<a href="#">CSCvd08992</a>	Updated configuration is not propagated to all the devices.
<a href="#">CSCvd21787</a>	LLDP packets from the monitor ports are hitting the controller.
<a href="#">CSCvd61295</a>	OpenFlow ports are in admin down state in the switch when the NDB restarts.
<a href="#">CSCvf08579</a>	Cisco NDB not working properly.

## Open Bugs for this Release

[Table 2](#) lists the descriptions of open bugs in Cisco Nexus Data Broker Release 3.2.3. You can use the bug ID to search the [Cisco Bug Search Tool](#) for details about the bug.

**Table 2 Open Bugs in Cisco Nexus Data Broker Release 3.2.3**

Bug ID	Description
<a href="#">CSCuu41674</a>	Removing an existing connection fails and a pop-up window appears to inform the user about connection inconsistency and request the user to fix the problem through the Troubleshooting tab. After fixing the connection through the Troubleshooting tab, the connection status is displayed in green, and the connection is not removed from NDB and the device. This issue occurs occasionally only if NX-API device connection is lost at the exact time that the connection is being removed.
<a href="#">CSCuy81389</a>	Cisco Nexus 9000 devices do not have an error pop up message for the connection installation of VLAN + Layer 3 filters.
<a href="#">CSCuy81365</a>	After a successful node configuration for symmetric load balancing on a port channel, the configured load balancing method in the label shows sporadically for some devices.
<a href="#">CSCvc27514</a>	Connection source ports are not listed on the Open Flow device.
<a href="#">CSCvc41941</a>	Node Id of the device group is not updated after upgrading from NDB release 3.X to 3.2 and above.
<a href="#">CSCvc87973</a>	The IPv6 <b>hardware</b> command should be configure in Cisco Nexus 9000 switches.
<a href="#">CSCvc87978</a>	Upgrading to Cisco Nexus Data Broker 3.2 with a Cisco Nexus 9000 NX-API switch needs the IPv6 hardware CLI command on the switch.
<a href="#">CSCvc87992</a>	Connections are not matched with the VLAN ID of source ports on ISL links with an IPv6 filter.

## Usage Guidelines

This section lists the usage guidelines for the Cisco Nexus Data Broker.

- APIC version to be supported is 1.1 and 1.2 series
- The **spanning-tree bpdudfilter enable** command should be configured for all inter-switch ports for all platform series.
- Cisco Nexus Data Broker Embedded will be supported on NX-OS Release 7.0(3)I5(1) and earlier.
- The following features will not be supported in embedded mode deployment of Cisco Nexus Data Broker
  - Adding SPAN session
  - Adding copy device
  - Adding copy sessions
  - Scheduling Configuration Backup
  - Backing Up or Restoring the Configuration
- HTTP access on port 8080 is disabled by default. Only HTTPS access on port 8443 is enabled. If required, HTTP can be enabled by editing the tomcat.xml file. Please refer to *Cisco Nexus Data Broker Configuration Guide* for details.
- The Cisco Nexus Data Broker assumes inter-switch link interfaces are configured to be layer 2 switch ports, and these interfaces are set to **switchport trunk** by default.
- It is required to use JRE version 1.8.0\_45 for latest security fixes.

## Limitations

- Cisco Nexus 9000 switches managed by Cisco Nexus Data Broker release 3.2.2 or later must have LLDP features enabled. Disabling LLDP may cause inconsistencies and require devices to be deleted and re-added.
- When removing devices from the Cisco Nexus Data Broker, the device associated port definitions and connections should be removed first. Otherwise, the device might contain stale configurations created by the Cisco Nexus Data Broker.
- For Cisco NX-API devices, there is a 2 minute or more wait after the Cisco Nexus Data Broker configuration operations (port definitions, connections creation/deletion, and stats) to reload the device and avoid any inconsistency between the Cisco Nexus Data Broker and the device.
- The TLS KeyStore and TrustStore passwords are sent to the Cisco Nexus Data Broker so it can read the password-protected TLS KeyStore and TrustStore files only through HTTPS.

```
./xnc config-keystore-passwords [--user {user} --password {password} --url {url} --verbose --prompt --keystore-  
password {keystore_password} --truststore-password {truststore_password}. Here default URL to be -  
https://Nexus\_Data\_Broker\_IP:8443
```

## Limitations

- The same Cisco Nexus Data Broker instance can support either the OpenFlow or NX-API configuration mode, but it does not support both configuration modes.

## Device Support Matrix

Table 4 lists the supported Cisco Nexus Data Broker software for the various Cisco Nexus switches.

**Table 3 Cisco Nexus Data Broker Application Device Support Matrix**

Device Model	Cisco Nexus Data Broker Minimum version	Deployment Mode Supported	Supported Use Cases
Cisco Nexus 3000 Series	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 3100 platform	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 3164Q Switch	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 3500 Series	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9300 platform	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 9500 platform	Cisco Nexus Data Broker 3.0 or later	Centralized only	Tap/SPAN aggregation only
Cisco Nexus 3200 switch	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9200 switch	Cisco Nexus Data Broker 3.1 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9300-EX switch	Cisco Nexus Data Broker 3.1 or later	Centralized and Embedded	Tap/SPAN aggregation only

## Scale Information

Table 4 lists the scale limits for Cisco Nexus Data Broker.

**Table 4 Scale Limits**

Description	Small	Medium	Large
Number of switches used for Tap and SPAN aggregation	25	50	75

## System Requirements

Table 5 lists the system requirements for Cisco Nexus Data Broker 3.2.3.

**Table 5 System Requirements per Deployment Size**

Description	Small	Medium	Large
CPUs (virtual or physical)	6-core	12-core	18-core
Memory	8 GB RAM	16 GB RAM	32 GB RAM
Hard disk	Minimum of 40 GB of free space available on the partition on which the Cisco Nexus Data Broker software is installed.		
Operating system	A recent 64-bit Linux distribution that supports Java, preferably Ubuntu, Fedora, or Red Hat.		
Other	Java Virtual Machine 1.8 or later.		

## Supported Web Browsers

The following web browsers are supported for Cisco Nexus Data Broker 3.2.3:

- Firefox 45.x and later
- Chrome 45.x and later

**Note:** Javascript 1.5 or a later version must be enabled in your browser.

## Upgrading to Release 3.2.3

This section explains the supported method for upgrading your release.

From	Supported Method
3.0 or later	Direct upgrade is supported



Earlier than 3.0	Perform the following procedure: <ol style="list-style-type: none"><li>1. Upgrade to 3.0</li><li>2. Upgrade to 3.2</li></ol>
------------------	--

**Caution:** Upgrading from NDB 3.2.3 to NDB 3.3 is not supported.

**Caution:** Downloading system configuration files from NDB 3.2.3 and uploading the saved system configuration to NDB 3.3 is not supported.

## Related Documentation

For more information, see the related documents at the following link:

<http://www.cisco.com/c/en/us/support/cloud-systems-management/nexus-data-broker/tsd-products-support-series-home.html>

## New Documentation

There are no new documents for this release.

## Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see *What's New in Cisco Product Documentation* at:

<http://www.cisco.com/c/en/us/td/docs/general/whatsnew/whatsnew.html>.

Subscribe to *What's New in Cisco Product Documentation*, which lists all new and revised Cisco technical documentation, as an RSS feed and deliver content directly to your desktop using a reader application. The RSS feeds are a free service.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2017 Cisco Systems, Inc. All rights reserved.