



Introduction

The Cisco ASR 900 Series Routers are full-featured, modular aggregation platforms designed for the cost-effective delivery of converged mobile, residential, and business services. This document provides information about the IOS XE software release for the Cisco ASR 900 Series Routers.



- Note** Explore the [Content Hub](#), the all new portal that offers an enhanced product documentation experience.
- Use faceted search to locate content that is most relevant to you.
 - Create customized PDFs for ready reference.
 - Benefit from context-based recommendations.

Get started with the Content Hub at content.cisco.com to craft a personalized documentation experience.

Do provide feedback about your experience with the Content Hub.

- [Overview of Cisco ASR 900 Series Routers](#) , on page 1
- [Feature Navigator](#), on page 2
- [Hardware Support](#) , on page 3
- [Feature Matrix](#), on page 13
- [Software Licensing Overview](#), on page 13
- [Determining the Software Version](#) , on page 14
- [Upgrading to a New Software Release](#), on page 14
- [Supported FPGA, HoFPGA, and ROMMON Versions for Cisco IOS XE 17.10.x Release](#), on page 15
- [MIB Support](#), on page 17
- [Additional References](#), on page 20

Overview of Cisco ASR 900 Series Routers

The Cisco ASR 900 Series Router is a fully-featured routing platform designed for the cost-effective delivery of converged mobile and business services. With full redundancy, shallow depth, low power consumption and high service scale, this 3-rack-unit (3RU) router is optimized for small aggregation and remote point-of-presence (POP) applications. The Cisco ASR 900 Series Router provides a rich and scalable feature set of Legacy, Timing, Carrier Ethernet, Layer 2 VPN (L2VPN) and Layer 3 VPN (L3VPN) services in a compact package.

The Cisco ASR 900 Series Router is a fully modular platform with support for upto 6-Interface Modules (IMs), two Route Switch Processor (RSP) slots, two power supplies and redundant fans, based on the router model. Cisco offers a wide choice of LAN and WAN interfaces available in speeds ranging from nxDS0 to 10 Gigabit Ethernet. The design of the Cisco ASR 900 Series Router delivers in-box hardware redundancy for all hardware components and supports software redundancy with In Service Software Upgrade (ISSU) and Non-Stop Forwarding (NSF) support.

Cisco ASR 902 Router

The Cisco ASR 902 Router is a full-featured aggregation platform designed for cost-effective delivery of converged mobile and business services. With shallow depth, low power consumption, and an extended temperature range, this compact 2-rack unit (2RU) router provides high service scale and flexible hardware configuration.

Cisco ASR 903 Router

The Cisco ASR 903 Series Aggregation Services Router is a Cisco aggregation router product. This router uses an innovative and powerful forwarding technology known as the Cisco Carrier Ethernet ASIC.

The Cisco ASR 903 Series Router is a 6-Interface Module (IM), 3-RU, hardware-redundant chassis with two Route Switch Processor (RSP) slots, and six IM slots. It supports fully redundant RSPs that allow for full RSP hardware redundancy, NSF, ISSU, and future RSP service upgrades.

Cisco ASR 907 Router

The Cisco ASR 907 Router seven-rack (7RU) unit router that belongs to the Cisco ASR90x family of routers. This router complements Cisco's offerings for IP RAN solutions for the GSM, UMTS, LTE and CDMA. Given its form-factor, interface types and Gigabit Ethernet density the Cisco ASR 907 Router can also be positioned as a Carrier Ethernet aggregation platform.

The Cisco ASR 907 Router is a cost optimized, fully redundant, centralized forwarding, extended temperature, and flexible pre-aggregation router.

Cisco ASR 914 Router

The Cisco ASR 914 Router is a 14-rack unit router that belongs to the Cisco ASR 900 family of routers. This router complements Cisco's offerings for IP RAN solutions for the GSM, UMTS, LTE, and CDMA. Given its form-factor, interface types and GigabitEthernet density the Cisco ASR 914 Router can also be positioned as a Carrier Ethernet aggregation platform.

The Cisco ASR 914 Router is a cost optimized, fully redundant, centralized forwarding, extended temperature, and flexible pre-aggregation router.

Feature Navigator

You can use Cisco Feature Navigator to find information about feature, platform, and software image support. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on cisco.com is not required.

Hardware Support

Cisco ASR 902 Supported Interface Modules

A900-RSP2-Supported Interface Modules (ASR 902 Router)

Table 1: A900-RSP2-Supported Interface Modules and Part Numbers

| RSP | Interface Modules | Part Numbers | Slots |
|-----------------------------------|---|--------------|-------|
| A900-RSP2A-128 A900U-RSP2A-128 | 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | All |
| | 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| | 1-port 10-Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | |
| | 16-port T1/E1 Interface Module | A900-IMA16D | |
| | 4-port OC3/STM-1 (OC-3) or 1-port OC12/STM-4 (OC-12) Interface Module | A900-IMA4OS | |
| | SFP Combo IM—8-port Gigabit Ethernet (8x1GE) + | A900-IMA8S1Z | |
| | 1-port 10-Gigabit Ethernet (1x10GE) | | |
| | Copper Combo IM—8-port Gigabit Ethernet (8x1GE) + 1-port 10-Gigabit Ethernet Interface Module (1x10GE) | A900-IMA8T1Z | |
| | 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| 14-port Serial Interface Module | A900-IMASER14A/S | | |

| RSP | Interface Modules | Part Numbers | Slots |
|---------------------------------|---|------------------|------------|
| | 4-port C37.94 Interface Module | A900-IMA4C3794 | |
| A900-RSP2A-64 A900U-RSP2A-64 | 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | 0-2 |
| | 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| | 4-port OC3/STM-1 (OC-3) or 1-port OC12/STM-4 (OC-12) Interface Module | A900-IMA4OS | |
| | 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | 0, 2 and 3 |
| | 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| | 16-port T1/E1 Interface Module | A900-IMA16D | |
| | 32-port T1/E1 Interface Module | A900-IMA32D | |
| | 8-port T1/E1 Interface Module | A900-IMA8D | |
| | 6-port E & M Interface Module | A900-IMA6EM | |
| | 14-port Serial Interface Module | A900-IMASER14A/S | |
| | 4-port C37.94 Interface Module | A900-IMA4C3794 | |

A900-RSP3C-200-S Supported Interface Modules (ASR 902 Router)

Table 2: A900-RSP3C-200 Supported Interface Modules and Part Numbers

| RSP Module | Supported Interface Modules | Part Numbers | Slot |
|------------------|--|--------------|------------------|
| A900-RSP3C-200-S | 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | All ¹ |
| | 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| | 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | 0 and 1 |
| | SFP Combo IM—8-port Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet (1x10GE) | A900-IMA8S1Z | All |
| | Copper Combo IM—8-port Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet Interface Module (1x10GE) | A900-IMA8T1Z | |
| | 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| | 8-port 10 Gigabit Ethernet Interface Module (8x10GE) | A900-IMA8Z | 0 |
| | 2-port 40 Gigabit Ethernet QSFP Interface Module (2x40GE) | A900-IMA2F | |

¹ There are restrictions using the interface modules in different slots with RSP3 module. Contact Cisco Sales/Support for the valid combinations..

Cisco ASR 903 Supported Interface Modules

A900-RSP2 Supported Interface Modules

A900-IMA2Z IM supports SFP+ and XFP on ports 0 and 1. Either SFP+ or XFP can be connected on each port. If both are connected on the same port, the port will go down.

The combination IMs (A900-IMA8S1Z, A900-IMA8T1Z) are not supported on the A900-RSP2-64 RSP module on the Cisco ASR 903 Router.

The table below is applicable for A900-RSP2A-128 and A900U-RSP2A-128 RSP modules.

Table 3: A900-RSP2A-128 Supported Interface Modules and Part Numbers

| Supported Interface Modules | Part Numbers | Slot |
|--|------------------|---------|
| 1-port OC48/ STM-16 or 4-port OC-12/OC-3 / STM-1/STM-4 + 12-Port T1/E1 + 4-Port T3/E3 CEM Interface Module | A900-IMA3G-IMSG | 2,3,4,5 |
| 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | All |
| 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | |
| 16-port T1/E1 Interface Module | A900-IMA16D | |
| 32-port T1/E1 Interface Module | A900-IMA32D | |
| 8-port T1/E1 Interface Module | A900-IMA8D | |
| 4-port OC3/STM-1 (OC-3) or 1-port OC12/STM-4 (OC-12) Interface Module | A900-IMA4OS | |
| SFP Combo IM—8-port SFP Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet (1x10GE) | A900-IMA8S1Z | |
| Copper Combo IM—8-port 10/100/1000 Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet Interface Module (1x10GE) | A900-IMA8T1Z | |
| 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| 6-port E & M Interface Module | A900-IMA6EM | |
| 14-port Serial Interface Module | A900-IMASER14A/S | |
| 4-port C37.94 Interface Module | A900-IMA4C3794 | |

The table below is applicable for A900-RSP2A-64 and A900U-RSP2A-64 RSP modules.

Table 4: A900-RSP2A-64 Supported Interface Modules and Part Numbers

| Supported Interface Modules | Part Numbers | Slot |
|---|--------------|------|
| 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | 0-2 |
| 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| 4-port OC3/STM-1 (OC-3) or 1-port OC12/STM-4 (OC-12) Interface Module | A900-IMA4OS | |

| Supported Interface Modules | Part Numbers | Slot |
|--|------------------|------|
| 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | 3-5 |
| 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| 16-port T1/E1 Interface Module | A900-IMA16D | |
| 32-port T1/E1 Interface Module | A900-IMA32D | |
| 8-port T1/E1 Interface Module | A900-IMA8D | |
| 6-port E & M Interface Module | A900-IMA6EM | |
| 14-port Serial Interface Module | A900-IMASER14A/S | |
| 4-port C37.94 Interface Module | A900-IMA4C3794 | |

A900-RSP3C-400-S Supported Interface Modules

The table below is applicable for A900-RSP3C-400-S RSP module.



Note If the **license feature service-offload enable** command is configured, then the following IMs are not supported in the router for RSP3:

- A900-IMA8S
- A900-IMA8T
- A900-IMA8S1Z
- A900-IMA8T1Z



Note There are certain restrictions in using the interface modules on different slots with RSP3 module. Contact Cisco Sales/Support for the valid combinations.

Table 5: A900-RSP3C-400 Supported Interface Modules and Part Numbers

| Supported Interface Modules | Part Numbers | Slot |
|--|------------------|------|
| 6-port E & M Interface Module | A900-IMA6EM | All |
| 4-port C37.94 Interface Module | A900-IMA4C3794 | All |
| 14-port Serial Interface Module | A900-IMASER14A/S | All |
| 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | All |

| Supported Interface Modules | Part Numbers | Slot |
|--|-----------------------|----------------------|
| 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | All |
| 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | All |
| SFP Combo IM—8-port SFP Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet (1x10GE) | A900-IMA8S1Z | All |
| Copper Combo IM—8-port 10/100/1000 Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet Interface Module (1x10GE) | A900-IMA8T1Z | All |
| 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | All |
| 8-port 10 Gigabit Ethernet Interface Module (8x10GE) | A900-IMA8Z | All |
| 1-port 100 Gigabit Ethernet Interface Module (1x100GE) | A900-IMA1C | 4 or 5 |
| 2-port 100 Gigabit Ethernet (QSFP) Interface Module (2x100GE) | N560-IMA2C/A900-IMA2C | 4 and 5 ² |
| 2-port 40 Gigabit Ethernet QSFP Interface Module (2x40GE) | A900-IMA2F | 4 or 5 |
| 8/16-port 1 Gigabit Ethernet (SFP/SFP) + 1-port 10 Gigabit Ethernet (SFP+) / 2-port 1 Gigabit Ethernet (CSFP) Interface Module | A900-IMA8CS1Z-M | 0,3,4 or 5 |
| 48-port T1/E1 Interface module | A900-IMA48D-C | All |
| 48-port T3/E3 Interface module | A900-IMA48T-C | All |
| 1-port OC-192 or 8-Port Low Rate CEM Interface Module | A900-IMA8S1Z-CX | 2,3,4,5 |
| 4-port OC-48/OC-12/OC-3 + 12-Port A900-IMA3G-IMSG T1/E1 + 4-Port T3/E3 CEM Interface Module | A900-IMA3G-IMSG | All |

| Supported Interface Modules | Part Numbers | Slot |
|---|-------------------|--|
| ASR 900 1-Port OC-192 or 8-Port Low Rate CEM 20G Bandwidth Interface Module | A900-IMA1Z8S-CXMS | 2, 3, 4, 5 ³ Note To enable this IM on slot 0 or slot 1, do the following and reload the router: <pre>Router# configure t Router(config)# license feature service-offload enable</pre> |

² IM supports only one port of 100G with RSP3 as QSFP28 on Port 0 in both slots 4 and 5.

³ These slots are supported on 10G or 20G mode.

A900-RSP3C-200-S Supported Interface Modules

The table below is applicable for A900-RSP3C-200-S RSP module.



Note If the **license feature service-offload enable** command is configured, then the following IMs are not supported in the router for RSP3:

- A900-IMA8S
- A900-IMA8T
- A900-IMA8S1Z
- A900-IMA8T1Z



Note There are certain restrictions in using the interface modules on different slots with RSP3 module. Contact Cisco Sales/Support for the valid combinations.



Note FAN OIR is applicable every time the IM based fan speed profile is switched to the IMA1C and IMA2F interface modules. Even though the IMs remain in the Out-of-Service state, they are still considered as present in the chassis.

Table 6: A900-RSP3C-200 Supported Interface Modules and Part Numbers

| Supported Interface Modules | Part Numbers | Slot |
|--|-----------------------------|------------------|
| 8-port Gigabit Ethernet SFP Interface Module (8x1GE) | A900-IMA8S | All |
| 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8x1GE) | A900-IMA8T | |
| 1-port 10 Gigabit Ethernet XFP Interface Module (1x10GE) | A900-IMA1X | 0, 2 or 4 |
| SFP Combo IM—8-port SFP Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet (1x10GE) | A900-IMA8S1Z | 1-5 ⁴ |
| Copper Combo IM—8-port 10/100/1000 Gigabit Ethernet (8x1GE) + 1-port 10 Gigabit Ethernet Interface Module (1x10GE) | A900-IMA8T1Z | 0-4 |
| 2-port 10 Gigabit Ethernet Interface Module (2x10GE) | A900-IMA2Z | |
| 8-port 10 Gigabit Ethernet Interface Module (8x10GE) | A900-IMA8Z | 4 |
| 2-port 40 Gigabit Ethernet QSFP Interface Module (2x40GE) | A900-IMA2F | 4 |
| 4-port OC-48/OC-12/OC-3 + 12-Port A900-IMA3G-IMSG T1/E1 + 4-Port T3/E3 CEM Interface Module | A900-IMA3G-IMSG | 2-5 ⁵ |
| 8-Port 10 Gigabit Ethernet (8x10GE) SFP+ Interface Module with Conformal Coating | ⁶ ASR900-IMA8ZCC | 0 |

⁴ If you have a 1-port 10G IM in slot 0, then SFP combo may not be supported in slot 5.

⁵ If slot 0 has 8X10G IM and you want to insert IMA-3G-IMSG to slot 5, then insert 8X10G IM on slot 6, by using the **hw-module subslot 0/0 A900-IMA8Z mode 6-Port** command.

⁶ Supported only from release XE-17.13.1 onwards.

Cisco ASR 907 Supported Interface Modules

Supported Interface Modules



Note If the **license feature service-offload enable** command is configured, then the following IMs are not supported in the router for RSP3:

- A900-IMA8S
- A900-IMA8T
- A900-IMA8S1Z
- A900-IMA8T1Z



Note There are certain restrictions in using the interface modules on different slots in the chassis. Contact Cisco Sales and Support for the valid combinations.

Table 7: A900-RSP3 Supported Interface Modules and Part Numbers

| RSP Module | Interface Modules | Part Number | Slot |
|------------------|--|------------------|----------------------------|
| A900-RSP3C-400-W | 8-port Gigabit Ethernet SFP Interface Module (8X1GE) | A900-IMA8S | 0,1,2,5,6,9,10,13,14,15 |
| | 8-port Gigabit Ethernet RJ45 (Copper) Interface Module (8X1GE) | A900-IMA8T | 0,1,2,5,6,9,10,13,14,15 |
| | 1-port 10 Gigabit Ethernet XFP Interface Module (1X10GE) | A900-IMA1X | Not Supported |
| | SFP Combo IM—8-port Gigabit Ethernet (8X1GE) + 1-port 10 Gigabit Ethernet (1X10GE) | ASR900-IMA8S1Z | 2,5,6,9,10,13,14,15 |
| | Copper Combo IM—8-port Gigabit Ethernet (8X1GE) + 1-port 10 Gigabit Ethernet Interface Module (1X10GE) | ASR900-IMA8T1Z | 2,5,6,9,10,13,14,15 |
| | 2-port 10 Gigabit Ethernet Interface Module (2X10GE) | ASR900-IMA2Z | 3,4,7,8,11,12 |
| | 16-port T1/E1 Interface Module | A900-IMA16D | Not Supported |
| | 14-port Serial Interface Module | A900-IMASER14A/S | 3,4,7,8,11,12 ⁷ |
| | 8-port T1/E1 Interface Module | A900-IMA8D | Not Supported |

| RSP Module | Interface Modules | Part Number | Slot |
|------------|--|-------------------------|---|
| | 32-port T1/E1 Interface Module | A900-IMA32D | Not Supported |
| | 1x100G Interface module | A900-IMA1C | 7 and 8 |
| | 2-port 100 Gigabit Ethernet (QSFP) Interface Module (2X100GE) | A900-IMA2C | 7 and 8 ⁸ |
| | 2x40G Interface module | A900-IMA2F | 3,4,7,8,11,12 |
| | 8x10G Interface module | A900-IMA8Z ⁹ | 3,4,7,8,11,12 |
| | 8/16-port 1 Gigabit Ethernet (SFP/SFP) + 1-port 10 Gigabit Ethernet (SFP+) / 2-port 1 Gigabit Ethernet (CSFP) Interface Module | A900-IMA8CS1Z-M | 0,1,2,3,4,5,6,7,8,9,10,11,12,13,14,15 |
| | 1-port OC-192 or 8-Port Low Rate CEM Interface Module | A900-IMA8S1Z-CX | 3,4,7,8,11,12 (10 G Mode) 0,1,2,5,6,9,10,13,14,15 (5 G Mode) |
| | 48-port T1/E1 Interface module | A900-IMA48D-C | 2,3,4,5,6,7,8,9,10,11,12,13,14,15 |
| | 48-port T3/E3 Interface module | A900-IMA48T-C | 2,3,4,5,6,7,8,9,10,11,12,13,14,15 |
| | 1-port OC48/ STM-16 or 4-port OC-12/OC-3 / STM-1/STM-4 + 12-Port T1/E1 + 4-Port T3/E3 CEM Interface Module | A900-IMA3G-IMSG | 3,5,7,9,11,13,15 |
| | ASR 900 1-Port OC-192 or 8-Port Low Rate CEM 20G Bandwidth Interface Module | A900-IMA1Z8S-CXMS | 3, 7, 11 ¹⁰ 4, 8, 12 ¹¹ 5, 9, 13, 15 ¹² Note To enable this IM on slot 0 or slot 1, do the following and reload the router: Router# configure t Router(config)# license feature service-offload enable |
| | 6-port E&M Module | A900-IMA6EM | All slots |
| | 4-port C37.94 Interface Module | A900-IMA4C3794 | All slots |

- ⁷ The serial IM will not work on slots 11 and 12, if the IMs A900-IMA8T or A900-IMA8S is inserted on any slot in the router.
- ⁸ The IMs A900-IMA6EM, A900-IMASER14A/S, and A900-IMA4C3794 can be installed in slots 3, 4, 7, 8, 11, 12. Slots 3, 4 and 11, 12 have dependency with 1 Gigabit Ethernet IMs. These IMs can be placed in slots 3 only if Gigabit Ethernet IM is not present in slot 5. These IMs can be placed in slots 4 only if Gigabit Ethernet IM is not present in slot 6. These IMs can be placed in slots 11 only if Gigabit Ethernet IM is not present in slots 1, 5, 9, 13, and 15. These IMs can be placed in slots 12 only if Gigabit Ethernet IM is not present in slots 0,2,6,10 and 14.
- ⁹ Six IM slots are supported with various combinations but only five IM slots are functional at a time.
- ¹⁰ These slots are supported on 10G or 20G mode.
- ¹¹ These slots are supported on 10G or 20G mode, only if the adjacent odd slots are empty.
- ¹² These slots are supported on 10G mode.

Cisco ASR 914 Supported Interface Modules

For information in interface modules supported, see [Cisco A900-RSP3C-400-W Supported Interface Modules](#).

Feature Matrix

The feature matrix lists the features that are supported for each platform. For more information, see the cumulative [Feature Compatibility Release Matrix](#) on the Content Hub.

Software Licensing Overview

The router offers the following base licenses:

- Metro Services
- Metro IP Services
- Metro Aggregation Services



Note Starting with Cisco IOS XE Cupertino 17.7.1, licenses are not enabled by default. We recommend that you move to Smart Licensing.

Smart Licensing

Starting with Cisco IOS XE Cupertino 17.7.1, PAK licenses are no longer available. When you purchase the Cisco IOS XE Cupertino 17.7.1 release or later, Smart Licensing is enabled by default. We recommend that you move to Smart Licensing before upgrading to Cisco IOS XE Cupertino 17.7.1 or a higher release, for a seamless experience.

If you are using Cisco IOS XE Bengaluru 17.6.1 or an earlier release version, Smart Licensing is not enabled by default. To enable Smart Licensing, see [Software Activation Configuration Guide \(Cisco IOS XE ASR 900 Series\)](#).

Table 8: Cisco ASR 900 Software Licenses Feature Set

| Metro Services | Metro IP Services | Metro Aggregation Services |
|--|--|---|
| — | Includes all features in Metro Services | Includes all features in Metro IP Services |
| QoS, with deep buffers and hierarchical QoS (HQoS) | IP routing (RIP, OSPF, EIGRP, BGP, IS-IS) | MPLS (LDP and VPN) |
| Layer 2: 802.1d, 802.1q | PIM (SM, DM, SSM), SSM mapping | MPLS TE and FRR |
| Ethernet Virtual Circuit (EVC) | BFD | MPLS OAM |
| Ethernet OAM (802.1ag, 802.3ah) | Multi-VRF CE (VRF lite) with service awareness (ARP, ping, SNMP, syslog, trace-route, FTP, TFTP) | MPLS-TP |
| Multiple Spanning Tree (MST) and Resilient Ethernet Protocol (REP) | IEEE 1588-2008 Ordinary Slave Clock and Transparent Clock | Pseudowire emulation (EoMPLS, CESoPSN, and SAToP) |
| Synchronous Ethernet | — | VPLS and HVPLS |
| IPv4 and IPv6 host connectivity | — | Pseudowire redundancy |
| — | — | MR-APS and mLACP |

The router offers the following additional feature licenses:

- ATM
- IEEE 1588-2008 Boundary Clock/Master Clock
- OCx-overview- Port License



Note These features require a software license to use.

Determining the Software Version

You can use the following commands to verify your software version:

- Consolidated Package—**show version**
- Individual sub-packages—**show version installed** (lists all installed packages)

Upgrading to a New Software Release

Only the latest consolidated packages can be downloaded from Cisco.com; users who want to run the router using individual subpackages must first download the image from Cisco.com and extract the individual subpackages from the consolidated package.

For information about upgrading to a new software release, see the [Upgrading the Software on the Cisco ASR 900 Series Routers](#).

Upgrading the FPD Firmware

FPD Firmware packages are bundled with the software package. FPD upgrade is automatically performed on the router.

If you like to manually change the FPD Firmware software, use the **upgrade hw-module subslot 0/0 fpd bundle** to perform FPD firmware upgrade.

ROMMON Version

We recommend you to upgrade the ROMMON version to 15.6(49r)S.

For more information on the ROMMON package, see [Cisco Software Download](#).



Note ROMMON upgrade is mandatory to boot RSP3 images.

Supported FPGA, HoFPGA, and ROMMON Versions for Cisco IOS XE 17.10.x Release

Use the **show hw-module all fpd** command to display the IM FPGA version on the router.

The below table lists the FPGA version for the software releases.



Note If there is an FPGA upgrade during ISSU, it will cause traffic disruption. TDM interface modules get reset irrespective of FPGA upgrade during the ISSU.

Table 9: IM FPGA Versions for Ethernet Phase 3 IM

| Cisco IOS XE Release | IO FGPA | 8 x10 FPGA | 2x40 FPGA | 1x100 FPGA |
|----------------------|---------|------------|-----------|------------|
| 17.10.1 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.9.2 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.9.1 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.8.1 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.7.1 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.6.1 | 0x34 | 0.21 | 0.22 | 0.20 |
| 17.5.1 | 0x34 | 0.21 | 0.22 | 0.20 |

Table 10: CEM and IM FPGA Versions for ASR 903 RSP3 and ASR 907

| Category | Release | 48-port T1/E1 CEM Interface Module FPGA (A900-IMA48D-C) | 48-port T3/E3 CEM Interface Module FPGA (A900-IMA48T-C) | 1-port OC-192 Interface Module + 8-port Low Rate Interface Module FPGA (A900-IMA8S1Z-CX) | 1-port OC-48/STM-16 or 4-port OC-12/OC-3 / STM-1/STM-4 + 12-port T1/E1 + 4-port T3/E3 CEM Interface Module (A900-IMA3G-IMSG) | ASR 900 1-Port OC-192 or 8-Port Low Rate CEM 20G Bandwidth Interface Module (A900-IMA1Z8S-CXMS) |
|----------|----------------------|---|---|--|--|---|
| IM FPGA | Cisco IOS XE 17.10.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.95 |
| CEM FPGA | | 6.0 | 5.2 | 5G mode: 6.5 10G mode: 7.9 | 9.3 | 10G mode: 7.3 20G mode: 7.3 |
| IM FPGA | Cisco IOS XE 17.9.2 | 1.22 | 1.22 | 1.15 | 2.00 | 0.95 |
| CEM FPGA | | 6.0 | 5.2 | 5G mode: 6.5 10G mode: 7.9 | 9.1 | 10G mode: 7.2 20G mode: 7.2 |
| IM FPGA | Cisco IOS XE 17.9.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.95 |
| CEM FPGA | | 6.0 | 5.2 | 5G mode: 6.5 10G mode: 7.9 | 9.1 | 10G mode: 7.2 20G mode: 7.2 |
| IM FPGA | Cisco IOS XE 17.8.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.93 |
| CEM FPGA | | 6.0 | 5.2 | 5G mode: 6.5 10G mode: 7.9 | 9.0 | 10G mode: 7.0 20G mode: 6.0 |
| IM FPGA | Cisco IOS XE 17.7.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.93 |
| CEM FPGA | | 0x52110052 | 0x52510052 | 5G mode: 0x10090065 10G mode: 0x10070079 | 0x10030076 | 10G mode: 0x10290051 20G mode: 0x10290051 |
| IM FPGA | Cisco IOS XE 17.6.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.93 |
| CEM FPGA | | 0x52110052 | 0x52520052 | 5G mode: 0x10090065 10G mode: 0x10070079 | 0x10030076 | 10G mode: 0x10290051 20G mode: 0x10290051 |

| Category | Release | 48-port T1/E1 CEM Interface Module FPGA (A900-IMA48D-C) | 48-port T3/E3 CEM Interface Module FPGA (A900-IMA48T-C) | 1-port OC-192 Interface Module + 8-port Low Rate Interface Module FPGA (A900-IMA8S1Z-CX) | 1-port OC-48/STM-16 or 4-port OC-12/OC-3 / STM-1/STM-4 + 12-port T1/E1 + 4-port T3/E3 CEM Interface Module (A900-IMA3G-IMSG) | ASR 900 1-Port OC-192 or 8-Port Low Rate CEM 20G Bandwidth Interface Module (A900-IMA1ZS-CXMS) |
|----------|---------------------|---|---|--|--|--|
| IM FPGA | Cisco IOS XE 17.5.1 | 1.22 | 1.22 | 1.15 | 2.00 | 0.93 |
| CEM FPGA | | 0x52050052 | 0x52420052 | 5G mode: 0x10210063 10G mode: 0x10530078 | 0x10020076 | 10G mode: 0x10090051 20G mode: 0x10090051 |

Table 11: FPGA, HoFPGA, and ROMMON Versions for Cisco IOS XE 17.10.1 Release

| Platform | Interface Module | FPGA Current Version | FPGA Minimum Required Version | RSP HoFPGA Active | RSP HoFPGA Standby | ROMMON |
|-----------|------------------|----------------------|-------------------------------|-------------------|--------------------|------------|
| RSP2-128 | A900-IMA2Z | 69.24 | 69.24 | 0X00030011 | 0X00030011 | 15.6(54r)S |
| | A900-IMA8S | 0.75 | 0.75 | | | |
| | A900-IMA8T1Z | 69.32 | 69.32 | | | |
| RSP3-400S | A900-IMA1C | 0.20 | 0.20 | 40035 | 40035 | 15.6(54r)S |
| | A900-IMA8Z | 0.22 | 0.21 | | | |
| | A900-IMA8S1Z | 69.32 | 69.32 | | | |
| RSP3-400W | A900-IMA1C | 0.20 | 0.20 | 20040034 | 20040034 | 15.6(54r)S |
| | A900-IMA2Z | 69.24 | 69.24 | | | |

MIB Support

The below table summarizes the supported MIBs on the Cisco ASR 900 Series Router.

Table 12: Supported MIBs

| Supported MIBs | | |
|---------------------------------|------------------------------|-----------------------------|
| BGP4-MIB (RFC 1657) | CISCO-IMAGE-LICENSE-MGMT-MIB | MPLS-LDP-STD-MIB (RFC 3815) |
| CISCO-BGP-POLICY-ACCOUNTING-MIB | CISCO-IMAGE-MIB | MPLS-LSR-STD-MIB (RFC 3813) |
| CISCO-BGP4-MIB | CISCO-IPMROUTE-MIB | MPLS-TP-MIB |

| | | |
|---------------------------------|-------------------------------------|------------------------------------|
| CISCO-BULK-FILE-MIB | CISCO-LICENSE-MGMT-MIB | MSDP-MIB |
| CISCO-CBP-TARGET-MIB | CISCO-MVPN-MIB | NOTIFICATION-LOG-MIB (RFC 3014) |
| CISCO-CDP-MIB | CISCO-NETSYNC-MIB | OSPF-MIB (RFC 1850) |
| CISCO-CEF-MIB | CISCO-OSPF-MIB | OSPF-TRAP-MIB (RFC 1850) |
| CISCO-CLASS-BASED-QOS-MIB | CISCO-OSPF-TRAP-MIB | PIM-MIB (RFC 2934) |
| CISCO-CONFIG-COPY-MIB | CISCO-PIM-MIB | RFC1213-MIB |
| CISCO-CONFIG-MAN-MIB | CISCO-PROCESS-MIB | RFC2982-MIB |
| CISCO-DATA-COLLECTION-MIB | CISCO-PRODUCTS-MIB | RMON-MIB (RFC 1757) |
| CISCO-EMBEDDED-EVENT-MGRMIB | CISCO-PTP-MIB | RSVP-MIB |
| CISCO-ENHANCED-MEMPOOL-MIB | CISCO-RF-MIB | SNMP-COMMUNITY-MIB (RFC 2576) |
| CISCO-ENTITY-ALARM-MIB | CISCO-RTTMON-MIB | SNMP-FRAMEWORK-MIB (RFC 2571) |
| CISCO-ENTITY-EXT-MIB | CISCO-SONET-MIB | SNMP-MPD-MIB (RFC 2572) |
| CISCO-ENTITY-FRU-CONTROLMIB | CISCO-SYSLOG-MIB | SNMP-NOTIFICATION-MIB (RFC 2573) |
| CISCO-ENTITY-SENSOR-MIB | DS1-MIB (RFC 2495) | SNMP-PROXY-MIB (RFC 2573) |
| CISCO-ENTITY-VENDORTYPE-OID-MIB | ENTITY-MIB (RFC 4133) | SNMP-TARGET-MIB (RFC 2573) |
| CISCO-FLASH-MIB | ENTITY-SENSOR-MIB (RFC 3433) | SNMP-USM-MIB (RFC 2574) |
| CISCO-FTP-CLIENT-MIB | ENTITY-STATE-MIB | SNMPv2-MIB (RFC 1907) |
| CISCO-IETF-ISIS-MIB | EVENT-MIB (RFC 2981) | SNMPv2-SMI |
| CISCO-IETF-PW-ATM-MIB | ETHERLIKE-MIB (RFC 3635) | SNMP-VIEW-BASED-ACM-MIB (RFC 2575) |
| CISCO-IETF-PW-ENET-MIB | IF-MIB (RFC 2863) | SONET-MIB |
| CISCO-IETF-PW-MIB | IGMP-STD-MIB (RFC 2933) | TCP-MIB (RFC 4022) |
| CISCO-IETF-PW-MPLS-MIB | IP-FORWARD-MIB | TUNNEL-MIB (RFC 4087) |
| CISCO-IETF-PW-TDM-MIB | IP-MIB (RFC 4293) | UDP-MIB (RFC 4113) |
| CISCO-IF-EXTENSION-MIB | IPROUTE-STD-MIB (RFC 2932) | CISCO-FRAME-RELAY-MIB |
| CISCO-IGMP-FILTER-MIB | MPLS-LDP-GENERIC-STD-MIB (RFC 3815) | IF-MIB |
| CISCO-AAA-SERVER-MIB | — | — |

Table 13: Unverified MIBs

| Unverified MIBs | | |
|---------------------------------|---------------------------------------|------------------------------------|
| ATM-MIB | CISCO-IETF-DHCP-SERVER-EXT-MIB | EXPRESSION-MIB |
| CISCO-ATM-EXT-MIB | — | HC-ALARM-MIB |
| CISCO-ATM-IF-MIB | CISCO-IETF-PPVPN-MPLS-VPN-MIB | HC-RMON-MIB |
| CISCO-ATM-PVC-MIB | CISCO-IP-STAT-MIB | IEEE8021-CFM-MIB |
| CISCO-ATM-PVCTRAP-EXTN-MIB | CISCO-IPSLA-ETHERNET-MIB | IEEE8021-CFM-V2-MIB |
| CISCO-BCP-MIB | CISCO-L2-CONTROL-MIB | IEEE8023-LAG-MIB |
| CISCO-CALLHOME-MIB | CISCO-LAG-MIB | INT-SERV-GUARANTEED-MIB |
| CISCO-CIRCUIT-INTERFACE-MIB | CISCO-MAC-NOTIFICATION-MIB | INTEGRATED-SERVICES-MIB |
| CISCO-CONTEXT-MAPPING-MIB | CISCO-MEMORY-POOL-MIB | MPLS-L3VPN-STD-MIB (RFC 4382) |
| CISCO-EIGRP-MIB | CISCO-NHRP-EXT-MIB | MPLS-LDP-ATM-STD-MIB (RFC 3815) |
| CISCO-ERM-MIB | CISCO-NTP-MIB | MPLS-LDP-MIB |
| CISCO-ETHER-CFM-MIB | CISCO-PING-MIB | MPLS-TE-STD-MIB |
| CISCO-ETHERLIKE-EXT-MIB | CISCO-RESILIENT-ETHERNET-PROTOCOL-MIB | MPLS-VPN-MIB |
| CISCO-EVC-MIB | CISCO-RTTMON-ICMP-MIB | NHRP-MIB |
| CISCO-HSRP-EXT-MIB | CISCO-RTTMON-IP-EXT-MIB | RFC2006-MIB (MIP) |
| CISCO-HSRP-MIB | CISCO-RTTMON-RTP-MIB | RMON2-MIB (RFC 2021) |
| CISCO-IETF-ATM2-PVCTRAP-MIB | CISCO-SNMP-TARGET-EXT-MIB | SMON-MIB |
| CISCO-IETF-ATM2-PVCTRAP-MIBEXTN | CISCO-TCP-MIB | VRRP-MIB |
| CISCO-IETF-BFD-MIB | CISCO-VRF-MIB | — |
| CISCO-IETF-DHCP-SERVER-MIB | ETHER-WIS (RFC 3637) | — |

MIB Documentation

The following resources provide more detail about MIBs on the Cisco ASR 900 Series Router:

- Cisco ASR 900 Series Router MIB Guide—For information about the Cisco ASR 903 Series Router product implementation of the MIB protocol, see *Cisco ASR 903 Series Aggregation Services Router MIB Specifications Guide* at the following location:

http://www.cisco.com/c/en/us/td/docs/wireless/asr_900/mib/guide/asr903mib.html

- MIB Locator—To locate and download MIBs for selected platforms, Cisco IOS and Cisco IOS XE releases, and feature sets, use Cisco MIB Locator found at the following location:

<http://tools.cisco.com/ITDIT/MIBS/servlet/index>

Additional References

Product Information

- [Cisco ASR 900 Series Aggregation Services Routers Data Sheets](#)

Hardware Installation Guides

- [Cisco ASR 900 Series Aggregation Services Routers Hardware Guides](#)

Software Configuration Guides

- [Cisco ASR 900 Series Aggregation Services Routers Configuration Guides](#)

Regulatory Compliance and Safety Information

- [Regulatory Compliance and Safety Information for the Cisco ASR 900 Series Aggregation Services Routers](#)

Field Notices and Bulletins

- Field Notices—We recommend that you view the field notices for this release to determine whether your software or hardware platforms are affected. You can find field notices at http://www.cisco.com/en/US/support/tsd_products_field_notice_summary.html.
- Bulletins—You can find bulletins at http://www.cisco.com/en/US/products/sw/iosswrel/ps5012/prod_literature.html.

Accessibility Features in the Cisco ASR 900 Series Routers

For a list of accessibility features in Cisco ASR 900 Series Routers, see the [Voluntary Product Accessibility Template \(VPAT\)](#) on the Cisco website, or contact accessibility@cisco.com.

All product documents are accessible except for images, graphics, and some charts. If you would like to receive the product documentation in audio format, braille, or large print, contact accessibility@cisco.com.

End-of-Life and End-of-Sale Notices

For End-of-Life and End-of-Sale Notices for the Cisco ASR 900 Series Routers, see <https://www.cisco.com/c/en/us/products/routers/asr-903-series-aggregation-services-routers/eos-eol-notice-listing.html>.