



## OSPF Enhanced Traffic Statistics

This document describes new and modified commands that provide enhanced OSPF traffic statistics for OSPFv2 and OSPFv3. The ability to collect and display more detailed traffic statistics increases high availability for the OSPF network by making the troubleshooting process more efficient.

New OSPF traffic statistics are collected and displayed to include the following information:

- OSPF Hello input queue and OSPF process queue status and statistics.
- Global OSPF traffic statistics.
- Per-OSPF-interface traffic statistics.
- Per-OSPF-process traffic statistics.
- [Prerequisites for OSPF Enhanced Traffic Statistics, on page 1](#)
- [Information About OSPF Enhanced Traffic Statistics, on page 1](#)
- [How to Display and Clear OSPF Enhanced Traffic Statistics, on page 2](#)
- [Configuration Examples for OSPF Enhanced Traffic Statistics, on page 3](#)
- [Additional References, on page 7](#)
- [Feature Information for OSPF Enhanced Traffic Statistics, on page 8](#)

## Prerequisites for OSPF Enhanced Traffic Statistics

OSPFv2 or OSPFv3 must be configured on the router.

## Information About OSPF Enhanced Traffic Statistics

The OSPF enhanced traffic statistics are enabled by default and cannot be disabled.

The detailed OSPF traffic statistics are especially beneficial for troubleshooting the following types of OSPF instabilities:

- OSPF process queue status and statistical information can help the network administrator determine if an OSPF process can handle the amount of traffic sent to OSPF.
- OSPF packet header errors and LSA errors statistics keep a record of different errors found in received OSPF packets.

OSPF enhanced traffic control statistics also monitor the amount of traffic control exchanged between OSPF processes--an important consideration in network environments with slow links and frequent topology changes.

# How to Display and Clear OSPF Enhanced Traffic Statistics

## Displaying and Clearing OSPF Traffic Statistics for OSPFv2

### SUMMARY STEPS

1. enable
2. `show ip ospf [process-id] traffic[interface-type interface-number]`
3. `clear ip ospf traffic`

### DETAILED STEPS

#### Procedure

	Command or Action	Purpose
<b>Step 1</b>	<b>enable</b> <b>Example:</b> <pre>Router&gt; enable</pre>	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>• Enter your password if prompted.</li> </ul>
<b>Step 2</b>	<b>show ip ospf [process-id] traffic[interface-type interface-number]</b> <b>Example:</b> <pre>Router# show ip ospf 10 traffic gigabitethernet 0/0/0</pre>	Displays OSPFv2 traffic statistics.
<b>Step 3</b>	<b>clear ip ospf traffic</b> <b>Example:</b> <pre>Router# clear ip ospf traffic</pre>	Clears OSPFv2 traffic statistics.

## Displaying and Clearing OSPF Traffic Statistics for OSPFv3

### SUMMARY STEPS

1. enable
2. `show ipv6 ospf [process-id] traffic[interface-type interface-number]`
3. `clear ipv6 ospf traffic`

## DETAILED STEPS

Procedure		
	Command or Action	Purpose
Step 1	<b>enable</b> <b>Example:</b> Router> enable	Enables privileged EXEC mode. • Enter your password if prompted.
Step 2	<b>show ipv6 ospf</b> [ <i>process-id</i> ] <b>traffic</b> [ <i>interface-type interface-number</i> ] <b>Example:</b> Router# show ipv6 ospf traffic	Displays OSPFv3 traffic statistics.
Step 3	<b>clear ipv6 ospf traffic</b> <b>Example:</b> Router# clear ipv6 ospf traffic	Clears OSPFv3 traffic statistics.

# Configuration Examples for OSPF Enhanced Traffic Statistics

## Example Displaying and Clearing Enhanced Traffic Statistics for OSPFv2

The following example shows display output for the **show ip ospf traffic** command for OSPFv2:

```
Router# show ip ospf traffic
OSPF statistics:
  Rcvd: 55 total, 0 checksum errors
        22 hello, 7 database desc, 2 link state req
        6 link state updates, 6 link state acks
  Sent: 68 total
        45 hello, 7 database desc, 2 link state req
        10 link state updates, 4 link state acks
        OSPF Router with ID (10.1.1.1) (Process ID 8)
OSPF queues statistic for process ID 8:
  OSPF Hello queue size 0, no limit, drops 0, max size 0
  OSPF Router queue size 0, limit 200, drops 0, max size 0
Interface statistics:
  Interface GigabitEthernet0/0/1
OSPF packets received/sent
  Type           Packets      Bytes
  RX Invalid      0             0
  RX Hello        0             0
  RX DB des       0             0
  RX LS req       0             0
  RX LS upd       0             0
  RX LS ack       0             0
  RX Total        0             0
  TX Failed       0             0
```

## Example Displaying and Clearing Enhanced Traffic Statistics for OSPFv2

```

TX Hello      16      1216
TX DB des     0        0
TX LS req     0        0
TX LS upd     0        0
TX LS ack     0        0
TX Total      16      1216
OSPF header errors
Length 0, Checksum 0, Version 0, Bad Source 0,
No Virtual Link 0, Area Mismatch 0, No Sham Link 0,
Self Originated 0, Duplicate ID 0, Hello 0,
MTU Mismatch 0, Nbr Ignored 0, LLS 0,
Authentication 0,
OSPF LSA errors
Type 0, Length 0, Data 0, Checksum 0,
Summary traffic statistics for process ID 8:
OSPF packets received/sent
Type          Packets      Bytes
RX Invalid    0            0
RX Hello      0            0
RX DB des     0            0
RX LS req     0            0
RX LS upd     0            0
RX LS ack     0            0
RX Total      0            0
TX Failed     0            0
TX Hello      16          1216
TX DB des     0            0
TX LS req     0            0
TX LS upd     0            0
TX LS ack     0            0
TX Total      16          1216
OSPF header errors
Length 0, Checksum 0, Version 0, Bad Source 0,
No Virtual Link 0, Area Mismatch 0, No Sham Link 0,
Self Originated 0, Duplicate ID 0, Hello 0,
MTU Mismatch 0, Nbr Ignored 0, LLS 0,
Authentication 0,
OSPF LSA errors
Type 0, Length 0, Data 0, Checksum 0,
OSPF Router with ID (10.1.1.4) (Process ID 1)
OSPF queues statistic for process ID 1:
OSPF Hello queue size 0, no limit, drops 0, max size 2
OSPF Router queue size 0, limit 200, drops 0, max size 2
Interface statistics:
Interface Serial2/0/0
OSPF packets received/sent
Type          Packets      Bytes
RX Invalid    0            0
RX Hello      11          528
RX DB des     4            148
RX LS req     1            60
RX LS upd     3            216
RX LS ack     2            128
RX Total      21          1080
TX Failed     0            0
TX Hello      14          1104
TX DB des     3            252
TX LS req     1            56
TX LS upd     3            392
TX LS ack     2            128
TX Total      23          1932
OSPF header errors
Length 0, Checksum 0, Version 0, Bad Source 0,
No Virtual Link 0, Area Mismatch 0, No Sham Link 0,

```

```

Self Originated 0, Duplicate ID 0, Hello 0,
MTU Mismatch 0, Nbr Ignored 0, LLS 0,
Authentication 0,
OSPF LSA errors
  Type 0, Length 0, Data 0, Checksum 0,
    Interface GigabitEthernet0/0/0
OSPF packets received/sent
  Type           Packets           Bytes
  RX Invalid      0                0
  RX Hello        13              620
  RX DB des       3              116
  RX LS req       1               36
  RX LS upd       3              228
  RX LS ack       4              216
  RX Total        24             1216
  TX Failed       0                0
  TX Hello        17             1344
  TX DB des       4              276
  TX LS req       1               56
  TX LS upd       7             656
  TX LS ack       2              128
  TX Total        31             2460
OSPF header errors
  Length 0, Checksum 0, Version 0, Bad Source 13,
  No Virtual Link 0, Area Mismatch 0, No Sham Link 0,
  Self Originated 0, Duplicate ID 0, Hello 0,
  MTU Mismatch 0, Nbr Ignored 0, LLS 0,
  Authentication 0,
OSPF LSA errors
  Type 0, Length 0, Data 0, Checksum 0,

Summary traffic statistics for process ID 1:
OSPF packets received/sent
  Type           Packets           Bytes
  RX Invalid      0                0
  RX Hello        24             1148
  RX DB des       7              264
  RX LS req       2               96
  RX LS upd       6             444
  RX LS ack       6             344
  RX Total        45             2296
  TX Failed       0                0
  TX Hello        31             2448
  TX DB des       7             528
  TX LS req       2             112
  TX LS upd      10            1048
  TX LS ack       4             256
  TX Total        54            4392
OSPF header errors
  Length 0, Checksum 0, Version 0, Bad Source 13,
  No Virtual Link 0, Area Mismatch 0, No Sham Link 0,
  Self Originated 0, Duplicate ID 0, Hello 0,
  MTU Mismatch 0, Nbr Ignored 0, LLS 0,
  Authentication 0,
OSPF LSA errors
  Type 0, Length 0, Data 0, Checksum 0,

```

The network administrator can issue the **clear ip ospf traffic** command to reset all counters and restart all statistics collections:

```
Router# clear ip ospf traffic
```

## Example Displaying and Clearing Enhanced Traffic Statistics for OSPFv3

The following example shows display output for the **show ipv6 ospf traffic** command for OSPFv3:

```
Router# show ipv6 ospf traffic

OSPFv3 statistics:
  Rcvd: 32 total, 0 checksum errors
        10 hello, 7 database desc, 2 link state req
        9 link state updates, 4 link state acks
        0 LSA ignored
  Sent: 45 total, 0 failed
        17 hello, 12 database desc, 2 link state req
        8 link state updates, 6 link state acks
        OSPFv3 Router with ID (10.1.1.4) (Process ID 6)
OSPFv3 queues statistic for process ID 6
  Hello queue size 0, no limit, max size 2
  Router queue size 0, limit 200, drops 0, max size 2
Interface statistics:
  Interface Serial2/0/0
OSPFv3 packets received/sent
  Type           Packets           Bytes
  RX Invalid      0                0
  RX Hello        5               196
  RX DB des       4               172
  RX LS req       1                52
  RX LS upd       4               320
  RX LS ack       2               112
  RX Total       16               852
  TX Failed       0                0
  TX Hello        8               304
  TX DB des       3               144
  TX LS req       1                52
  TX LS upd       3               252
  TX LS ack       3               148
  TX Total       18               900
OSPFv3 header errors
  Length 0, Checksum 0, Version 0, No Virtual Link 0,
  Area Mismatch 0, Self Originated 0, Duplicate ID 0,
  Instance ID 0, Hello 0, MTU Mismatch 0,
  Nbr Ignored 0, Authentication 0,
OSPFv3 LSA errors
  Type 0, Length 0, Data 0, Checksum 0,
Interface GigabitEthernet0/0/0
OSPFv3 packets received/sent
  Type           Packets           Bytes
  RX Invalid      0                0
  RX Hello        6               240
  RX DB des       3               144
  RX LS req       1                52
  RX LS upd       5               372
  RX LS ack       2               152
  RX Total       17               960
  TX Failed       0                0
  TX Hello       11               420
  TX DB des       9               312
  TX LS req       1                52
  TX LS upd       5               376
  TX LS ack       3               148
  TX Total       29              1308
OSPFv3 header errors
  Length 0, Checksum 0, Version 0, No Virtual Link 0,
  Area Mismatch 0, Self Originated 0, Duplicate ID 0,
```

```

Instance ID 0, Hello 0, MTU Mismatch 0,
Nbr Ignored 0, Authentication 0,
OSPFv3 LSA errors
Type 0, Length 0, Data 0, Checksum 0,
Summary traffic statistics for process ID 6:
OSPFv3 packets received/sent
Type           Packets           Bytes
RX Invalid      0                0
RX Hello        11             436
RX DB des        7             316
RX LS req        2             104
RX LS upd        9             692
RX LS ack        4             264
RX Total        33            1812
TX Failed        0                0
TX Hello        19             724
TX DB des       12             456
TX LS req        2             104
TX LS upd        8             628
TX LS ack        6             296
TX Total        47            2208
OSPFv3 header errors
Length 0, Checksum 0, Version 0, No Virtual Link 0,
Area Mismatch 0, Self Originated 0, Duplicate ID 0,
Instance ID 0, Hello 0, MTU Mismatch 0,
Nbr Ignored 0, Authentication 0,
OSPFv3 LSA errors
Type 0, Length 0, Data 0, Checksum 0,

```

The network administrator can issue the **clear ipv6 ospf traffic** command to reset all counters and restart all statistics collections:

```
Router# clear ipv6 ospf traffic
```

## Additional References

The following sections provide references related to the OSPF Sham-Link MIB Support feature.

### Related Documents

Related Topic	Document Title
Configuring OSPF sham-links	OSPF Sham-Link Support for MPLS VPN
SNMP configuration	<i>Cisco IOS Network Management Configuration Guide.</i>
SNMP commands	<i>Cisco IOS Network Management Command Reference.</i>

### Standards

Standard	Title
None	--

**MIBs**

MIB	MIBs Link
<ul style="list-style-type: none"> <li>• CISCO-OSPF-MIB</li> <li>• CISCO-OSPF-TRAP-MIB</li> </ul>	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: <a href="http://www.cisco.com/go/mibs">http://www.cisco.com/go/mibs</a>

**RFCs**

RFC	Title
None	--

**Technical Assistance**

Description	Link
The Cisco Support website provides extensive online resources, including documentation and tools for troubleshooting and resolving technical issues with Cisco products and technologies. Access to most tools on the Cisco Support website requires a Cisco.com user ID and password. If you have a valid service contract but do not have a user ID or password, you can register on Cisco.com.	<a href="http://www.cisco.com/techsupport">http://www.cisco.com/techsupport</a>

## Feature Information for OSPF Enhanced Traffic Statistics

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.