



# Configuring Switchport Blocking

- [About Switchport Blocking, on page 1](#)
- [Configuring Switchport Blocking, on page 1](#)

## About Switchport Blocking

By default, the router floods packets with unknown destination MAC addresses to all ports. To prevent the forwarding of such traffic, you can configure a port to block unknown multicast or unicast packets.

Occasionally, unknown multicast or unicast traffic is flooded to a switch port because a MAC address has timed out or has not been learned by the switch. Security issues could arise if unknown multicast and unicast traffic is forwarded to a switch port. You can enable switchport blocking to guarantee that no multicast or unicast traffic is flooded to the port. The interface can be a physical interface or an EtherChannel group. When you block multicast or unicast traffic for a port channel, it is blocked on all ports in the port channel group.

## Configuring Switchport Blocking

Follow these steps to configure switchport blocking. Blocking of unicast or multicast traffic is not automatically enabled on a switch port.

### Procedure

	Command or Action	Purpose
<b>Step 1</b>	<b>configure terminal</b> <b>Example:</b> Router# <code>configure terminal</code>	Enter global configuration mode.
<b>Step 2</b>	<b>interface {interface-id   port-channel number}</b> <b>Example:</b> Router (config)# <code>interface gigabitethernet 0/1/1</code>	Enters interface configuration mode.
<b>Step 3</b>	<b>switchport mode access</b> <b>Example:</b>	Configures the interface as an access port.

	Command or Action	Purpose
	Router(config-if)# <b>switchport mode access</b>	
<b>Step 4</b>	<b>switchport access vlan <i>vlan-id</i></b> <b>Example:</b> Router(config-if)# <b>switchport access vlan 20</b>	Specifies the VLAN for which this access port will carry traffic.
<b>Step 5</b>	<b>[no] switchport block {multicast   unicast}</b> <b>Example:</b> Router(config-if)# <b>switchport block multicast</b> Router(config-if)# <b>switchport block unicast</b>	Prevents the flooding of unknown multicast or unicast packets on the specified interface.  Use the no form of this command to resume normal forwarding on the port.
<b>Step 6</b>	<b>end</b> <b>Example:</b> Router(config)# <b>end</b>	Returns to privileged EXEC mode.
<b>Step 7</b>	(Optional) <b>show interface {<i>interface-id</i>   port-channel <i>number</i>} switchport</b> <b>Example:</b> Router# <b>show interface gigabitEthernet 0/1/1 switchport</b>	(Optional) Displays the switchport blocking configuration.

### Example

The following example shows how to block multicast and unicast flooding on GigabitEthernet interface 0/1/1 and how to verify the configuration:

```
Router# configure terminal
Router(config)# interface GigabitEthernet0/1/1
Router(config-if)# switchport access vlan 20
Router(config-if)# switchport mode access
Router(config-if)# switchport block multicast
Router(config-if)# switchport block unicast
Router(config-if)# exit
Router(config)# end
Router#
```

Following command shows the blocking state of unknown unicast and multicast on the interface:

```
Router#show interfaces gigabitEthernet 0/1/1 switchport
Name: Gi0/1/1
Switchport: Enabled
Administrative Mode: static access
Operational Mode: static access
Administrative Trunking Encapsulation: dot1q
Operational Trunking Encapsulation: native
Negotiation of Trunking: Off
Access Mode VLAN: 20 (VLAN0020)
Trunking Native Mode VLAN: 1 (default)
Administrative Native VLAN tagging: disabled
Voice VLAN: none
```

```
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk Native VLAN tagging: enabled
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk associations: none
Administrative private-vlan trunk mappings: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled
Capture VLANs Allowed: ALL

Protected: false
Unknown unicast blocked: enabled
Unknown multicast blocked: enabled
Appliance trust: none
Router#
```

