



Release Notes for Cisco NCS 5000 Series Routers, IOS XR Release 7.3.4

[Network Convergence System 5000 Series Routers](#) 2

[Release 7.3.4 Package](#) 2

[What's New in Cisco IOS XR Release 7.3.4](#) 3

[Caveats](#) 3

[Supported Packages and System Requirements](#) 3

[Other Important Notes](#) 3

[Related Documentation](#) 4

Network Convergence System 5000 Series Routers



Note Explore the [Content Hub](#), the all new portal that offers an enhanced product documentation experience.

- Use faceted search to locate content that is most relevant to you.
- Create customized PDFs for ready reference.
- Benefit from context-based recommendations.

Get started with the Content Hub at content.cisco.com to craft a personalized documentation experience.

Do provide feedback about your experience with the Content Hub.

Release 7.3.4 Package

Table 1: Release 7.3.4 Packages for Cisco NCS 5000 Series Router

Composite Package		
Feature Set	Filename	Description
Cisco IOS XR IP Unicast Routing Core Bundle	ncs5k-mini-x.iso	Contains base image contents that includes: <ul style="list-style-type: none">• Host operating system• System Admin boot image• IOS XR boot image• Alarm co-relation
Individually-Installable Optional Packages		
Feature Set	Filename	Description
Cisco IOS XR Manageability Package	ncs5k-mgbl-3.0.0.0-r734.x86_64.rpm	XML, Parser, HTTP Server, Telemetry, and gRPC.
Cisco IOS XR MPLS Package	ncs5k-mpls-3.1.0.0-r734.x86_64.rpm	Label Distribution Protocol (LDP), MPLS forwarding , MPLS operations , Administration and maintenance (OAM), Layer3-vpn , layer-2 vpn.
Cisco IOS XR MPLS RSVP TE package	ncs5k-mpls-te-rsvp-1.1.0.0-r734.x86_64.rpm	Supports MPLS RSVP-TE (Resource Reservation Protocol with Traffic Engineering extensions)

Cisco IOS XR Security Package	ncs5k-k9sec-3.2.0.0-r734.x86_64.rpm	Support for Encryption, Decryption, and Secure Shell (SSH),
Cisco IOS XR Multicast Package	ncs5k-mcast-2.2.0.0-r734.x86_64.rpm	Multicast routing protocols (PIM, IGMP, Auto-rp, BSR) and infrastructure (Multicast routing information Base) , Multicast forwarding (mfw)
Cisco IOS XR ISIS package	ncs5k-isis-2.2.0.0-r734.x86_64.rpm	Supports ISIS
Cisco IOS XR OSPF package	ncs5k-ospf-2.0.0.0-r734.x86_64.rpm	Supports OSPF

What's New in Cisco IOS XR Release 7.3.4

Software Features Introduced and Enhanced

To learn about features introduced in other Cisco IOS XR releases, select the release from the [What's new](#) page.

No new features introduced in this release.

Caveats

No caveats are applicable in this release.

Supported Packages and System Requirements

Supported Hardware

For a complete list of supported optics, hardware and ordering information for NCS 5001 and NCS 5002 series router, see the [Cisco NCS 5000 Series Data Sheet](#)

For a complete list of supported optics, hardware and ordering information for NCS 5011 router, see the [Cisco NCS 5011 Series Data Sheet](#)

To install the Cisco NCS 5000 series routers, see [Hardware Installation Guide for Cisco NCS 5000 Series Routers](#).

Other Important Notes

Upgrading Cisco IOS XR Software

Cisco IOS XR Software is installed and activated from modular packages, allowing specific features or software patches to be installed, upgraded, or downgraded without affecting unrelated processes. Software packages can be upgraded or downgraded on all supported card types, or on a single card (node).

Before starting the software upgrade, use the **show install health** command in the admin mode. This command validates if the statuses of all relevant parameters of the system are ready for the software upgrade without interrupting the system.



Note If you use a TAR package to upgrade from a Cisco IOS XR release prior to 7.x, the output of the **show install health** command in admin mode displays the following error messages:

```
sysadmin-vm:0_RSP0# show install health
. . .
ERROR /install_repo/gl/xr -rw-r--r--. 1 8413 floppy 3230320 Mar 14 05:45 <platform>-isis-2.2.0.0-r702.x86_64
ERROR /install_repo/gl/xr -rwxr-x---. 1 8413 165 1485781 Mar 14 06:02 <platform>-k9sec-3.1.0.0-r702.x86_64
ERROR /install_repo/gl/xr -rw-r--r--. 1 8413 floppy 345144 Mar 14 05:45 <platform>-li-1.0.0.0-r702.x86_64
```

You can ignore these messages and proceed with the installation operation.

Production Software Maintenance Updates (SMUs)

A production SMU is a SMU that is formally requested, developed, tested, and released. Production SMUs are intended for use in a live network environment and are formally supported by the Cisco TAC and the relevant development teams. Software bugs identified through software recommendations or Bug Search Tools are not a basis for production SMU requests.

For information on production SMU types, refer the [Production SMU Types](#) section of the *IOS XR Software Maintenance Updates (SMUs)* guide.

Cisco IOS XR Error messages

To view, search, compare, and download Cisco IOS XR Error Messages, refer to the [Cisco IOS XR Error messages](#) tool.

Cisco IOS XR MIBs

To determine the MIBs supported by platform and release, refer to the [Cisco IOS XR MIBs](#) tool.

Related Documentation

The most current Cisco router documentation is located at the following URL:

<https://www.cisco.com/c/en/us/td/docs/iosxr/ncs-5000-series-routers.html>



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA 95134-1706
USA

Asia Pacific Headquarters
CiscoSystems(USA)Pte.Ltd.
Singapore

Europe Headquarters
CiscoSystemsInternationalBV
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.