



Configuring DMM over VPLS

Delay Measurement Message (DMM) is part of the ITU-T Y.1731 standard. It can be used to periodically measure Frame Delay and Frame Delay Variation between a pair of point to point MEPs. Measurements are made between two MEPs belonging to the same domain and MA.

- [Restrictions for DMM support over VPLS, on page 1](#)
- [Configuring DMM over VPLS, on page 1](#)
- [Configuration Example for DMM over VPLS, on page 2](#)

Restrictions for DMM support over VPLS

- With *SR_5_label_push* template, IP SLA DMM is not supported on RSP3 module.
- Only Up MEP(Maintenance End Point) on EVC(ethernet virtual circuit) BD(bridge domain) with VPLS towards the core is supported. Down MEP on VFI is not supported.
- To send unicast packets (LBR, LTM/R, Y1731 packets), port-emulation method is used. The access interface (the interface where Up MEP is configured) needs to be up to send unicast packets.

Configuring DMM over VPLS

SUMMARY STEPS

1. Configure CFM on PE Device.
2. Configure CFM over VPLS using **l2 vfi vfi-name manual evc** command or **l2vpn vfi context vfi-name** command.
3. Configure a Sender MEP.

DETAILED STEPS

	Command or Action	Purpose
Step 1	Configure CFM on PE Device.	For configuration details see, Configuring Ethernet Connectivity Fault Management in a Service Provider Network .

	Command or Action	Purpose
		In case of H-VPLS configuration, see, CFM Configuration over EFP Interface with Cross Connect Feature .
Step 2	Configure CFM over VPLS using l2 vfi vfi-name manual evc command or l2vpn vfi context vfi-name command.	The evc should be the EVC name used in the CFM on PE device configuration. For configuration details, see, Configuring the VFI in the PE .
Step 3	Configure a Sender MEP.	For configuration details see, <i>Configuring a Sender MEP for a Single-Ended Ethernet Delay or Delay Variation Operation</i> .

Configuration Example for DMM over VPLS

The following sample output shows the configuration of DMM over VPLS:

```

ethernet evc EVC_100
ethernet cfm global
ethernet cfm domain CFM-VPLS level 5
service ser1 evc EVC_100 vlan 100
continuity-check
continuity-check interval 1s
l2 vfi VPLS-CFM manual EVC_100
vpn id 100
bridge-domain 100
neighbor 2.2.2.2 encapsulation mpls
interface GigabitEthernet0/4/4
service instance 100 ethernet EVC_100
encapsulation dot1q 100
cfm mep domain CFM-VPLS mpid 1001
bridge-domain 100
ip sla 200
ethernet y1731 delay DMM domain CFM-VPLS evc EVC_100 mpid 1002 cos 7 source mpid 1001
ip sla schedule 200 start-time now

```

The following sample output shows the configuration of DMM over VPLS using the **l2vpn vfi context** command:

```

ethernet evc EVC_100
ethernet cfm global
ethernet cfm domain CFM-VPLS level 5
service ser1 evc EVC_100 vlan 100
continuity-check
continuity-check interval 1s
l2vpn vfi context VPLS-CFM
vpn id 100
evc EVC_100
neighbor 2.2.2.2 encapsulation mpls
interface GigabitEthernet0/4/4
service instance 100 ethernet EVC_100
encapsulation dot1q 100
cfm mep domain CFM-VPLS mpid 1001
bridge-domain 100
member GigabitEthernet0/4/4 service-instance 100
member vfi VPLS-CFM
ip sla 200
ethernet y1731 delay DMM domain CFM-VPLS evc EVC_100 mpid 1002 cos 7 source mpid 1001
ip sla schedule 200 start-time now

```



Note The EVC name is mandatory and should be the same as the one configured in CFM.

Configuration Verification Example for DMM over VPLS

The following sample output shows the configuration verification of DMM over VPLS:

```
Router#sh ip sla configuration
IP SLAs Infrastructure Engine-III
Entry number: 200
Owner:
Tag:
Operation timeout (milliseconds): 5000
Ethernet Y1731 Delay Operation
Frame Type: DMM
Domain: CFM_VPLS
Evc: EVC_100
Target Mpid: 1002
Source Mpid: 1001
CoS: 7
  Max Delay: 5000
  Request size (Padding portion): 64
  Frame Interval: 1000
  Clock: Not In Sync
Threshold (milliseconds): 5000
Schedule:
  Operation frequency (seconds): 900 (not considered if randomly scheduled)
  Next Scheduled Start Time: Start Time already passed
  Group Scheduled : FALSE
  Randomly Scheduled : FALSE
  Life (seconds): 3600
  Entry Ageout (seconds): never
  Recurring (Starting Everyday): FALSE
  Status of entry (SNMP RowStatus): Active
Statistics Parameters
  Frame offset: 1
  Distribution Delay Two-Way:
    Number of Bins 10
    Bin Boundaries: 5000,10000,15000,20000,25000,30000,35000,40000,45000,-1
  Distribution Delay-Variation Two-Way:
    Number of Bins 10
    Bin Boundaries: 5000,10000,15000,20000,25000,30000,35000,40000,45000,-1
  Aggregation Period: 900
History
  Number of intervals: 2

Router#
```

