



Small form-factor pluggables

Small Form-Factor Pluggables (SFPs) that are not Cisco certified are called third-party SFPs. Cisco approved means the SFPs have undergone rigorous testing with Cisco products and the SFPs are guaranteed to have 100% compatibility.



Note Cisco does not provide any kind of support for the third-party SFPs because they are not validated by Cisco.

- [Configuring third-party SFPs, on page 1](#)

Configuring third-party SFPs

Third-party SFPs are manufactured by companies that are not on the Cisco-approved Vendor List (AVL). Currently, Cisco 8100 Series Secure Routers support only Cisco-approved SFPs.

Procedure

	Command or Action	Purpose
Step 1	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 2	service unsupported-transceiver Example: Router(config)# service unsupported-transceiver	Enables third-party SFP support.
Step 3	interface type slot subslot port number Example: Router(config-if)# interface ethernet 0/3/0	Selects an interface to configure.
Step 4	media-type sfp Example: Router(config-if)#media-type sfp	Changes media type to SFP.

	Command or Action	Purpose
Step 5	speed <i>value</i> Example: Router# speed 100	Configures the speed of the interface. Note For 100BASE SFPs, configure the speed to 100 Mbps only. Similarly, for 1000BASE SFPs, configure the speed to 1000 Mbps only.
Step 6	shutdown Example: Router(config)# shutdown	Disables the interface, changing its state from administratively UP to administratively DOWN.
Step 7	no shutdown Example: Router(config-if)# no shutdown	Enables the interface, changing its state from administratively DOWN to administratively UP.
Step 8	exit Example: Router(config-if)# exit	Exits the configuration mode and returns the global configuration mode.

Examples

This example shows how to configure a third-party SFP on Cisco 8100 Series Secure Routers:

```

Router# configure terminal
Router(config)# interface ethernet 0/3/0
Router(config-if)# service unsupported-transceiver
Router(config)# interface ethernet 0/3/0
Router(config-if)# media-type sfp
Router(config-if)# speed 100
Router(config-if)# shutdown
Router(config-if)# no shutdown
Router(config-if)# exit
Router(config)# exit

```