



Run the System Setup Wizard

- [Run the System Setup Wizard, on page 1](#)
- [Check for Available Upgrades, on page 2](#)

Run the System Setup Wizard

Run the System Setup Wizard to configure basic settings and enable a set of system defaults. The System Setup Wizard starts automatically when you access the appliance through the web-based interface and displays the end user license agreement (also known as the EULA).

-
- Step 1** Accept the end user license agreement.
- Step 2** Enter information from the “[Document Network Settings](#)”.
- If you need additional information about the settings, choose **Help and Support** > **Online Help**.
- Step 3** Review the configuration summary page.
- Step 4** Click **Install this Configuration**.
- Step 5** The appliance may not appear to have accepted your configuration or be performing the installation. This is because you have changed the IP address, but the installation is underway.
- Step 6** If you temporarily changed the IP address of your computer as described above, change the IP address settings back to the original values.
- Step 7** Ensure that your computer and the appliance are connected to the network.
- Step 8** Log in to the appliance again, at the hostname or IP address that you noted in the “[Plan the Installation](#)”. Use the username **admin** and the new password that you entered in the wizard.
- The Cisco Web Security Appliance uses a self-signed certificate that may trigger a warning from your web browser. Accept the certificate and ignore this warning.
- Step 9** Be sure to keep your new administrator password in a safe place.
-

Check for Available Upgrades

After logging in to the appliance, look at the top of the web browser window for an upgrade notification (or for a notice in the CLI.) If an upgrade is available, evaluate whether you should install it.

Details about each release are available in the release notes for that Async OS version.