



Managing the WiFi Engage Configurations

This chapter describes how to manage the MSE, groups, buildings, floors, zones, and access points of the WiFi Engage. This chapter also explains how to manage the apps and BLE beacons.

- [Managing the Customer Name, page 9-1](#)
- [Managing the MSE Accounts, page 9-2](#)
- [Managing the Campuses, page 9-4](#)
- [Managing the Buildings, page 9-6](#)
- [Managing the Floors, page 9-8](#)
- [Managing the Groups, page 9-10](#)
- [Managing the Zones, page 9-13](#)
- [Managing the Access Points, page 9-15](#)
- [Managing the Captive Portal Rules, page 9-16](#)
- [Managing the Engagement Rules, page 9-18](#)
- [Managing the Profile Rules, page 9-19](#)
- [Managing the Apps, page 9-22](#)
- [Managing the Social Networking Apps, page 9-23](#)
- [Managing the BLE Beacons, page 9-25](#)

Managing the Customer Name

The WiFi Engage enables you to rename the default Customer name.

- [Renaming the Customer Name, page 9-1](#)

Renaming the Customer Name

To rename the customer name, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, click **Manage Locations**.
 - Step 2** In the Locations page, click the drop-down menu icon at the far right of the customer name.
 - Step 3** Click **Rename**.

Send documentation comments to emsp-docfeedback@cisco.com

- Step 4** In the Rename - Root window that appears, enter the customer name you want.
- Step 5** Click **Rename**.
-

Managing the MSE Accounts

The WiFi Engage enables you to view the MSE map and the users who have access rights to the MSE. Also, you can rename the MSE name, delete an independent MSE, and edit the MSE details.

- [Renaming a MSE, page 9-2](#)
- [Editing a MSE, page 9-2](#)
- [Deleting a MSE, page 9-3](#)
- [Viewing the Maps for a MSE, page 9-3](#)
- [Managing the Users in a MSE, page 9-3](#)

Renaming a MSE

To rename a MSE, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the MSE that you want to rename.
- Step 3** Click **Rename mse**.
- Step 4** In the Rename - MSE window that appears, enter the new name for the MSE.
- Step 5** Click **Rename**.
-

Editing a MSE

You can edit the MSE connection credentials.

To edit a MSE, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the MSE that you want to edit.
- Step 3** Click **Edit MSE**.
- Step 4** In the Add MSE window that appears, select the location elements that you want to be part of the MSE.
- Step 5** Click **Edit**.
-

Send documentation comments to emsp-docfeedback@cisco.com

Deleting a MSE

To delete a MSE, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the MSE that you want to delete.
- Step 3** Click **Delete MSE**.
-

**Note**

The Delete location option is available for a MSE only if there is no location element under that MSE. That is, to delete a MSE, first you have to delete the location elements and sub groups under that MSE, if any.

**Note**

You cannot delete an MSE that is associated with the experience zones or proximity rules.

Viewing the Maps for a MSE

To view the map for a MSE, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the MSE for which you want to view the map.
The map appears in the Maps tab.
-

**Note**

The map appears for a MSE only if it has at least one location under that MSE. The maps are displayed from the MSE.

Managing the Users in a MSE

When creating users, you can provide access to an entire MSE. You can search for those users under that MSE.

Searching for a User in a MSE

To search for a user in a MSE, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
-

Send documentation comments to emsp-docfeedback@cisco.com

The Locations page appears with the location hierarchy.

Step 2 In the location hierarchy, click the **Users** icon for that MSE.

Step 3 On the Users and Permission tab, enter the name of the user whom you want to search in the Search text field.

The user gets listed in the window.

Managing the Campuses

The WiFi Engage enables you to view the campus map and the users who have access rights to the campus. Also, you can rename the campus name, and delete an independent campus.

- [Renaming a Campus, page 9-4](#)
- [Deleting a Campus, page 9-4](#)
- [Viewing the Maps for a Campus, page 9-5](#)
- [Managing the Users in a Campus, page 9-5](#)

Renaming a Campus

To rename a campus, perform the following steps

Step 1 In the WiFi Engage dashboard, choose **Manage Locations**.

The Locations page appears with the location hierarchy.

Step 2 In the location hierarchy, click the drop-down menu icon for the campus that you want to rename.

Step 3 Click **Rename campus**.

Step 4 In the Rename- campus window that appears, enter the new name for the campus.

Step 5 Click **Rename**.

Deleting a Campus

To delete a campus, perform the following steps:

Step 1 In the WiFi Engage dashboard, choose **Manage Locations**.

The Locations page appears with the location hierarchy.

Step 2 In the location hierarchy, click the drop-down menu icon for the campus that you want to delete.

Step 3 Click **Delete campus**.

Send documentation comments to emsp-docfeedback@cisco.com



Note

The Delete campus option is available for a campus only if there is no building under that campus. That is, to delete a campus, first you have to delete the location elements under that campus, if any.



Note

You cannot delete a campus that is associated with the experience zones or proximity rules.

Viewing the Maps for a Campus

To view the maps for a campus, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the campus for which you want to view the map.
The map appears in the Maps tab.
-



Note

The map configured in the MSE for the campus is shown.

Managing the Users in a Campus

When creating users, you can restrict their access only to a particular campus. You can search for those users under that campus.

Searching for a User in a Campus

To search for a user in a campus, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the **Users** icon for that campus.
- Step 3** On the Users and Permission tab, in the Search text field, enter the name of the user whom you want to search.
The user gets listed in the window.
-

Send documentation comments to emsp-docfeedback@cisco.com

Managing the Buildings

The WiFi Engage enables you to view the Building map and the users who have access rights to the building. Also, you can rename the building name, and delete an independent building.

- [Renaming a Building, page 9-6](#)
- [Deleting a Building, page 9-6](#)
- [Viewing the Maps for a Building, page 9-7](#)
- [Managing the Users in a Building, page 9-7](#)

Renaming a Building

To rename a building, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the building that you want to rename.
- Step 3** Click **Rename network**.
- Step 4** In the Rename - network window that appears, enter the new name for the building.
- Step 5** Click **Rename**.
-

Deleting a Building

To delete a building, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the building that you want to delete.
- Step 3** Click **Delete building**.
-



Note

The Delete building option is available for a building only if there is no floor or zones with access points under that building. That is, to delete a building, first you have to delete the floor or zones under that building, if any.



Note

You cannot delete a location that is associated with an experience zone or proximity rule.

Send documentation comments to emsp-docfeedback@cisco.com

Viewing the Maps for a Building

To view the maps for a building, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the building for which you want to view the map.
The map appears in the Maps tab.
-



Note

The map configured in the MSE for that the particular building is shown.

Managing the Users in a Building

When creating users, you can restrict their access only to a particular building. You can search for those users under that building.

Searching for a User in a Building

To search for a user in a building, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the **Users** icon for that building.
- Step 3** On the Users and Permission tab, in the Search text field, enter the name of the user whom you want to search.
The user gets listed in the window.
-

Send documentation comments to emsp-docfeedback@cisco.com

Managing the Floors

The WiFi Engage enables you to view the floor map and manage the users who have access rights to the floor. Also, you can rename the floor name, and delete an independent floor.

- [Renaming a Floor, page 9-8](#)
- [Deleting a Floor, page 9-8](#)
- [Viewing the Maps for a Floor, page 9-9](#)
- [Managing the Users in a Floor, page 9-10](#)

Renaming a Floor

To rename a floor, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the floor that you want to rename.
- Step 3** Click **Rename floor**.
- Step 4** In the Rename -floor window that appears, enter the new name for the floor.
- Step 5** Click **Rename**.
-

Deleting a Floor

To delete a floor, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the floor that you want to delete.
- Step 3** Click **Delete floor**.
-



Note

If the floor that you delete has any zone under it, that zone is moved under the building after the deletion of the floor.



Note

You cannot delete a floor that is associated with an experience zone or proximity rule.

Send documentation comments to emsp-docfeedback@cisco.com

Managing the Maps for a Floor

The maps are displayed by default based on the map configuration in the CUWN. The WiFi Engage enables you to display the Micello map for the floors. Also, you can upload external maps for the floors.

- [Viewing the Maps for a Floor, page 9-9](#)
- [Configuring a Micello Map, page 9-9](#)
- [Uploading an External Map, page 9-10](#)

Viewing the Maps for a Floor

To view the map for a floor, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the floor for which you want to view the map.
The map appears in the Maps tab.
-

Configuring a Micello Map

To configure the Micello map, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the floor or zone for which you want to configure the Micello map.
- Step 3** Click the **Micello** tab.
- Step 4** In the Map Name text field, enter a name for the map.
- Step 5** In the Enter Micello details area, choose whether you want to configure the Map ID or Map URL to display the Micello map.
- Step 6** In the following text field, enter the Map ID or Map URL for the Micello map based on the previous selection.
- Step 7** In the API Key text field, enter the API key for the Micello map.
- Step 8** Click **Save**.
The maps gets loaded from the Micello and appears in the page.
-



Note

To configure a Micello map, you must have a Micello account. For a Micello account, contact support@micello.com.

Send documentation comments to emsp-docfeedback@cisco.com

Uploading an External Map

The WiFi Engage enables you to configure external maps of your choice for a floor or zone.

To configure an external map, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
 - Step 2** In the location hierarchy, click the Maps icon for the floor or zone for which you want to configure the external map.
 - Step 3** Click the **Image** tab.
 - Step 4** In the Map Name text field, enter a name for the map.
 - Step 5** Click the **Browse** button and upload the image file for the map.
 - Step 6** Click **Save**.
-



Note

You can upload the map image file in png, jpeg, and gif formats.

Managing the Users in a Floor

When creating users, you can restrict their access only to a particular floor. You can search for those users under that floor.

Searching for a User for a Floor

To search for a user for a floor, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
 - Step 2** In the location hierarchy, click the **Users** icon for the floor of which you want to find the user.
 - Step 3** On the Users and Permission tab, in the Search text field, enter the name of the user whom you want to search.
The user gets listed in the window.
-

Managing the Groups

The WiFi Engage enables you to view the group map and view the users who have access rights to the group. Also, you can rename the group name, and delete an independent group.

- [Renaming a Group, page 9-11](#)
- [Editing a Group, page 9-11](#)

Send documentation comments to emsp-docfeedback@cisco.com

- [Deleting a Group](#), page 9-11
- [Viewing the Maps for a Group](#), page 9-12
- [Managing the Users in a Group](#), page 9-13

Renaming a Group

To rename a group, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the group that you want to rename.
- Step 3** Click **Rename group**.
- Step 4** In the Rename - group window that appears, enter the new name for the group.
- Step 5** Click **Rename**.
-

Editing a Group

You can add or remove the location elements from a group.

To edit a group, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the group that you want to edit.
- Step 3** Click **Edit group**.
- Step 4** In the Edit Group window that appears, select the location elements that you want to be part of the group.
- Step 5** Click **Update**.
-

Deleting a Group

To delete a group, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the group that you want to delete.
- Step 3** Click **Delete group**.
-

Send documentation comments to emsp-docfeedback@cisco.com

**Note**

The Delete group option is available for a group only if there is no location element or sub group under that group. That is, to delete a group, first you have to delete the location elements and sub groups under that group, if any.

**Note**

You cannot delete a group that is associated with the experience zones or proximity rules.

Viewing the Maps for a Group

To view the map for a group, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the group for which you want to view the map.
The map appears in the Maps tab.
-

**Note**

The map appears for a group only if it has at least one location under that group. The maps are displayed from the MSE.

Send documentation comments to emsp-docfeedback@cisco.com

Managing the Users in a Group

When creating users, you can restrict their access only to a particular group. You can search for those users under that group

Searching for a User in a Group

To search for a user in a group, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the **Users** icon for that group.
- Step 3** On the Users and Permission tab, enter the name of the user whom you want to search in the Search text field.
The user gets listed in the window.
-

Managing the Zones

The WiFi Engage enables you to view the zones map and the users who have access rights to the zones. Also, you can rename the zone name, and delete a zone.

- [Renaming a Zone, page 9-13](#)
- [Deleting a Zone, page 9-14](#)
- [Viewing the Maps for a Zone, page 9-14](#)
- [Managing the Users in a Zone, page 9-14](#)

Renaming a Zone

To rename a zone, perform the following steps

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the zone that you want to rename.
- Step 3** Click **Rename zone**.
- Step 4** In the Rename- zone window that appears, enter the new name for the zone.
- Step 5** Click **Rename**.
-

Send documentation comments to emsp-docfeedback@cisco.com

Deleting a Zone

To delete a zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the drop-down menu icon for the zone that you want to delete.
- Step 3** Click **Delete zone**.
-



Note

You cannot delete any zone that is associated with the experience zones or proximity rules.

Viewing the Maps for a Zone

The maps are displayed by default based on the map configuration in the MSE. The WiFi Engage enables you to display the Micello map for the zones. Also, you can upload external maps for the zones.

- [Configuring a Micello Map, page 9-9](#)
- [Uploading an External Map, page 9-10](#)

To view the map for a zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the Maps icon for the zone for which you want to view the map.
The map appears in the Maps tab.
-

Managing the Users in a Zone

When creating users, you can restrict their access only to a particular zone. You can search for those users under that zone.

Searching for a User in a Zone

To search for a user in a zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the **Users** icon for that zone.
- Step 3** On the Users and Permission tab, in the Search text field, enter the name of the user whom you want to search.

Send documentation comments to emsp-docfeedback@cisco.com

The user gets listed in the window.

Managing the Access Points

You can add or remove access points to a zone.

- [Adding an Access Point to a Zone, page 9-15](#)
- [Removing an Access Point from a Zone, page 9-15](#)

Adding an Access Point to a Zone

To add access points to a zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the zone to which you want to add the access point.
- Step 3** Click **Modify Access Points**.
- Step 4** Select the check box for the access point that you want to add.
- Step 5** Click **Modify Access Points**.
The access point gets added to the zone.
-



Note If there are no access points under that zone, the button name will be **Add Access Points**.

Removing an Access Point from a Zone

To remove an access point from a zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the zone from which you want to delete the access point.
- Step 3** Click **Modify Access Points**.
- Step 4** Unselect the check box for the access point that you want to delete.
- Step 5** Click **Modify Access Points**.
The access point gets deleted from the zone.
-

[Send documentation comments to emsp-docfeedback@cisco.com](mailto:emsp-docfeedback@cisco.com)

Managing the Captive Portal Rules

You can pause a captive portal rule, and make it live again, whenever required. You can modify a captive portal rule, and delete it if required. You can create captive portal rules specific to a location element, and view them from the location hierarchy.

- [Pausing a Captive Portal Rule, page 9-16](#)
- [Restarting a Captive Portal Rule, page 9-16](#)
- [Modifying a Captive Portal Rule, page 9-17](#)
- [Deleting a Captive Portal Rule, page 9-17](#)
- [Viewing a Captive Portal Rule for a Location Element, page 9-17](#)

Pausing a Captive Portal Rule

To pause a captive portal rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Captive Portal Rule**.
The captive portal rules created get listed.
- Step 2** Click the **Pause** icon that appears for the captive portal rule that you want to pause.
The captive portal rule is paused.
-



Note

To pause multiple captive portal rules, select the check box for the captive portal rules that you want to pause, and click the Pause button that appears at the top left of the page.

Restarting a Captive Portal Rule

To restart a captive portal rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Captive Portal Rule**.
The captive portal rules created get listed.
- Step 2** Click the **Make Live** icon that appears for the captive portal rule that you want to restart.
The captive portal rule is restarted.
-



Note

To restart multiple captive portal rules, select the check box for the captive portal rules that you want to restart, and click the Make Live button that appears at the top left of the page.

Send documentation comments to emsp-docfeedback@cisco.com

Modifying a Captive Portal Rule

To modify a captive portal rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Captive Portal Rule**.
The captive portal rules created get listed.
 - Step 2** Click the captive portal rule that you want to modify.
 - Step 3** Make necessary changes.
 - Step 4** Click **Save and Resume**.
The captive portal rule gets published with the changes.
-

Deleting a Captive Portal Rule

To delete a captive portal rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Captive Portal Rule**.
The captive portal rules created get listed.
 - Step 2** Click the **Delete** icon that appears for the captive portal rule that you want to delete.
-

**Note**

To delete multiple captive portal rules, select the check box for the captive portal rules that you want to delete, and click the Delete button that appears at the top left of the page.

Viewing a Captive Portal Rule for a Location Element

To view a captive portal rule for a location element such as group, building, floor, and so on, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
 - Step 2** Click the **Proximity Rules** icon for the location element for which you want to view the captive portal rule.
 - Step 3** Click the **Captive Portal Rule** tab.
The captive portal rules for the location element gets listed.
-

[Send documentation comments to emsp-docfeedback@cisco.com](mailto:emsp-docfeedback@cisco.com)

Managing the Engagement Rules

- [Pausing an Engagement Rule, page 9-18](#)
- [Restarting an Engagement Rule, page 9-18](#)
- [Modifying an Engagement Rule, page 9-18](#)
- [Deleting an Engagement Rule, page 9-19](#)
- [Viewing an Engagement Rule for a Location Element, page 9-19](#)

Pausing an Engagement Rule

To pause an engagement rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Engagement Rule**.
The engagement rules created get listed.
- Step 2** Click the **Pause** icon that appears for the engagement rule that you want to pause.
The engagement rule is paused.
-



Note To pause multiple engagement rules, select the check box for the engagement rules that you want to pause, and click the Pause button that appears at the top left of the page.

Restarting an Engagement Rule

To restart an engagement rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Engagement Rule**.
The engagement rules created get listed.
- Step 2** Click the **Make Live** icon that appears for the engagement rule that you want to restart.
The engagement rule is restarted.
-



Note To restart multiple engagement rules, select the check box for the engagement rules that you want to restart, and click the Make Live button that appears at the top left of the page.

Modifying an Engagement Rule

To modify an engagement rule, perform the following steps:

Send documentation comments to emsp-docfeedback@cisco.com

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Engagement Rule**.
The engagement rules created get listed.
- Step 2** Click the engagement rule that you want to modify.
- Step 3** Make necessary changes.
- Step 4** Click **Save and Resume**.
The engagement rule gets published with the changes.
-

Deleting an Engagement Rule

To delete an engagement rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Engagement Rule**.
The engagement rules created get listed.
- Step 2** Click the **Delete** icon that appears for the engagement rule that you want to delete.
-

**Note**

To delete multiple engagement rules, select the check box for the engagement rules that you want to delete, and click the Delete button that appears at the top left of the page.

Viewing an Engagement Rule for a Location Element

To view an engagement rule for a location element such as group, building, floor, and so on, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** Click the **Proximity Rules** icon for the location element for which you want to view the engagement rule.
- Step 3** Click the **Engagement Rule** tab.
The engagement rules for the location element gets listed.
-

Managing the Profile Rules

You can pause a profile rule, and make it live again, whenever required. You can modify a profile rule, and delete it if required. You can create profile rules specific to a location element, and view them from the location hierarchy.

Send documentation comments to emsp-docfeedback@cisco.com

- [Pausing an Profile Rule, page 9-20](#)
- [Restarting a Profile Rule, page 9-20](#)
- [Modifying a Profile Rule, page 9-20](#)
- [Deleting a Profile Rule, page 9-21](#)
- [Viewing a Profile Rule for a Location Element, page 9-21](#)

Pausing an Profile Rule

To pause a profile rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Profile Rule**.
The profile rules created get listed.
- Step 2** Click the **Pause** icon that appears for the profile rule that you want to pause.
The profile rule is paused.
-



Note

To pause multiple profile rules, select the check box for the profile rules that you want to pause, and click the Pause button that appears at the top left of the page.

Restarting a Profile Rule

To restart a profile rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Profile Rule**.
The profile rules created get listed.
- Step 2** Click the **Make Live** icon that appears for the profile rule that you want to restart.
The profile rule is restarted.
-



Note

To restart multiple profile rules, select the check box for the profile rules that you want to restart, and click the Make Live button that appears at the top left of the page.

Modifying a Profile Rule

To modify a profile rule, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Profile Rule**.
The profile rules created get listed.

Send documentation comments to emsp-docfeedback@cisco.com

- Step 2** Click the profile rule that you want to modify.
 - Step 3** Make necessary changes.
 - Step 4** Click **Save and Resume**.
The profile rule gets published with the changes.
-

Deleting a Profile Rule

To delete a profile rule, perform the following steps:

- Step 1** In the WiFi Engage dashboard, choose **Proximity Rules > Profile Rule**.
The profile rules created get listed.
 - Step 2** Click the **Delete** icon that appears for the profile rule that you want to delete.
-



Note

To delete multiple profile rules, select the check box for the profile rules that you want to delete, and click the Delete button that appears at the top left of the page.

Viewing a Profile Rule for a Location Element

To view an profile rule for a location element such as group, building, floor, and so on, perform the following steps:

- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
 - Step 2** Click the **Proximity Rules** icon for the location element for which you want to view the profile rule.
 - Step 3** Click the **Profile Rule** tab.
The profile rules for the location element gets listed.
-

Send documentation comments to emsp-docfeedback@cisco.com

Managing the Apps

You can rename, modify, or delete the apps that are configured to send the push notifications.

Renaming an App

To rename an app, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose the Tools icon in the left pane.
 - Step 2** Click the **Notification Channels** tab.
The Apps window appears with the details of all the configured apps.
 - Step 3** Click the drop-down menu icon for the app that you want to rename.
 - Step 4** Click **Rename**.
 - Step 5** In the app name field that is enabled for editing, enter the new name for the app.
 - Step 6** Click **Rename**.
-

Modifying an App

To modify an app, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose the Tools icon in the left pane.
 - Step 2** Click the **Notification Channels** tab.
The Apps window appears with the list of all the configured apps.
 - Step 3** Click the name of the app that you want to modify.
The details of the app is shown.
 - Step 4** Make necessary changes to the app.
 - Step 5** Click **Save**.
-

Deleting an App

To delete an app, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose the Tools icon in the left pane.
 - Step 2** Click the **Notification Channels** tab.
The Apps window appears with the details of all the configured apps.
 - Step 3** Click the drop-down menu icon for the app that you want to delete.
 - Step 4** Click **Delete**.

Send documentation comments to emsp-docfeedback@cisco.com

The app gets deleted.



Note

The Delete option appears for an app only if it is not associated with any proximity rule.

Managing the Social Networking Apps

You can modify the details of the social networking apps configured for the social authentication. The WiFi Engage enables you to configure the apps of Facebook, Google, Twitter, and Linked In.

- [Modifying the Facebook App, page 9-23](#)
- [Modifying the Google App, page 9-23](#)
- [Modifying the Twitter App, page 9-24](#)
- [Modifying the LinkedIn App, page 9-24](#)

Modifying the Facebook App

To modify the Facebook app, perform the following steps:

- Step 1** In the WiFi Engage dashboard, choose the **Tools** icon in the left pane.
- Step 2** Click the **Social Apps** tab.
- Step 3** Click the **Edit** button for the Facebook app.
- Step 4** Make necessary changes.



Note

You cannot edit the name of the app.

- Step 5** Click **Save**.
-



Note

The Edit button is available only if you have added a Facebook app.

Modifying the Google App

To modify the Google app, perform the following steps:

- Step 1** In the WiFi Engage dashboard, choose the **Tools** icon in the left pane.
- Step 2** Click the **Social Apps** tab.
- Step 3** Click the **Edit** button for the Google app.
- Step 4** Make necessary changes.

Send documentation comments to emsp-docfeedback@cisco.com



Note You cannot edit the name of the app.

Step 5 Click **Save**.



Note The Edit button is available only if you have added a Google app.

Modifying the Twitter App

To modify the Twitter app, perform the following steps:

Step 1 In the WiFi Engage dashboard, choose the **Tools** icon in the left pane.

Step 2 Click the **Social Apps** tab.

Step 3 Click the **Edit** button for the Twitter app.

Step 4 Make necessary changes.



Note You cannot edit the name of the app.

Step 5 Click **Save**.



Note The Edit button is available only if you have added a Twitter app.

Modifying the LinkedIn App

To modify the LinkedIn app, perform the following steps:

Step 1 In the WiFi Engage dashboard, choose the **Tools** icon in the left pane.

Step 2 Click the **Social Apps** tab.

Step 3 Click the **Edit** button for the LinkedIn App.

Step 4 Make necessary changes.



Note You cannot edit the name of the app.

Step 5 Click **Save**.

Send documentation comments to emsp-docfeedback@cisco.com



Note

The Edit button is available only if you have added a LinkedIn app.

Managing the BLE Beacons

You can delete a BLE UUID, and modify or delete a BLE Beacon added to a building, floor, or zone.

- [Deleting a Beacon UUID, page 9-25](#)
- [Modifying a BLE Beacon, page 9-25](#)
- [Deleting a BLE Beacon, page 9-26](#)

Deleting a Beacon UUID

To delete a beacon UUID, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, click the Tools icon in the left pane.
- Step 2** Click the **BLE UUIDs** tab.
- Step 3** Click **Delete** corresponding to the BLE UUID that you want to delete.
The BLE UUID gets deleted.
-



Note

You cannot delete a UUID that is associated with any BLE Beacon. That is, to delete a UUID, first you must delete all the BLE Beacons associated with that UUID.

Modifying a BLE Beacon

You can assign a BLE beacon to an entire building, floor, or zone.

To modify a BLE beacon in a building, floor, or zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the BleBeacons icon for the building, floor, or zone of which you want to modify the BLE Beacon.
The BLE Beacons page appears with the list of all BLE Beacons added to that building, floor, or zone.
- Step 3** Click the BLE Beacon that you want to modify.
The Edit BLE Beacon window appears.
- Step 4** Make the necessary changes to the BLE Beacon.
- Step 5** Click **Save**.
-

Send documentation comments to emsp-docfeedback@cisco.com

Deleting a BLE Beacon

To delete a BLE Beacon from a building, floor, or zone, perform the following steps:

-
- Step 1** In the WiFi Engage dashboard, choose **Manage Locations**.
The Locations page appears with the location hierarchy.
- Step 2** In the location hierarchy, click the BLEBeacons icon for or the building, floor, or zone from which you want to delete the BLE Beacon.
- Step 3** Click the **BLE Beacons** tab.
The BLE Beacons page appears with a list of all the BLE Beacons added to that building, floor, or zone.
- Step 4** Click the **Delete** button corresponding to the BLE Beacon that you want to delete.
The BLE Beacon gets deleted successfully.
-