



K Commands

- [key-server-priority](#), on page 2
- [key](#), on page 3

key-server-priority

key-server-priority <NUMBER>

Description: Configure the key server priority

Syntax:

<0-255>	priority. Number range from=0 to=255
---------	--------------------------------------

Command Mode: template macsec access|fabric security-policy : Configure MAC security policy parameters

Command Path:

```
# configure [['terminal', 't']]
(config)# template macsec access|fabric security-policy <WORD>
(config-macsec-param)# key-server-priority <NUMBER>
```

key

key

Description: LDAP server key for authentication

Command Mode: ldap-server host : LDAP server DNS name or IP address

Command Path:

```
# configure [['terminal', 't']]
(config)# ldap-server host <A.B.C.D|A:B::C:D|WORD>
(config-host)# key
```

key

Description: RADIUS server key for authentication

Command Mode: radius-server host : RADIUS server's DNS name or its IP address

Command Path:

```
# configure [['terminal', 't']]
(config)# radius-server host <A.B.C.D|A:B::C:D|WORD>
(config-host)# key
```

key

Description: RSA server key for authentication

Command Mode: rsa-server host : RSA server's DNS name or its IP address

Command Path:

```
# configure [['terminal', 't']]
(config)# rsa-server host <A.B.C.D|A:B::C:D|WORD>
(config-host)# key
```

key

Description: TACACS server key for authentication

Command Mode: tacacs-server host : TACACS+ server's DNS name or its IP address

Command Path:

```
# configure [['terminal', 't']]
(config)# tacacs-server host <A.B.C.D|A:B::C:D|WORD>
(config-host)# key
```

key

Description: TACACS remote destination server key for authentication

Command Mode: remote-dest : TACACS Accounting remote destination's DNS name or its IP address

Command Path:

```
# configure [['terminal', 't']]
(config)# tacacslog-group <WORD>
(config-tacacslog-group)# remote-dest <A.B.C.D|A:B::C:D|WORD> port <port>
(config-remote-dest)# key
```

key <WORD>

Description: Configure CKN as hex string of max 64 characters

Syntax:

<i>WORD</i>	CKN as hex string (Max Size 64)
-------------	---------------------------------

Command Mode: template macsec access|fabric keychain : Configure macsec key chain

Command Path:

```
# configure [['terminal', 't']]
(config)# template macsec access|fabric keychain <WORD>
(config-macsec-keychain)# key <WORD>
```