



## K Commands

---

- [key-policy](#), on page 2
- [key-server-priority](#), on page 3
- [key](#), on page 4
- [keychain-policy](#), on page 6

# key-policy

**key-policy <NUMBER>**

**Description:** Configuration for Key Policy

**Syntax:**

<0-65535>	Id of the Key Policy. Number range from=0 to=65535
-----------	--

**Command Mode:** keychain-policy : Configuration for Keychain Policy

**Command Path:**

```
# configure [['terminal', 't']]  
(config)# tenant <WORD>  
(config-tenant)# keychain-policy <WORD>  
(config-tenant-keychainpolicy)# key-policy <NUMBER>
```

# key-server-priority

**key-server-priority <NUMBER>**

**Description:** Configure the key server priority

**Syntax:**

<0-255>	priority. Number range from=0 to=255
---------	--------------------------------------

**Command Mode:** template macsec access|fabric security-policy : Configure MAC security policy parameters

**Command Path:**

```
# configure [['terminal', 't']]  
(config)# template macsec access|fabric security-policy <WORD>  
(config-macsec-param)# key-server-priority <NUMBER>
```

# key

## key

**Description:** LDAP server key for authentication

**Command Mode:** ldap-server host : LDAP server DNS name or IP address

**Command Path:**

```
# configure [['terminal', 't']]
(config) # ldap-server host <A.B.C.D|A:B::C:D|WORD>
(config-host) # key
```

## key

**Description:** RADIUS server key for authentication

**Command Mode:** radius-server host : RADIUS server's DNS name or its IP address

**Command Path:**

```
# configure [['terminal', 't']]
(config) # radius-server host <A.B.C.D|A:B::C:D|WORD>
(config-host) # key
```

## key

**Description:** RSA server key for authentication

**Command Mode:** rsa-server host : RSA server's DNS name or its IP address

**Command Path:**

```
# configure [['terminal', 't']]
(config) # rsa-server host <A.B.C.D|A:B::C:D|WORD>
(config-host) # key
```

## key

**Description:** TACACS server key for authentication

**Command Mode:** tacacs-server host : TACACS+ server's DNS name or its IP address

**Command Path:**

```
# configure [['terminal', 't']]
(config) # tacacs-server host <A.B.C.D|A:B::C:D|WORD>
(config-host) # key
```

**key**

**Description:** TACACS remote destination server key for authentication

**Command Mode:** remote-dest : TACACS Accounting remote destination's DNS name or its IP address

**Command Path:**

```
# configure [['terminal', 't']]
(config)# tacacslog-group <WORD>
(config-tacacslog-group)# remote-dest <A.B.C.D|A:B::C:D|WORD> port <port>
(config-remote-dest)# key
```

**key <WORD>**

**Description:** Configure CKN as hex string of max 64 characters

**Syntax:**

<i>WORD</i>	CKN as hex string (Max Size 64)
-------------	---------------------------------

**Command Mode:** template macsec access|fabric keychain : Configure macsec key chain

**Command Path:**

```
# configure [['terminal', 't']]
(config)# template macsec access|fabric keychain <WORD>
(config-macsec-keychain)# key <WORD>
```

# keychain-policy

**keychain-policy <WORD>**

**Description:** Configuration for Keychain Policy

**Syntax:**

<i>WORD</i>	Name of the KeyChain Policy (Max Size 64)
-------------	---

**Command Mode:** tenant : Tenant configuration mode

**Command Path:**

```
# configure [['terminal', 't']]  
(config)# tenant <WORD>  
(config-tenant)# keychain-policy <WORD>
```