



X Commands

This chapter describes the Cisco Nexus 1000V commands that begin with the letter X.

xml server max-session

To set the number of allowed XML server sessions, use the **xml server max-session** command.

xml server max-session *sessions*

Syntax Description	<i>sessions</i>	Maximum number of XML sessions permitted at one time. The range is 1–8.
---------------------------	-----------------	-------------------------------------------------------------------------

Defaults	The default maximum number of sessions is eight.
-----------------	--------------------------------------------------

Command Modes	Global configuration (config)
----------------------	-------------------------------

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples	This example shows how to set the number of allowed XML server sessions to 6:
-----------------	-------------------------------------------------------------------------------

```
n1000v# config t
n1000v# xml server max-session 6
n1000v#
```

Related Commands	Command	Description
	show xml server status	Displays information about XML server settings and any active XML server sessions.
	xml server terminate session	Displays information about XML server settings and any active XML server sessions.
	xml server timeout	Sets the number of seconds after which an inactive XML server session is terminated.

xml server terminate session

To terminate the specified XML server session, use the **xml server terminate session** command.

xml server terminate session *session-number*

Syntax Description	<i>session-number</i> Identifier for an existing XML server session. The range is 0–214748364.
---------------------------	------------------------------------------------------------------------------------------------

Defaults	None
-----------------	------

Command Modes	Any
----------------------	-----

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples	This example shows how to terminate the XML server session 8665:
-----------------	------------------------------------------------------------------

```
n1000v# xml server terminate 8665
n1000v#
```

Related Commands	Command	Description
	show xml server status	Displays information about XML server settings and any active XML server sessions.
xml server max-session	Sets the number of allowed XML server sessions.	
xml server timeout	Sets the number of seconds after which an inactive XML server session is terminated.	

xml server timeout

To set the number of seconds after which an inactive XML server session is terminated, use the **xml server timeout** command.

xml server timeout *seconds*

Syntax Description	<i>seconds</i>	Maximum time that the XML server can remain inactive before session termination. The range is 0–1200 seconds.
---------------------------	----------------	---------------------------------------------------------------------------------------------------------------

Defaults	None	
-----------------	------	--

Command Modes	Global configuration (config)	
----------------------	-------------------------------	--

SupportedUserRoles	network-admin	
---------------------------	---------------	--

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples	<p>This example shows how to set the XML server timeout to 600 seconds:</p> <pre>n1000v# config t n1000v# xml server timeout 600 n1000v#</pre>
-----------------	------------------------------------------------------------------------------------------------------------------------------------------------

Related Commands	Command	Description
	show xml server status	Displays information about XML server settings and any active XML server sessions.
	xml server max-session	Sets the number of allowed XML server sessions.
	xml server terminate session	Displays information about XML server settings and any active XML server sessions.