



C Show Commands

- [show callhome, on page 4](#)
- [show callhome destination-profile, on page 6](#)
- [show callhome destination-profile profile, on page 7](#)
- [show callhome destination-profile profile CiscoTAC-1, on page 8](#)
- [show callhome destination-profile profile full-txt-destination, on page 9](#)
- [show callhome destination-profile profile short-txt-destination, on page 10](#)
- [show callhome transport-email, on page 11](#)
- [show callhome transport, on page 12](#)
- [show callhome user-def-cmds, on page 14](#)
- [show cdp, on page 15](#)
- [show cdp all, on page 17](#)
- [show cdp global, on page 18](#)
- [show cdp neighbors, on page 19](#)
- [show cdp neighbors detail, on page 20](#)
- [show cdp traffic interface2, on page 22](#)
- [show cfs application, on page 23](#)
- [show cfs lock, on page 24](#)
- [show cfs merge status, on page 25](#)
- [show cfs peers, on page 27](#)
- [show cfs regions, on page 28](#)
- [show cfs remote-app vsan domain, on page 30](#)
- [show cfs remote-switches vsan, on page 31](#)
- [show cfs static peers, on page 32](#)
- [show cfs status, on page 33](#)
- [show checkpoint, on page 34](#)
- [show checkpoint, on page 35](#)
- [show checkpoint summary, on page 36](#)
- [show class-map, on page 37](#)
- [show class-map type control-plane, on page 39](#)
- [show class-map type network-qos, on page 40](#)
- [show class-map type psp, on page 41](#)
- [show cli alias, on page 43](#)
- [show cli dynamic integers, on page 44](#)

- [show cli dynamic strings, on page 45](#)
- [show cli history, on page 46](#)
- [show cli interface table, on page 47](#)
- [show cli list, on page 48](#)
- [show cli registry, on page 49](#)
- [show cli syntax, on page 50](#)
- [show cli variables, on page 51](#)
- [show clock, on page 52](#)
- [show clock utc, on page 53](#)
- [show config-profile, on page 54](#)
- [show config-profile applied, on page 55](#)
- [show configuration session, on page 56](#)
- [show configuration session, on page 57](#)
- [show configuration session global-info, on page 58](#)
- [show configuration session status, on page 59](#)
- [show configuration session summary, on page 60](#)
- [show consistency-checker copp, on page 61](#)
- [show consistency-checker fex-interfaces fex, on page 62](#)
- [show consistency-checker forwarding ipv6 show forwarding ipv6 inconsistency, on page 63](#)
- [show consistency-checker forwarding recover, on page 64](#)
- [show consistency-checker forwarding show forwarding inconsistency, on page 65](#)
- [show consistency-checker l2-tahoe module, on page 67](#)
- [show consistency-checker l2-tahoe switchport interface, on page 68](#)
- [show consistency-checker l2 module, on page 69](#)
- [show consistency-checker l3-interface module, on page 70](#)
- [show consistency-checker link-state module, on page 71](#)
- [show consistency-checker membership port-channels, on page 72](#)
- [show consistency-checker membership vlan, on page 73](#)
- [show consistency-checker nxapi interface, on page 74](#)
- [show consistency-checker pacl module, on page 75](#)
- [show consistency-checker pacl port-channels, on page 76](#)
- [show consistency-checker port-security, on page 77](#)
- [show consistency-checker qinvni, on page 78](#)
- [show consistency-checker racl module, on page 79](#)
- [show consistency-checker racl port-channels, on page 80](#)
- [show consistency-checker stp-state vlan, on page 81](#)
- [show consistency-checker vacl, on page 82](#)
- [show consistency-checker vxlan bgp, on page 83](#)
- [show consistency-checker vxlan interface, on page 84](#)
- [show consistency-checker vxlan mh mac-addresses, on page 85](#)
- [show consistency-checker vxlan mh pathlist, on page 86](#)
- [show consistency-checker vxlan peers, on page 87](#)
- [show consistency-checker vxlan routes, on page 88](#)
- [show consistency-checker vxlan selective-qinvni, on page 89](#)
- [show consistency-checker vxlan selective-qinvni interface, on page 90](#)
- [show consistency-checker vxlan vlan, on page 91](#)

- show controller accounting log, on page 92
- show copp diff profile profile2, on page 93
- show copp profile, on page 94
- show copp status, on page 98
- show copyright, on page 99
- show cores, on page 100
- show crypto ca certificates, on page 101
- show crypto ca certificates, on page 102
- show crypto ca certstore, on page 103
- show crypto ca crl, on page 104
- show crypto ca remote-certstore, on page 105
- show crypto ca trustpoints, on page 106
- show crypto certificate-map, on page 107
- show crypto key mypubkey rsa, on page 108
- show crypto ssh-auth-map, on page 109
- show cts, on page 110
- show current, on page 111

show callhome

show callhome

```
show callhome [ __readonly__ <output_state> <info> <per_name> [ <name> ] <email_info> [ <email_conf> ]
] <ph_info> [ <ph_conf> ] <str_addr> [ <str_conf> ] <site_id> [ <site_id_conf> ] <cust_id> [ <cus_id_conf>
] <contr_id> [ <contr_id_conf> ] <swi_pri> [ <swi_pri_value> ] <dup_mess> <per_inv> <per_time>
<per_timeofday> <dist> ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
<u>__readonly__</u>	(Optional)
<i>output_state</i>	(Optional)
<i>info</i>	(Optional)
<i>per_name</i>	(Optional)
<i>name</i>	(Optional)
<i>email_info</i>	(Optional)
<i>email_conf</i>	(Optional)
<i>ph_info</i>	(Optional)
<i>ph_conf</i>	(Optional)
<i>str_addr</i>	(Optional)
<i>str_conf</i>	(Optional)
<i>site_id</i>	(Optional)
<i>site_id_conf</i>	(Optional)
<i>cust_id</i>	(Optional)
<i>cus_id_conf</i>	(Optional)
<i>contr_id</i>	(Optional)
<i>contr_id_conf</i>	(Optional)
<i>swi_pri</i>	(Optional)
<i>swi_pri_value</i>	(Optional)
<i>dup_mess</i>	(Optional)
<i>per_inv</i>	(Optional)

<i>per_time</i>	(Optional)
<i>per_timeofday</i>	(Optional)
<i>dist</i>	(Optional)

Command Mode

- /exec

show callhome destination-profile

show callhome destination-profile

```
show callhome destination-profile [ __readonly__ { TABLE_call_info [ <dest_full_info> ] [ <dest_short_info> ] [ <dest_xml_info> ] [ <dest_def_info> ] <max_mess_size> <mess_format> <mess_level> <trans_method> <email_info> [ <email_conf> ] <url_info> [ <url_conf> ] <alert_groups> [ <alert_conf> ] } ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
destination-profile	Show callhome destination profile information
__readonly__	(Optional)
TABLE_call_info	(Optional)
dest_full_info	(Optional)
dest_short_info	(Optional)
dest_xml_info	(Optional)
dest_def_info	(Optional)
max_mess_size	(Optional)
mess_format	(Optional)
mess_level	(Optional)
trans_method	(Optional)
email_info	(Optional)
email_conf	(Optional)
url_info	(Optional)
url_conf	(Optional)
alert_groups	(Optional)
alert_conf	(Optional)

Command Mode

- /exec

show callhome destination-profile profile

```
show callhome destination-profile profile <s0> [ __readonly__ <user_txt_info> <max_mess_size>
<mess_format> <mess_level> <trans_method> <email_info> [ TABLE_email [ <email_conf> ] ] <url_info>
[ TABLE_url [ <url_conf> ] ] <alert_groups> [ TABLE_alert [ <alert_conf> ] ] ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
destination-profile	Show callhome destination profile information
profile	Specify the destination profile
s0	Show information for user defined destination profile
__readonly__	(Optional)
user_txt_info	(Optional)
max_mess_size	(Optional)
mess_format	(Optional)
mess_level	(Optional)
trans_method	(Optional)
email_info	(Optional)
TABLE_email	(Optional)
email_conf	(Optional)
url_info	(Optional)
TABLE_url	(Optional)
url_conf	(Optional)
alert_groups	(Optional)
TABLE_alert	(Optional)
alert_conf	(Optional)

Command Mode

- /exec

```
show callhome destination-profile profile CiscoTAC-1
```

show callhome destination-profile profile CiscoTAC-1

```
show callhome destination-profile profile CiscoTAC-1 [ __readonly__ <tac_xml_info> <max_mess_size>
<mess_level> <trans_method> <email_info> [ <email_conf> ] <url_info> [ <url_conf> ] <alert_groups> [
<alert_conf> ] ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
destination-profile	Show callhome destination profile information
profile	Specify the destination profile
CiscoTAC-1	Show information for CiscoTAC-1 destination profile
<i>__readonly__</i>	(Optional)
<i>tac_xml_info</i>	(Optional)
<i>max_mess_size</i>	(Optional)
<i>mess_level</i>	(Optional)
<i>trans_method</i>	(Optional)
<i>email_info</i>	(Optional)
<i>email_conf</i>	(Optional)
<i>url_info</i>	(Optional)
<i>url_conf</i>	(Optional)
<i>alert_groups</i>	(Optional)
<i>alert_conf</i>	(Optional)

Command Mode

- /exec

show callhome destination-profile profile full-txt-destination

show callhome destination-profile profile full-txt-destination [__readonly__ <full_txt_info> <max_mess_size> <mess_level> <trans_method> <email_info> [<email_conf>] <url_info> [<url_conf>] <alert_groups> [<alert_conf>]]

Syntax Description

show	Show running system information
callhome	Show callhome information
destination-profile	Show callhome destination profile information
profile	Specify the destination profile
full-txt-destination	Show information for full-txt-destination destination profile
__readonly__	(Optional)
<i>full_txt_info</i>	(Optional)
<i>max_mess_size</i>	(Optional)
<i>mess_level</i>	(Optional)
<i>trans_method</i>	(Optional)
<i>email_info</i>	(Optional)
<i>email_conf</i>	(Optional)
<i>url_info</i>	(Optional)
<i>url_conf</i>	(Optional)
<i>alert_groups</i>	(Optional)
<i>alert_conf</i>	(Optional)

Command Mode

- /exec

show callhome destination-profile profile short-txt-destination

```
show callhome destination-profile profile short-txt-destination [ __readonly__ <shrt_txt_info>
<max_mess_size> <mess_level> <trans_method> <email_info> [ <email_conf> ] <url_info> [ <url_conf> ]
<alert_groups> [ <alert_conf> ] ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
destination-profile	Show callhome destination profile information
profile	Specify the destination profile
short-txt-destination	Show information for short-txt-destination destination profile
<i>__readonly__</i>	(Optional)
<i>shrt_txt_info</i>	(Optional)
<i>max_mess_size</i>	(Optional)
<i>mess_level</i>	(Optional)
<i>trans_method</i>	(Optional)
<i>email_info</i>	(Optional)
<i>email_conf</i>	(Optional)
<i>url_info</i>	(Optional)
<i>url_conf</i>	(Optional)
<i>alert_groups</i>	(Optional)
<i>alert_conf</i>	(Optional)

Command Mode

- /exec

show callhome transport-email

```
show callhome transport-email [ __readonly__ { <from_email> } [ <reply_to_email> ] [ <return_receipt_addr> ] { <smtp_server> } [ <smtp_server_port> ] ]
```

Syntax Description

__readonly__	(Optional)
show	Show running system information
callhome	Show callhome information
transport-email	Show callhome email transport configuration
<i>from_email</i>	(Optional)
<i>reply_to_email</i>	(Optional)
<i>return_receipt_addr</i>	(Optional)
<i>smtp_server</i>	(Optional)
<i>smtp_server_port</i>	(Optional)

Command Mode

- /exec

show callhome transport

show callhome transport

```
show callhome transport [ __readonly__ <vrf> <from_email> [ <rep_email> ] [ <ret_email> ] [ <smtp_ser> ]
] [ <smtp_ser_port> ] [ <smtp_ser_vrf> ] [ <smtp_ser_prior> ] [ <smtp_ser_do> ] [ <smtp_ser_port_do> ] [
<smtp_ser_vrf_do> ] [ <smtp_ser_prior_do> ] [ <smtp_ser_got> ] [ <smtp_ser_port_got> ] [
<smtp_ser_vrf_got> ] [ <smtp_ser_prior_got> ] <http_prox> <http_port> <http_state> ]
```

Syntax Description

show	Show running system information
callhome	Show callhome information
transport	Show callhome transport configuration (email and http)
<u>__readonly__</u>	(Optional)
<i>vrf</i>	(Optional)
<i>from_email</i>	(Optional)
<i>rep_email</i>	(Optional)
<i>ret_email</i>	(Optional)
<i>smtp_ser</i>	(Optional)
<i>smtp_ser_port</i>	(Optional)
<i>smtp_ser_vrf</i>	(Optional)
<i>smtp_ser_prior</i>	(Optional)
<i>smtp_ser_do</i>	(Optional)
<i>smtp_ser_port_do</i>	(Optional)
<i>smtp_ser_vrf_do</i>	(Optional)
<i>smtp_ser_prior_do</i>	(Optional)
<i>smtp_ser_got</i>	(Optional)
<i>smtp_ser_port_got</i>	(Optional)
<i>smtp_ser_vrf_got</i>	(Optional)
<i>smtp_ser_prior_got</i>	(Optional)
<i>http_prox</i>	(Optional)
<i>http_port</i>	(Optional)
<i>http_state</i>	(Optional)

Command Mode

- /exec

```
show callhome user-def-cmds
```

show callhome user-def-cmds

show callhome user-def-cmds

Syntax Description

show	Show running system information
callhome	Show callhome information
user-def-cmds	Show the cli commands configured for each alert group

Command Mode

- /exec

show cdp

```
show cdp { entry { all1 | name <s0> } } [ __readonly__ TABLE_cdp_entry_all <device_id> [ <sysname> ] [ { <v4addr> | <v6addr> } + ] <platform_id> <capability> + <intf_id> <port_id> <ttl> <version> <version_no> [ <nativvlan> ] [ <vtppname> ] [ <duplexmode> ] [ <syslocation> ] [ { <v4mgmtaddr> | <v6mgmtaddr> } + ] ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
entry	Show CDP entries in database
all1	Show all CDP entries in database
name	Show a specific CDP entry matching a name
s0	
__readonly__	(Optional) Read only
TABLE_cdp_entry_all	(Optional) output of show cdp entry all
device_id	(Optional) Device Identifier
sysname	(Optional) System Name
v4addr	(Optional) Interface IP V4 Address
v6addr	(Optional) Interface IP V6 Address
platform_id	(Optional) Platform Id
capability	(Optional) Capability
intf_id	(Optional) Interface Id
port_id	(Optional) Port Identifier
ttl	(Optional) Hold Time
version	(Optional) Software Version
version_no	(Optional) CDP version number
nativvlan	(Optional) NativeVLAN
vtppname	(Optional) Vtp Management Domain Name
duplexmode	(Optional) Duplex Mode
syslocation	(Optional) System Location

show cdp

<i>v4mgmtaddr</i>	(Optional) IP V4 Mgmt Address
<i>v6mgmtaddr</i>	(Optional) IP V6 Mgmt Address

Command Mode

- /exec

show cdp all

```
show cdp { all | interface <if0> } [ __readonly__ TABLE_cdp_all <intf_id> <port_up> [ <cdp_global_enabled> ] <cdp_intf_enabled> [ <oper_mode> ] <refresh_time> <ttl> ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
all	Show all interfaces in CDP database
interface	Show CDP parameters for an interface
<i>if0</i>	
<u>__readonly__</u>	(Optional) Read only
TABLE_cdp_all	(Optional) output of show cdp all
<i>intf_id</i>	(Optional) Interface Id
<i>port_up</i>	(Optional) Port status
<i>cdp_global_enabled</i>	(Optional) CDP global status
<i>cdp_intf_enabled</i>	(Optional) CDP interface status
<i>oper_mode</i>	(Optional) CDP operation mode
<i>refresh_time</i>	(Optional) Refresh Time
<i>ttl</i>	(Optional) Hold Time

Command Mode

- /exec

show cdp global

show cdp global

```
show cdp global [ __readonly__ <cdp_global_enabled> <refresh_time> <ttl> <v2_advertisement>
<deviceid_format> ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
global	Show CDP global parameters
<u>__readonly__</u>	(Optional) Read only
<i>cdp_global_enabled</i>	(Optional) CDP global status
<i>refresh_time</i>	(Optional) Refresh Time
<i>ttl</i>	(Optional) Hold Time
<i>v2_advertisement</i>	(Optional) Show v2 advertisement
<i>deviceid_format</i>	(Optional) Show deviceId Format

Command Mode

- /exec

show cdp neighbors

```
show cdp neighbors [ interface <if> ] [ __readonly__ { TABLE_cdp_neighbor_brief_info <ifindex>
<device_id> <intf_id> <ttl> <capability> + <platform_id> <port_id> } { <neigh_count> } ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
neighbors	Show CDP neighbors
interface	(Optional) Show CDP neighbors on an interface
<i>if</i>	(Optional) Specify Interface
<u>__readonly__</u>	(Optional) Read only
TABLE_cdp_neighbor_brief_info	(Optional) output of show cdp neighbor - in breif
<i>ifindex</i>	(Optional) Interface index
<i>device_id</i>	(Optional) System Name (or) Device Identifier
<i>intf_id</i>	(Optional) Interface Id
<i>port_id</i>	(Optional) Port Identifier
<i>platform_id</i>	(Optional) Platform Id
<i>ttl</i>	(Optional) Hold Time
<i>capability</i>	(Optional) Capability
<i>neigh_count</i>	(Optional) Neighbor Count

Command Mode

- /exec

show cdp neighbors detail

show cdp neighbors detail

```
show cdp neighbors [ interface <if> ] detail [ __readonly__ TABLE_cdp_neighbor_detail_info <ifindex>
<device_id> [ <sysname> ] [ <vtpname> ] <numaddr> { <v4addr> | <v6addr> } + <platform_id> <capability>
+ <intf_id> <port_id> <ttl> <version> <version_no> [ <nativvlan> ] [ <duplexmode> ] [ <mtu> ] [
<syslocation> ] [ <num_mgmtaddr> { <v4mgmtaddr> | <v6mgmtaddr> } + ] ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
neighbors	Show CDP neighbors
detail	Show CDP neighbors detailed
interface	(Optional) Show CDP neighbors on an interface
<i>if</i>	(Optional) Specify Interface
<i>__readonly__</i>	(Optional) Read only
TABLE_cdp_neighbor_detail_info	(Optional) output of show cdp neighbor detail
<i>ifindex</i>	(Optional) Interface index
<i>device_id</i>	(Optional) Device Identifier
<i>sysname</i>	(Optional) System Name
<i>vtpname</i>	(Optional) Vtp Management Domain Name
<i>numaddr</i>	(Optional) No of IP Address configured
<i>v4addr</i>	(Optional) Interface IP V4 Address
<i>v6addr</i>	(Optional) Interface IP V6 Address
<i>platform_id</i>	(Optional) Platform Id
<i>capability</i>	(Optional) Capability
<i>intf_id</i>	(Optional) Interface Id
<i>port_id</i>	(Optional) Port Identifier
<i>ttl</i>	(Optional) Hold Time
<i>version</i>	(Optional) Software Version
<i>version_no</i>	(Optional) CDP version number
<i>nativvlan</i>	(Optional) NativeVLAN

<i>duplexmode</i>	(Optional) Duplex Mode
<i>mtu</i>	(Optional) MTU
<i>syslocation</i>	(Optional) System Location
<i>num_mgmtaddr</i>	(Optional) No of Mgmt Address configured
<i>v4mgmtaddr</i>	(Optional) IP V4 Mgmt Address
<i>v6mgmtaddr</i>	(Optional) IP V6 Mgmt Address

Command Mode

- /exec

show cdp traffic interface2

show cdp traffic interface2

```
show cdp traffic interface2 <if2> [ __readonly__ <intf_id> <total_input_packets> <valid_cdp_packets>
<input_v1_packets> <input_v2_packets> <invalid_cdp_packets> <unsupported_version> <checksum_errors>
<malformed_packets> <total_output_packets> <output_v1_packets> <output_v2_packets> <send_errors> ]
```

Syntax Description

show	Show running system information
cdp	Show Cisco Discovery Protocol information
traffic	Show CDP traffic statistics
interface2	Show CDP traffic statistics on an interface
<i>if2</i>	
<i>__readonly__</i>	(Optional) Read only
<i>intf_id</i>	(Optional) Interface Id
<i>total_input_packets</i>	(Optional) Total input cdp packets
<i>valid_cdp_packets</i>	(Optional) Total valid cdp packets
<i>input_v1_packets</i>	(Optional) Input version1 packets
<i>input_v2_packets</i>	(Optional) Input version2 packets
<i>invalid_cdp_packets</i>	(Optional) Invalid cdp packets
<i>unsupported_version</i>	(Optional) Packets having unsupported version
<i>checksum_errors</i>	(Optional) Packets having checksum errors
<i>malformed_packets</i>	(Optional) Total malformed packets
<i>total_output_packets</i>	(Optional) Total output packets
<i>output_v1_packets</i>	(Optional) Output version1 packets
<i>output_v2_packets</i>	(Optional) Output version2 packets
<i>send_errors</i>	(Optional) Number of send errors

Command Mode

- /exec

show cfs application

```
show cfs application [ { name <cfs-dyn-app-name> | sap <i0> } ] [ __readonly__ [ { enabled <enabled> } { timeout <timeout> } { merge_capable <merge_capable> } { scope <scope> } { region <region> } ] [ { TABLE_apps <app_name> <app_enabled> <app_scope> } ] ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
application	Show locally registered applications
name	(Optional) Show local application information by name
<i>cfs-dyn-app-name</i>	(Optional) Registered name of the local application
sap	(Optional) Show local application information by sap
<i>i0</i>	(Optional) Registered sap of the local application
__readonly__	(Optional)
enabled	(Optional) whether application is CFS enabled
<i>enabled</i>	(Optional) whether application is CFS enabled
timeout	(Optional) timeout
<i>timeout</i>	(Optional) timeout
merge_capable	(Optional) merge_capable
<i>merge_capable</i>	(Optional) merge_capable
scope	(Optional) scope
<i>scope</i>	(Optional) scope
region	(Optional) region
<i>region</i>	(Optional) region
TABLE_apps	(Optional) all cfs applications
<i>app_name</i>	(Optional) name of cfs application
<i>app_enabled</i>	(Optional) whether application is cfs enabled
<i>app_scope</i>	(Optional) distribution scope of cfs application

Command Mode

- /exec

show cfs lock

show cfs lock

```
show cfs lock [ { name <cfs-dyn-app-name> | sap <i1> } ] [ __readonly__ [ { TABLE_locks [ <app_name> ] <app_scope> [ <vsan> ] [ <domain> ] [ <wwn> ] <ip_addr> <u_name> <u_type> [ <hostname> ] } ] ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
lock	Show state of application's logical/physical locks
name	(Optional) Application name for which the lock status is required
<i>cfs-dyn-app-name</i>	(Optional) Registered name of the local application
sap	(Optional) Application sap for which the lock status is required
<i>i1</i>	(Optional) Application SAP
<u>__readonly__</u>	(Optional)
TABLE_locks	(Optional) table of all CFS locks
<i>app_name</i>	(Optional) name of CFS application
<i>app_scope</i>	(Optional) scope of CFS application
<i>vsan</i>	(Optional) vsan
<i>domain</i>	(Optional) domain
<i>wwn</i>	(Optional) wwn of switch holding CFS lock
<i>ip_addr</i>	(Optional) ip address of switch holding CFS lock
<i>u_name</i>	(Optional) user name
<i>u_type</i>	(Optional) user type
<i>hostname</i>	(Optional) hostname

Command Mode

- /exec

show cfs merge status

```
show cfs merge status [ { name <cfs-dyn-app-name> [ detail ] | sap <i1> [ detail2 ] } ] [ __readonly__ [ { scope <scope> } ] [ { merge_status <status> } ] [ { failure_reason <reason> } ] [ { TABLE_all_merge <app_name> <scope> <vsan> <status> } ] [ { TABLE_local_fabric [ <domain> ] <wwn> <ip_addr> <app_scope> [ <master> ] [ <hostname> ] } ] [ { TABLE_remote_fabric [ <domain> ] <wwn> <ip_addr> <app_scope> [ <master> ] [ <hostname> ] } ] [ { TABLE_remaining_fabric [ <domain> ] <wwn> <ip_addr> [ <hostname> ] } ] ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
merge	Show cfs merge information
status	Show status of merge
name	(Optional) Show merge status by name
<i>cfs-dyn-app-name</i>	(Optional) Registered name of the local application
detail	(Optional) Show merge status by name in detail
sap	(Optional) Show merge status by sap
<i>i1</i>	(Optional) Application sap
detail2	(Optional) Show merge status by sap in detail
__readonly__	(Optional)
scope	(Optional) distribution scope of application
<i>scope</i>	(Optional) scope
merge_status	(Optional) status
<i>status</i>	(Optional) status
failure_reason	(Optional) reason
<i>reason</i>	(Optional) reason
TABLE_all_merge	(Optional) all
<i>app_name</i>	(Optional) name
<i>scope</i>	(Optional) scope
<i>vsan</i>	(Optional) vsan
<i>status</i>	(Optional) status

show cfs merge status

TABLE_local_fabric	(Optional) local fabric
<i>domain</i>	(Optional) domain
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_addr
<i>app_scope</i>	(Optional) scope
<i>master</i>	(Optional) master
<i>hostname</i>	(Optional) hname
TABLE_remote_fabric	(Optional) remote fabric
<i>domain</i>	(Optional) domain
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_addr
<i>app_scope</i>	(Optional) scope
<i>master</i>	(Optional) master
<i>hostname</i>	(Optional) hname
TABLE_remaining_fabric	(Optional) remote fabric
<i>domain</i>	(Optional) domain
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_addr
<i>hostname</i>	(Optional) hname

Command Mode

- /exec

show cfs peers

```
show cfs peers [ { name <cfs-dyn-app-name> | sap <i1> } ] [ __readonly__ [ { scope <scope> } ] [ { TABLE_peers <wwn> <ip_addr> <local> [ <hostname> ] [ <domain> ] } ] ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
peers	Show all the peers in the physical fabric
name	(Optional) Show peers for given application name
<i>cfs-dyn-app-name</i>	(Optional) Registered name of the local application
sap	(Optional) Show peers for given application sap
<i>i1</i>	(Optional) Application sap
<u>__readonly__</u>	(Optional)
scope	(Optional) scope
<i>scope</i>	(Optional) scope
TABLE_peers	(Optional) all peers
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_addr
<i>local</i>	(Optional) local
<i>hostname</i>	(Optional) hname
<i>domain</i>	(Optional) domain

Command Mode

- /exec

show cfs regions

show cfs regions

```
show cfs regions [ { brief [ region <i0> ] | name <cfs-dyn-app-name> | region1 <i1> } ] [ __readonly__ [ { region <id> } ] [ { application <name> } ] [ { scope <scope> } ] [ { TABLE_PEERS <wwn> <ip_addr> <local> [ <hostname> ] [ <domain> ] } ] [ { TABLE_switches [ <wwn> ] [ <ip_addr> ] <region> <app_name> <enabled> [ <scope> ] } ] ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
regions	Show all the applications with peers and region information
brief	(Optional) Show all configured regions and applications(no peers)
region	(Optional) Show all configured applications(no peers)
<i>i0</i>	(Optional) Region Id
name	(Optional) Show peers and region information for a given application
<i>cfs-dyn-app-name</i>	(Optional) Registered name of the local application
region1	(Optional) Show all configured applications with peers
<i>i1</i>	(Optional) Region Id
<u>__readonly__</u>	(Optional)
region	(Optional) region
<i>id</i>	(Optional) id
application	(Optional) app
<i>name</i>	(Optional) name
scope	(Optional) scope
<i>scope</i>	(Optional) scope
TABLE_PEERS	(Optional) all region peers
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_address
<i>local</i>	(Optional) local
<i>hostname</i>	(Optional) hname
<i>domain</i>	(Optional) domain

TABLE_switches	(Optional) all switches in region
<i>wwn</i>	(Optional) wwn
<i>ip_addr</i>	(Optional) ip_addr
<i>region</i>	(Optional) region
<i>app_name</i>	(Optional) name
<i>enabled</i>	(Optional) enabled
<i>scope</i>	(Optional) scope

Command Mode

- /exec

```
show cfs remote-app vsan domain
```

show cfs remote-app vsan domain

show cfs remote-app vsan <i0> domain <i1>

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
remote-app	Show remote cfs registered applications
vsan	Show remote applications given a vsan
<i>i0</i>	VSAN id
domain	Show remote applications
<i>i1</i>	Enter the domain id

Command Mode

- /exec

show cfs remote-switches vsan

show cfs remote-switches vsan <i0> [__readonly__ { local <domain> } [{ TABLE_switches <remote_domain> <wwn> }]]

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
remote-switches	Show remote switches on a given vsan
vsan	Show remote switches on a given vsan
<i>i0</i>	VSAN id
__readonly__	(Optional)
local	(Optional) local
<i>domain</i>	(Optional) domain
TABLE_switches	(Optional) all remote switches
<i>remote_domain</i>	(Optional) rdomain
<i>wwn</i>	(Optional) wwn

Command Mode

- /exec

show cfs static peers

show cfs static peers

show cfs static peers

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
static	Show all static peers with status
peers	Show all configured static peers with status

Command Mode

- /exec

show cfs status

```
show cfs status [ __readonly__ { distribution <distribution> } { distribution_over_ip <dist_over_ip> } {  
    ipv4_multicast_address <ipv4_mcast_addr> } { ipv6_multicast_address <ipv6_mcast_addr> } {  
    distribution_over_etherent <dist_over_eth> } ]
```

Syntax Description

show	Show running system information
cfs	CFS Show Command handler
status	Show current status of CFS
__readonly__	(Optional)
distribution	(Optional) runtime status of CFS distribution
<i>distribution</i>	(Optional) operational status of CFS distribution
distribution_over_ip	(Optional) runtime information of CFSoIP
<i>dist_over_ip</i>	(Optional) operational status of CFS overIP
ipv4_multicast_address	(Optional) ipv4 multicast address
<i>ipv4_mcast_addr</i>	(Optional) ipv4 multicast address
ipv6_multicast_address	(Optional) ipv6 multicast address
<i>ipv6_mcast_addr</i>	(Optional) ipv6 multicast address
distribution_over_etherent	(Optional) runtime status if CFSoE
<i>dist_over_eth</i>	(Optional) operations status of CFSoE

Command Mode

- /exec

show checkpoint

show checkpoint

```
show checkpoint [ all ] [ user | system ] [ __readonly__ TABLE_checkpoint_details <name>
<checkpoint_config> + ]
```

Syntax Description

show	Show running system information
checkpoint	Show configuration rollback checkpoints
all	(Optional) Show default config
user	(Optional) Show only user configuration rollback checkpoints
system	(Optional) Show only system configuration rollback checkpoints
<u>__readonly__</u>	(Optional) Read only
TABLE_checkpoint_details	(Optional) checkpoint details
<i>name</i>	(Optional) Checkpoint name
<i>checkpoint_config</i>	(Optional) Configuration entry from checkpoint

Command Mode

- /exec

show checkpoint

```
show checkpoint <chkpoint_name> [ all ] [ __readonly__ TABLE_checkpoint_details <name1> <checkpoint_config> + ]
```

Syntax Description

show	Show running system information
checkpoint	Show configuration rollback checkpoint contents
<i>chkpoint_name</i>	Checkpoint name
all	(Optional) Show default config
__readonly__	(Optional) Read only
TABLE_checkpoint_details	(Optional) Checkpoint details
<i>name1</i>	(Optional) Checkpoint name
<i>checkpoint_config</i>	(Optional) Configuration entry from checkpoint

Command Mode

- /exec

show checkpoint summary

show checkpoint summary

```
show checkpoint summary [ user | system ] [ __readonly__ TABLE_checkpoint_header_info <name>
<user_name> <timestamp> <file_path> <chkpt_type> <description> ]
```

Syntax Description

show	Show running system information
checkpoint	Show configuration rollback checkpoints
summary	Show configuration rollback checkpoints summary
user	(Optional) Show only user configuration rollback checkpoints summary
system	(Optional) Show only system configuration rollback checkpoints summary
__readonly__	(Optional) Read only
TABLE_checkpoint_header_info	(Optional) Checkpoint header info
<i>user_name</i>	(Optional) Username
<i>name</i>	(Optional) Checkpoint name
<i>file_path</i>	(Optional) Checkpoint name
<i>timestamp</i>	(Optional) Timestamp of checkpoint creation
<i>chkpt_type</i>	(Optional) Type of checkpoint either user or system
<i>description</i>	(Optional) Checkpoint description

Command Mode

- /exec

show class-map

```
show class-map [ { [ type qos ] [ <cmap-name> | xxx <color-map-enum-name> ] } | { type queuing [ yyy <cmap-enum-name> | zzz <default-cmap-enum-name> | <cmap-dce-name> | <cmap-name-hque> ] } ] [ __readonly__ { [ <display-all> ] [ TABLE_cmap <cmap-key> [ <id> ] <xqos-or-q> [ <any_or_all> ] <cmap-name-out> [ <desc> ] [ TABLE_match <match-key> [ <not> ] [ <dscp-list> ] [ <precedence-list> ] [ <cos-list> ] [ <qos-group-list> ] [ <discard-class-list> ] [ <vlan-list> ] [ <match-cmap-name> ] [ <match-acl-name> ] [ <note-string> ] [ <pkt-len-list> ] [ <rtp-port-list> ] [ <prot> ] [ <input-iface-list> ] [ <exp-list> ] [ <cl-def> ] ] } ] ]
```

Syntax Description

xxx	(Optional) xxx
yyy	(Optional) yyy
zzz	(Optional) zzz
show	Show running system information
class-map	Show class maps
type	(Optional) Type of the class-map
qos	(Optional) type qos
queuing	(Optional) type queuing
<i>cmap-name</i>	(Optional) class map name
<i>cmap-enum-name</i>	(Optional)
<i>default-cmap-enum-name</i>	(Optional)
<i>cmap-dce-name</i>	(Optional) Queuing class-map name
<i>cmap-name-hque</i>	(Optional) Hierarchical class-map name
<i>color-map-enum-name</i>	(Optional)
<u>__readonly__</u>	(Optional)
<i>display-all</i>	(Optional) Display all kinds of class-maps
TABLE_cmap	(Optional) all cmap xml sessions
<i>cmap-key</i>	(Optional) Class-map name: xml key
TABLE_match	(Optional) all match xml sessions
<i>match-key</i>	(Optional) match count: xml key
<i>cmap-name-out</i>	(Optional) Class-map name
<i>xqos-or-q</i>	(Optional)

show class-map

<i>any_or_all</i>	(Optional) Enter match-any or match-all
<i>id</i>	(Optional) Class-map ID
<i>desc</i>	(Optional) Description string
<i>not</i>	(Optional) Negate this match result
<i>dscp-list</i>	(Optional) List of DSCP values
<i>precedence-list</i>	(Optional) List of precedence values
<i>cos-list</i>	(Optional) List of class-of-service values
<i>qos-group-list</i>	(Optional) List of qos-group values
<i>discard-class-list</i>	(Optional) List of discard-class values
<i>vlan-list</i>	(Optional) List of vlan-ids
<i>match-cmap-name</i>	(Optional) class-map name
<i>match-acl-name</i>	(Optional) Match class-map name
<i>note-string</i>	(Optional) Placeholder string param to display any info in string format
<i>pkt-len-list</i>	(Optional) Packet length multi-range
<i>rtp-port-list</i>	(Optional) IP RTP UDP port multi-range
<i>prot</i>	(Optional) Protocol
<i>input-iface-list</i>	(Optional) Input Interface multi-range
<i>exp-list</i>	(Optional) List of MPLS exp values
<i>cl-def</i>	(Optional) Match any criteria for class-default only

Command Mode

- /exec

show class-map type control-plane

```
show class-map type control-plane [ <cmap-name> ] [ __readonly__ [ { TABLE_cmap <cmap-key>
<cmap-name-out><opt_any_or_all> [ TABLE_match <match-key> [ access_grp <acc_grp_name> ] [ redirect
<opt_match_redirect> ] [ exception <opt_match_except> ] [ protocol <opt_match_protocol> ] ] } ] ]
```

Syntax Description

show	Show running system information
class-map	Show class maps
type	Type of the class-map
control-plane	This is for copp policy
<i>cmap-name</i>	(Optional) Name of the class-map
<i>__readonly__</i>	(Optional)
TABLE_cmap	(Optional) all cmap xml sessions
<i>cmap-name-out</i>	(Optional) Name of the class-map
<i>cmap-key</i>	(Optional) Class-map name: xml key
<i>opt_any_or_all</i>	(Optional) Enter match-any or match-all
TABLE_match	(Optional) all match xml sessions
<i>match-key</i>	(Optional) match count: xml key
access_grp	(Optional)
<i>acc_grp_name</i>	(Optional)
redirect	(Optional)
<i>opt_match_redirect</i>	(Optional) Match criteria for redirected packets
exception	(Optional)
<i>opt_match_except</i>	(Optional) Match criteria for exception packets
protocol	(Optional)
<i>opt_match_protocol</i>	(Optional) Match criteria for protocol packets

Command Mode

- /exec

```
show class-map type network-qos
```

show class-map type network-qos

show class-map type network-qos [<cmap-name-nq>] [__readonly__ { <display-all> <desc> <xcmapp-name> <cos-list> <qos-group-list> <protocol> }]

Syntax Description

show	Show running system information
class-map	Show class maps
type	Type of the class-map
<i>cmap-name-nq</i>	(Optional) Class-map name
network-qos	type network-qos
<u>__readonly__</u>	(Optional)
<i>display-all</i>	(Optional) Display all network-qos class-maps
<i>desc</i>	(Optional) Description string
<i>xcmapp-name</i>	(Optional) Class-map name
<i>protocol</i>	(Optional) protocol
<i>cos-list</i>	(Optional) List of class-of-service values
<i>qos-group-list</i>	(Optional) List of qos-group values

Command Mode

- /exec

show class-map type psp

```
show class-map type psp { [ <cmap-name-plc> [ client <clienttype> <clientID> ] [ cfg-mode <cfgmode> ] ]
| [ handle <ppf_id> ] } [ __readonly__ { [ <display-all> ] [ TABLE_cmap <cmap-key> [ <id> ] [ <any_or_all>
] [ <__inline__> ] [ class-default ] <cmap-name-out> [ <desc> ] [ TABLE_match <match-key> [ <not> ] [ <any> ] [ <cos-list> ] [ <mac_src> <mac_src_wild> ] [ <mac_dest> <mac_dest_wild> ] [ <eth-value> ] [ <vlan-number> ] [ <tos-value> ] [ <ip-protocol-value> ] [ <ip-s-addr> <ip-s-mask> ] [ <ip-d-addr> <ip-d-mask> ] [ <tcp-src-port-addr> ] [ <tcp-dest-port-addr> ] [ <udp-src-port-addr> ] [ <udp-dest-port-addr> ] [ <interface-name> ] [ <ipv6-s-addr> <ipv6-s-mask> ] [ <ipv6-d-addr> <ipv6-d-mask> ] [ <dscp-list> ] ] ] }
```

Syntax Description

show	Show running system information
class-map	Show class maps
type	Type of the class-map
psp	type psp
<i>cmap-name-plc</i>	(Optional) Class-map name
client	(Optional) set client type
<i>clienttype</i>	(Optional) cli/onep
<i>clientID</i>	(Optional) client appID
cfg-mode	(Optional) cfg-mode
<i>cfgmode</i>	(Optional) persistent/transient
handle	(Optional) Handle
<i>ppf_id</i>	(Optional) PPF ID
<u>__readonly__</u>	(Optional)
<i>display-all</i>	(Optional) Display all kinds of class-maps
TABLE_cmap	(Optional) all cmap xml sessions
<i>cmap-key</i>	(Optional) Class-map name: xml key
TABLE_match	(Optional) all match xml sessions
<i>match-key</i>	(Optional) match count: xml key
class-default	(Optional)
<i>cmap-name-out</i>	(Optional) Class-map name
<i>any_or_all</i>	(Optional) Enter match-any or match-all
<u>__inline__</u>	(Optional) Inline class

```
show class-map type psp
```

<i>id</i>	(Optional) Class-map ID
<i>desc</i>	(Optional) Description string
<i>not</i>	(Optional) Negate this match result
<i>any</i>	(Optional) Wildcard match
<i>cos-list</i>	(Optional) List of class-of-service values
<i>mac_src</i>	(Optional) Source MAC address
<i>mac_src_wild</i>	(Optional) Source MAC mask
<i>mac_dest</i>	(Optional) Destination MAC address
<i>mac_dest_wild</i>	(Optional) Destination MAC mask
<i>eth-value</i>	(Optional) Ethernet type
<i>vlan-number</i>	(Optional) Vlan number
<i>tos-value</i>	(Optional) IPv4 TOS
<i>ip-protocol-value</i>	(Optional) IPV4 protocol
<i>ip-s-addr</i>	(Optional) IP address in format a.b.c.d
<i>ip-d-addr</i>	(Optional) IP address in format a.b.c.d
<i>ip-s-mask</i>	(Optional) IP address Mask in format a.b.c.d
<i>ip-d-mask</i>	(Optional) IP address Mask in format a.b.c.d
<i>tcp-src-port-addr</i>	(Optional) Transport layer port number
<i>tcp-dest-port-addr</i>	(Optional) Transport layer port number
<i>udp-src-port-addr</i>	(Optional) Transport layer port number
<i>udp-dest-port-addr</i>	(Optional) Transport layer port number
<i>interface-name</i>	(Optional) Physical interface Name and Number
<i>dscp-list</i>	(Optional) List of DSCP values

Command Mode

- /exec

show cli alias

show cli alias [name <s0>]

Syntax Description

show	Show running system information
cli	Show CLI information
alias	Display the alias configuration
name	(Optional) Display a specific alias
s0	(Optional) Specify the alias

Command Mode

- /exec

show cli dynamic integers

show cli dynamic integers

```
show cli dynamic integers [ <name> ] [ __readonly__ TABLE_dynamic_integers <name-o> <min> <max> ]
```

Syntax Description

show	Show running system information
cli	CLI commands
dynamic	Display current range of dynamic parameters
integers	Display current range of dynamic integer parameters
<i>name</i>	(Optional) name of the dynamic parameter
<u>__readonly__</u>	(Optional)
TABLE_dynamic_integers	(Optional)
<i>name-o</i>	(Optional)
<i>min</i>	(Optional)
<i>max</i>	(Optional)

Command Mode

- /exec

show cli dynamic strings

```
show cli dynamic strings [ <name> ] [ __readonly__ TABLE_dynamic_strings <name-o> <value> + ]
```

Syntax Description

show	Show running system information
cli	CLI commands
dynamic	Display current range of dynamic parameters
strings	Display current range of dynamic string parameters
<i>name</i>	(Optional) name of the dynamic parameter
<u>__readonly__</u>	(Optional)
TABLE_dynamic_strings	(Optional)
<i>name-o</i>	(Optional)
<i>value</i>	(Optional)

Command Mode

- /exec

show cli history

show cli history

show cli history [this-mode-only | exec-mode | config-mode] [<count> | unformatted] +

Syntax Description

show	Show running system information
cli	debug cli
history	history of cli commands
<i>count</i>	(Optional) number of lines to display (from end)
unformatted	(Optional) display just the commands
this-mode-only	(Optional) display history from current mode only
exec-mode	(Optional) display history of exec commands only
config-mode	(Optional) display history of config commands only

Command Mode

- /exec

show cli interface table

show cli interface table

Syntax Description

show	show
cli	cli
interface	interface
table	table

Command Mode

- /exec

show cli list

show cli list

show cli list [detail | recurse | <component> | <max-per-cmd>] +

Syntax Description

show	Show running system information
cli	Show CLI information
list	show
<i>component</i>	(Optional) component
<i>max-per-cmd</i>	(Optional) max
recurse	(Optional) go
detail	(Optional) formats

Command Mode

- /exec

show cli registry

show cli registry [ctags | tags | modes | session | inherit]

Syntax Description

show	Show running system information
cli	
registry	
ctags	(Optional)
tags	(Optional)
modes	(Optional)
session	(Optional)
inherit	(Optional)

Command Mode

- /exec

show cli syntax

show cli syntax

show cli syntax [long | recurse] + [has-xml-out | has-no-xml-out | is-data-modeled] [roles [network-admin | network-operator | <roles-mask>]]

Syntax Description

show	Show running system information
cli	Show CLI information
syntax	show
long	(Optional) use
recurse	(Optional) also
has-xml-out	(Optional) show
has-no-xml-out	(Optional) show
is-data-modeled	(Optional) show
roles	(Optional) show
network-admin	(Optional) show
network-operator	(Optional) show
<i>roles-mask</i>	(Optional) show

Command Mode

- /exec

show cli variables

show cli variables

Syntax Description

show	Show running system information
cli	Show CLI information
variables	Show CLI variables

Command Mode

- /exec

show clock

show clock

```
show clock [ detail ] [ __readonly__ { <simple_time> [ <daylight_zone> <daylight_start_week>
<daylight_start_weekday> <daylight_start_month> <daylight_start_time> <daylight_end_week>
<daylight_end_weekday> <daylight_end_month> <daylight_end_time> <daylight_utc_min_offset> ] } ]
```

Syntax Description

show	Show running system information
clock	Display current Date
detail	(Optional) Display current date and summertime configuration
__readonly__	(Optional)
<i>simple_time</i>	(Optional) simple clock format
<i>daylight_zone</i>	(Optional) summer-time daylight zone
<i>daylight_start_week</i>	(Optional) daylight start week
<i>daylight_start_weekday</i>	(Optional) daylight start weekday
<i>daylight_start_month</i>	(Optional) daylight start month
<i>daylight_start_time</i>	(Optional) daylight start time
<i>daylight_end_week</i>	(Optional) daylight end week
<i>daylight_end_weekday</i>	(Optional) daylight end weekday
<i>daylight_end_month</i>	(Optional) daylight end month
<i>daylight_end_time</i>	(Optional) daylight end time
<i>daylight_utc_min_offset</i>	(Optional) daylight utc offset

Command Mode

- /exec

show clock utc

show clock utc

Syntax Description

show	Show running system information
clock	Display current Date
utc	Display current time in UTC

Command Mode

- /exec

show config-profile

show config-profile

```
show config-profile [ name <all_conf_profile_name> ] [ __readonly__ TABLE_conf_profile_all
<conf_profile_name> { <conf_profile_desc><conf_profile_cfg> + <conf_profile_applied> +
<conf_profile_include> + } ]
```

Syntax Description

show	Show running system information
config-profile	Show config-profiles
name	(Optional) config-profile name
<i>all_conf_profile_name</i>	(Optional) Enter the name of configuration profile
<u>__readonly__</u>	(Optional)
TABLE_conf_profile_all	(Optional)
<i>conf_profile_name</i>	(Optional)
<i>conf_profile_desc</i>	(Optional)
<i>conf_profile_cfg</i>	(Optional)
<i>conf_profile_applied</i>	(Optional)
<i>conf_profile_include</i>	(Optional)

Command Mode

- /exec

show config-profile applied

```
show config-profile { applied [ auto | manually ] | non-applied } [ match-name <profile_substring> ] [ __readonly__ <profiles> ]
```

Syntax Description

show	Show running system information
config-profile	Show config-profiles
applied	List of config-profiles that are applied
auto	(Optional) List of config-profiles that are applied via auto-config
manually	(Optional) List of all config-profiles which were applied directly from cli
non-applied	List of config-profiles that are not applied
match-name	(Optional) List of all config-profiles that have matching sub-string
__readonly__	(Optional)
profiles	(Optional)
profile_substring	(Optional) Enter a substring to match with config-profile name

Command Mode

- /exec

show configuration session

show configuration session

show configuration session [__readonly__ { <ssn-name> <ssn-cmd-num> <command> } + <trlr>]

Syntax Description

show	Show running system information
configuration	Show information about configuration sessions
session	Show active configuration sessions
__readonly__	(Optional) Read only
<i>ssn-name</i>	(Optional)
<i>ssn-cmd-num</i>	(Optional)
<i>command</i>	(Optional)
<i>trlr</i>	(Optional)

Command Mode

- /exec

show configuration session

```
show configuration session <s3> [ __readonly__ <ssn-name> { <ssn-cmd-num> <command> } + ]
```

Syntax Description

show	Show running system information
configuration	Show information about configuration sessions
session	Show active configuration sessions
<i>s3</i>	Shows configuration session given a name
<u>__readonly__</u>	(Optional) Read only
<i>ssn-name</i>	(Optional)
<i>ssn-cmd-num</i>	(Optional)
<i>command</i>	(Optional)

Command Mode

- /exec

show configuration session global-info

show configuration session global-info

show configuration session global-info [readonly <max-ssns> <max-cmds> <curr-num-ssns> <curr-num-cmds>]

Syntax Description

show	Show running system information
configuration	Show information about configuration sessions
session	Show active configuration sessions
global-info	Show configuration sessions global-info
<u>readonly</u>	(Optional) Read only
<i>max-ssns</i>	(Optional)
<i>max-cmds</i>	(Optional)
<i>curr-num-ssns</i>	(Optional)
<i>curr-num-cmds</i>	(Optional)

Command Mode

- /exec

show configuration session status

```
show configuration session status [ <s3> ] [ __readonly__ <ssn-name> { <last-action> <ac-tstamp> <ac-status>
<ac-reason> } { <failed-cmd-num> + <failed-cmd> } + { <last-vfy-cmd-num> <last-vfy-cmd>
<last-vfy-tstamp> } + <rollback-status> + <trlr> ]
```

Syntax Description

show	Show running system information
configuration	Show information about configuration sessions
session	Show active configuration sessions
status	Show configuration session-mgr status
<i>s3</i>	(Optional) Shows configuration session status given a name
<u>__readonly__</u>	(Optional) Read only
<i>ssn-name</i>	(Optional)
<i>last-action</i>	(Optional)
<i>ac-tstamp</i>	(Optional)
<i>ac-status</i>	(Optional)
<i>ac-reason</i>	(Optional)
<i>failed-cmd-num</i>	(Optional)
<i>failed-cmd</i>	(Optional)
<i>last-vfy-cmd-num</i>	(Optional)
<i>last-vfy-cmd</i>	(Optional)
<i>last-vfy-tstamp</i>	(Optional)
<i>rollback-status</i>	(Optional)
<i>trlr</i>	(Optional)

Command Mode

- /exec

show configuration session summary

show configuration session summary

```
show configuration session summary [ __readonly__ <hdr> { <ssn-name> <username> <tstamp> } + <trlr> ]
```

Syntax Description

show	Show running system information
configuration	Show information about configuration sessions
session	Show active configuration sessions
summary	Show summary of the active configuration sessions
<u>__readonly__</u>	(Optional) Read only
<i>hdr</i>	(Optional)
<i>ssn-name</i>	(Optional)
<i>username</i>	(Optional)
<i>tstamp</i>	(Optional)
<i>trlr</i>	(Optional)

Command Mode

- /exec

show consistency-checker copp

show consistency-checker copp

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
copp	Verify copp programming from software context

Command Mode

- /exec

```
show consistency-checker fex-interfaces fex
```

show consistency-checker fex-interfaces fex

show consistency-checker fex-interfaces fex <id>

Syntax Description

show	Show running system information
fex	Limit display to interfaces on this fex
<i>id</i>	Enter module number
consistency-checker	Consistency Checker
fex-interfaces	Compares software and hardware state of fex interfaces

Command Mode

- /exec

show consistency-checker forwarding ipv6 show forwarding ipv6 inconsistency

```
show consistency-checker forwarding ipv6 [ unicast ] [ vrf { <vrf-name> | all_vrfs } ] [ module { <module> | all_modules } ] | show forwarding ipv6 [ unicast ] inconsistency [ vrf { <vrf-name> | all_vrfs } ] [ module { <module> | all_modules } ] [ __readonly__ TABLE_inconsistency <idipv6><slotipv6> [ <unitipv6> ] <vrifipv6> [ <ipv6addr> ] [ <ip6prefix> ] [ <interfaceipv6> ] <reasonipv6> ]
```

Syntax Description

show	show
consistency-checker	Consistency Checker
forwarding	Display Forwarding Information
inconsistency	route inconsistency check
ipv6	ipv6
unicast	(Optional) unicast
vrf	(Optional) check routes for a specific VRF
<i>vrf-name</i>	(Optional) VRF name
module	(Optional) check routes for a specific module
<i>module</i>	(Optional) module number
all_modules	(Optional) all module's
all_vrfs	(Optional) all vrf's
__readonly__	(Optional)
TABLE_inconsistency	(Optional)
<i>idipv6</i>	(Optional)
<i>slotipv6</i>	(Optional)
<i>unitipv6</i>	(Optional)
<i>vrifipv6</i>	(Optional)
<i>interfaceipv6</i>	(Optional)
<i>reasonipv6</i>	(Optional)

Command Mode

- /exec

```
show consistency-checker forwarding recover
```

show consistency-checker forwarding recover

show consistency-checker forwarding recover

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
forwarding	Display Forwarding Information
recover	Recover inconsistent routes

Command Mode

- /exec

show consistency-checker forwarding show forwarding inconsistency

```
show consistency-checker forwarding [ ip | ipv4 ] [ unicast ] [ vrf { <vrf-name> | all_vrfs } ] [ module { <module> | all_modules } ] | show forwarding [ ip | ipv4 ] [ unicast ] inconsistency [ vrf { <vrf-name> | all_vrfs } ] [ module { <module> | all_modules } ] [ __readonly__ TABLE_inconsistency<id><slot> [ <unit> ] <vrf> [ <ipaddr> ] [ <ipprefix> ] [ <interface> ] <reason> ]
```

Syntax Description

show	show
consistency-checker	Consistency Checker
forwarding	Display Forwarding Information
inconsistency	route inconsistency check
ip	(Optional) ipv4
ipv4	(Optional) ipv4
unicast	(Optional) unicast
vrf	(Optional) check routes for a specific VRF
<i>vrf-name</i>	(Optional) VRF name
module	(Optional) check routes for a specific module
<i>module</i>	(Optional) module number
all_modules	(Optional) all module's
all_vrfs	(Optional) all vrf's
__readonly__	(Optional)
TABLE_inconsistency	(Optional)
<i>id</i>	(Optional)
<i>slot</i>	(Optional)
<i>unit</i>	(Optional)
<i>vrf</i>	(Optional)
<i>ipaddr</i>	(Optional)
<i>ipprefix</i>	(Optional)
<i>interface</i>	(Optional)

```
■ show consistency-checker forwarding show forwarding inconsistency
```

<i>reason</i>	(Optional)
---------------	------------

Command Mode

- /exec

show consistency-checker l2-tahoe module

show consistency-checker l2-tahoe module <module> [unit <unit>]

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
l2-tahoe	Verify l2 mac programming in the hardware
module	Module to run the consistency-checker on
<i>module</i>	Enter module number
unit	(Optional) Unit to run the consistency checker on
<i>unit</i>	(Optional) Enter unit number

Command Mode

- /exec

```
show consistency-checker l2-tahoe switchport interface
```

show consistency-checker l2-tahoe switchport interface

show consistency-checker l2-tahoe switchport interface <if_name>

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
l2-tahoe	Verify l2 switchport parameters
switchport	Switchport Interface
interface	interface
<i>if_name</i>	Physical or Logical interface

Command Mode

- /exec

show consistency-checker l2 module

```
show consistency-checker l2 module <modnum> [ __readonly__ <l2entry> <header> TABLE_mac_address
<disp_mac_addr><disp_type><disp_vlan><disp_is_static><disp_age><disp_is_secure><disp_is_ntfy><disp_port>
]
```

Syntax Description

show	show
consistency-checker	Consistency Checker
l2	l2
module	Module number
<i>modnum</i>	Module Number
__readonly__	(Optional)
<i>header</i>	(Optional) Header
<i>l2entry</i>	(Optional) L2 Entry String
TABLE_mac_address	(Optional) Mac address table

Command Mode

- /exec

```
show consistency-checker l3-interface module
```

show consistency-checker l3-interface module

show consistency-checker l3-interface module <moduleid>

Syntax Description

show	Show running system information
module	Limit display to interfaces on module
<i>moduleid</i>	Enter module number
consistency-checker	Consistency Checker
l3-interface	Compares software and hardware properties of L3 interfaces

Command Mode

- /exec

show consistency-checker link-state module

show consistency-checker link-state module <module>

Syntax Description

show	Show running system information
module	Limit display to interfaces on module
<i>module</i>	Enter module number
consistency-checker	Consistency Checker
link-state	Compares software and hardware link state of interfaces

Command Mode

- /exec

show consistency-checker membership port-channels

show consistency-checker membership port-channels

show consistency-checker membership port-channels [interface <ch-id>]

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
membership	Check various memberships
port-channels	Verifies port channel membership in the hardware
interface	(Optional) Port-channel number
<i>ch-id</i>	(Optional) Port-Channel name

Command Mode

- /exec

show consistency-checker membership vlan

show consistency-checker membership vlan <vlanid> [private-vlan [interface [<int-id> | <ch-id>]]]

Syntax Description

show	Show running system information
vlan	Verifies vlan membership in the hardware
<i>vlanid</i>	Enter vlan id
consistency-checker	Consistency Checker
membership	Check various memberships
private-vlan	(Optional) Check private-vlan primary vlan
interface	(Optional) Interface
<i>int-id</i>	(Optional) Interface name
<i>ch-id</i>	(Optional) Port-Channel name

Command Mode

- /exec

```
show consistency-checker nxapi interface
```

show consistency-checker nxapi interface

show consistency-checker nxapi interface

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
nxapi	Nxapi
interface	Compares interface configs between dme and pss

Command Mode

- /exec

show consistency-checker pacl module

show consistency-checker pacl module <module>

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
pacl	Verify pacl programming in the hardware
module	Limit display to L2 interfaces on this module
<i>module</i>	Enter module number

Command Mode

- /exec

show consistency-checker pacl port-channels

show consistency-checker pacl port-channels

show consistency-checker pacl port-channels [interface <ch-id>]

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
pacl	Verify pacl programming in the hardware
port-channels	Verifies port channel pacl programming in the hardware
interface	(Optional) Port-channel number
<i>ch-id</i>	(Optional) Port-Channel name

Command Mode

- /exec

show consistency-checker port-security

show consistency-checker port-security [module <mod> [interface <intf-id>]]

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
port-security	Port-Security information
module	(Optional) Module
interface	(Optional) Port-security interface
<i>intf-id</i>	(Optional) Port-security interface
<i>mod</i>	(Optional) Module Number

Command Mode

- /exec

```
show consistency-checker qinvni
```

show consistency-checker qinvni

show consistency-checker qinvni

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
qinvni	QinVNI consistency checker

Command Mode

- /exec

show consistency-checker racl module

show consistency-checker racl module <module>

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
racl	Verify racl programming in the hardware
module	Limit display to L3 interfaces on this module
<i>module</i>	Enter module number

Command Mode

- /exec

show consistency-checker racl port-channels

show consistency-checker racl port-channels

show consistency-checker racl port-channels [interface <ch-id>]

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
racl	Verify racl programming in the hardware
port-channels	Verifies port channel racl programming in the hardware
interface	(Optional) Port-channel number
<i>ch-id</i>	(Optional) Port-Channel name

Command Mode

- /exec

show consistency-checker stp-state vlan

show consistency-checker stp-state vlan <vlan>

Syntax Description

show	Show running system information
vlan	Verifies spanning tree state in the hardware for all interfaces in the vlan
<i>vlan</i>	Enter vlan id
consistency-checker	Consistency Checker
stp-state	Verify spanning tree state in the hardware

Command Mode

- /exec

```
show consistency-checker vacl
```

show consistency-checker vacl

show consistency-checker vacl

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vacl	Verify vacl programming in the hardware

Command Mode

- /exec

show consistency-checker vxlan bgp

show consistency-checker vxlan bgp

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN consistency checker
bgp	Display VxLAN BGP EVPN consistency information

Command Mode

- /exec

```
show consistency-checker vxlan interface
```

show consistency-checker vxlan interface

show consistency-checker vxlan interface { <int-id> | <ch-id> }

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN VLANs
interface	Interface
<i>int-id</i>	Interface
<i>ch-id</i>	Port-Channel name

Command Mode

- /exec

show consistency-checker vxlan mh mac-addresses

show consistency-checker vxlan mh mac-addresses

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN VLANs
mh	VxLAN BGP EVPN Multi Homing CC commands
mac-addresses	Check mac address consistency between L2RIB and L2FM

Command Mode

- /exec

```
show consistency-checker vxlan mh pathlist
```

show consistency-checker vxlan mh pathlist

show consistency-checker vxlan mh pathlist

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN VLANs
mh	VxLAN BGP EVPN Multi Homing CC commands
pathlist	Check Vxlan BGP EVPN MH Control plane and resultant pathlists consistency

Command Mode

- /exec

show consistency-checker vxlan peers

show consistency-checker vxlan peers

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN consistency checker
peers	Display VxLAN peers consistency information

Command Mode

- /exec

```
show consistency-checker vxlan routes
```

show consistency-checker vxlan routes

show consistency-checker vxlan routes

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN consistency checker
routes	Display VxLAN L3 routes consistency information

Command Mode

- /exec

show consistency-checker vxlan selective-qinvni

show consistency-checker vxlan selective-qinvni

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN VLANs
selective-qinvni	Selective QinVNI consistency checker

Command Mode

- /exec

```
show consistency-checker vxlan selective-qinvni interface
```

show consistency-checker vxlan selective-qinvni interface

show consistency-checker vxlan selective-qinvni interface { <int-id> | <ch-id> }

Syntax Description

show	Show running system information
consistency-checker	Consistency Checker
vxlan	VxLAN VLANs
selective-qinvni	Selective QinVNI consistency checker
interface	Interface
<i>int-id</i>	Interface
<i>ch-id</i>	Port-Channel name

Command Mode

- /exec

show consistency-checker vxlan vlan

show consistency-checker vxlan vlan <vlanid>

Syntax Description

show	Show running system information
vxlan	VxLAN VLANs
vlan	Verifies flood list programming for vxlan vlans
consistency-checker	Consistency Checker
<i>vlanid</i>	Enter vlan id

Command Mode

- /exec

```
show controller accounting log
```

show controller accounting log

show controller <ctrl-id> accounting log

Syntax Description

show	Show running system information
controller	Controller command
<i>ctrl-id</i>	Controller id value
accounting	Accounting
log	Show log information

Command Mode

- /exec

show copp diff profile profile2

show copp diff profile <profile_type> [prior-ver] profile2 <profile_type2>

Syntax Description

show	Show running system information
copp	Control-Plane Policing
diff	Difference between CoPP Profiles
profile	CoPP Profile
<i>profile_type</i>	CoPP Profile Types
prior-ver	(Optional) Previous Configured Version
profile2	CoPP Profile
<i>profile_type2</i>	CoPP Profile Types

Command Mode

- /exec

show copp profile

show copp profile

```
show copp profile { strict | moderate | lenient | dense } [ __readonly__ <acl-type> <acl-grp-name> {
<permitdeny> { <proto_str> | <proto> | <ip> | <ipv6> } { <src_any> | <src_ip_prefix> | <src_ip_addr>
<src_ip_mask> | <src_ipv6_prefix> | <src_addrgrp> | <src_mac_any> | <src_mac_addr> <src_mac_mask>
} [ <src_port_op> { <src_port1_str> | <src_port1_num> } [ <src_port2_str> | <src_port2_num> ] | <src_portgrp>
] { <dest_any> | <dest_ip_prefix> | <dest_ip_addr> <dest_ip_mask> | <dest_ipv6_prefix> | <dest_addrgrp>
| <dest_mac_any> | <dest_mac_addr> <dest_mac_mask> } [ <dest_port_op> { <dest_port1_str> |
<dest_port1_num> } [ <dest_port2_str> | <dest_port2_num> ] | <dest_portgrp> ] [ { <icmp_type> [
<icmp_code> ] | <icmp_str> } | { <icmpv6_type> [ <icmpv6_code> ] | <icmpv6_str> } ] <eth_proto> }
<newline> <cmap_name> <opt_any_or_all> { { access_grp <acc_grp_name> } | { redirect
<opt_match_redirect> } | { exception <opt_match_except> } { protocol <opt_match_protocol> } } +
<pmap_name> <class-name> <cir> <opt_kbps_mbps_gb_ps_cir> { percent <cir-perc> } <pir>
<opt_kbps_mbps_gb_ps_pir> { percent1 <pir-perc> } <bc> <opt_kbytes_mbytes_gbytes_bc> <be>
<opt_kbytes_mbytes_gbytes_be> { { <opt_drop_transmit_conform> } | { set-cos-transmit <set-cos-val> } |
{ set-dscp-transmit <set-dscp-val> } | { set-prec-transmit <set-prec-val> } } { { <opt_drop_transmit_exceed>
} | { set dscp1 dscp2 table cir-markdown-map } } { { <opt_drop_transmit_violate> } | { set1 dscp3 dscp4
table1 pir-markdown-map } } { { cos [ inner ] <cos-val> } | { dscp [ tunnel ] <dscp-val> } } | { precedence [
tunnel1 ] <prec-val> } <policer_show_flags> <set_vld_flg> } + ]
```

Syntax Description

show	Show running system information
copp	Control-Plane Policing
profile	CoPP Profile
strict	display strict profile
moderate	display moderate profile
lenient	display lenient profile
dense	display dense profile
<u>__readonly__</u>	(Optional) Read Only
<i>acl-type</i>	(Optional) access-list type
<i>acl-grp-name</i>	(Optional) name of the access-list
<i>permitdeny</i>	(Optional) permit/deny
<i>proto</i>	(Optional) A protocol number
<i>proto_str</i>	(Optional) Protocol name
<i>ip</i>	(Optional) IP
<i>ipv6</i>	(Optional) IPV6
<i>src_any</i>	(Optional) SRCAny

<i>dest_any</i>	(Optional) DESTAny
<i>src_ip_prefix</i>	(Optional) Source IP prefix
<i>src_ip_addr</i>	(Optional) Source IP address
<i>src_ip_mask</i>	(Optional) Source IP mask
<i>src_mac_addr</i>	(Optional) Source MAC address
<i>src_mac_mask</i>	(Optional) Source MAC mask
<i>src_mac_any</i>	(Optional) SRCMACAny
<i>dest_ip_prefix</i>	(Optional) Destination IP prefix
<i>dest_ip_addr</i>	(Optional) Destination IP address
<i>dest_ip_mask</i>	(Optional) Destination IP mask
<i>dest_mac_addr</i>	(Optional) Destination MAC address
<i>dest_mac_mask</i>	(Optional) Destination MAC mask
<i>dest_mac_any</i>	(Optional) DESTMACAny
<i>src_port_op</i>	(Optional) Source Port operator
<i>dest_port_op</i>	(Optional) Destination Port operator
<i>src_port1_str</i>	(Optional) Source port name
<i>src_port1_num</i>	(Optional) Source port number
<i>src_port2_str</i>	(Optional) Source port name
<i>src_port2_num</i>	(Optional) Source port number
<i>dest_port1_str</i>	(Optional) Destination port name
<i>dest_port1_num</i>	(Optional) Destination port number
<i>dest_port2_str</i>	(Optional) Destination port name
<i>dest_port2_num</i>	(Optional) Destination port number
<i>icmp_type</i>	(Optional) ICMP type
<i>icmp_code</i>	(Optional) ICMP code
<i>icmp_str</i>	(Optional) ICMP message
<i>icmpv6_type</i>	(Optional) ICMP type
<i>icmpv6_code</i>	(Optional) ICMP code
<i>icmpv6_str</i>	(Optional) ICMP message

show copp profile

<i>src_addrgrp</i>	(Optional) Source address group
<i>dest_addrgrp</i>	(Optional) Destination address group
<i>src_portgrp</i>	(Optional) Source port group
<i>dest_portgrp</i>	(Optional) Destination port group
<i>eth_proto</i>	(Optional) MAC protocol number
<i>newline</i>	(Optional) newline between access-list and cmaps
<i>cmap_name</i>	(Optional) Name of the class-map
<i>opt_any_or_all</i>	(Optional) Enter match-any or match-all
<i>access_grp</i>	(Optional)
<i>acc_grp_name</i>	(Optional)
<i>redirect</i>	(Optional)
<i>opt_match_redirect</i>	(Optional) Match criteria for redirected packets
<i>exception</i>	(Optional)
<i>opt_match_excpt</i>	(Optional) Match criteria for exception packets
<i>protocol</i>	(Optional)
<i>opt_match_protocol</i>	(Optional) Match criteria for protocol packets
<i>pmap_name</i>	(Optional) Name of the Policy-map
<i>class-name</i>	(Optional) Name if the policy member
<i>opt_kbps_mbps_gbps_pps_cir</i>	(Optional) Units
<i>percent</i>	(Optional)
<i>opt_kbps_mbps_gbps_pps_pir</i>	(Optional) Units
<i>percent1</i>	(Optional)
<i>opt_kbytes_mbytes_gbytes_bc</i>	(Optional) Units
<i>opt_kbytes_mbytes_gbytes_be</i>	(Optional) Units
<i>opt_drop_transmit_conform</i>	(Optional) Set the action
<i>set-cos-transmit</i>	(Optional)
<i>set-cos-val</i>	(Optional) Conform action cos val
<i>set-dscp-transmit</i>	(Optional)
<i>set-dscp-val</i>	(Optional) Conform action dscp val

set-prec-transmit	(Optional)
<i>set-prec-val</i>	(Optional) Conform action prec val
<i>opt_drop_transmit_exceed</i>	(Optional) Set the action
set	(Optional)
dscp1	(Optional)
dscp2	(Optional)
table	(Optional)
cir-markdown-map	(Optional)
<i>opt_drop_transmit_violate</i>	(Optional) Set the action
set1	(Optional)
dscp3	(Optional)
dscp4	(Optional)
table1	(Optional)
pir-markdown-map	(Optional)
cos	(Optional)
inner	(Optional)
<i>cos-val</i>	(Optional) Set cos val
dscp	(Optional)
tunnel	(Optional)
<i>dscp-val</i>	(Optional) Set dscp val
precedence	(Optional)
tunnel1	(Optional)
<i>prec-val</i>	(Optional) Set prec val
<i>policer_show_flags</i>	(Optional) Policer show flags
<i>set_vld_flg</i>	(Optional) Set valid flag

Command Mode

- /exec

show copp status

show copp status

```
show copp status [ __readonly__ { last_config_operation <last_cfg_oper> } { last_config_operation_time
<last_cfg_oper_time> } { last_config_operation_status <last_cfg_oper_status> } [ last_config_operation_error
<last_cfg_oper_error> ] { service_policy <srv_policy> } ]
```

Syntax Description

show	Show running system information
copp	Control-Plane Policing
status	Show the internal status of CoPP
<u>__readonly__</u>	(Optional)
last_config_operation	(Optional) last config operation
<i>last_cfg_oper</i>	(Optional) last config operation
last_config_operation_time	(Optional) timestamp of last config operation
<i>last_cfg_oper_time</i>	(Optional) timestamp of last config operation
last_config_operation_status	(Optional) status of last config operation
<i>last_cfg_oper_status</i>	(Optional) status of last config operation
last_config_operation_error_time	(Optional) timestamp of last config operation's error
<i>last_cfg_oper_error_time</i>	(Optional) timestamp of last config operation's error
last_config_operation_error	(Optional) last config operation's error
<i>last_cfg_oper_error</i>	(Optional) last config operation's error
service_policy	(Optional) policy-map attached to control-plane
<i>srv_policy</i>	(Optional) policy-map attached to control-plane

Command Mode

- /exec

show copyright

show copyright [__readonly__ { <content> }]

Syntax Description

show	Show running system information
copyright	Copyright information
__readonly__	(Optional)
<i>content</i>	(Optional) Copyrigh information

Command Mode

- /exec

show cores

show cores

```
show cores [ vdc-all | { vdc [ <e-vdc2> | <vdc-id> ] } ] [ __readonly__ { [ TABLE_cores <vdc_id> <module_id><instance><process_name><pid><sys_time> ] } ]
```

Syntax Description

show	Show running system information
cores	show all core dumps for the current vdc
vdc-all	(Optional) show core dumps from all vdcs
vdc	(Optional) show all core dumps for the vdc
__readonly__	(Optional)
TABLE_cores	(Optional)
<i>vdc_id</i>	(Optional) vdc id
<i>module_id</i>	(Optional) module id
<i>instance</i>	(Optional) instance number
<i>process_name</i>	(Optional) name of the process
<i>pid</i>	(Optional) process id
<i>sys_time</i>	(Optional) core generate time
<i>e-vdc2</i>	(Optional) Enter VDC <vdc-id>
<i>vdc-id</i>	(Optional) vdc number

Command Mode

- /exec

show crypto ca certificates

```
show crypto ca certificates <s0> [ __readonly__ { Trustpoint <trustpoint> } [ { Certificate <certificate> } ] [ { TABLE_ca_cert_chains <index><ca_certificate> } ] ]
```

Syntax Description

show	Show running system information
crypto	show crypto configuration
ca	show trustpoint configuration
certificates	show various certificates
<i>s0</i>	trustpoint label
<u>__readonly__</u>	(Optional)
Trustpoint	(Optional) Trustpoint
<i>trustpoint</i>	(Optional) Trustpoint
Certificate	(Optional) Certificate
<i>certificate</i>	(Optional) Certificate
TABLE_ca_cert_chains	(Optional) Table of CA certificates in chain
<i>index</i>	(Optional) CA Certificate Index
<i>ca_certificate</i>	(Optional) CA certificate

Command Mode

- /exec

show crypto ca certificates

show crypto ca certificates

```
show crypto ca certificates [ __readonly__ [ { TABLE_ca_certificates <trustpoint> [ <certificate> ] [ { TABLE_ca_cert_chains <index> <ca_certificate> } ] } ]]
```

Syntax Description

show	Show running system information
crypto	show crypto configuration
ca	show trustpoint configuration
certificates	show various certificates
<u>__readonly__</u>	(Optional)
TABLE_ca_certificates	(Optional) Table of CA certificates
<i>trustpoint</i>	(Optional) Trustpoint name
<i>certificate</i>	(Optional) Certificate
TABLE_ca_cert_chains	(Optional) Table of CA certificates in chain
<i>index</i>	(Optional) CA Certificate Index
<i>ca_certificate</i>	(Optional) CA certificate

Command Mode

- /exec

show crypto ca certstore

```
show crypto ca certstore [ __readonly__ { certstore_lookup <lookup_type> } ]
```

Syntax Description

show	Show running system information
crypto	Show crypto configuration
ca	show crypto ca configuration
certstore	Show the configured certstore
__readonly__	(Optional)
certstore_lookup	(Optional) Certificate strore lookup
<i>lookup_type</i>	(Optional) Lookup type

Command Mode

- /exec

show crypto ca crl

show crypto ca crl <s0> [__readonly__ { Trustpoint <trustpoint> } [{ CRL <crl> }]]

Syntax Description

show	Show running system information
crypto	show crypto configuration
ca	show trustpoint configuration
crl	show CRL
<i>s0</i>	trustpoint label
__readonly__	(Optional)
Trustpoint	(Optional) Trustpoint
<i>trustpoint</i>	(Optional) Trustpoint
CRL	(Optional) Certificate Revocation List
<i>crl</i>	(Optional) Certificate Revocation List

Command Mode

- /exec

show crypto ca remote-certstore

```
show crypto ca remote-certstore [ __readonly__ { remote_cert_store <rem_cert_store> } [ { crl_timer <crltimer> } { ldap_server_group <ldap_server_grp> } ] ]
```

Syntax Description

show	Show running system information
crypto	Show crypto configuration
ca	show crypto ca configuration
remote-certstore	Show remote certstore configuration
__readonly__	(Optional)
remote_cert_store	(Optional) Remote cert store
rem_cert_store	(Optional) Remote certificate store
crl_timer	(Optional) CRL timer
crltimer	(Optional) CRL timer
ldap_server_group	(Optional) LDAP Server Group
ldap_server_grp	(Optional) LDAP Server Group

Command Mode

- /exec

show crypto ca trustpoints

show crypto ca trustpoints

```
show crypto ca trustpoints [ __readonly__ [ { TABLE_ca_truspoints <trustpoint> <key-pair> [ { TABLE_revocation_methods <revocation-method> } ] [ <ocsp-url> ] } ]]
```

Syntax Description

show	Show running system information
crypto	show crypto configuration
ca	show trustpoint configuration
trustpoints	show trustpoint configuration
<u>__readonly__</u>	(Optional)
<i>trustpoint</i>	(Optional) Trustpoint
<i>key-pair</i>	(Optional) Key pair
TABLE_revocation_methods	(Optional) Table of revocation methods
<i>revocation-method</i>	(Optional) Revocation mehtod
<i>ocsp-url</i>	(Optional) OCSP URL
TABLE_ca_truspoints	(Optional) Table of CA trustpoints

Command Mode

- /exec

show crypto certificatemap

```
show crypto certificatemap [ __readonly__ [ { TABLE_certmap <map_name> <subject_name>
<alternate_email> <alternate_upn> } ] ]
```

Syntax Description

show	Show running system information
crypto	show crypto configuration
certificatemap	show certificatemap filters
__readonly__	(Optional)
TABLE_certmap	(Optional) Table of Certificate Map
<i>map_name</i>	(Optional) Map name
<i>subject_name</i>	(Optional) Subject name
<i>alternate_email</i>	(Optional) Alternate Email
<i>alternate_upn</i>	(Optional) Alternate UPN

Command Mode

- /exec

```
show crypto key mypubkey rsa
```

show crypto key mypubkey rsa

show crypto key mypubkey rsa [__readonly__ [{ TABLE_rsa_keys <key_label> <key_size> <exportable> <err_string> }]]

Syntax Description

show	Show running system information
crypto	show crypto configuration
key	show key configuration
mypubkey	show my public keys configuration
rsa	show my rsa public keys configuration
<u>__readonly__</u>	(Optional)
TABLE_rsa_keys	(Optional) Table of RSA keys
<i>key_label</i>	(Optional) Key Lable
<i>key_size</i>	(Optional) Key size
<i>exportable</i>	(Optional) Exportable
<i>err_string</i>	(Optional) Error String

Command Mode

- /exec

show crypto ssh-auth-map

```
show crypto ssh-auth-map [ __readonly__ [ { TABLE_ssh_auth_map <issuer_name> <map1> [ <map2> ] } ] ]
```

Syntax Description

show	Show running system information
crypto	show crypto configuration
ssh-auth-map	show mapping filters applied for ssh authentication
__readonly__	(Optional)
TABLE_ssh_auth_map	(Optional) Table of SSH Auth MAP
<i>issuer_name</i>	(Optional) Issuer Name
<i>map1</i>	(Optional) Map 1
<i>map2</i>	(Optional) Map 2

Command Mode

- /exec

show cts

show cts

`show cts [__readonly__ <device-id> <cache_en> <num-dot1x> <num-man> <sgt>]`

Syntax Description

<code>cts</code>	Show CTS global configuration
<code>__readonly__</code>	(Optional)
<code>device-id</code>	(Optional) name
<code>cache_en</code>	(Optional) enable/disable
<code>num-dot1x</code>	(Optional) number of interfaces in dot1x mode
<code>num-man</code>	(Optional) number of interfaces in manual mode
<code>sgt</code>	(Optional)

Command Mode

- /exec

show current

show current

Syntax Description

show	Display region configurations
current	Display mst configuration currently used

Command Mode

- /exec/configure/spanning-tree/mst/configuration

show current