



## V Commands

---

- [vlan, page 2](#)

# vlan

To assign a VLAN to a configured VLAN group, use the **vlan** command. To remove the VLAN from the VLAN group, use the **no** form of this command.

**verify** *vlan-range*

## Syntax Description

|                   |  |
|-------------------|--|
| <i>vlan-range</i> | Specifies the VLAN range. The range is from 1 to 3967. |
|-------------------|--|

## Command Default

None.

## Command Modes

VLAN group configuration mode (config-vlan-group)

## Command History

| Release            | Modification                 |
|--------------------|------------------------------|
| Cisco NX-OS 8.0(1) | This command was introduced. |

## Usage Guidelines

Catena must be enabled and configured before using this command. For more information about these task, see "[Cisco Nexus 7000 Series Switches Configuration Guide: The Catena Solution.](#)"

## Examples

The following example shows how to assign a VLAN to a VLAN group:

```
switch# configure terminal
switch(config)# catena vlan-group vgl
switch(config-vlan-group)# vlan 10
switch(config-vlan-group)# vlan 20-30
switch(config-vlan-group)# vlan 40,50
```

## Related Commands

| Command                           | Description           |
|-----------------------------------|-----------------------|
| <a href="#">catena vlan-group</a> | Creates a VLAN group. |