



## U Commands

---

- [unsuppress-map, page 2](#)

## unsuppress-map

To unsuppress routes that are suppressed by using the aggregate-address command, use the **unsuppress-map** command.

**unsuppress-map** *map-name*

### Syntax Description

<i>map-name</i>	Map name.
-----------------	-----------

### Command Default

None

### Command Modes

config-router-neighbor-af mode

### Command History

Release	Modification
6.2(2)	This command was introduced.

### Usage Guidelines

This command requires the Enterprise Services license.

### Examples

This example shows how to unsuppress routes that are suppressed by using the aggregate-address command:

```
switch# configure terminal
switch(config)# ip prefix-list IPLIST seq 5 permit 10.1.1.0/24
switch(config)# route-map UNSUPPRESS_MAP permit 10
switch(config-route-map)# match ip address prefix-list IPLIST
switch(config-route-map)# exit
switch(config)# router bgp 100
switch(config-router)# address-family ipv4 unicast
switch(config-router-af)# aggregate-address 10.1.1.0/16 summary-only
switch(config-router-af)# exit
switch(config-router)# neighbor 10.2.3.4 remote-as 300
switch(config-router-neighbor)# address-family ipv4 unicast
switch(config-router-neighbor-af)# unsuppress-map UNSUPPRESS_MAP
switch(config-router-neighbor-af)#
```

### Related Commands

Command	Description
<b>address-family ipv4 unicast</b>	Enters IPv4 unicast address family mode.