



## V Show Commands

---

- [show vdc](#), on page 4
- [show vdc current-vdc](#), on page 6
- [show vdc fcoe-vlan-range](#), on page 7
- [show vdc internal bitmaps](#), on page 8
- [show vdc internal create\\_possible](#), on page 9
- [show vdc internal errors](#), on page 10
- [show vdc internal event-history vdc\\_id](#), on page 11
- [show vdc internal mac\\_address\\_table](#), on page 12
- [show vdc internal mem-stats](#), on page 13
- [show vdc internal msgs](#), on page 14
- [show vdc internal pss](#), on page 15
- [show vdc resource](#), on page 16
- [show vdc resource](#), on page 17
- [show vdc resource template](#), on page 18
- [show version](#), on page 19
- [show version compatibility](#), on page 21
- [show version image](#), on page 22
- [show version internal build-identifier](#), on page 23
- [show version module](#), on page 24
- [show version module epld](#), on page 25
- [show virtual-service](#), on page 26
- [show virtual-service storage pool list](#), on page 29
- [show virtual-service tech-support](#), on page 30
- [show virtual-service utilization name](#), on page 31
- [show virtual-service version](#), on page 33
- [show vlan access-list](#), on page 34
- [show vlan access-map](#), on page 38
- [show vlan counters](#), on page 39
- [show vlan dot1Q tag native](#), on page 40
- [show vlan filter](#), on page 41
- [show vlan id counters](#), on page 42
- [show vlan id vn-segment](#), on page 43
- [show vlan mib private-vlan type](#), on page 44

- [show vlan private-vlan, on page 45](#)
- [show vlan private-vlan interface host, on page 46](#)
- [show vlan private-vlan interface mapping, on page 47](#)
- [show vlan private-vlan interface mode, on page 48](#)
- [show vlan private-vlan interface trunk, on page 49](#)
- [show vlan private-vlan mapping, on page 50](#)
- [show vlan private-vlan type, on page 51](#)
- [show vmtracker, on page 52](#)
- [show vmtracker certificate, on page 53](#)
- [show vmtracker fabric auto-config, on page 54](#)
- [show vmtracker status, on page 55](#)
- [show vpc, on page 56](#)
- [show vpc, on page 59](#)
- [show vpc consistency-parameters, on page 60](#)
- [show vpc consistency-parameters vlans, on page 61](#)
- [show vpc internal peer-keepalive snmp parame-table domain-id, on page 62](#)
- [show vpc internal peer-keepalive snmp status-table domain-id, on page 64](#)
- [show vpc internal role snmp role-table domain-id, on page 65](#)
- [show vpc internal statistics peer-keepalive snmp stats-table domain-id, on page 66](#)
- [show vpc internal status snmp host-link-table domain-id vpc-id, on page 67](#)
- [show vpc internal status snmp peer-link-table domain-id, on page 68](#)
- [show vpc orphan-ports, on page 69](#)
- [show vpc peer-keepalive, on page 70](#)
- [show vpc role, on page 71](#)
- [show vpc statistics peer-keepalive, on page 72](#)
- [show vpc statistics vpc, on page 73](#)
- [show vrf, on page 74](#)
- [show vrf, on page 76](#)
- [show vrf topology, on page 77](#)
- [show vrrp, on page 78](#)
- [show vrrp bfd-sessions, on page 80](#)
- [show vrrp internal configuration event-history errors, on page 81](#)
- [show vrrp internal configuration event-history msgs, on page 82](#)
- [show vrrp internal debugs, on page 83](#)
- [show vrrp internal engine event-history errors, on page 84](#)
- [show vrrp internal engine event-history msgs, on page 85](#)
- [show vrrp internal info, on page 86](#)
- [show vrrp internal info global, on page 87](#)
- [show vrrp internal mem-stats, on page 88](#)
- [show vrrpv3, on page 89](#)
- [show vrrpv3 internal debug, on page 92](#)
- [show vrrpv3 internal high-availability database, on page 93](#)
- [show vrrpv3 internal mem-stats, on page 94](#)
- [show vrss client, on page 95](#)
- [show vrss pathway, on page 96](#)
- [show vrss pathway address, on page 97](#)

- [show vrss server, on page 98](#)
- [show vrss tag, on page 99](#)
- [show vxlan, on page 100](#)

show vdc

# show vdc

```
{ show vdc [ <e-vdc2> ] [ feature-set | detail | membership [ all | status | module <module> ] | shared membership ] [ __readonly__ [ detail2 ] [ <swmode> ] { TABLE_vdc <vdc_id><vdc_name><state><mac><hap><sw><boot_order> [ <prio><prio_per> ] [ <create_time> ] [ <reload_count> ] [ <restart_count> ] [ <restart_time> ] [ <restart_reason> ] <vtype><lc-support> [ TABLE_fs <fs_id><fs_name> ] [ TABLE_port <port-list> ] } ] }
```

## Syntax Description

<b>Syntax Description</b>	
show	Show Virtual Device Contexts
vdc	Show Virtual Device Contexts
<i>e-vdc2</i>	(Optional) Enter Virtual Device Context <vdc-id>
detail	(Optional) Show detailed vdc information
membership	(Optional) Show vdc interface membership information
shared	(Optional) Show the shared interfaces in a vdc
membership	(Optional) Show the shared interfaces in a vdc
module	(Optional) Show vdc interface membership information for a specific module only
<i>module</i>	(Optional) Show vdc interface membership information for a specific module only
status	(Optional) Show vdc related port-status
feature-set	(Optional) Show vdc feature-set information
all	(Optional) Show offline modules as well
<u>__readonly__</u>	(Optional) Read Only
detail2	(Optional)
<i>swmode</i>	(Optional)
TABLE_vdc	(Optional)
<i>vdc_id</i>	(Optional) vdc-id
TABLE_port	(Optional)
<i>port-list</i>	(Optional) port membership for VDC
<i>vdc_name</i>	(Optional) vdc-name
<i>state</i>	(Optional) state
<i>mac</i>	(Optional) mac address for VDC

<i>hap</i>	(Optional) hap policy
<i>sw</i>	(Optional) sw policy
<i>vtype</i>	(Optional)
<i>lc-support</i>	(Optional)
<i>create_time</i>	(Optional)
<i>reload_count</i>	(Optional)
<i>restart_count</i>	(Optional)
<i>restart_time</i>	(Optional)
<i>restart_reason</i>	(Optional)
TABLE_fs	(Optional)
<i>fs_id</i>	(Optional) fs id
<i>fs_name</i>	(Optional)
<i>boot_order</i>	(Optional)
<i>prio</i>	(Optional)
<i>prio_per</i>	(Optional)

**Command Mode**

- /exec

**show vdc current-vdc**

```
show vdc current-vdc [ __readonly__ <mode> <name> ]
```

**Syntax Description**

Syntax Description	
show	Show Virtual Device Contexts
vdc	Show Virtual Device Contexts
current-vdc	Show which vdc you are currently in
__readonly__	(Optional) Read Only
<i>mode</i>	(Optional) cli mode
<i>name</i>	(Optional) vdc name

**Command Mode**

- /exec

# show vdc fcoe-vlan-range

show vdc fcoe-vlan-range [ \_\_readonly\_\_ <fcoe-vdc> [ <fcoe-vlans> ] [ <sharing-vdcs> ] ]

## Syntax Description

<b>Syntax Description</b>	
show	Show Virtual Device Contexts
vdc	Show Virtual Device Contexts
fcoe-vlan-range	vlans reserved for FCoE
__readonly__	(Optional) Read Only
<i>fcoe-vdc</i>	(Optional)
<i>sharing-vdcs</i>	(Optional)
<i>fcoe-vlans</i>	(Optional)

## Command Mode

- /exec

show vdc internal bitmaps

# show vdc internal bitmaps

show vdc internal bitmaps

## Syntax Description

### Syntax Description

show	Show Virtual Device Contexts
vdc	Show Virtual Device Contexts
internal	Show Internal info for vdc_mgr
bitmaps	Kernel bitmap tables

## Command Mode

- /exec

# show vdc internal create\_possible

show vdc internal create\_possible

## Syntax Description

Syntax Description		
show	Show running system information	
vdc	Show Virtual Device Contexts	
internal	Show Internal info for vdc_mgr	
create_possible	Is creation possible	

## Command Mode

- /exec

**show vdc internal errors**

# show vdc internal errors

show vdc internal [ event-history ] errors

## Syntax Description

Syntax Description		
show	Show running system information	
vdc	Show information about vdc_mgr	
internal	Show internal vdc_mgr information	
event-history	(Optional) Show various event logs of vdc_mgr	
errors	Show error logs of vdc_mgr	

## Command Mode

- /exec

# show vdc internal event-history vdc\_id

show vdc internal event-history vdc\_id <new\_id>

## Syntax Description

Syntax Description		
show	Show running system information	
vdc	Show Virtual Device Contexts	
internal	Show internal vdc_mgr information	
event-history	Show various event logs of vdc_mgr	
vdc_id	Enter Virtual Device Context <vdc-id>	
<i>new_id</i>	Enter vdc id	

## Command Mode

- /exec

```
■ show vdc internal mac_address_table
```

## show vdc internal mac\_address\_table

show vdc internal mac\_address\_table [ \_\_readonly\_\_ <mac> ]

### Syntax Description

Syntax Description	
show	Show Virtual Device Contexts
vdc	Show Virtual Device Contexts
internal	Show Internal info for vdc_mgr
mac_address_table	Table of mac addresses
__readonly__	(Optional) Read Only
<i>mac</i>	(Optional) mac address for VDC

### Command Mode

- /exec

# show vdc internal mem-stats

show vdc internal mem-stats [ detail ]

## Syntax Description

Syntax Description	
show	Show running system information
vdc	Show information about vdc_mgr
internal	Show internal vdc_mgr information
mem-stats	Show memory allocation statistics of vdc_mgr
detail	(Optional) Show detail memstats for F_Port Server

## Command Mode

- /exec

**show vdc internal msgs**

## show vdc internal msgs

show vdc internal [ event-history ] msgs

### Syntax Description

Syntax Description		
show	Show running system information	
vdc	Show information about vdc_mgr	
internal	Show internal vdc_mgr information	
event-history	(Optional) Show various event logs of vdc_mgr	
msgs	Show various message logs of vdc_mgr	

### Command Mode

- /exec

# show vdc internal pss

```
show vdc internal { { pss [ { <e-vdc2> | interface [ <interface-name> ] } ] } | port-hash }
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vdc	Show Virtual Device Contexts
internal	Show Internal info for vdc_mgr
pss	Show Internal info pss for vdc_mgr
<i>e-vdc2</i>	(Optional) Enter Virtual Device Context <vdc-id>
interface	(Optional) Show Internal info for vdc_mgr
<i>interface-name</i>	(Optional) Show Internal info for vdc_mgr
port-hash	vdc_mgr port hash table

## Command Mode

- /exec

show vdc resource

# show vdc resource

```
show vdc resource [ <res-mgr-res-known-name> ] [ detail | hidden-too | with-flags ] + [ __readonly__ {  
    TABLE_resource <resource_name> <total_used> <total_unused> <total_free> <total_avail> <total> [  
    TABLE_vdc_resource_across_vdcs <vdc_name> <min> <max> <used> <unused> <free> ] } ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vdc	Show Virtual Device Contexts
resource	Show resource configuration across VDCs
<i>res-mgr-res-known-name</i>	(Optional) Resource name
detail	(Optional) Show detail resource configuration
hidden-too	(Optional) Also show hidden resources
with-flags	(Optional) Also show resource flags
__readonly__	(Optional) Read Only
TABLE_resource	(Optional)
<i>resource_name</i>	(Optional) Resource Name
<i>total_used</i>	(Optional) Resource current usage for all VDC
<i>total_unused</i>	(Optional) Resources currently reserved but not used across all VDC
<i>total_free</i>	(Optional) Resource current free for all VDC
<i>total_avail</i>	(Optional) Resource current available across all VDC
<i>total</i>	(Optional) Resources grand total
TABLE_vdc_resource_across_vdcs	(Optional)
<i>vdc_name</i>	(Optional) VDC name
<i>min</i>	(Optional) Resource min configuration
<i>max</i>	(Optional) Resource max configuration
<i>used</i>	(Optional) Resource current usage for this VDC
<i>unused</i>	(Optional) Resource reserved for this VDC but currently not used
<i>free</i>	(Optional) Resource current free for this VDC

## Command Mode

- /exec

# show vdc resource

```
show vdc <id> resource [ <res-mgr-res-known-name> ] [ __readonly__ { TABLE_vdc_resource_single_vdc
<res_name> <min> <max> <used> <unused> <free> } ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vdc	Show Virtual Device Contexts
<i>id</i>	Enter Virtual Device Context <vdc-id>
resource	Show resource configuration for VDC
<i>res-mgr-res-known-name</i>	(Optional) Resource name
<u>__readonly__</u>	(Optional) Read Only
<i>res_name</i>	(Optional) Resource Name
<i>min</i>	(Optional) Resource min configuration
<i>max</i>	(Optional) Resource max configuration
<i>used</i>	(Optional) Resource current usage for this VDC
<i>unused</i>	(Optional) Resource reserved for this VDC but currently not used
<i>free</i>	(Optional) Resource current free for this VDC
TABLE_vdc_resource_single_vdc	(Optional)

## Command Mode

- /exec

show vdc resource template

## show vdc resource template

```
show vdc resource template [ <res-mgr-template-known-name-all> ] [ __readonly__ TABLE_template
<template_name> { TABLE_resource <resource_name> <min> <max> } ]
```

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vdc	Show Virtual Device Contexts
resource	Show resource configuration for VDC
template	Resource template configuration
<i>res-mgr-template-known-name-all</i>	(Optional) Resource template name
<i>__readonly__</i>	(Optional) Read Only
<i>TABLE_template</i>	(Optional)
<i>template_name</i>	(Optional) Resource Template Name
<i>TABLE_resource</i>	(Optional)
<i>resource_name</i>	(Optional) Resource Name
<i>min</i>	(Optional) Resource min configuration
<i>max</i>	(Optional) Resource max configuration

### Command Mode

- /exec

# show version

```
show version [ __readonly__ <header_str> <bios_ver_str> [ <loader_ver_str> ] <kickstart_ver_str> [ <sys_ver_str> ] <bios_cmpl_time> <kick_file_name> <kick_cmpl_time> <kick_tmstmp> [ <isan_file_name> ] [ <isan_cmpl_time> ] [ <isan_tmstmp> ] [ <boot_lxc_mode> ] <chassis_id> <module_id> <cpu_name> <memory> <mem_type> <proc_board_id> <host_name> <bootflash_size> [ <slot0_size> ] <kern_uptm_days> <kern_uptm_hrs> <kern_uptm_mins> <kern_uptm_secs> [ <rr_usecs> ] [ <rr_ctime> ] <rr_reason> <rr_sys_ver> <rr_service> [ TABLE_smu_list <install_smu_id> + ] [ TABLE_package_list <package_id> ] <manufacturer> ]
```

## Syntax Description

### Syntax Description

show	
version	Show the software version
__readonly__	(Optional)
header_str	(Optional)
bios_ver_str	(Optional)
loader_ver_str	(Optional)
kickstart_ver_str	(Optional)
sys_ver_str	(Optional)
bios_cmpl_time	(Optional)
kick_file_name	(Optional)
kick_cmpl_time	(Optional)
kick_tmstmp	(Optional)
isan_file_name	(Optional)
isan_cmpl_time	(Optional)
isan_tmstmp	(Optional)
boot_lxc_mode	(Optional)
chassis_id	(Optional)
module_id	(Optional)
cpu_name	(Optional)
memory	(Optional)
mem_type	(Optional)

**show version**

<i>proc_board_id</i>	(Optional)
<i>host_name</i>	(Optional)
<i>bootflash_size</i>	(Optional)
<i>slot0_size</i>	(Optional)
<i>kern_uptm_days</i>	(Optional)
<i>kern_uptm_hrs</i>	(Optional)
<i>kern_uptm_mins</i>	(Optional)
<i>kern_uptm_secs</i>	(Optional)
<i>rr_usecs</i>	(Optional)
<i>rr_ctime</i>	(Optional)
<i>rr_reason</i>	(Optional)
<i>rr_sys_ver</i>	(Optional)
<i>rr_service</i>	(Optional)
TABLE_smu_list	(Optional)
<i>install_smu_id</i>	(Optional)
TABLE_package_list	(Optional)
<i>package_id</i>	(Optional) Package name
<i>manufacturer</i>	(Optional)

**Command Mode**

- /exec

# show version compatibility

show version compatibility <uri0>

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
version	Show the software version
compatibility	Show the software compatibility matrix with given image
<i>uri0</i>	Enter URI

## Command Mode

- /exec

**show version image**

# show version image

show version image <uri0>

## Syntax Description

### Syntax Description

show Show running system information

version Show the software version

image Show the software version of a given image

*uri0* Enter URI

## Command Mode

- /exec

# show version internal build-identifier

show version internal build-identifier

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
version	Show the software version
internal	internal commands
build-identifier	Show the build id of currently running software versions

## Command Mode

- /exec

show version module

## show version module

```
show version module <module> [ __readonly__ { TABLE_version <slot> <type> <sw> <interim> <bios> } ]
```

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
version	Show the software version
module	Show the software version of a Module
<i>module</i>	Enter module number
__readonly__	(Optional)
TABLE_version	(Optional) Show version info
<i>slot</i>	(Optional) Slot
<i>type</i>	(Optional) image type
<i>sw</i>	(Optional) SW version
<i>interim</i>	(Optional) SW interim version
<i>bios</i>	(Optional) BIOS version

### Command Mode

- /exec

# show version module epld

show version module <module> epld

## Syntax Description

### Syntax Description

show	Show running system information
version	Show the software version
module	Show the software version of a Module
<i>module</i>	Enter module number
epld	Show a module's current EPLD versions

## Command Mode

- /exec

show virtual-service

# show virtual-service

```
show virtual-service [ { list } | { global } | { detail [ name <virt_serv_name> ] } | { core [ name
<virt_serv_name_core> ] } ][ __readonly__ [ <infrastructure_major_version><infrastructure_minor_version>
<total_virtual_services_installed><total_virtual_services_activated><maximum_vcpus_per_virtual_service>
<machine_types_supported><machine_types_disabled> TABLE_resource_limits <media_name><quota>
<committed><available> ] [ TABLE_list <name><status><package_name> ] [ TABLE_detail <name>
<package_name><application_name><application_version><application_description><key_type>
<signing_method><licensing_name><licensing_version><ova_path><state><disk_reservation>
<memory_reservation><cpu_reservation> TABLE_attached_devices <type><name><alias> ] [ TABLE_core
<name><name_core> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
virtual-service	Display virtualization service information
global	(Optional) Virtual service global information
list	(Optional) List virtual services
detail	(Optional) Detailed information
core	(Optional) Core information
name	(Optional) Information for a specific virtual service
<i>virt_serv_name</i>	(Optional) Name of a virtual service
<i>virt_serv_name_core</i>	(Optional) Name of a virtual service
<u>__readonly__</u>	(Optional) Read Only
<i>infrastructure_major_version</i>	(Optional) Infrastructure major version
<i>infrastructure_minor_version</i>	(Optional) Infrastructure minor version
<i>total_virtual_services_installed</i>	(Optional) Total virtual services installed
<i>total_virtual_services_activated</i>	(Optional) Total virtual services activated
<i>maximum_vcpus_per_virtual_service</i>	(Optional) Maximum VCPUs per virtual service
<i>machine_types_supported</i>	(Optional) Machine types supported
<i>machine_types_disabled</i>	(Optional) Machine types disabled
TABLE_resource_limits	(Optional) Virtual service global resource limits
<i>media_name</i>	(Optional) Resource name
<i>quota</i>	(Optional) Resource Virtualization quota

<i>committed</i>	(Optional) Resource Virtualization committed
<i>available</i>	(Optional) Resource Virtualization available
<i>TABLE_list</i>	(Optional) Virtual service list table
<i>name</i>	(Optional) Virtual service name
<i>status</i>	(Optional) Virtual service status
<i>package_name</i>	(Optional) Virtual service package name
<i>TABLE_detail</i>	(Optional) Virtual service detail table
<i>name</i>	(Optional) Virtual service name
<i>package_name</i>	(Optional) Virtual service package name
<i>application_name</i>	(Optional) Name of the application
<i>application_version</i>	(Optional) Version of the application
<i>application_description</i>	(Optional) Description of the application
<i>key_type</i>	(Optional) Virtual service key type
<i>signing_method</i>	(Optional) Method used to sign the package
<i>licensing_name</i>	(Optional) Name of the license
<i>licensing_version</i>	(Optional) Version of the license
<i>ova_path</i>	(Optional) Virtual service OVA path
<i>state</i>	(Optional) Virtual service state
<i>disk_reservation</i>	(Optional) Virtual service disk reservation
<i>memory_reservation</i>	(Optional) Virtual service memory reservation
<i>cpu_reservation</i>	(Optional) Virtual service CPU reservation
<i>TABLE_attached_devices</i>	(Optional) Attached devices table
<i>type</i>	(Optional) Type of the attached device
<i>name</i>	(Optional) Name of the attached device
<i>alias</i>	(Optional) Alias for the attached device
<i>TABLE_core</i>	(Optional) Virtual service core table
<i>name</i>	(Optional) Virtual service name
<i>name_core</i>	(Optional) Name of core

**Command Mode**

show virtual-service

- /exec

# show virtual-service storage pool list

```
show virtual-service storage pool list [ __readonly__ [ TABLE_storage <pool_name> <pool_type> <pool_path> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
virtual-service	Display virtualization service storage pool information
storage	Storage information about virtual service
pool	Storage pool information about virtual service
list	List storage pool for virtual service
__readonly__	(Optional) Read Only
TABLE_storage	(Optional) Virtual service storage pool list table
<i>pool_name</i>	(Optional) Virtual service storage pool name
<i>pool_type</i>	(Optional) Virtual service storage pool type
<i>pool_path</i>	(Optional) Virtual service storage pool path

## Command Mode

- /exec

```
show virtual-service tech-support
```

# show virtual-service tech-support

show virtual-service tech-support

## Syntax Description

### Syntax Description

show Show running system information

virtual-service Gather information for virtualization services trouble shooting

tech-support Gather information for trouble shooting

## Command Mode

- /exec

# show virtual-service utilization name

```
show virtual-service utilization name <virt_serv_name> [ __readonly__ [ TABLE_storage <name> <alias> <rd_bytes> <wr_bytes> <rd_requests> <wr_requests> <errors> <capacity> <used> <available> <usage> ] [ TABLE_network <name> <alias> <rx_packets> <tx_packets> <rx_bytes> <tx_bytes> <rx_drops> <tx_drops> <rx_errors> <tx_errors> ] [ TABLE_memory <allocation> <used> ] [ TABLE_cpu <request> <actual> <state> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
virtual-service	Display virtualization service utilization information
utilization	Utilization information about virtual service
name	Utilization of a virtual service
<i>virt_serv_name</i>	Name of a virtual service
<i>__readonly__</i>	(Optional) Read Only
TABLE_storage	(Optional) Virtual service storage utilization
<i>name</i>	(Optional) storage device name
<i>alias</i>	(Optional) storage device alias
<i>rd_bytes</i>	(Optional) Read Bytes
<i>wr_bytes</i>	(Optional) Write Bytes
<i>rd_requests</i>	(Optional) Read requests
<i>wr_requests</i>	(Optional) Write requests
<i>errors</i>	(Optional) errors
<i>capacity</i>	(Optional) Capacity 1k blocks
<i>used</i>	(Optional) Used 1k blocks
<i>available</i>	(Optional) Available 1k blocks
<i>usage</i>	(Optional) Usage
TABLE_network	(Optional) Virtual service network utilization
<i>name</i>	(Optional) network device name
<i>alias</i>	(Optional) network device alias
<i>rx_packets</i>	(Optional) Received packets

show virtual-service utilization name

<i>tx_packets</i>	(Optional) Transmitted packets
<i>rx_bytes</i>	(Optional) Received bytes
<i>tx_bytes</i>	(Optional) Transmitted bytes
<i>rx_drops</i>	(Optional) Received drops
<i>tx_drops</i>	(Optional) Transmitted drops
<i>rx_errors</i>	(Optional) Received errors
<i>tx_errors</i>	(Optional) Trnasmitted errors
TABLE_memory	(Optional) Virtual service memory utilization
<i>allocation</i>	(Optional) Memory allocation
<i>used</i>	(Optional) Memory used
TABLE_cpu	(Optional) Virtual service cpu utilization
<i>request</i>	(Optional) Requested Application Utilization
<i>actual</i>	(Optional) Actual Application Utilization
<i>state</i>	(Optional) CPU state

#### Command Mode

- /exec

# show virtual-service version

```
show virtual-service version { { installed } | { name <virt_serv_name> installed } } [ __readonly__ <virt_service_name> <application_name> <application_version> ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
virtual-service	Display virtualization service version information
version	Version information about virtual service
installed	Installed version
name	Version of a virtual service
<i>virt_serv_name</i>	Name of a virtual service
<i>__readonly__</i>	(Optional) Read Only
<i>virt_service_name</i>	(Optional) Virtual service name
<i>application_name</i>	(Optional) Application name
<i>application_version</i>	(Optional) Application version

## Command Mode

- /exec

show vlan access-list

# show vlan access-list

```
show vlan access-list <name> [ <inp_seqno> ] [ __readonly__ TABLE_vacl <vacl_name> [ <vacl_seqno> ]
[ TABLE_list<ip_ipv6_mac><acl_name> [ TABLE_seqno<seqno> { <permitdeny> [ <proto_str> | <proto>
| <ip> | <ipv6> ] { <src_any> | <src_ip_prefix> | <src_ip_addr> <src_ip_mask> | <src_ipv6_prefix> |
<src_ipv6_addr> <src_ipv6_mask> | <mac_src> <mac_src_wild> | <src_addrgrp> } [ <src_port_op> [
<src_port1_str> ] { <src_port1_num> } [ <src_port2_str> | <src_port2_num> ] | <src_portgrp> ] { <dest_any>
| <dest_ip_prefix> | <dest_ip_addr> <dest_ip_mask> | <dest_ipv6_prefix> | <dest_ipv6_addr>
<dest_ipv6_mask> | <mac_dest> <mac_dest_wild> | <dest_addrgrp> } [ <dest_port_op> [ <dest_port1_str>
] { <dest_port1_num> } [ <dest_port2_str> | <dest_port2_num> ] | <dest_portgrp> ] [ { <icmp_type> [
<icmp_code> ] | <icmp_str> } | { <icmpv6_type> [ <icmpv6_code> ] | <icmpv6_str> } ] [ <igmp_type> |
<igmp_type_str> ] [ [ <precedence> | <precedence_str> ] [ <tos> | <tos_str> ] | [ <dscp> | <dscp_str> ] | [
<ttl> ] [ <log> ] [ <udfs> ] [ <capture_session> ] [ <fragments> ] [ <plen_op> <plen1> [ <plen2> ] ] [ <urg>
] [ <ack> ] [ <psh> ] [ <rst> ] [ <syn> ] [ <fin> ] [ <established> ] [ <http-method> | <http_opt_str> ] [
<tcp-option-length> ] [ <tcp-flags-mask> ] [ <flow_label> ] [ <timerange> ] [ <eth_proto> | <eth_proto_str>
] [ <vlan> ] [ <cos> ] [ <match_count> ] | [ <nve_vni> ] | <remark> } ] [ <action> <actionid> ] ] ]]
```

## Syntax Description

### Syntax Description

show	Show running system information
vlan	Vlan commands
access-list	Vlan access list
<i>name</i>	List name
<i>inp_seqno</i>	(Optional) Sequence number
<i>vacl_name</i>	(Optional) List name
<i>readonly</i>	(Optional)
<i>vacl_seqno</i>	(Optional) Sequence number
TABLE_vacl	(Optional)
TABLE_list	(Optional)
<i>ip_ipv6_mac</i>	(Optional) IP/iIPV6/MAC
<i>acl_name</i>	(Optional) Access list name
<i>seqno</i>	(Optional) Sequence number
<i>permitdeny</i>	(Optional) Permit/deny
<i>proto</i>	(Optional) A protocol number
TABLE_seqno	(Optional)
<i>proto_str</i>	(Optional) Protocol name

<i>ip</i>	(Optional) IP
<i>ipv6</i>	(Optional) IPV6
<i>src_any</i>	(Optional) SRCAny
<i>dest_any</i>	(Optional) DESTAny
<i>src_ip_prefix</i>	(Optional) Source IP prefix
<i>src_ip_addr</i>	(Optional) Source IP address
<i>src_ip_mask</i>	(Optional) Source IP mask
<i>mac_src</i>	(Optional) Source MAC address
<i>mac_src_wild</i>	(Optional) Source MAC mask
<i>dest_ip_prefix</i>	(Optional) Destination IP prefix
<i>dest_ip_addr</i>	(Optional) Destination IP address
<i>dest_ip_mask</i>	(Optional) Destination IP mask
<i>mac_dest</i>	(Optional) Destination MAC address
<i>mac_dest_wild</i>	(Optional) Destination MAC mask
<i>src_port_op</i>	(Optional) Source Port operator
<i>dest_port_op</i>	(Optional) Destination Port operator
<i>src_port1_str</i>	(Optional) Source port name
<i>src_port1_num</i>	(Optional) Source port number
<i>src_port2_str</i>	(Optional) Source port name
<i>src_port2_num</i>	(Optional) Source port number
<i>dest_port1_str</i>	(Optional) Destination port name
<i>dest_port1_num</i>	(Optional) Destination port number
<i>dest_port2_str</i>	(Optional) Destination port name
<i>dest_port2_num</i>	(Optional) Destination port number
<i>icmp_type</i>	(Optional) ICMP type
<i>icmp_code</i>	(Optional) ICMP code
<i>icmp_str</i>	(Optional) ICMP message
<i>icmpv6_type</i>	(Optional) ICMP type
<i>icmpv6_code</i>	(Optional) ICMP code

**show vlan access-list**

<i>icmpv6_str</i>	(Optional) ICMP message
<i>igmp_type</i>	(Optional) IGMP type
<i>igmp_type_str</i>	(Optional) IGMP type String
<i>precedence</i>	(Optional) precedence
<i>precedence_str</i>	(Optional) precedence string
<i>tos</i>	(Optional) tos
<i>tos_str</i>	(Optional) tos string
<i>dscp</i>	(Optional) dscp
<i>dscp_str</i>	(Optional) dscp string
<i>udfs</i>	(Optional) udfs string
<i>ttl</i>	(Optional) ttl
<i>capture_session</i>	(Optional) capture session
<i>log</i>	(Optional) Log
<i>fragments</i>	(Optional) Fragments
<i>urg</i>	(Optional) URG
<i>ack</i>	(Optional) ACK
<i>psh</i>	(Optional) PSH
<i>rst</i>	(Optional) RST
<i>syn</i>	(Optional) SYN
<i>fin</i>	(Optional) FIN
<i>established</i>	(Optional) ESTABLISHED
<i>http-method</i>	(Optional) http-method
<i>http_opt_str</i>	(Optional) http_option string
<i>tcp-option-length</i>	(Optional) TCP Option size
<i>tcp-flags-mask</i>	(Optional) TCP Flags mask
<i>flow_label</i>	(Optional) IPv6 flow label
<i>timerange</i>	(Optional) Time-range
<i>eth_proto</i>	(Optional) MAC protocol number
<i>eth_proto_str</i>	(Optional) MAC protocol name

<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
<i>match_count</i>	(Optional) Number of packets matching the ACL
<i>nve_vni</i>	(Optional) nve vni
<i>remark</i>	(Optional) Remark String
<i>src_addrgrp</i>	(Optional) Source address group
<i>dest_addrgrp</i>	(Optional) Destination address group
<i>src_portgrp</i>	(Optional) Source port group
<i>dest_portgrp</i>	(Optional) Destination port group
<i>plen_op</i>	(Optional) Source Port operator
<i>plen1</i>	(Optional) Packet length minimum
<i>plen2</i>	(Optional) packet length maximum
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

**Command Mode**

- /exec

show vlan access-map

## show vlan access-map

```
show vlan access-map [ <name> ] [ __readonly__ [ TABLE_vacl <vacl_name> [ TABLE_seqno [ <seqno> ] [ <ip_ipv6_mac> { <match_name> } +[ <action_drop> ][ <action_log> ][ <action_fwd> ][ <action_capture> ] [ <action_redirect> <intf> ] ] [ <statistics> ] ] ] ]
```

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	Vlan commands
access-map	List VLAN access maps
<i>name</i>	(Optional) List name
<i>vacl_name</i>	(Optional) List name
<u>__readonly__</u>	(Optional)
<i>seqno</i>	(Optional) Sequence number
TABLE_vacl	(Optional)
TABLE_seqno	(Optional)
<i>ip_ipv6_mac</i>	(Optional) IP/iIPV6/MAC
<i>match_name</i>	(Optional) Access list name
<i>action_drop</i>	(Optional) DROP
<i>action_log</i>	(Optional) LOG
<i>action_fwd</i>	(Optional) FWD
<i>action_capture</i>	(Optional) CAPTURE
<i>action_redirect</i>	(Optional) REDIRECT
<i>intf</i>	(Optional) Interface traffic is redirected to
<i>statistics</i>	(Optional) STATISTICS

### Command Mode

- /exec

# show vlan counters

```
show vlan counters [ __readonly__ { TABLE_vlancounters <vlanshowbr-vlanid> [ <l2_ing_unicast_b> ] [ <l2_ing_unicast_p> ] [ <l2_ing_multicast_b> ] [ <l2_ing_multicast_p> ] [ <l2_ing_broadcast_b> ] [ <l2_ing_broadcast_p> ] [ <l2_egress_unicast_b> ] [ <l2_egress_unicast_p> ] [ <l3_unicast_recv_b> ] [ <l3_unicast_recv_p> ] [ <total_recv_b> ] [ <total_recv_p> ] [ <total_sent_b> ] [ <total_sent_p> ] } ]
```

## Syntax Description

<b>Syntax Description</b>	show	Show running system information
	vlan	Vlan commands
	counters	display counters
	__readonly__	(Optional) Read Only
	TABLE_vlancounters	(Optional) vlan counters table format
	vlanshowbr-vlanid	(Optional) VLAN brief VLAN ID
	l2_ing_unicast_b	(Optional) L2 Ingress unicast octets
	l2_ing_unicast_p	(Optional) L2 Ingress unicast packets
	l2_ing_multicast_b	(Optional) L2 Ingress multicast octets
	l2_ing_multicast_p	(Optional) L2 Ingress multicast packets
	l2_ing_broadcast_b	(Optional) L2 Ingress broadcast octets
	l2_ing_broadcast_p	(Optional) L2 Ingress broadcast packets
	l2_egress_unicast_b	(Optional) L2 Egress unicast octets
	l2_egress_unicast_p	(Optional) L2 Egress unicast packets
	l3_unicast_recv_b	(Optional) L3 unicast octets in
	l3_unicast_recv_p	(Optional) L3 unicast packets in
	total_recv_b	(Optional) Total octets in
	total_recv_p	(Optional) Total packets in
	total_sent_b	(Optional) Total octets out
	total_sent_p	(Optional) Total packets out

## Command Mode

- /exec

**show vlan dot1Q tag native**

## show vlan dot1Q tag native

show vlan dot1Q tag native [ \_\_readonly\_\_ <tag\_native\_mode> ]

### Syntax Description

Syntax Description		
show	Show running system information	
vlan	VTP VLAN status	
dot1Q	Display dot1q parameters	
tag	Display tag parameters	
native	Display native vlan tagging	
__readonly__	(Optional) Read Only	
<i>tag_native_mode</i>	(Optional) Native vlan tagging mode	

### Command Mode

- /exec

# show vlan filter

```
show vlan filter [ access-map <name> | vlan <vlan> ] [ __readonly__ TABLE_vlan_filter <name> <configured_vlans> ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	Vlan commands
filter	Information about VLAN filters
access-map	(Optional) Show the VLANs where an access-map is applied
<i>name</i>	(Optional) List name
vlan	(Optional) Show the access-map applied to a VLAN
<i>vlan</i>	(Optional) VLAN number
__readonly__	(Optional)
TABLE_vlan_filter	(Optional)
<i>configured_vlans</i>	(Optional) VLAN numbers

## Command Mode

- /exec

**show vlan id counters**

# show vlan id counters

```
show vlan id <vlan-id> counters [ __readonly__ { TABLE_vlancounters <vlanshowbr-vlanid> [
<l2_ing_unicast_b> ] [ <l2_ing_unicast_p> ] [ <l2_ing_multicast_b> ] [ <l2_ing_multicast_p> ] [ <l2_ing_broadcast_b> ]
[ <l2_ing_broadcast_p> ] [ <l2_egress_unicast_b> ] [ <l2_egress_unicast_p> ] [ <total_rcv_b> ] [ <total_rcv_p> ] [
<total_sent_b> ] [ <total_sent_p> ] } ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	Vlan commands
id	VLAN status by VLAN id
counters	display counters
<i>vlan-id</i>	VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
<u>__readonly__</u>	(Optional) Read Only
TABLE_vlancounters	(Optional) vlan counters table format
<i>vlanshowbr-vlanid</i>	(Optional) VLAN brief VLAN ID
<i>l2_ing_unicast_b</i>	(Optional) L2 Ingress unicast octets
<i>l2_ing_unicast_p</i>	(Optional) L2 Ingress unicast packets
<i>l2_ing_multicast_b</i>	(Optional) L2 Ingress multicast octets
<i>l2_ing_multicast_p</i>	(Optional) L2 Ingress multicast packets
<i>l2_ing_broadcast_b</i>	(Optional) L2 Ingress broadcast octets
<i>l2_ing_broadcast_p</i>	(Optional) L2 Ingress broadcast packets
<i>l2_egress_unicast_b</i>	(Optional) L2 Egress unicast octets
<i>l2_egress_unicast_p</i>	(Optional) L2 Egress unicast packets
<i>total_rcv_b</i>	(Optional) Total octets in
<i>total_rcv_p</i>	(Optional) Total packets in
<i>total_sent_b</i>	(Optional) Total octets out
<i>total_sent_p</i>	(Optional) Total packets out

## Command Mode

- /exec

# show vlan id vn-segment

```
show vlan id <vlan-id> vn-segment [ __readonly__ <vlanshowinfo-segid-hdr> { TABLE_seginfoid
<vlanshowinfo-seg-vlanid> <vlanshowinfo-segment-id> } <show-end> [ <true-end> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
id	VLAN status by VLAN id
vn-segment	Show vn-segment mapping
<i>vlan-id</i>	VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
<u>__readonly__</u>	(Optional) Read Only
TABLE_seginfoid	(Optional) Segment id information table format
<i>vlanshowinfo-segid-hdr</i>	(Optional) Vlan info segment id header
<i>vlanshowinfo-seg-vlanid</i>	(Optional) Vlan info VLAN ID
<i>vlanshowinfo-segment-id</i>	(Optional) Vlan info SEGMENT ID
<i>show-end</i>	(Optional) Show vlan end marker
<i>true-end</i>	(Optional) Show vlan end marker

## Command Mode

- /exec

show vlan mib private-vlan type

## show vlan mib private-vlan type

show vlan [ id <vlan-id> ] mib private-vlan type [ \_\_readonly\_\_ <start> <vlan> <pvlan-type> <primary> ]

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
id	(Optional) VLAN status by VLAN id
<i>vlan-id</i>	(Optional) VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
private-vlan	Private VLAN information
type	Private VLAN type information
mib	mib
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>vlan</i>	(Optional) vlan
<i>pvlan-type</i>	(Optional) PVLAN Type
<i>primary</i>	(Optional) associated to primary

### Command Mode

- /exec

# show vlan private-vlan

show vlan [ id <vlan-id> ] private-vlan [ \_\_readonly\_\_ [ { TABLE\_pvlan\_primary <vlan-key> [ <primary> ] [ <secondary> ] <pvlan-type> [ <ports> + ] } ] ]

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
id	(Optional) VLAN status by VLAN id
<i>vlan-id</i>	(Optional) VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
private-vlan	Private VLAN information
__readonly__	(Optional) Read Only
TABLE_pvlan_primary	(Optional) Pvlan primary vlan table
<i>vlan-key</i>	(Optional) Vlan key
<i>primary</i>	(Optional) Primary VLAN
<i>secondary</i>	(Optional) Secondary VLAN
<i>pvlan-type</i>	(Optional) PVLAN Type
<i>ports</i>	(Optional) Port list

## Command Mode

- /exec

show vlan private-vlan interface host

## show vlan private-vlan interface host

show vlan private-vlan interface [ <if> ] host [ next <data> ] [ \_\_readonly\_\_ <start> <interface-id> <secondary-vlan> ]

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
private-vlan	Private VLAN information
interface	Show interface status and information
<i>if</i>	(Optional) Interface id
host	private-vlan host
next	(Optional) next-entry
<i>data</i>	(Optional) ignore junk value
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>interface-id</i>	(Optional) Interface
<i>secondary-vlan</i>	(Optional) Secondary Vlan

### Command Mode

- /exec

# show vlan private-vlan interface mapping

show vlan private-vlan interface [ <if> ] mapping [ \_\_readonly\_\_ <start> <interface-id> <multi-primary> <secondary-vlan> <two-way> ]

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
private-vlan	Private VLAN information
interface	Show interface status and information
<i>if</i>	(Optional) Interface id
mapping	private-vlan mapping
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>interface-id</i>	(Optional) Interface
<i>multi-primary</i>	(Optional) multiple primay capable
<i>secondary-vlan</i>	(Optional) seconadry vlans bitmap
<i>two-way</i>	(Optional) multiple primay capable

## Command Mode

- /exec

show vlan private-vlan interface mode

## show vlan private-vlan interface mode

show vlan private-vlan interface [ <if> ] mode [ next <data> ] [ \_\_readonly\_\_ <start> <interface-id> <port-mode> ]

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
private-vlan	Private VLAN information
interface	Show interface status and information
<i>if</i>	(Optional) Interface id
mode	private-vlan port mode
next	(Optional) next-entry
<i>data</i>	(Optional) ignore junk value
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>interface-id</i>	(Optional) Interface
<i>port-mode</i>	(Optional) Port mode

### Command Mode

- /exec

# show vlan private-vlan interface trunk

show vlan private-vlan interface [ <if> ] trunk [ \_\_readonly\_\_ <start> <interface-id> <dynamic-state> <encap-type> <native-vlan> <secondary-vlans> <normal-vlans> <dynamic-status> <encap-oper-type> ]

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
private-vlan	Private VLAN information
interface	Show interface status and information
<i>if</i>	(Optional) Interface id
trunk	pvlan trunk
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>interface-id</i>	(Optional) Interface
<i>dynamic-state</i>	(Optional) dynamic state
<i>encap-type</i>	(Optional) encapsulation type
<i>native-vlan</i>	(Optional) native vlan
<i>secondary-vlans</i>	(Optional) secondary vlans
<i>normal-vlans</i>	(Optional) normal vlans
<i>dynamic-status</i>	(Optional) dynamic status
<i>encap-oper-type</i>	(Optional) encap oper type

## Command Mode

- /exec

show vlan private-vlan mapping

# show vlan private-vlan mapping

show vlan [ id <vlan-id> ] private-vlan mapping [ next <data> ] [ \_\_readonly\_\_ <start> <vlan-id> <primary> ]

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
id	(Optional) VLAN status by VLAN id
<i>vlan-id</i>	(Optional) VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
private-vlan	Private VLAN information
mapping	private-vlan mapping
next	(Optional) next-entry
<i>data</i>	(Optional) ignore junk value
__readonly__	(Optional) Read Only
<i>start</i>	(Optional) Start
<i>vlan-id</i>	(Optional) secondary
<i>primary</i>	(Optional) primary-vlan

## Command Mode

- /exec

# show vlan private-vlan type

```
show vlan [ id<vlan-id> ] private-vlan type [ __readonly__ [ { TABLE_pvlantype <vlan-num><pvlan-type> } ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vlan	VLAN status
id	(Optional) VLAN status by VLAN id
<i>vlan-id</i>	(Optional) VLAN ID 1-4094 or range(s): 1-5, 10 or 2-5,7-19
private-vlan	Private VLAN information
type	Private VLAN type information
__readonly__	(Optional) Read Only
TABLE_pvlantype	(Optional) Pvlan type table
<i>vlan-num</i>	(Optional) vlan
<i>pvlan-type</i>	(Optional) PVLAN Type

## Command Mode

- /exec

show vmtracker

# show vmtracker

```
show vmtracker [ connection <conn_name> ] { { info { { [ interface <intf_id> ] { summary | detail | host |  
vm | port-group } } | { vxlan-segment | vxlan-vms } } } | event-history }
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vmtracker	Show vmtracker info
connection	(Optional) Show vmtracker configured connections
<i>conn_name</i>	(Optional) Show vmtracker Connection name
info	Display vmtracker information
interface	(Optional) Display vmtracker interface information
<i>intf_id</i>	(Optional) Interface name to display
summary	Display a summary of vmtracker information
detail	Display vmtracker information details
host	Display vmtracker host information
vm	Display vmtracker related Virtual Machine information
port-group	Display vmtracker related port-group information
vxlan-segment	Print all segment info
vxlan-vms	Print all vm info
event-history	Display vmtracker related event-history

## Command Mode

- /exec

# show vmtracker certificate

show vmtracker certificate

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vmtracker	VMTRACKER commands
certificate	Show the default certificate used

## Command Mode

- /exec

show vmtracker fabric auto-config

# show vmtracker fabric auto-config

show vmtracker fabric auto-config [ interface <intf\_id> ] [ vlan <vlan\_id> ] [ status { success | pending | failure | skipped } ]

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vmtracker	VMTRACKER commands
fabric	VM Tracker Fabric paramters
auto-config	VM Tracker Fabric AutoConfiguration
interface	(Optional) Display vmtracker interface information
<i>intf_id</i>	(Optional) Interface name to display
vlan	(Optional) vlan to display
<i>vlan_id</i>	(Optional) VLAN ID 1-4094 or range(s) like: 1-5, 10 or 2-5,7-19
status	(Optional) Auto-config status
success	(Optional) Success
pending	(Optional) Pending
failure	(Optional) Failure
skipped	(Optional) Skipped

## Command Mode

- /exec

# show vmtracker status

```
show vmtracker [ connection <conn_name> ] status [ __readonly__ { TABLE_connection <name><host_or_ip> <conn_status> } ]
```

## Syntax Description

<b>Syntax Description</b>	
__readonly__	(Optional)
TABLE_connection	(Optional)
<i>name</i>	(Optional)
<i>host_or_ip</i>	(Optional)
<i>conn_status</i>	(Optional)
show	Show running system information
vmtracker	Show vmtracker info
connection	(Optional) Show vmtracker configured connections
<i>conn_name</i>	(Optional) Show vmtracker Connection name
status	Show vmtracker connection status

## Command Mode

- /exec

show vpc

# show vpc

```
show vpc [ brief ] [ __readonly__ <vpc-domain-id> [ <vpc-l2mp-switch-id> ] <vpc-peer-status>
<vpc-peer-status-reason> <vpc-peer-keepalive-status> [ <vpc-peer-l2mp-status> ] <vpc-peer-consistency> {
[ <vpc-peer-consistency-reason> ] [ <vpc-peer-vlan-peer-consistency> ] <vpc-peer-consistency-status> }
<vpc-type-2-consistency> { [ <vpc-type-2-consistency-reason> ] <vpc-type-2-consistency-status> } <vpc-role>
<num-of-vpcs> [ <track-obj> ] [ <peer-gateway> ] [ <peer-gateway-excluded-vlans> ]
<dual-active-excluded-vlans> <vpc-graceful-consistency-check-status> [ <vpc-auto-recovery-status> ] [
<vpc-delay-restore-status> ] [ <vpc-delay-restore-svi-status> ] [ <vpc-delay-peer-link-status> ]
<operational-l3-peer> [ <vpc-scale-high-status> ] [ <fp-enhanced-load-balancing> ] [
<vpc-per-vlan-peer-consistency> ] <vpc-peer-link-hdr> [ { TABLE_peerlink <peer-link-id> <peerlink-ifindex>
<peer-link-port-state> <peer-up-vlan-bitset> } ] <vpc-end> <vpc-hdr> [ <vpc-is-es> ] [ <vpc-not-es> ] [ {
TABLE_vpc <vpc-id> <vpc-ifindex> <vpc-port-state> <vpc-thru-peerlink> <vpc-consistency> { [
<vpc-consistency-reason> ] [ <vpc-consistency-status> ] } <up-vlan-bitset> <es-attr> } ] <vpc-end> ]
```

## Syntax Description

Syntax Description	
vpc	Virtual Port Channel configuration
brief	(Optional) Brief display of vPC status
__readonly__	(Optional) Read Only
TABLE_peerlink	(Optional) vPC peerlink table
TABLE_vpc	(Optional) vPC table
vpc-domain-id	(Optional) vPC domain id
vpc-l2mp-switch-id	(Optional) vPC+ switch ID
vpc-peer-status	(Optional) vPC peer status
vpc-peer-status-reason	(Optional) vPC peer status reason
vpc-peer-keepalive-status	(Optional) vpc peer keepalive status
vpc-peer-l2mp-status	(Optional) vPC fabricpath status
vpc-role	(Optional) vPC role
peer-gateway	(Optional) Peer gateway status
peer-gateway-excluded-vlans	(Optional) peer-gateway excluded VLANs
dual-active-excluded-vlans	(Optional) dual-active excluded VLANs
fp-enhanced-load-balancing	(Optional) Fabricpath enhanced load balancing status
num-of-vpcs	(Optional) Number of vPCs configured
track-obj	(Optional) Track object for vPC
vpc-graceful-consistency-check-status	(Optional) vPC graceful consistency check

<i>vpc-consistency</i>	(Optional) vPC global configuration consistency
<i>vpc-consistency-reason</i>	(Optional) vPC consistency reason
<i>vpc-consistency-status</i>	(Optional) vPC consistency reason
<i>vpc-peer-consistency</i>	(Optional) vPC global configuration consistency
<i>vpc-peer-consistency-reason</i>	(Optional) vPC consistency reason
<i>vpc-peer-consistency-status</i>	(Optional) vPC consistency reason
<i>vpc-per-vlan-peer-consistency</i>	(Optional) vPC per-vlan global configuration consistency
<i>vpc-type-2-consistency</i>	(Optional) vPC type-2 configuration consistency status
<i>vpc-type-2-consistency-reason</i>	(Optional) vPC type-2 configuration consistency reason
<i>vpc-type-2-consistency-status</i>	(Optional) vPC type-2 configuration consistency status
<i>operational-l3-peer</i>	(Optional) Operational Layer 3 peer status
<i>vpc-scale-high-status</i>	(Optional) vPC scale high status
<i>vpc-hdr</i>	(Optional) Start of vPC table
<i>vpc-is-es</i>	(Optional) Flag to indicate vPC+ complex
<i>vpc-not-es</i>	(Optional) Flag to indicate vPC complex
<i>vpc-peer-link-hdr</i>	(Optional) Start of vPC peer-link table
<i>vpc-thru-peerlink</i>	(Optional) vPC Routing through peerlink
<i>vpc-port-state</i>	(Optional) vPC port state
<i>vpc-end</i>	(Optional) End of table
<i>vpc-id</i>	(Optional) vPC id
<i>vpc-ifindex</i>	(Optional) vPC ifindex
<i>peer-link-id</i>	(Optional) peer link id
<i>peerlink-ifindex</i>	(Optional) peer link ifindex
<i>peer-link-port-state</i>	(Optional) peer-link port state
<i>peer-up-vlan-bitset</i>	(Optional) peer link UP VLAN bitset
<i>up-vlan-bitset</i>	(Optional) vPC UP VLAN bitset
<i>es-attr</i>	(Optional) vPC+ attributes
<i>vpc-auto-recovery-status</i>	(Optional) Auto-recovery status
<i>vpc-delay-restore-status</i>	(Optional) Delay-resotre status

**show vpc**

<i>vpc-delay-restore-svi-status</i>	(Optional) Dealy-restore-svi status
<i>vpc-delay-peer-link-status</i>	(Optional) Delay-peer-link status

**Command Mode**

- /exec

# show vpc

```
show vpc { <vpc-number> | brief vpc <vpc-number> } [ __readonly__ [ <vpc-hdr> ] [ <vpc-is-es> ] [ <vpc-not-es> ] [ TABLE_vpc <vpc-id><vpc-ifindex><vpc-port-state><vpc-thru-peerlink><vpc-consistency> { [ <vpc-consistency-reason> ] [ <vpc-consistency-status> ] } <up-vlan-bitset> <es-attr> ] <vpc-end> ]
```

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
brief	Brief display of vPC status
<i>vpc-number</i>	Enter a Virtual Port Channel number
__readonly__	(Optional) Read Only
<i>vpc-hdr</i>	(Optional) Start of vPC table
<i>vpc-is-es</i>	(Optional) Flag to indicate vPC+ complex
<i>vpc-not-es</i>	(Optional) Flag to indicate vPC complex
TABLE_vpc	(Optional) vPC table
<i>vpc-id</i>	(Optional) vPC id
<i>vpc-ifindex</i>	(Optional) vPC ifindex
<i>vpc-port-state</i>	(Optional) vPC port state
<i>vpc-thru-peerlink</i>	(Optional) vPC Routing through peerlink
<i>vpc-consistency</i>	(Optional) vPC global configuration consistency
<i>vpc-consistency-reason</i>	(Optional) vPC consistency reason
<i>vpc-consistency-status</i>	(Optional) vPC consistency reason
<i>up-vlan-bitset</i>	(Optional) vPC UP VLAN bitset
<i>es-attr</i>	(Optional) vPC+ attributes
<i>vpc-end</i>	(Optional) End of table

## Command Mode

- /exec

show vpc consistency-parameters

# show vpc consistency-parameters

```
show vpc consistency-parameters { global | interface <if> | vpc <vpc-num> } [ __readonly__  
TABLE_vpc_consistency <vpc-param-name><vpc-param-type><vpc-param-local-val><vpc-param-peer-val>  
]
```

## Syntax Description

Syntax Description	
vpc	Virtual Port Channel configuration
consistency-parameters	Show vPC Consistency Parameters
global	Global Parameters
<i>if</i>	
<i>vpc-num</i>	Enter a Virtual Port Channel number
<i>__readonly__</i>	(Optional) Read Only
TABLE_vpc_consistency	(Optional) vPC table
<i>vpc-param-name</i>	(Optional)
<i>vpc-param-type</i>	(Optional)
<i>vpc-param-local-val</i>	(Optional)
<i>vpc-param-peer-val</i>	(Optional)

## Command Mode

- /exec

# show vpc consistency-parameters vlans

show vpc consistency-parameters vlans [ \_\_readonly\_\_ TABLE\_vpc\_consistency <vpc-param-name> <vpc-param-type> [ <reason\_code> ] [ <syserr> ] <vpc-pass-vlans> [ <reason\_code> ] ]

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
consistency-parameters	Show vPC Consistency Parameters
vlans	vlans
__readonly__	(Optional) Read Only
TABLE_vpc_consistency	(Optional) vPC table
<i>vpc-param-name</i>	(Optional)
<i>vpc-param-type</i>	(Optional)
<i>vpc-pass-vlans</i>	(Optional)
<i>syserr</i>	(Optional) vPC consistency reason
<i>reason_code</i>	(Optional) vPC consistency reason

## Command Mode

- /exec

show vpc internal peer-keepalive snmp parame-table domain-id

## showvpcinternalpeer-keepalivesnmpparame-tabledomain-id

```
show vpc internal peer-keepalive snmp parame-table domain-id <id> [ __readonly__  
TABLE<cVpcPeerKeepAliveConfigTable <cVpcPeerKeepAliveConfigDomainID>  
<cVpcPeerKeepAliveDestAddrType><cVpcPeerKeepAliveDestAddr><cVpcPeerKeepAliveSourceAddrType>  
<cVpcPeerKeepAliveSourceAddr><cVpcPeerKeepAliveUdpPort><cVpcPeerKeepAliveInterval>  
<cVpcPeerKeepAliveTimeout><cVpcPeerKeepAliveHoldTimeout><cVpcPeerKeepAliveTos>  
<cVpcPeerKeepAlivePrecedence><cVpcPeerKeepAliveTosByte><cVpcPeerKeepAliveVrfName> ]
```

### Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
internal	Commands for internal use
peer-keepalive	vPC peer keep-alive
snmp	vPC keep-alive snmp information
parame-table	Peer keep-alive parameters table
domain-id	vPC domain ID
<i>id</i>	vPC domain ID value
<u>__readonly__</u>	(Optional) Read Only
TABLE<cVpcPeerKeepAliveConfigTable	(Optional) Keep-alive xml parameters table
<i>cVpcPeerKeepAliveConfigDomainID</i>	(Optional)
<i>cVpcPeerKeepAliveDestAddrType</i>	(Optional)
<i>cVpcPeerKeepAliveDestAddr</i>	(Optional)
<i>cVpcPeerKeepAliveSourceAddrType</i>	(Optional)
<i>cVpcPeerKeepAliveSourceAddr</i>	(Optional)
<i>cVpcPeerKeepAliveUdpPort</i>	(Optional)
<i>cVpcPeerKeepAliveInterval</i>	(Optional)
<i>cVpcPeerKeepAliveTimeout</i>	(Optional)
<i>cVpcPeerKeepAliveHoldTimeout</i>	(Optional)
<i>cVpcPeerKeepAliveTos</i>	(Optional)
<i>cVpcPeerKeepAlivePrecedence</i>	(Optional)
<i>cVpcPeerKeepAliveTosByte</i>	(Optional)
<i>cVpcPeerKeepAliveVrfName</i>	(Optional)

**Command Mode**

- /exec

show vpc internal peer-keepalive snmp status-table domain-id

## show vpc internal peer-keepalive snmp status-table domain-id

```
show vpc internal peer-keepalive snmp status-table domain-id <id> [ __readonly__  
TABLE-cVpcPeerKeepAliveTable <cVpcPeerKeepAliveDomainID><cVpcPeerKeepAliveStatus>  
<cVpcPeerKeepAliveTime><cVpcPeerKeepAliveMsgSendStatus><cVpcPeerKeepAliveMsgLastSendTime>  
<cVpcPeerKeepAliveMsgSendInterface><cVpcPeerKeepAliveMsgRcvrStatus>  
<cVpcPeerKeepAliveMsgLastReceiveTime><cVpcPeerKeepAliveMsgReceiveInterface> ]
```

### Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
internal	Commands for internal use
peer-keepalive	vPC peer keep-alive
snmp	vPC keep-alive snmp information
status-table	Peer keep-alive status table
domain-id	vPC domain ID
<i>id</i>	vPC domain ID value
__readonly__	(Optional) Read Only
TABLE-cVpcPeerKeepAliveTable	(Optional) Keep-alive xml status table
cVpcPeerKeepAliveDomainID	(Optional)
cVpcPeerKeepAliveStatus	(Optional)
cVpcPeerKeepAliveTime	(Optional)
cVpcPeerKeepAliveMsgSendStatus	(Optional)
cVpcPeerKeepAliveMsgLastSendTime	(Optional)
cVpcPeerKeepAliveMsgSendInterface	(Optional)
cVpcPeerKeepAliveMsgRcvrStatus	(Optional)
cVpcPeerKeepAliveMsgLastReceiveTime	(Optional)
cVpcPeerKeepAliveMsgReceiveInterface	(Optional)

### Command Mode

- /exec

# show vpc internal role snmp role-table domain-id

```
show vpc internal role snmp role-table domain-id <id> [ __readonly__ TABLE-cVpcRoleTable
<cVpcRoleDomainID> <cVpcRoleStatus> <cVpcDualActiveDetectionStatus>
<cVpcSystemAdminMacAddress> <cVpcSystemOperMacAddress> <cVpcLocalOperMacAddress>
<cVpcSystemAdminPriority> <cVpcSystemOperPriority> <cVpcLocalRoleAdminPriority>
<cVpcLocalRoleOperPriority> ]
```

## Syntax Description

<b>Syntax Description</b>	vpc	Virtual Port Channel configuration
	internal	Commands for internal use
	role	vPC peer role
	snmp	vPC role snmp information
	role-table	vPC role parameters table
	domain-id	vPC domain ID
	<i>id</i>	vPC domain ID value
	__readonly__	(Optional) Read Only
	TABLE-cVpcRoleTable	(Optional) vPC role xml table
	<i>cVpcRoleDomainID</i>	(Optional)
	<i>cVpcRoleStatus</i>	(Optional)
	<i>cVpcDualActiveDetectionStatus</i>	(Optional)
	<i>cVpcSystemAdminMacAddress</i>	(Optional)
	<i>cVpcSystemOperMacAddress</i>	(Optional)
	<i>cVpcLocalOperMacAddress</i>	(Optional)
	<i>cVpcSystemAdminPriority</i>	(Optional)
	<i>cVpcSystemOperPriority</i>	(Optional)
	<i>cVpcLocalRoleAdminPriority</i>	(Optional)
	<i>cVpcLocalRoleOperPriority</i>	(Optional)

## Command Mode

- /exec

```
show vpc internal statistics peer-keepalive snmp stats-table domain-id
```

# show vpc internal statistics peer-keepalive snmp stats-table domain-id

```
show vpc internal statistics peer-keepalive snmp stats-table domain-id <id> [ __readonly__  
TABLE-cVpcStatsPeerKeepAliveTable <cVpcStatsPeerKeepAliveDomainID>  
<cVpcStatsPeerKeepAliveMsgsSent> <cVpcStatsPeerKeepAliveMsgsRcved>  
<cVpcStatsPeerKeepAliveAvgInterval> <cVpcStatsPeerStatusChangeCount> ]
```

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
internal	Commands for internal use
statistics	vPC statistics
peer-keepalive	vPC peer keep-alive
snmp	vPC role snmp information
stats-table	vPC statistics peer-keepalive table
domain-id	vPC domain ID
<i>id</i>	vPC domain ID value
<u>__readonly__</u>	(Optional) Read Only
TABLE-cVpcStatsPeerKeepAliveTable	(Optional) vPC statistics xml table
<i>cVpcStatsPeerKeepAliveDomainID</i>	(Optional)
<i>cVpcStatsPeerKeepAliveMsgsSent</i>	(Optional)
<i>cVpcStatsPeerKeepAliveMsgsRcved</i>	(Optional)
<i>cVpcStatsPeerKeepAliveAvgInterval</i>	(Optional)
<i>cVpcStatsPeerStatusChangeCount</i>	(Optional)

## Command Mode

- /exec

# show vpc internal status snmp host-link-table domain-id vpc-id

show vpc internal status snmp host-link-table domain-id <did> vpc-id <vid> [ \_\_readonly\_\_  
 TABLE-cVpcStatusHostLinkTable <cVpcStatusHostLinkDomainID> <cVpcStatusHostLinkVpcID>  
 <cVpcStatusHostLinkIfIndex> <cVpcStatusHostLinkStatus> <cVpcStatusHostLinkConsistencyStatus>  
 <cVpcStatusHostLinkConsistencyDetail> ]

## Syntax Description

<b>Syntax Description</b>	vpc	Virtual Port Channel configuration
	internal	Commands for internal use
	status	vPC brief status information
	snmp	vPC brief host-link information
	host-link-table	Host-link summary table
	domain-id	vPC domain ID
	<i>did</i>	vPC domain ID value
	vpc-id	vPC link ID
	<i>vid</i>	vPC link ID value
	__readonly__	(Optional) Read Only
	TABLE-cVpcStatusHostLinkTable	(Optional) Host-link xml status table
	<i>cVpcStatusHostLinkDomainID</i>	(Optional)
	<i>cVpcStatusHostLinkVpcID</i>	(Optional)
	<i>cVpcStatusHostLinkIfIndex</i>	(Optional)
	<i>cVpcStatusHostLinkStatus</i>	(Optional)
	<i>cVpcStatusHostLinkConsistencyStatus</i>	(Optional)
	<i>cVpcStatusHostLinkConsistencyDetail</i>	(Optional)

## Command Mode

- /exec

show vpc internal status snmp peer-link-table domain-id

## show vpc internal status snmp peer-link-table domain-id

show vpc internal status snmp peer-link-table domain-id <did> [ \_\_readonly\_\_  
TABLE-cVpcStatusPeerLinkTable <cVpcStatusPeerLinkDomainID> <cVpcStatusPeerLinkIfIndex> ]

### Syntax Description

Syntax Description	
vpc	Virtual Port Channel configuration
internal	Commands for internal use
status	vPC brief status information
snmp	vPC brief peer-link information
peer-link-table	Peer-link summary table
domain-id	vPC domain ID
<i>did</i>	vPC domain ID value
__readonly__	(Optional) Read Only
TABLE-cVpcStatusPeerLinkTable	(Optional) Peer-link xml status table
<i>cVpcStatusPeerLinkDomainID</i>	(Optional)
<i>cVpcStatusPeerLinkIfIndex</i>	(Optional)

### Command Mode

- /exec

# show vpc orphan-ports

show vpc orphan-ports [ \_\_readonly\_\_ TABLE\_orphan\_ports <vpc-vlan> <vpc-orphan-ports> ]

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
orphan-ports	Show ports that are not part of vPC but have common VLANs
__readonly__	(Optional) Read Only
TABLE_orphan_ports	(Optional) vPC orphan ports table
<i>vpc-vlan</i>	(Optional)
<i>vpc-orphan-ports</i>	(Optional)

## Command Mode

- /exec

show vpc peer-keepalive

# show vpc peer-keepalive

```
show vpc peer-keepalive [ __readonly__ <vpc-peer-keepalive-status> <vpc-keepalive-dest>
<vpc-keepalive-send-interface> <vpc-keepalive-receive-interface> <vpc-keepalive-send-tstamp>
<vpc-keepalive-receive-tstamp> <vpc-peer-keepalive-up-time> <vpc-keepalive-send-status>
<vpc-keepalive-receive-status> <vpc-keepalive-lastupdate> [ <vpc-keepalive-dest> ] <vpc-keepalive-interval>
<vpc-keepalive-timeout> <vpc-keepalive-hold-timeout> <vpc-keepalive-vrf> <vpc-keepalive-udp-port>
<vpc-keepalive-tos> ]
```

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
peer-keepalive	vPC keepalive status
__readonly__	(Optional) Read Only
<i>vpc-peer-keepalive-status</i>	(Optional) vpc peer keepalive status
<i>vpc-keepalive-dest</i>	(Optional) vPC keepalive destination ip address
<i>vpc-keepalive-send-status</i>	(Optional) vPC keepalive send status
<i>vpc-keepalive-receive-status</i>	(Optional) vPC keepalive receive status
<i>vpc-peer-keepalive-up-time</i>	(Optional) keepalive- alive time
<i>vpc-keepalive-send-tstamp</i>	(Optional) vPC keepalive last send timestamp
<i>vpc-keepalive-send-interface</i>	(Optional) vPC keepalive send interface
<i>vpc-keepalive-receive-tstamp</i>	(Optional) vPC keepalive last receive timestamp
<i>vpc-keepalive-receive-interface</i>	(Optional) vPC keepalive receive interface
<i>vpc-keepalive-lastupdate</i>	(Optional) vPC keepalive last update from peer
<i>vpc-keepalive-interval</i>	(Optional) vPC keepalive timeout
<i>vpc-keepalive-timeout</i>	(Optional) vPC keepalive interval
<i>vpc-keepalive-hold-timeout</i>	(Optional) hold timeout
<i>vpc-keepalive-vrf</i>	(Optional) vrf name
<i>vpc-keepalive-udp-port</i>	(Optional) udp port
<i>vpc-keepalive-tos</i>	(Optional) tos value

## Command Mode

- /exec

# show vpc role

```
show vpc role [ __readonly__ <vpc-peer-status> <vpc-peer-status-reason> [ <vpc-current-role> ] [ <vpc-es-current-role> ] <dual-active-detected> <vpc-system-mac> <vpc-system-prio> <vpc-local-system-mac> <vpc-local-system-prio> ]
```

## Syntax Description

<b>Syntax Description</b>	
vpc	Virtual Port Channel configuration
role	vPC role status
__readonly__	(Optional) Read Only
<i>vpc-peer-status</i>	(Optional) vPC peer status
<i>vpc-peer-status-reason</i>	(Optional) vPC peer status reason
<i>vpc-current-role</i>	(Optional) vPC role
<i>vpc-es-current-role</i>	(Optional) vPC role
<i>dual-active-detected</i>	(Optional) Dual active detection status
<i>vpc-system-mac</i>	(Optional) vPC system mac
<i>vpc-local-system-mac</i>	(Optional) vPC local system mac
<i>vpc-system-prio</i>	(Optional) vPC system priority
<i>vpc-local-system-prio</i>	(Optional) vPC local system priority

## Command Mode

- /exec

show vpc statistics peer-keepalive

## show vpc statistics peer-keepalive

show vpc statistics peer-keepalive [ \_\_readonly\_\_ <vpc-keepalive-counters-tx> <vpc-keepalive-counters-rx> <vpc-keepalive-avg-rx-interval> <vpc-keepalive-peer-state-changes> ]

### Syntax Description

Syntax Description		
vpc		Virtual Port Channel configuration
statistics		Statistics
peer-keepalive		peer keepalive module related statistics
__readonly__		(Optional) Read Only
<i>vpc-keepalive-counters-tx</i>		(Optional) tx counters
<i>vpc-keepalive-counters-rx</i>		(Optional) rx counters
<i>vpc-keepalive-avg-rx-interval</i>		(Optional) avg rx interval in ms
<i>vpc-keepalive-peer-state-changes</i>		(Optional) peer state changes

### Command Mode

- /exec

# show vpc statistics vpc

show vpc statistics { vpc <vpc\_num> | peer-link }

## Syntax Description

<b>Syntax Description</b>	vpc      Virtual Port Channel configuration
	statistics    Statistics
	<i>vpc_num</i> Virtual Port Channel number
	peer-link    stats for peer-link

## Command Mode

- /exec

show vrf

# show vrf

```
show vrf [<vrf-name> | <vrf-known-name> | all ] [ order id ] [ detail ] [ passive ] [ __readonly__ TABLE_vrf
<vrf_name><vrf_id><vrf_state> [ <vrf_reason> ] [ <vrf_pend> ] [ <vpnid><rd><vni><max_routes>
<mid_threshold> ] [ { TABLE_tib <tib_id><tib_af><tib_nonce><tib_state> [ <tib_reason> ] [ <tib_pend>
] } ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrf	Display VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
all	(Optional) Display VRF information for all VRFs
order	(Optional) Specify ordering
id	(Optional) Order by ID
detail	(Optional) Display VRF detail information
passive	(Optional) Display passive VRF information
__readonly__	(Optional)
TABLE_vrf	(Optional)
TABLE_tib	(Optional)
<i>vrf_name</i>	(Optional)
<i>vrf_id</i>	(Optional)
<i>vrf_state</i>	(Optional)
<i>vrf_reason</i>	(Optional)
<i>vrf_pend</i>	(Optional)
<i>vpnid</i>	(Optional)
<i>rd</i>	(Optional)
<i>max_routes</i>	(Optional)
<i>mid_threshold</i>	(Optional)
<i>tib_id</i>	(Optional)
<i>tib_af</i>	(Optional)

<i>tib_nonce</i>	(Optional)
<i>tib_state</i>	(Optional)
<i>tib_reason</i>	(Optional)
<i>tib_pend</i>	(Optional)
<i>vni</i>	(Optional)

**Command Mode**

- /exec

**show vrf**

# show vrf

```
show vrf [ <vrf-name> | <vrf-known-name> | all ]
```

## Syntax Description

Syntax Description		
show	Show running system information	
vrf	Display VRF information	
<i>vrf-name</i>	(Optional) VRF name	
<i>vrf-known-name</i>	(Optional) Known VRF name	
all	(Optional) Display VRF information for all VRFs	

## Command Mode

- /exec

# show vrf topology

```
show vrf topology [ order id ] [ detail ] [ __readonly__ TABLE_tib <vrf_name> <tib_af> <tib_name> <tib_id>
<tib_state> [ <tib_reason> <tib_pend> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrf	Configure VRF parameters
topology	Display topology information
order	(Optional) Specify ordering
id	(Optional) Order by ID
detail	(Optional) Display topology detail information
__readonly__	(Optional)
TABLE_tib	(Optional)
<i>vrf_name</i>	(Optional)
<i>tib_af</i>	(Optional)
<i>tib_name</i>	(Optional)
<i>tib_id</i>	(Optional)
<i>tib_state</i>	(Optional)
<i>tib_reason</i>	(Optional)
<i>tib_pend</i>	(Optional)

## Command Mode

- /exec

show vrrp

# show vrrp

```
show vrrp [ [ summary ] | { [ statistics | detail ] [ interface <interface_id> ] [ vr <vr_id> ] [ master | backup | init ] + } ] [ __readonly__ <show_vrrp_start> { TABLE_vrrp_group <sh_if_index><sh_group_id> <sh_group_type><sh_group_state><sh_group_preempt><sh_vip_addr> { [ TABLE_sec_vip_addr <sh_sec_vip_addr> ] <sh_priority> [ <sh_cfg_priority><sh_fwd_thr_lower><sh_fwd_thr_upper> ] <sh_adv_interval> [ <sh_auth_text> ] [ <sh_vmac> ] [ <sh_master_router> ] [ <sh_native_track_intf><sh_native_track_priotiry> ] { [ TABLE_vrrp_track <sh_track_object_id><sh_decrement_priority><sh_track_object_state> ] } [ <sh_bfd_status><sh_bfd_session> ] } <sh_vrrp_end> ]
```

## Syntax Description

### Syntax Description

show	Show running system information
vrrp	Show vrrp information
summary	(Optional) Show vrrp summary
statistics	(Optional) Show vrrp statistics
detail	(Optional) Show detailed information
interface	(Optional) Show vrrp info for the interface
<i>interface_id</i>	(Optional)
vr	(Optional) Show vrrp info for the group
<i>vr_id</i>	(Optional) [1-255] enter IPv4 vr group
master	(Optional) Groups in Master state
backup	(Optional) Groups in Backup state
init	(Optional) Groups in Init state
__readonly__	(Optional) Read only
<i>show_vrrp_start</i>	(Optional) Show vrrp start
TABLE_vrrp_group	(Optional) Group detail table
<i>sh_if_index</i>	(Optional) Interface type and number
<i>sh_group_id</i>	(Optional) Group number
<i>sh_group_type</i>	(Optional) Group type
<i>sh_group_state</i>	(Optional) VRRP group state
<i>sh_group_preempt</i>	(Optional) Group preemption statue
<i>sh_vip_addr</i>	(Optional) Virtual IP Address

TABLE_sec_vip_addr	(Optional) Secondary virtual ip address table
<i>sh_sec_vip_addr</i>	(Optional) Secondary virtual ip address
<i>sh_priority</i>	(Optional) Priority of VRRP group
<i>sh_auth_text</i>	(Optional) Authentication text
<i>sh_cfg_priority</i>	(Optional) Configured priority of VRRP group
<i>sh_fwd_thr_lower</i>	(Optional) Lower forwarding threshold
<i>sh_fwd_thr_upper</i>	(Optional) Upper forwarding threshold
<i>sh_adv_interval</i>	(Optional) Advertisement interval
<i>sh_vmac</i>	(Optional) Virtual MAC
<i>sh_master_router</i>	(Optional) Master router
<i>sh_native_track_intf</i>	(Optional) Native tracked interface
<i>sh_native_track_priotiry</i>	(Optional) Decrement priority for Native tracking
TABLE_vrrp_track	(Optional) VRRP tracking table
<i>sh_track_object_id</i>	(Optional) Object id of tracking object
<i>sh_decrement_priority</i>	(Optional) Decrement priority
<i>sh_track_object_state</i>	(Optional) Tracking object state
<i>sh_bfd_status</i>	(Optional) BFD status
<i>sh_bfd_session</i>	(Optional) BFD session status
<i>sh_vrrp_end</i>	(Optional) Show vrrp end

**Command Mode**

- /exec

show vrrp bfd-sessions

## show vrrp bfd-sessions

```
show vrrp bfd-sessions [ interface <interface-id> [ to <ipaddress> ] ] [ __readonly__ TABLE_bfd_sess
<interface> { <src_addr> | <src_addr_v6> } { <dst_addr> | <dst_addr_v6> } <session_state> <ref_count>
<displayed_interface> { TABLE_groups <group_id> <vrrp_state> <bfd_status> <operation> <time> } ]
```

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show vrrp information
bfd-sessions	BFD sessions
interface	(Optional) Groups on this interface
<i>interface-id</i>	(Optional) Interface
to	(Optional) To IP address
<i>ipaddress</i>	(Optional) Sessions to IP address
<u>__readonly__</u>	(Optional)
TABLE_bfd_sess	(Optional)
<i>interface</i>	(Optional) Interface
<i>src_addr</i>	(Optional) IPv4 Source address
<i>dst_addr</i>	(Optional) IPv4 Destination address
<i>session_state</i>	(Optional) Session state
<i>ref_count</i>	(Optional) Ref count
<i>displayed_interface</i>	(Optional) Displayed interface
TABLE_groups	(Optional)
<i>group_id</i>	(Optional) Group id
<i>vrrp_state</i>	(Optional) VRRP STATE
<i>bfd_status</i>	(Optional) BFD STATE
<i>operation</i>	(Optional) Operation
<i>time</i>	(Optional) Time

### Command Mode

- /exec

# show vrrp internal configuration event-history errors

show vrrp internal configuration event-history errors

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show vrrp information
internal	Show internal vrrp information
configuration	Show internal vrrp configuration information
event-history	Show event history
errors	Show error logs of VRRP Mgr

## Command Mode

- /exec

```
■ show vrrp internal configuration event-history msgs
```

## show vrrp internal configuration event-history msgs

show vrrp internal configuration event-history msgs

### Syntax Description

Syntax Description		
show	Show running system information	
vrrp	Show vrrp information	
internal	Show internal vrrp information	
configuration	Show internal vrrp configuration information	
event-history	Show event history	
msgs	Show MTS logs of VRRP Mgr	

### Command Mode

- /exec

# show vrrp internal debugs

show vrrp internal [ event-history ] debugs

## Syntax Description

Syntax Description		
show	Show running system information	
vrrp	Show information about VRRP	
internal	Show internal vrrp information	
event-history	(Optional) Show various event logs of VRRP	
debugs	Show debug logs of VRRP	

## Command Mode

- /exec

```
show vrrp internal engine event-history errors
```

## show vrrp internal engine event-history errors

show vrrp internal engine event-history errors

### Syntax Description

Syntax Description		
show	Show running system information	
vrrp	Show vrrp information	
internal	Show internal vrrp information	
engine	Show internal vrrp configuration information	
event-history	Show event history	
errors	Show error logs of VRRP Engine	

### Command Mode

- /exec

# show vrrp internal engine event-history msgs

show vrrp internal engine event-history msgs

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show vrrp information
internal	Show internal vrrp information
engine	Show internal vrrp configuration information
event-history	Show event history
msgs	Show MTS logs of VRRP Engine

## Command Mode

- /exec

show vrrp internal info

## show vrrp internal info

```
show vrrp internal info { { counters [ <ctr_num> ] } | { { data-structures | state-history } [ vr <vr_id> ] [ interface <intf_num> ] } | bulking-stats }
```

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show vrrp information
internal	Show internal vrrp information
info	Show internal vrrp info
counters	Show counters for vrrp
data-structures	Show vrrp data structures
<i>ctr_num</i>	(Optional) Enter the counter number to view
vr	(Optional) Show IPv4 virtual router information
<i>vr_id</i>	(Optional) [1-255] enter IPv4 vr group
interface	(Optional) Select interface
<i>intf_num</i>	(Optional)
bulking-stats	Bulk Queue Statistics/Info
state-history	Show vrrp state-history

### Command Mode

- /exec

# show vrrp internal info global

show vrrp internal info global

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show vrrp information
internal	Show internal vrrp information
info	Show internal vrrp info
global	Show vrrp global information(FSRV)

## Command Mode

- /exec

show vrrp internal mem-stats

## show vrrp internal mem-stats

show vrrp internal mem-stats [ uuid <uuid\_num> ] [ vrrp-only ] [ detail ]

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrp	Show information about vrrp
internal	Show internal vrrp information
mem-stats	Show memory allocation statistics of VRRP
uuid	(Optional) Show stats only for this uuid
<i>uuid_num</i>	(Optional) Enter uuid
vrrp-only	(Optional) Show stats of only VRRP Engine
detail	(Optional) Show detail memstats for vrrp

### Command Mode

- /exec

# show vrrpv3

```
show vrrpv3 [ brief | detail | statistics ] [ <intf> [ <group_num> ] ] [ <opt_v4_or_v6> ] [ all ] [ __readonly__ <global_drops> { TABLE_istats <i_intf> <i_drops> <ttl> <checksum> <version> <type> <length> <badid> <other> } { TABLE_grp <intf> <id> <af> <desc> <state> <duration> <vip> { TABLE_sec <addr> <prefix> } <vmac> <adv> <owner> <preempt> <delay> <delay_rem> <priority> <m_addr> <m_priority> <m_adv> <m_expire> <down> <down_expire> <adv_sent> <adv_err> <adv_rcvd> <v2adv_sent> <v2adv_err> <v2adv_rcvd> <drops> <incompat> <conflict> <bad_count> <bad_addr> <bad_config> <bad_advert> <bad_state> <bad_other> <init_master> <init_master_time> <init_backup> <init_backup_time> <back_master> <back_master_time> <master_back> <master_back_time> <mast_init> <mast_init_time> <back_init> <back_init_time> } ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrpv3	VRRPv3 Show commands
all	(Optional) All VRRPV3 information
brief	(Optional) Brief output
detail	(Optional) Detail output
statistics	(Optional) Statistics output
<i>opt_v4_or_v6</i>	(Optional) Enter ipv4 or ipv6
<i>intf</i>	(Optional) Interface
<i>group_num</i>	(Optional) Group Number
<i>__readonly__</i>	(Optional)
TABLE_istats	(Optional) Interface-level VRRPv3 statistics
TABLE_grp	(Optional) VRRP Groups
TABLE_sec	(Optional) Secondary Addresses
<i>global_drops</i>	(Optional) Total dropped packets
<i>i_intf</i>	(Optional) Interface
<i>i_drops</i>	(Optional) Total dropped packets
<i>ttl</i>	(Optional) Invalid TTL/Hop limit
<i>checksum</i>	(Optional) Invalid checksum
<i>version</i>	(Optional) Invalid version
<i>type</i>	(Optional) Invalid message type

**show vrrpv3**

<i>length</i>	(Optional) Invalid length
<i>baid</i>	(Optional) Invalid group ID
<i>other</i>	(Optional) Other
<i>intf</i>	(Optional) Interface
<i>id</i>	(Optional) Group ID
<i>af</i>	(Optional) Address family
<i>desc</i>	(Optional) Description
<i>state</i>	(Optional) Group state
<i>duration</i>	(Optional) Time in current state
<i>vip</i>	(Optional) Primary virtual IP address
<i>addr</i>	(Optional) Secondary virtual IP address
<i>prefix</i>	(Optional) Secondary vIP prefix
<i>vmac</i>	(Optional) Virtual MAC address
<i>adv</i>	(Optional) Advertisement interval
<i>preempt</i>	(Optional) Preemption status
<i>owner</i>	(Optional) Owner mode
<i>delay</i>	(Optional) Preemption delay
<i>delay_rem</i>	(Optional) Preemption delay remaining
<i>priority</i>	(Optional) Priority
<i>m_addr</i>	(Optional) Group master router address
<i>m_priority</i>	(Optional) Group master priority
<i>m_adv</i>	(Optional) Master advertisement interval
<i>m_expire</i>	(Optional) Master expiration
<i>down</i>	(Optional) Master down interval
<i>down_expire</i>	(Optional) Master down expiration
<i>adv_sent</i>	(Optional) Advertisements sent
<i>adv_err</i>	(Optional) Advertisement errors
<i>adv_recv</i>	(Optional) Advertisements received
<i>v2adv_sent</i>	(Optional) Advertisements sent (v2)

<i>v2adv_err</i>	(Optional) Advertisement errors (v2)
<i>v2adv_recv</i>	(Optional) Advertisements received (v2)
<i>drops</i>	(Optional) Total dropped packets
<i>incompat</i>	(Optional) v2, Incompatible
<i>conflict</i>	(Optional) Address owner conflicts
<i>bad_count</i>	(Optional) Invalid address count
<i>bad_addr</i>	(Optional) Invalid IP address
<i>bad_config</i>	(Optional) Invalid IP address config
<i>bad_advert</i>	(Optional) Invalid advertisement interval
<i>bad_state</i>	(Optional) Invalid group state
<i>bad_other</i>	(Optional) Other
<i>init_master</i>	(Optional) Init to Master
<i>init_master_time</i>	(Optional) Last Occurrence
<i>init_backup</i>	(Optional) Init to Backup
<i>init_backup_time</i>	(Optional) Last Occurrence
<i>back_master</i>	(Optional) Backup to Master
<i>back_master_time</i>	(Optional) Last Occurrence
<i>master_back</i>	(Optional) Master to Backup
<i>master_back_time</i>	(Optional) Last Occurrence
<i>mast_init</i>	(Optional) Master to Init
<i>mast_init_time</i>	(Optional) Last Occurrence
<i>back_init</i>	(Optional) Backup to Init
<i>back_init_time</i>	(Optional) Last Occurrence

**Command Mode**

- /exec

```
show vrrpv3 internal debug
```

## show vrrpv3 internal debug

show vrrpv3 internal debug

### Syntax Description

#### Syntax Description

show	Show running system information
vrrpv3	VRRPv3 Show commands
internal	Internal command
debug	Core Code Debug flags

#### Command Mode

- /exec

# show vrrpv3 internal high-availability database

show vrrpv3 internal high-availability { database [ summary ] | status }

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrpv3	VRRPv3 Show commands
internal	Internal command
high-availability	VRRPv3 HA Information
database	HA database
summary	(Optional) Summary counters only
status	HA status and events

## Command Mode

- /exec

```
show vrrpv3 internal mem-stats
```

## show vrrpv3 internal mem-stats

show vrrpv3 internal mem-stats [ no-libs ] [ detail ]

### Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vrrpv3	VRRPv3 Show commands
internal	Internal command
mem-stats	Memory usage stats
no-libs	(Optional) Exclude shared library information
detail	(Optional) Detailed information

### Command Mode

- /exec

# show vrrs client

```
show vrrs client [ <cname> ] [ __readonly__ { TABLE_client <name> <id> <all> <priority> { TABLE_tags <tname> } } ]
```

## Syntax Description

<b>Syntax Description</b>	vrrs	VRSS Show commands
	show	Show running system information
	client	Information about VRSS clients
	<i>cname</i>	(Optional) VRSS client name
	__readonly__	(Optional)
	TABLE_client	(Optional) VRSS clients
	TABLE_tags	(Optional) VRSS tags
	<i>name</i>	(Optional) VRSS client name
	<i>id</i>	(Optional) VRSS client id
	<i>priority</i>	(Optional) Priority
	<i>all</i>	(Optional) Client follows all tags
	<i>tname</i>	(Optional) VRSS tag name

## Command Mode

- /exec

show vrrs pathway

# show vrrs pathway

```
show vrrs pathway [ <intf> ] [ __readonly__ { TABLE_pws <name> <state> <vrrs_push_state> <vmac>
<vmac_state> <vmac_dbg> <pvmac> <pvmac_state> <pvmac_dbg> <af> [ <desc> ] <opt> <eval> [ {
TABLE_vips <addr> [ <flags> ] } ] } ]
```

## Syntax Description

<b>Syntax Description</b>	
vrrs	VRSS Show commands
show	Show running system information
pathway	Information about VRSS pathways
<i>intf</i>	(Optional) Interface
<i>__readonly__</i>	(Optional)
TABLE_pws	(Optional) Show VRSS pathways
TABLE_vips	(Optional) Pathway vIP addresses
<i>name</i>	(Optional) Pathway name
<i>state</i>	(Optional) Pathway state
<i>vrrs_push_state</i>	(Optional) VRSS push state
<i>vmac</i>	(Optional) Virtual MAC address
<i>vmac_state</i>	(Optional) Virtual MAC state
<i>vmac_dbg</i>	(Optional) Virtual MAC debug flags
<i>pvmac</i>	(Optional) Previous Virtual MAC address
<i>pvmac_state</i>	(Optional) Previous MAC state
<i>pvmac_dbg</i>	(Optional) Previous MAC debug flags
<i>af</i>	(Optional) Pathway address-family
<i>desc</i>	(Optional) Pathway description
<i>opt</i>	(Optional) Option flags
<i>eval</i>	(Optional) Eval flags
<i>addr</i>	(Optional) Virtual IP address
<i>flags</i>	(Optional) Virtual IP address flags

## Command Mode

- /exec

# show vrrs pathway address

show vrrs pathway [ <intf> ] address

## Syntax Description

<b>Syntax Description</b>	
vrrs	VRRS Show commands
show	Show running system information
pathway	Information about VRRS pathways
<i>intf</i>	(Optional) Interface
address	Internal information about pathway addresses

## Command Mode

- /exec

show vrrs server

## show vrrs server

```
show vrrs server [ __readonly__ { TABLE_srv <name> <af> <intf> <state> <vmac> <vip> [ { TABLE_tag <tag> } ] } ]
```

### Syntax Description

<b>Syntax Description</b>	
vrrs	VRRS Show commands
show	Show running system information
server	Information about VRRS servers
__readonly__	(Optional)
TABLE_srv	(Optional) VRRS Servers
TABLE_tag	(Optional) VRRS tags associated with each server
<i>name</i>	(Optional) VRRS server name
<i>af</i>	(Optional) Address-family
<i>intf</i>	(Optional) Interface
<i>state</i>	(Optional) VRRS server state
<i>vmac</i>	(Optional) Virtual MAC address
<i>vip</i>	(Optional) Virtual IP address
<i>tag</i>	(Optional) VRRS tag

### Command Mode

- /exec

# show vrrs tag

```
show vrrs tag [ <tagname> ] [ __readonly__ { TABLE_tag <name><server>[ { TABLE_client <id><client> <all> } ] } ]
```

## Syntax Description

<b>Syntax Description</b>	
vrrs	VRSS Show commands
show	Show running system information
tag	Information about VRSS tags
<i>tagname</i>	(Optional) VRSS tag
__readonly__	(Optional)
TABLE_tag	(Optional) Known VRSS tags
TABLE_client	(Optional) VRSS clients listening
<i>name</i>	(Optional) VRSS tag name
<i>server</i>	(Optional) VRSS server name
<i>id</i>	(Optional) VRSS client id
<i>client</i>	(Optional) VRSS client name
<i>all</i>	(Optional) Client follows all tags

## Command Mode

- /exec

**show vxlan**

# show vxlan

```
show vxlan [ interface [ <int-id> | <ch-id> ] ]
```

## Syntax Description

<b>Syntax Description</b>	
show	Show running system information
vxlan	VxLAN VLANs
interface	(Optional) Interface
<i>int-id</i>	(Optional) Interface
<i>ch-id</i>	(Optional) Port-Channel name

## Command Mode

- /exec