



N Commands

- [name-lookup](#), on page 4
- [name-lookup](#), on page 5
- [name](#), on page 6
- [name](#), on page 7
- [name](#), on page 8
- [nat destination](#), on page 9
- [nbm external-link](#), on page 10
- [nbm fabric-link](#), on page 11
- [nbm flow-policy](#), on page 12
- [nbm flow acceptance-mode guaranteed nbm flow acceptance-mode](#), on page 13
- [nbm flow asm range](#), on page 14
- [nbm flow bandwidth kbps mbps gbps](#), on page 15
- [nbm flow dscp](#), on page 16
- [nbm host-policy](#), on page 17
- [nbm mode controller](#), on page 18
- [nbm mode pim-active](#), on page 19
- [nbm mode verbose](#), on page 20
- [nbm multicast route add](#), on page 21
- [nbm multicast route delete](#), on page 22
- [nbm reserve unicast fabric bandwidth](#), on page 23
- [nbm test-rest-api secure request-type](#), on page 24
- [nbm unit-test all](#), on page 25
- [nbm vpc transport-vlan](#), on page 26
- [negotiate auto](#), on page 27
- [negotiate auto 25000](#), on page 28
- [neighbor-down fib-accelerate](#), on page 29
- [neighbor](#), on page 30
- [neighbor](#), on page 31
- [neighbor](#), on page 32
- [neighbor](#), on page 33
- [neighbor](#), on page 34
- [neighbor maximum-prefix](#), on page 35
- [nemo config address port interval](#), on page 36

- [net](#), on page 37
- [net](#), on page 38
- [net](#), on page 39
- [network](#), on page 40
- [network](#), on page 41
- [network](#), on page 42
- [network](#), on page 43
- [network area](#), on page 44
- [next-address exclude-address](#), on page 45
- [next-hop-self](#), on page 46
- [next-hop-self](#), on page 47
- [next-hop-third-party](#), on page 48
- [next-hop-third-party](#), on page 49
- [next-hop out-label explicit-null implicit-null next-hop auto-resolve out-label explicit-null implicit-null](#), on page 50
- [next-hop out-label explicit-null implicit-null next-hop auto-resolve out-label explicit-null implicit-null](#), on page 51
- [nexthop route-map](#), on page 52
- [nexthop trigger-delay critical non-critical](#), on page 53
- [ngoam authentication-key](#), on page 54
- [ngoam connect-check](#), on page 55
- [ngoam install acl](#), on page 56
- [ngoam install acl draft-pang action fwd](#), on page 57
- [ngoam probe start](#), on page 58
- [ngoam profile](#), on page 59
- [ngoam xconnect hb-interval](#), on page 60
- [no-more](#), on page 61
- [no](#), on page 62
- [no](#), on page 63
- [no](#), on page 64
- [no](#), on page 65
- [no](#), on page 66
- [no](#), on page 69
- [no](#), on page 74
- [no](#), on page 78
- [no](#), on page 81
- [no](#), on page 84
- [no](#), on page 87
- [no](#), on page 90
- [no](#), on page 93
- [no](#), on page 96
- [no](#), on page 98
- [no](#), on page 99
- [no](#), on page 100
- [no](#), on page 101
- [no](#), on page 102

- no, on page 103
- node, on page 104
- node, on page 105
- node, on page 106
- node ip, on page 107
- node ip, on page 108
- npiv enable, on page 109
- npv auto-load-balance disruptive, on page 110
- npv inject-event, on page 111
- npv traffic-map server-interface external-interface, on page 113
- nsf await-redist-proto-convergence, on page 114
- ntp access-group, on page 115
- ntp access-group match-all, on page 116
- ntp allow private, on page 117
- ntp authenticate, on page 118
- ntp authentication-key md5, on page 119
- ntp drop-aged-packet, on page 120
- ntp logging, on page 121
- ntp master, on page 122
- ntp passive, on page 123
- ntp peer, on page 124
- ntp rts-update, on page 125
- ntp server, on page 126
- ntp source-interface, on page 127
- ntp source, on page 128
- ntp sync-retry, on page 129
- ntp trusted-key, on page 130
- nv overlay evpn, on page 131
- nve event-history size, on page 132
- nve interface remap-replication-servers, on page 133
- nve interface replication-server up, on page 134
- nve oam mode draft-pang, on page 135
- nxapi certificate, on page 136
- nxapi flow, on page 137
- nxapi http port, on page 138
- nxapi ssl ciphers weak, on page 139
- nxapi ssl protocols, on page 140
- nxapi use-vrf management default, on page 141
- nx sdk enable app, on page 142
- nx sdk service-name, on page 143

name-lookup

[no] name-lookup

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Enable Name Lookup for OSPF Neighbors

Command Mode

- /exec/configure/router-ospf3 /exec/configure/router-ospf3/vrf

name-lookup

[no] name-lookup

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Display OSPF router ids as DNS names

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

name

name <vlan-name> | no name

Syntax Description

no	Negate a command or set its defaults
name	Ascii name of the VLAN
<i>vlan-name</i>	The ascii name for the VLAN

Command Mode

- /exec/configure/vlan

name

name [<name>] | no name

Syntax Description

no	Negate a command or set its defaults
name	Redundancy name string
<i>name</i>	(Optional) name string

Command Mode

- /exec/configure/if-eth-any/hsrp_ipv4 /exec/configure/if-eth-any/hsrp_ipv6

name

name <name-val> | no name [<name-val>]

Syntax Description

no	Negate a command or set its defaults
name	Set configuration name
<i>name-val</i>	Configuration name

Command Mode

- /exec/configure/spanning-tree/mst/configuration

nat destination

{ nat destination } | { no nat destination }

Syntax Description

no	Negate a command or set its defaults
nat	Network Address Translation
destination	Destination NAT

Command Mode

- /exec/configure/plb

nbm external-link

[no] nbm external-link

Syntax Description

nbm	Non Blocking Multicast
external-link	link connected to external router. Configuring this will flap the interface

Command Mode

- /exec/configure/if-igp

nbm fabric-link

[no] nbm fabric-link

Syntax Description

nbm	Non Blocking Multicast
fabric-link	Link interconnecting NBM fabric nodes

Command Mode

- /exec/configure/if-igp

nbm flow-policy

[no] nbm flow-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-policy	Flow Policy Characteristics

Command Mode

- /exec/configure

nbm flow acceptance-mode guaranteed nbm flow acceptance-mode

{ nbm flow acceptance-mode { guaranteed | best-fit } } | [no] nbm flow acceptance-mode

Syntax Description

nbm	Non Blocking Multicast
flow	Flow Characteristics
acceptance-mode	Flow Acceptance Mode
guaranteed	New flows are guaranteed to be accepted
best-fit	New flows are best-fit among fabric links

Command Mode

- /exec/configure

nbm flow asm range

nbm flow asm range

[no] nbm flow asm range <group> +

Syntax Description

nbm	Non Blocking Multicast
flow	Flow Characteristics
asm	Any-Source Multicast (ASM) groups
range	Configure explicit group ranges
<i>group</i>	List of group range prefixes

Command Mode

- /exec/configure

nbm flow bandwidth kbps mbps gbps

{ nbm flow bandwidth { <val_kbps> kbps | <val_mbps> mbps | <val_gbps> gbps } } | { no nbm flow bandwidth }

Syntax Description

nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
<i>val_kbps</i>	Per Flow Bandwidth in Kbps
kbps	Bandwidth value in Kbps
<i>val_mbps</i>	Per Flow Bandwidth in Mbps
mbps	Bandwidth value in Mbps
<i>val_gbps</i>	Per Flow Bandwidth in Gbps
gbps	Bandwidth value in Gbps

Command Mode

- /exec/configure

nbm flow dscp

nbm flow dscp

{ nbm flow dscp <val_dscp> } | { no nbm flow dscp }

Syntax Description

nbm	Non Blocking Multicast
flow	Flow Characteristics
dscp	DSCP for the flow
<i>val_dscp</i>	Integer value

Command Mode

- /exec/configure

nbm host-policy

[no] nbm host-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
host-policy	NBM SW Host Admission Policy

Command Mode

- /exec/configure

nbm mode controller

[no] nbm mode controller [__readonly__ <output>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
mode	Set pmn mode
controller	Enable controller-mode for pmn
__readonly__	(Optional)
<i>output</i>	(Optional)

Command Mode

- /exec/configure

nbm mode pim-active

[no] nbm mode pim-active [__readonly__ <output>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
mode	Set pmn mode
pim-active	Bandwidth engine running in fabric
__readonly__	(Optional)
<i>output</i>	(Optional)

Command Mode

- /exec/configure

nbm mode verbose

nbm mode verbose

[no] nbm mode verbose

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
mode	Set NBM flow mode
verbose	Enable verbose Logs

Command Mode

- /exec/configure

nbm multicast route add

[no] nbm multicast route add

Syntax Description

nbm	Non Blocking Multicast
multicast	MULTICAST
route	Route
add	add

Command Mode

- /exec/configure

nbm multicast route delete

nbm multicast route delete

[no] nbm multicast route delete

Syntax Description

nbm	Non Blocking Multicast
multicast	MULTICAST
route	Route
delete	delete

Command Mode

- /exec/configure

nbm reserve unicast fabric bandwidth

nbm reserve unicast fabric bandwidth <percentage> | no nbm reserve unicast fabric bandwidth

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
reserve	reserve bandwidth
unicast	unicast
fabric	fabric
bandwidth	percentage of bandwidth for unicast flow
<i>percentage</i>	percentage value

Command Mode

- /exec/configure

nbm test-rest-api secure request-type

nbm test-rest-api secure request-type

nbm test-rest-api { secure | plain } request-type { POST | GET | PUT | DELETE }

Syntax Description

nbm	Non Blocking Multicast
test-rest-api	Test REST API
secure	Over HTTPS
plain	Over plain HTTP
request-type	type of http request
POST	HTTP POST
GET	HTTP GET
PUT	HTTP PUT
DELETE	HTTP DELETE

Command Mode

- /exec

nbm unit-test all

nbm unit-test all

Syntax Description

nbm	Non Blocking Multicast
unit-test	unit test
all	perform all unit tests

Command Mode

- /exec/configure

nbm vpc transport-vlan

nbm vpc transport-vlan

[no] nbm vpc transport-vlan <vlan_id>

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	non blocking multicast
vpc	nbm vpc related commands
transport-vlan	configure nbm vpc transport vlan
<i>vlan_id</i>	vlan value

Command Mode

- /exec/configure

negotiate auto

negotiate auto | no negotiate auto

Syntax Description

no	Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation

Command Mode

- /exec/configure/if-ethernet-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

negotiate auto 25000

negotiate auto 25000

[no] negotiate auto 25000

Syntax Description

no	(Optional) Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation
25000	Force auto-negotiate to only 25000 and change fec to auto

Command Mode

- /exec/configure/if-ether-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

neighbor-down fib-accelerate

[no] neighbor-down fib-accelerate

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor-down	Handle BGP neighbor down event, due to various reasons
fib-accelerate	Accelerate the hardware updates for IP/IPv6 adjacencies for neighbor

Command Mode

- /exec/configure/router-bgp/vrf-cmds

neighbor

[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [remote-as [<asn> | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

```
neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> { implicit-withdraw | labels accept <pfx-list>
| targeted } | no neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> [ implicit-withdraw | labels
accept | targeted ]
```

Syntax Description

no	Negate a command or set its defaults
neighbor	Configure neighbor parameters
vrf	(Optional) VRF Routing/Forwarding instance information
<i>vrf-name</i>	(Optional) VPN Routing/Forwarding instance name
<i>vrf-known-name</i>	(Optional) Known VRF name
<i>ipaddr</i>	IP address for LDP neighbor
implicit-withdraw	Enable LDP Implicit Withdraw Label
labels	Configure label binding exchange controls
accept	Specify label bindings to accept
<i>pfx-list</i>	Name of prefix list
targeted	Establish targeted session

Command Mode

- /exec/configure/ldp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as <asn>]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as <asn>]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [remote-as [<asn> | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp

neighbor maximum-prefix

```
{ { neighbor <address> { <interface> | maximum-prefix <value> [ warning-only ] } } | { no neighbor <address> [ <interface> | maximum-prefix <value> [ warning-only ] ] } } | { { neighbor maximum-prefix <value> [ <threshold> ] [ warning-only ] [ restart <time1> ] [ restart-count <count> ] [ reset-time <time2> ] [ dampened ] } | { no neighbor maximum-prefix [ <value> [ <threshold> ] [ warning-only ] [ restart <time1> ] [ restart-count <count> ] ] } }
```

Syntax Description

no	Negate a command or set its defaults
neighbor	Specify a neighbor router
<i>interface</i>	Interface
<i>address</i>	Neighbor address
maximum-prefix	Maximum number of IP prefixes acceptable from a neighbor
<i>value</i>	Number of IP prefixes for maximum-prefix limit
<i>threshold</i>	(Optional) Threshold value (%) at which to generate a warning message
warning-only	(Optional) Only give warning message when limit is exceeded
restart	(Optional) Duration for which a prefix source is ignored
<i>time1</i>	(Optional) Restart interval in minutes
restart-count	(Optional) Number of times sessions are auto-restarted
<i>count</i>	(Optional) Number of times
reset-time	(Optional) Duration after which restart history is cleared
<i>time2</i>	(Optional) Reset time in minutes
dampened	(Optional) Exponentially increase restart time interval

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

nemo config address port interval

nemo config address port interval

[no] nemo config address <ip_address> port <portnum> interval <interval-num>

Syntax Description

no	(Optional) Negate a command or set its defaults
nemo	Nemo switch onboarding enabler
config	Configure Nemo for switch onboarding
address	IP address of the Nemo platform
<i>ip_address</i>	IP Address
port	Port number of the Nemo platform
<i>portnum</i>	Port number
interval	Config interval in millisecond
<i>interval-num</i>	Config interval in millisecond

Command Mode

- /exec/configure

net

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/l2mp-isis/l2mp-isis-vrf-common

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/router-isis/router-isis-vrf-common

net

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/otv-isis

network

[no] network { <ip-addr> mask <ip-mask> | <ip-prefix> } [route-map <rmap-name> | summarize | evpn] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IP prefix to advertise
<i>ip-addr</i>	IP network to advertise
mask	Configure the mask of the IP prefix to advertise
<i>ip-mask</i>	Dotted 4-octet mask
<i>ip-prefix</i>	IP prefix in CIDR format
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	(Optional) Summarize more specific prefixes from routing table
evpn	(Optional) Only advertise route towards evpn side

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv4 /exec/configure/router-bgp/router-bgp-vrf-af-ipv4

network

[no] network { <ip-dest> <ip-mask> | <ip-prefix> }

Syntax Description

no	(Optional) Negate a command or set its defaults
network	RIP IP network
<i>ip-dest</i>	IP addr format
<i>ip-mask</i>	IP network mask format
<i>ip-prefix</i>	Exact prefix

Command Mode

- /exec/configure/router-rip/router-rip-af-ipv4 /exec/configure/router-rip/router-rip-vrf-af-ipv4

network

[no] network { { <address> <mask> } | <prefix> }

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Enable routing on an IP network
<i>address</i>	Network number
<i>mask</i>	EIGRP wild card bits
<i>prefix</i>	IP prefix in slash format

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-ipv4

network

[no] network <ipv6-prefix> [route-map <rmap-name> | summarize] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IPv6 prefix to advertise
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	(Optional) Summarize more specific prefixes from routing table

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv6 /exec/configure/router-bgp/router-bgp-vrf-af-ipv6

network area

[no] network { <ip-dest> <ip-mask> | <ip-prefix> } area { <area-id-ip> | <area-id-int> }

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Enable routing on an IP network
<i>ip-dest</i>	IP prefix format: i.i.i.i
<i>ip-mask</i>	IP network mask format: m.m.m.m
<i>ip-prefix</i>	IP prefix format: x.x.x.x/ml
area	Configure area properties
<i>area-id-ip</i>	OSPF area ID in IP address format
<i>area-id-int</i>	OSPF area ID as a decimal format

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

next-address exclude-address

{ next-address [loose | strict] <ipaddr> | exclude-address <ipaddr> }

Syntax Description

next-address	Specify the next address in the path
loose	(Optional) Target address is loose
strict	(Optional) Target address is strict
exclude-address	Exclude an address from subsequent partial path segments
<i>ipaddr</i>	Enter IP address (A.B.C.D)

Command Mode

- /exec/configure/te/expl-path

next-hop-self

next-hop-self

[no | default] next-hop-self

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-self	Set our peering address as nexthop

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt

next-hop-self

[no | default] next-hop-self

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-self	Set our peering address as nexthop

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv4
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv6

next-hop-third-party

[no | default] next-hop-third-party

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-third-party	Compute a third-party nexthop if possible

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt

next-hop-third-party

[no | default] next-hop-third-party

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-third-party	Compute a third-party nexthop if possible

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-label

next-hop out-label explicit-null implicit-null next-hop auto-resolve out-label explicit-null implicit-null

next-hop out-label explicit-null implicit-null next-hop auto-resolve out-label explicit-null implicit-null

[no] { next-hop [backup <interface>] <next-hop> out-label { <static-outlabel> | explicit-null | implicit-null } | next-hop auto-resolve out-label { <static-outlabel> | explicit-null | implicit-null } }

Syntax Description

no	(Optional) Negate a command or set its defaults
next-hop	Nexthop
<i>next-hop</i>	Destination IPv4 next hop
<i>static-outlabel</i>	Label Value
<i>interface</i>	(Optional) Back up interface
out-label	Output label
explicit-null	IETF MPLS IPv4 explicit null label (0)
implicit-null	IETF MPLS implicit null label (3)
auto-resolve	auto resolve the destination path
backup	(Optional) Backup destination

Command Mode

- /exec/configure/mpls_static/ipv4/input

next-hop out-label explicit-null implicit-null next-hop auto-resolve out-label explicit-null implicit-null

[no] { next-hop [backup <interface>] <ipv6-next-hop> out-label { <static-outlabel> | explicit-null | implicit-null } | next-hop auto-resolve out-label { <static-outlabel> | explicit-null | implicit-null } }

Syntax Description

no	(Optional) Negate a command or set its defaults
next-hop	Nexthop
<i>static-outlabel</i>	Label Value
<i>interface</i>	(Optional) Back up interface
out-label	Output label
explicit-null	IETF MPLS IPv6 explicit null label (2)
implicit-null	IETF MPLS implicit null label (3)
auto-resolve	auto resolve the destination path
backup	(Optional) Backup destination

Command Mode

- /exec/configure/mpls_static/ipv6/input

nexthop route-map

[no] **nexthop route-map <rmap-name>**

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Nexthop tracking
route-map	Route map for valid nexthops
<i>rmap-name</i>	Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn
 /exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn
 /exec/configure/router-bgp/router-bgp-af-ipv6-mvpn /exec/configure/router-bgp/router-bgp-af-ipv4-mdt
 /exec/configure/router-bgp/router-bgp-af-l2vpn-vpls

nexthop trigger-delay critical non-critical

```
{ nexthop trigger-delay critical <criticaldelay> non-critical <noncriticaldelay> } | { no nexthop trigger-delay }
```

Syntax Description

no	Negate a command or set its defaults
nexthop	Nexthop tracking
trigger-delay	Set the delay to trigger nexthop tracking
critical	Nexthop changes affecting reachability
non-critical	Other nexthop changes
<i>noncriticaldelay</i>	Delay value (milliseconds)
<i>criticaldelay</i>	Delay value (milliseconds)

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-ipv4-mdt
 /exec/configure/router-bgp/router-bgp-af-vpnv4 /exec/configure/router-bgp/router-bgp-af-vpnv6
 /exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-l2vpn-vpls
 /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn /exec/configure/router-bgp/router-bgp-af-ipv6-mvpn
 /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn

ngoam authentication-key

ngoam authentication-key

{ ngoam authentication-key <value> } | { no ngoam authentication-key [<value>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
authentication-key	Ngoam authentication-key
<i>value</i>	authentication key

Command Mode

- /exec/configure

ngoam connect-check

[no] ngoam connect-check <id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
connect-check	Configure ngoam oam connectivity check
<i>id</i>	connect check id

Command Mode

- /exec/configure

ngoam install acl

ngoam install acl

[no] ngoam install acl

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
install	Ngoam install
acl	Ngoam install acl

Command Mode

- /exec/configure

ngoam install acl draft-pang action fwd

[no] ngoam install acl draft-pang action { fwd | drop }

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	ngoam
install	Ngoam install
acl	Ngoam install acl
draft-pang	Ngoam install acl based on draft pang
action	Choose the action to perform
fwd	Copy and Forward the packet
drop	Copy and Drop the packet

Command Mode

- /exec/configure

ngoam probe start

ngoam probe start

ngoam probe start <hex-string>

Syntax Description

ngoam	ngoam exec command
probe	ngoam probe
start	start ngoam probe
<i>hex-string</i>	Specify string in hex string format: 0A1B .. starting with outer header of real draft pang probe packet

Command Mode

- /exec

ngoam profile

[no] ngoam profile <profile-id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
profile	Configure ngoam oam profile
<i>profile-id</i>	ngoam profile id

Command Mode

- /exec/configure

ngoam xconnect hb-interval

ngoam xconnect hb-interval

{ ngoam xconnect hb-interval <ms> } | { no ngoam xconnect hb-interval [<ms>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
xconnect	Configure xconnect parameters
hb-interval	Configure xconnect heartbeat interval
<i>ms</i>	interval in ms, 3 failures triggers failure default is 190

Command Mode

- /exec/configure

no-more

| no-more

Syntax Description

	Pipe command output to filter
no-more	Turn-off pagination for command output

Command Mode

- /output

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/macacl

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/arpacl /exec/configure/ipgroup /exec/configure/ipv6group /exec/configure/portgroup
/exec/configure/timerange

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/mplsacl

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/ipacl /exec/configure/ipv6acl

no

no

```
{ [ <seqno> ] | no } <permitdeny> { { { { ethertype <ethertypeid> } | { { ip | <proto> | <ip_other_proto> } { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { dscp { <dscp_num> } | <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + [ capture session <session-id> ] } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] } | { udf { <udf_name> <udf_val> <udf_mask> } + } } { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>ip</i>	Any IP protocol
<i>proto</i>	A protocol number
<i>ip_other_proto</i>	ip_other_proto
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix

src_key_host	A single source host
src_host	Source address
src_key_addrgrp	Source address group
src_addrgrp_name	Address group name
dst_any	Any
dst_addr	Destination network address
dst_wild	Destination wildcard bits
dst_prefix	Destination network prefix
dst_key_host	A single destination host
dst_host	Destination address
dst_key_addrgrp	Destination address group
dst_addrgrp_name	Address group name
dscp	(Optional) Match packets with given dscp value
dscp_num	(Optional) Differentiated services codepoint value
dscp_str	(Optional) Differentiated services codepoint label
tos	(Optional) Match packets with given TOS value
tos_num	(Optional) Type of service value
tos_str	(Optional) Type of service label
precedence	(Optional) Match packets with given precedence value
prec_num	(Optional) Precedence value
prec_str	(Optional) Precedence label
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
time-range	(Optional) Specify a time range
time_range_name	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
plen_op	(Optional) Packet-length operator
plen_range	(Optional) Packet-length range
plen0	(Optional) Packet length

<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_tcp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] { { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { dscp { <dscp_num> | <dscp_str> } } } | { http-method { <opt_num> | <opt_str> } } | { tcp-option-length <tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } ] } + { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { tos { <tos_num> | <tos_str> } } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + { { udf { <udf_name><udf_val><udf_mask> } + } } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } } | { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } } { [ [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { dscp { <dscp_num> | <dscp_str> } } | { ttl <ttl_num> } } | { udf { <udf_name><udf_val><udf_mask> } + } } ] } + { [ [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name><udf_val><udf_mask> } + } ] } ] } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + { { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { dscp { <dscp_num> | <dscp_str> } } | { http-method { <opt_num> | <opt_str> } } } | { tcp-option-length <tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } ] } + { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + { { udf { <udf_name><udf_val><udf_mask> } + } } ] ] } [ capture session <session-id> ] { [ action <actionid> ] } + [ log ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number

<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_tcp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group

<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	(Optional) Match packets with given TOS value
<i>tos_num</i>	(Optional) Type of service value
<i>tos_str</i>	(Optional) Type of service label
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length

<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>tcp-option-length</i>	(Optional) Specify TCP Options size
<i>tcp_opt_len</i>	(Optional) TCP option length (multiples of 4 bytes)
<i>tcp-flags-mask</i>	(Optional) Specify TCP Flags
<i>tcp_flags_mask</i>	(Optional) TCP flags mask
<i>http-method</i>	(Optional) Match packets based on http-method
<i>opt_num</i>	(Optional) http_option value
<i>opt_str</i>	(Optional) http_option_param
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>urg</i>	(Optional) Match on the URG bit
<i>ack</i>	(Optional) Match on the ACK bit
<i>psh</i>	(Optional) Match on the PSH bit
<i>rst</i>	(Optional) Match on the RST bit
<i>syn</i>	(Optional) Match on the SYN bit
<i>fin</i>	(Optional) Match on the FIN bit
<i>established</i>	(Optional) Match established connections
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session

<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipacl

no

no

```
{ [ <seqno> ] | no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_udp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] { { [ [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> | <dscp_str> } } | { ttl <ttl_num> } ] } + | { [ [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ nve vni <vni-id> ] } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ [ fragments ] [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> | <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ [ fragments ] [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + } [ nve vni <vni-id> ] } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + { { [ [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { dscp { <dscp_num> | <dscp_str> } } | { ttl <ttl_num> } ] } + | { [ [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] # 2282 ./feature/acl_mgr/cli/aclmgr.cmd [ capture session <session-id> ] { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name

<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_udp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator

no

<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	(Optional) Match packets with given TOS value
<i>tos_num</i>	(Optional) Type of service value
<i>tos_str</i>	(Optional) Type of service label
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value

<i>ttl_num</i>	(Optional)
<i>nve</i>	(Optional) VNI ID <0-16777215>
<i>vni</i>	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipacl

no

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_igmp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr>
<dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [
[ log ] [ time-range <time_range_name> ] | <igmp_num> | packet-length { <plen_op> <plen0> | <plen_range>
<plen1> <plen2> } | { dscp { <dscp_num> | <dscp_str> } } ] + | [ [ log ] [ time-range <time_range_name> ]
| <igmp_str> | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num>
| <dscp_str> } } ] + | [ [ log ] [ time-range <time_range_name> ] | <igmp_num> | packet-length { <plen_op>
<plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num>
| <prec_str> } } ] + | [ [ log ] [ time-range <time_range_name> ] | <igmp_str> | packet-length { <plen_op>
<plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num>
| <prec_str> } } ] + } } | { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host>
} | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ [ fragments ] | [ log ] [ time-range
<time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp {
<dscp_num> | <dscp_str> } } | { ttl <ttl_num> } ] } + | { [ [ fragments ] | [ log ] [ time-range
<time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos {
<tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } } [ capture
session <session-id> ] { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_igmp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits

<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	(Optional) Match packets with given TOS value
<i>tos_num</i>	(Optional) Type of service value
<i>tos_str</i>	(Optional) Type of service label
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>igmp_num</i>	(Optional) IGMP message type
<i>igmp_str</i>	(Optional) IGMP type
<i>capture</i>	(Optional) Enable packet capture on this filter for session

no

session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { { ethertype <ethertypeid> } | { <proto_icmp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ log ] [ time-range <time_range_name> ] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { dscp { <dscp_num> | <dscp_str> } } + | [ [ log ] [ time-range <time_range_name> ] | <icmp_str> | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { dscp { <dscp_num> | <dscp_str> } } ] + | [ [ log ] [ time-range <time_range_name> ] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + | [ [ log ] [ time-range <time_range_name> ] | <icmp_str> | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + } } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { dscp { <dscp_num> | <dscp_str> } } | { ttl <ttl_num> } ] + | [ [ fragments ] | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] + } } ] [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] { [ <action> <actionid> ] + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_icmp</i>	Protocol
<i>src_any</i>	Any

no

<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	(Optional) Match packets with given TOS value
<i>tos_num</i>	(Optional) Type of service value
<i>tos_str</i>	(Optional) Type of service label
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length

<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>icmp_type</i>	(Optional) ICMP message type
<i>icmp_code</i>	(Optional) ICMP message code
<i>icmp_str</i>	(Optional) ICMP label
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_tcp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] { { dscp { <dscp_num> | <dscp_str> } } } | [ { flow-label
<flow_num> } | [ log ] [ time-range <time_range_name> ] | [ urg | ack | psh | rst | syn | fin | established ] ] |
tcp-flags-mask <tcp_flags_mask> } | [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2>
} } + } | { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | {
src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { dscp { <dscp_num> | <dscp_str>
} } | { flow-label <flow_num> } | fragments | log | time-range <time_range_name> ] | packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] | { udf { <udf_name> <udf_val> <udf_mask>
} } + } | { vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> } + [
capture session <session-id> ] { <actionv6> <actionidv6> } }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_tcp</i>	Protocol
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host

src_key_addrgrp	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
src_portgroup	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
dst_key_host	A single destination host
dst_key_addrgrp	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
dst_portgroup	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
dscp	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label

no

flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
tcp-flags-mask	Specify TCP Flags
<i>tcp_flags_mask</i>	TCP flags mask
urg	(Optional) Match on the URG bit
ack	(Optional) Match on the ACK bit
psh	(Optional) Match on the PSH bit
rst	(Optional) Match on the RST bit
syn	(Optional) Match on the SYN bit
fin	(Optional) Match on the FIN bit
established	(Optional) Match established connections
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_udp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] { { dsep { <dsep_num> | <dsep_str> } } } [ { flow-label <flow_num>
} ] [ log ] [ time-range <time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } ] } + } [ nve vni <vni-id> ] | { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | {
src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild>
} | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { dscp {
<dscp_num> | <dscp_str> } } [ { flow-label <flow_num> } ] [ fragments ] [ log ] [ time-range
<time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf {
<udf_name> <udf_val> <udf_mask> } + } ] } + } [ nve vni <vni-id> ] [ vlan <vlanid> | ingress_intf {
<intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] { [ <actionv6>
<actionidv6> ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_udp</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host

no

src_key_addrgrp	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
src_portgroup	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
dst_key_host	A single destination host
dst_key_addrgrp	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
dst_portgroup	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
dscp	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label

flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
nve	(Optional) VNI ID <0-16777215>
vni	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1, port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_sctp> { { <src_any> | { <src_addr><src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> | <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> | <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] { [ { dscp { <dscp_num> | <dscp_str> } } ] [ { flow-label <flow_num>
} ] [ log ] [ time-range <time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } ] + } | { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> }
| { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { dscp { <dscp_num> | <dscp_str>
} } ] [ { flow-label <flow_num> } ] [ fragments ] [ log ] [ time-range <time_range_name> ] [ packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf { <udf_name> <udf_val> <udf_mask>
} } + } [ { vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | { vlan_priority <vlanpriorityid> } ] + [ capture
session <session-id> ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_sctp</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host

<code>src_key_addrgrp</code>	Source address group
<code>src_addrgrp_name</code>	Address group name
<code>src_port_op</code>	(Optional) Port operator
<code>src_port_range</code>	(Optional) Port range
<code>src_port0</code>	(Optional) Port number
<code>src_port0_str</code>	(Optional) SCTP port
<code>src_port1</code>	(Optional) Port number
<code>src_port1_str</code>	(Optional) SCTP port
<code>src_port2</code>	(Optional) Port number
<code>src_port2_str</code>	(Optional) SCTP port
<code>src_portgroup</code>	(Optional) src port group
<code>src_port_group</code>	(Optional) Port group name
<code>dst_any</code>	Any
<code>dst_key_host</code>	A single destination host
<code>dst_key_addrgrp</code>	Destination address group
<code>dst_addrgrp_name</code>	Address group name
<code>dst_port_op</code>	(Optional) Port operator
<code>dst_port_range</code>	(Optional) Port range
<code>dst_port0</code>	(Optional) Port number
<code>dst_port0_str</code>	(Optional) SCTP port
<code>dst_port1</code>	(Optional) Port number
<code>dst_port1_str</code>	(Optional) SCTP port
<code>dst_port2</code>	(Optional) Port number
<code>dst_port2_str</code>	(Optional) SCTP port
<code>dst_portgroup</code>	(Optional) dst port group
<code>dst_port_group</code>	(Optional) Port group name
<code>dscp</code>	(Optional) Match packets with given dscp value
<code>dscp_num</code>	(Optional) Differentiated services codepoint value
<code>dscp_str</code>	(Optional) Differentiated services codepoint label

no

flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_icmpv6> { { { { <src_any> | { <src_addr> <src_wild> } |
<src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | {
<dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name>
} } { { { <icmpv6_type> [ <icmpv6_code> ] } | { dscp { <dscp_num> | <dscp_str> } } | { flow-label
<flow_num> } | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range>
<plen1> <plen2> } ] + | [ <icmpv6_str> | { dscp { <dscp_num> | <dscp_str> } } | { flow-label <flow_num>
} | [ log ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } ] + } } | { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host>
} | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { { dscp { <dscp_num> | <dscp_str>
} } | { flow-label <flow_num> } | fragments ] | log ] [ time-range <time_range_name> ] | packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] | { udf { <udf_name> <udf_val> <udf_mask>
} } + } } | { vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] +
[ capture session <session-id> ] { [ <actionv6> <actionidv6> ] } }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_icmpv6</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group

<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>flow-label</i>	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>icmpv6_type</i>	(Optional) ICMPv6 message type
<i>icmpv6_code</i>	(Optional) ICMPv6 message code
<i>icmpv6_str</i>	(Optional) ICMPv6 label
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535>

Command Mode

- /exec/configure/ipv6acl

no

no

```
{ { [ <seqno> ] | no } <permitdeny> { { [ <arp_request> ] req_ip { <sender1_ip_any> | { { <sender1_host>
<sender1_ip> | { <sender1_net_ip> <sender1_ip_mask> } } } mac { <sender1_mac_any> | { {
<sender1_mac_host> <sender1_mac> | { <sender1_net_mac> <sender1_mac_mask> } } } } | {
<arp_response> resp_ip { <sender2_ip_any> | { { <sender2_host> <sender2_ip> | { <sender2_net_ip>
<sender2_ip_mask> } } } { <target_ip_any> | { { <target_host> <target_ip> | { <target_net_ip>
<target_ip_mask> } } } mac { <sender2_mac_any> | { { <sender2_mac_host> <sender2_mac> | {
<sender2_net_mac> <sender2_mac_mask> } } } [ { <target_mac_any> | { { <target_mac_host> <target_mac>
| { <target_net_mac> <target_mac_mask> } } } ] } [ <arp_log> ] [ capture session <session-id> ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>req_ip</i>	Any IP protocol
<i>resp_ip</i>	Any IP protocol
<i>arp_request</i>	(Optional) ARP_Request
<i>arp_response</i>	ARP_Response
<i>sender1_ip_any</i>	Any
<i>sender1_host</i>	Host
<i>sender1_ip</i>	IP address <a.b.c.d>
<i>sender1_net_ip</i>	IP address <a.b.c.d>
<i>sender1_ip_mask</i>	IP mask <a.b.c.d>
<i>sender2_ip_any</i>	Any
<i>sender2_host</i>	Host
<i>sender2_ip</i>	IP address <a.b.c.d>
<i>sender2_net_ip</i>	IP address <a.b.c.d>
<i>sender2_ip_mask</i>	IP mask <a.b.c.d>
<i>target_ip_any</i>	Any
<i>target_host</i>	Host
<i>target_ip</i>	IP address <a.b.c.d>
<i>target_net_ip</i>	IP address <a.b.c.d>

<i>target_ip_mask</i>	IP mask <a.b.c.d>
<i>mac</i>	MAC configuration commands
<i>sender1_mac_any</i>	Any
<i>sender1_mac_host</i>	Host
<i>sender1_mac</i>	MAC address EEEE.EEEE.EEEE
<i>sender1_net_mac</i>	MAC address EEEE.EEEE.EEEE
<i>sender1_mac_mask</i>	MAC mask EEEE.EEEE.EEEE
<i>sender2_mac_any</i>	Any
<i>sender2_mac_host</i>	Host
<i>sender2_mac</i>	MAC address EEEE.EEEE.EEEE
<i>sender2_net_mac</i>	MAC address EEEE.EEEE.EEEE
<i>sender2_mac_mask</i>	MAC mask EEEE.EEEE.EEEE
<i>target_mac_any</i>	(Optional) Any
<i>target_mac_host</i>	(Optional) Host
<i>target_mac</i>	(Optional) MAC address EEEE.EEEE.EEEE
<i>target_net_mac</i>	(Optional) MAC address EEEE.EEEE.EEEE
<i>target_mac_mask</i>	(Optional) MAC mask EEEE.EEEE.EEEE
<i>arp_log</i>	(Optional) Log
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session

Command Mode

- /exec/configure/arpacl

no

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>addr</i>	A.B.C.D Network address of object-group member
<i>wild</i>	A.B.C.D wildcard
<i>prefix</i>	A.B.C.D/nn Network prefix of the object-group member
<i>host</i>	Host address of the object-group member
<i>hostaddr</i>	A.B.C.D Host address

Command Mode

- /exec/configure/ipgroup

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
host	Host address of the object-group member

Command Mode

- /exec/configure/ipv6group

no

no

{ [<seqno>] | no } { <_port_op> <port0_num> | <_port_range> <port1_num> <port2_num> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>_port_op</i>	Port operator
<i>_port_range</i>	Port range
<i>port0_num</i>	Port number
<i>port1_num</i>	Port number
<i>port2_num</i>	Port number

Command Mode

- /exec/configure/portgroup

no

```
{ [ <seqno> ] | no } <permitdeny> { <src_any> | { <src_addr><src_wild> } } { <dst_any> | { <dst_addr>
<dst_wild> } } [ <mac_proto> | <mac_proto_str> ] [ vlan <vlan> | cos <cos> ] + [ time-range
<time_range_name> ] [ capture session <session-id> ] { [ <macaction> <macactionid> ] } +
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>src_any</i>	Any
<i>src_addr</i>	Source MAC address
<i>src_wild</i>	Source wildcard bits
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination MAC address
<i>dst_wild</i>	Destination wildcard bits
<i>mac_proto</i>	(Optional) MAC protocol number
<i>mac_proto_str</i>	(Optional) MAC protocol name
<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>macaction</i>	(Optional) MAC ACL Action
<i>macactionid</i>	(Optional) redirect: Ethernet1/1, port-channel1

Command Mode

- /exec/configure/macacl

no

no

[no] { userprofile | trustedCert | CRLLookup | user-switch-bind | user-certdn-match | user-pubkey-match }

Syntax Description

no	Negate a command or set its defaults
userprofile	Delete the userprofile
trustedCert	Delete the trustedCert
CRLLookup	Delete the CRLLookup
user-switch-bind	Delete the user-switch-bind
user-certdn-match	Delete the certificate matching
user-pubkey-match	Delete the pubkey matching

Command Mode

- /exec/configure/ldap/search

no

no

Syntax Description

no	Negate a command or set its defaults
----	--------------------------------------

Command Mode

- /exec/configure/vsan-db

node

[no] node [ip <ip-addr> | IPv6 <ip-addrv6>]

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	(Optional) ITD node IPv4 address
<i>ip-addr</i>	(Optional) ITD node IP4 prefix in format i.i.i.i
IPv6	(Optional) ITD node IPv6 address

Command Mode

- /exec/configure/itd-session-device-group

node

[no] node [ip <ip-addr> | IPv6 <ip-addrv6>]

Syntax Description

no	(Optional) Negate a command or set its defaults
node	Catena device-group node
ip	(Optional) Catena device-group node IPv4 address
<i>ip-addr</i>	(Optional) Catena device-group node IP4 prefix in format i.i.i.i
IPv6	(Optional) Catena device-group node IPv6 address

Command Mode

- /exec/configure/catena-device-grp

node

[no] node [ip <ip-addr> | IPv6 <ip-addrv6>]

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	(Optional) ITD node IPv4 address
<i>ip-addr</i>	(Optional) ITD node IP4 prefix in format i.i.i.i
IPv6	(Optional) ITD node IPv6 address

Command Mode

- /exec/configure/itd-device-group

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	Configure nodes for PLB device group
ip	node IPv4 address
<i>ip-addr</i>	IP4 prefix in format i.i.i.i
IPv6	node IPv6 address

Command Mode

- /exec/configure/plb-session-device-group

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	Configure nodes for PLB device group
ip	node IPv4 address
<i>ip-addr</i>	IP4 prefix in format i.i.i.i
IPv6	node IPv6 address

Command Mode

- /exec/configure/plb-device-group

npiv enable

[no] npiv enable

Syntax Description

no	(Optional) Negate a command or set its defaults
enable	Enable/Disable Nx port Id Virtualization (NPIV)

Command Mode

- /exec/configure

npv auto-load-balance disruptive

npv auto-load-balance disruptive

[no] npv auto-load-balance disruptive

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
auto-load-balance	configure auto load balancing among preferred external links
disruptive	enable disruptive auto load balancing among external links

Command Mode

- /exec/configure

npv inject-event

```
npv inject-event <i0> { ext-if-fsm interface <if0> vsan <i1> | ext-if-vsang fsm interface <if1> vsan <i2> |
flogi-fsm interface <if2> pwwn <wwn3> vsan <i4> | svr-if-fsm interface <if3> vsan <i5> }
```

Syntax Description

npv	Execute NPV commands
inject-event	Inject event to fsm
<i>i0</i>	Enter event-id
ext-if-fsm	Inject event to external interface fsm
interface	Enter external interface
<i>if0</i>	
vsan	Enter VSAN
<i>i1</i>	
ext-if-vsang fsm	Inject event to external interface vsan fsm
interface	Enter external interface
<i>if1</i>	
vsan	Enter VSAN
<i>i2</i>	
flogi-fsm	Inject event to flogi fsm
interface	Enter server interface
<i>if2</i>	
pwwn	Enter port WWN
<i>wwn3</i>	
vsan	Enter VSAN
<i>i4</i>	
svr-if-fsm	Inject event to server interface fsm
interface	Enter server interface
<i>if3</i>	
vsan	Enter VSAN

npv inject-event

i5	
----	--

Command Mode

- /exec

npv traffic-map server-interface external-interface

[no] npv traffic-map server-interface <if1> external-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
traffic-map	Configure NPV traffic engineering
server-interface	Configure server interface based traffic engineering
<i>if1</i>	
external-interface	Configure preferred external interface(s)
<i>interface</i>	

Command Mode

- /exec/configure

nsf await-redist-proto-convergence

{ [no] nsf await-redist-proto-convergence }

Syntax Description

no	(Optional) Negate a command or set its defaults
nsf	Non-stop forwarding
await-redist-proto-convergence	Specify whether EIGRP should wait for other protocols to converge before advertising routes

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

ntp access-group

[no] ntp access-group { peer | serve-only | serve | query-only } <acl-name>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
peer	access-group peer
serve	access-group serve
serve-only	access-group serve-only
query-only	access-group query-only
<i>acl-name</i>	Name of access list

Command Mode

- /exec/configure

ntp access-group match-all

ntp access-group match-all

[no] ntp access-group match-all

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
match-all	Scan ACLs present in all ntp access groups

Command Mode

- /exec/configure

ntp allow private

[no] ntp allow { private | control [rate-limit <delay>] }

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
allow	Enable/Disable the packets
private	Enable/Disable Private mode packets
control	Enable/Disable Control mode packets
rate-limit	(Optional) Rate-limit the control packets
delay	(Optional) Rate-limit delay (Default 3)

Command Mode

- /exec/configure

ntp authenticate

[no] ntp authenticate

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authenticate	Enable/Disable authentication

Command Mode

- /exec/configure

ntp authentication-key md5

[no] ntp authentication-key <number> md5 <md5> [0 | 7]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authentication-key	NTP authentication key
<i>number</i>	authentication key number (range 1-65535)
md5	use md5 authentication scheme
<i>md5</i>	MD5 string
0	(Optional) clear text
7	(Optional) encrypted

Command Mode

- /exec/configure

ntp drop-aged-packet

ntp drop-aged-packet

[no] ntp drop-aged-packet

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
drop-aged-packet	Enable or disable Riviera Timestamp Check.

Command Mode

- /exec/configure

ntp logging

[no] ntp logging

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
logging	Enable/Disable logging of NTPD Events

Command Mode

- /exec/configure

ntp master

ntp master

[no] ntp master [<stratum-no>]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
master	Act as NTP master clock
<i>stratum-no</i>	(Optional) Stratum number

Command Mode

- /exec/configure

ntp passive

[no] ntp passive

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
passive	NTP passive command

Command Mode

- /exec/configure

ntp peer

[no] ntp peer <host0> [prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll>] +

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
peer	NTP Peer address
<i>host0</i>	Hostname/IP address of the NTP Peer
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a peer
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a peer
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp rts-update

[no] ntp rts-update

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
rts-update	Enable or disable RTS update to linecards.

Command Mode

- /exec/configure

ntp server

[no] ntp server <host0> [prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll>] +

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
server	NTP server address
<i>host0</i>	Hostname/IP address of the NTP Server
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a server
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a server
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp source-interface

[no] ntp source-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
source-interface	Source interface sending NTP packets
<i>interface</i>	Source interface

Command Mode

- /exec/configure

ntp source

[no] ntp source <ip-addr>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP Configuration
source	Source of NTP packets
<i>ip-addr</i>	IPv4/IPv6 address

Command Mode

- /exec/configure

ntp sync-retry

ntp sync-retry

Syntax Description

ntp	NTP configuration
sync-retry	Retry synchronization with configured servers

Command Mode

- /exec

ntp trusted-key

ntp trusted-key

[no] ntp trusted-key <number>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
trusted-key	NTP trusted-key
number	trusted-key number

Command Mode

- /exec/configure

nv overlay evpn

[no] nv overlay evpn

Syntax Description

no	(Optional) Negate a command or set its defaults
nv	Command to enable/disable features
overlay	Command to enable/disable features
evpn	Enable/Disable Ethernet VPN (EVPN)

Command Mode

- /exec/configure

nve event-history size

nve event-history { <buffer-name> } size { <size_in_text> | <size_in_bytes> }

Syntax Description

nve	Display NVE information
event-history	Configure the event-history buffers
<i>buffer-name</i>	Event history buffer whose size is to be configured
size	Configure the buffer sizes
<i>size_in_text</i>	Size of event history buffer
<i>size_in_bytes</i>	Size in bytes in the range 1-5000000

Command Mode

- /exec/configure

nve interface remap-replication-servers

nve interface <nve-if> remap-replication-servers

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
remap-replication-servers	Remap Replication servers to VNIs

Command Mode

- /exec

nve interface replication-server up

nve interface <nve-if> replication-server <rep-addr> { up | down }

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
replication-server	Configure a replication server
<i>rep-addr</i>	Replication Server IP Address
up	mark replication-server up
down	mark replication-server down

Command Mode

- /exec

nve oam mode draft-pang

[no] nve oam mode draft-pang

Syntax Description

no	(Optional) Negate a command or set its defaults
nve	VxLAN functionality
oam	VxLAN OAM functionality
mode	Choose operation mode for OAM
draft-pang	OAM implementation as per Draft Pang

Command Mode

- /exec/configure

nxapi certificate

```
{ nxapi certificate { { httpskey { keyfile <uri0> | <line> } } | { httpscert { certfile <uri1> | <line1> } } | { enable } } }
```

Syntax Description

nxapi	Configure nxapi
certificate	Https certificate configuration
httpskey	Https private key
httpscert	Https certificate
keyfile	Https key file
certfile	Https certificate file
enable	Enable the current certificate
<i>uri0</i>	File containing https private key for the user
<i>line</i>	nxapi https private key
<i>uri1</i>	File containing https certificate
<i>line1</i>	nxapi https certificate

Command Mode

- /exec/configure

nxapi flow

{ [no] nxapi flow }

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
flow	allow frontend to access /sys/flow/

Command Mode

- /exec/configure

nxapi http port

{ nxapi { http | https } port <s0> } | { no nxapi { http | https } } | { no nxapi { http | https } port <s0> }

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
http	Http configuration
https	Https configuration
port	Port number
s0	Port number. Please do not use well-known protocol ports

Command Mode

- /exec/configure

nxapi ssl ciphers weak

{ [no] nxapi ssl ciphers weak }

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
ciphers	Configure allowed ciphers for ssl
weak	Allow weak ciphers

Command Mode

- /exec/configure

nxapi ssl protocols

{ nxapi ssl protocols <prot_string> } | { no nxapi ssl protocols }

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
protocols	Configure allowed ssl protocols
<i>prot_string</i>	String of supported protocols, Ex: TLSv1 TLSv1.1 TLSv1.2

Command Mode

- /exec/configure

nxapi use-vrf management default

```
{ nxapi use-vrf { management | default | <vrf_name> } } | { no nxapi use-vrf { management | default | <vrf_name> } }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
use-vrf	vrf to be used for nxapi communication
management	management vrf
default	default vrf
<i>vrf_name</i>	name of the vrf

Command Mode

- /exec/configure

nx sdk enable app

nx sdk enable app

[no] nx sdk enable app <app-index>

Syntax Description

no	(Optional) Negate a command or set its defaults
nx sdk	NXOS SDK
enable	Command to enable/disable nx sdk application
app	Enable/disable application
<i>app-index</i>	Application index

Command Mode

- /exec

nx sdk service-name

{ [no] nx sdk service-name <service-name> }

Syntax Description

nx sdk	NXOS SDK
service-name	Complete path and name of file to execute
<i>service-name</i>	Service name

Command Mode

- /exec/configure

nxSDK service-name