



Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

This chapter contains the following sections:

- [Information About Configuring Seamless Integration of EVPN with L3VPN \(MPLS SR\)](#), on page 1
- [Guidelines and Limitations for Configuring Seamless Integration of EVPN with L3VPN \(MPLS SR\)](#), on page 4
- [Configuring Seamless Integration of EVPN with L3VPN \(MPLS SR\)](#), on page 5
- [Example Configuration for Configuring Seamless Integration of EVPN with L3VPN \(MPLS SR\)](#), on page 9


Information About Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

Data Center (DC) deployments have adopted VXLAN EVPN for its benefits such as EVPN control-plane learning, multi tenancy, seamless mobility, redundancy, and easier horizontal scaling. Similarly, the Core network transitions to different technologies with their respective capabilities. MPLS with Label Distribution Protocol (LDP) and Layer-3 VPN (L3VPN) is present in many Core networks interconnecting Data Centers. With the technology evolution, a transformation from the traditional MPLS L3VPN with LDP-based underlay to MPLS-based Segment Routing (SR) with L3VPN, became available. Segment Routing is adopted for its benefits such as:

- Unified IGP and MPLS control planes
- Simpler traffic engineering methods


With the Data center (DC) established on VXLAN EVPN and the Core network requiring multi-tenant capable transport, there is a natural necessity to seamless integration. To provide this seamless integration between different control-plane protocols and encapsulations, in this case here from VXLAN to an MPLS-based Core network, the Cisco Nexus 9000 Series Switch provides the Border Provider Edge (Border PE) capability by interfacing the Data Center and the Core routers (Provider Routers or Provider Edge-Routers).

Figure 1: Topology with DC to Core Network Domain Separation



In the above figure, a single Data Center Fabric running VXLAN EVPN is depicted. The VRFs (VRF_A, VRF_B) present in the Data Center require to be extended over a WAN/Core running MPLS-based Segment Routing (MPLS-SR). The Data Center Fabric's Border switches act as Border Provider Edge (Border PE1, Border PE2) interconnecting VXLAN BGP EVPN with MPLS-SR with L3VPN (VPNv4/VPNv6). The BPEs are interconnected with the Provider Router (P-Router) via eBGP using the IPv4 Labeled-Unicast as well as the VPNv4/VPNv6 Address-Family (AF). The P-Routers act as BGP Route-Reflector for the mentioned AF and relay the necessary routes to the MPLS-SR Provider Edge (PE3, PE4) via iBGP. Beyond the usage of BGP as the control-plane, between the MPLS-SR nodes within the same Autonomous System (AS) uses an IGP (OSPF or ISIS) for label distribution. From the PEs shown in the above figure (PE3, PE4), Inter-AS Option A can be used to extend the Data Center or Core network VRFs to another external network. Even as this diagram shows only one Data Center, the MPLS-SR network can be used to interconnect multiple Data Center Fabrics.

Figure 2: Multiple Administrative Domains within the Core network



An alternative deployment scenario is when the Core network is separate into multiple Administrative Domains or Autonomous Systems (AS). In the above figure, a single Data Center Fabric running VXLAN EVPN is depicted. The VRFs (VRF_A, VRF_B) present in the Data Center requires to be extended over a WAN/Core running MPLS-based Segment Routing (MPLS-SR). The Data Center Fabrics Border switches acts as Border Provider Edge (Border PE1, Border PE2) interconnecting VXLAN BGP EVPN with MPLS-SR with L3VPN (VPNv4/VPNv6). The BPEs are interconnected with the Provider Router (P-Router) via eBGP using the IPv4 Labeled-Unicast as well as the VPNv4/VPNv6 Address-Family (AF). The P-Router act as BGP Route Server for the mentioned AF and relays the necessary routes to the MPLS-SR Provider Edge (PE3, PE4) via eBGP; no other control-plane protocol is used between the MPLS-SR nodes. Similar as in the previous scenario, the PEs (PE3, PE4) can operate with Inter-AS Option A to extend the Data Center or Core network VRFs to external network. Even as this diagram shows only one Data Center, the MPLS-SR network can be used to interconnect multiple Data Center Fabrics.

For additional information on MPLS SR, see the *Cisco Nexus 9000 Series NX-OS Label Switching Configuration Guide*.

Guidelines and Limitations for Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

Feature	Cisco Nexus 9300-FX2, FX3, GX Platform Switches	Cisco Nexus 9504 and 9508 switches with -R Line Cards	Comments
VXLAN EVPN to SR-L3VPN	Yes	Yes	Extend Layer 3 connectivity between different DC pods Underlay IGP/BGP with SR extensions.
VXLAN EVPN to SR-L3VPN	Yes	Yes	Extend Layer 3 connectivity between DC POD running VXLAN and any domain (DC or CORE) running SR.
VXLAN EVPN to MPLS L3VPN (LDP)	No	Yes	Underlay is LDP.

The following Cisco Nexus platform switches support seamless integration of EVPN with L3VPN (MPLS SR):

- 9336C-FX2 switches
- 93240YC-FX2 switches
- 9300-FX3 platform switches
- 9300-GX platform switches
- 9504 and 9508 platform switches with 96136YC-R and 9636C-RX line cards (The 9636C-R and 9636Q-R line cards are not supported.)

The following features are supported with seamless integration of EVPN with L3VPN (MPLS SR):

- Host Facing (Downlinks towards)
 - Individual Layer-3 interfaces (orphan ports)
 - Layer-3 Port-Channel
 - Layer-3 Sub-interfaces
 - Inter-AS Option A (often also called VRF-lite)
- Core Facing (Uplinks towards VXLAN)
 - Individual Layer-3 interfaces

- Layer-3 Port-Channel
- Core Facing (Uplinks towards MPLS SR)
 - Individual Layer-3 interface
 - Per-VRF labels
 - VPN label statistics
- End-to-End Time to Live (TTL) and Explicit Congestion Notification (ECN) with pipe-mode only.
- MPLS Segment Routing and MPLS LDP cannot be configured at the same time on a Cisco Nexus 9504 and 9508 platform switches with Cisco Nexus 96136YC-R and Cisco Nexus 9636C-RX line cards.

The VXLAN-to-SR handoff QoS value is preserved during handoff and propagated from VXLAN tunnel packets to SR-tunneled packets for Cisco Nexus 9336C-FX2, 93240YC-FX2, 9300-FX3, and 9300-GX platform switches.

The following features are not supported with seamless integration of EVPN with L3VPN (MPLS SR):

- Distributed Anycast Gateway or First-Hop Redundancy Protocol like HSRP, VRRP or GLBP.
- vPC for redundant Host or Network Service attachment.
- SVI/Sub-interfaces for Core facing uplinks (MPLS or VXLAN).
- SVI/Sub-interfaces with configured MAC addresses.
- MPLS Segment Routing and Border Gateway (BGW for VXLAN Multi-Site) cannot be configured at the same time.
- Layer-2 for stretched Subnet across the MPLS-SR domain
- No-drop for VXLAN/SR and SR/VXLAN handoff, for Cisco Nexus 9336C-FX2, 93240YC-FX2, and 9300-FX3 platform switches
- Statistics, for Cisco Nexus 9504 and 9508 platform switches with 96136YC-R and 9636C-RX line cards
- Priority flow control (PFC), for Cisco Nexus 9336C-FX2, 93240YC-FX2, 9300-FX3, and 9300-GX platform switches

Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

The following procedure for Border Provider Edge (Border PE) imports and reoriginates the routes from the VXLAN domain to the MPLS domain and in the other direction.

Procedure

	Command or Action	Purpose
Step 1	configure terminal Example:	Enters global configuration mode.

	Command or Action	Purpose
	<code>switch# configure terminal</code>	
Step 2	feature-set mpls Example: <code>switch(config)# feature-set mpls</code>	Enables the MPLS feature set.
Step 3	nv overlay evpn Example: <code>switch(config)# nv overlay evpn</code>	Enables VXLAN.
Step 4	feature bgp Example: <code>switch(config)# feature bgp</code>	Enables BGP.
Step 5	feature mpls l3vpn Example: <code>switch(config)# feature mpls l3vpn</code>	Enables Layer 3 VPN. Note Feature mpls l3vpn requires feature mpls segment-routing.
Step 6	feature mpls segment-routing Example: <code>switch(config)# feature mpls segment-routing</code>	Enables Segment Routing.
Step 7	feature interface-vlan Example: <code>switch(config)# feature interface-vlan</code>	Enables the interface VLAN.
Step 8	feature vn-segment-vlan-based Example: <code>switch(config)# feature vn-segment-vlan-based</code>	Enables the VLAN-based VN segment.
Step 9	feature nv overlay Example: <code>switch(config)# feature nv overlay</code>	Enables VXLAN.
Step 10	router bgp <i>autonomous-system-number</i> Example: <code>switch(config)# router bgp 65095</code>	Configures BGP. The value of <i>autonomous-system-number</i> is from 1 to 4294967295.
Step 11	address-family ipv4 unicast Example: <code>switch(config-router)# address-family ipv4 unicast</code>	Configures the address family for IPv4.

	Command or Action	Purpose
Step 12	network <i>address</i> Example: <pre>switch(config-router-af) # network 10.51.0.51/32</pre>	Injects prefixes into BGP for the MPLS-SR domain. Note All viable next-hops for MPLS-SR tunnel deposition on the Border PE must be advertised via the network statement (/32 only).
Step 13	allocate-label all Example: <pre>switch(config-router-af) # allocate-label all</pre>	Configures label allocation for every prefix injected via the network statement.
Step 14	exit Example: <pre>switch(config-router-af) # exit</pre>	Exits command mode.
Step 15	neighbor <i>address remote-as number</i> Example: <pre>switch(config-router) # neighbor 10.95.0.95 remote-as 65095</pre>	Defines the iBGP neighbor IPv4 address and remote Autonomous-System (AS) number towards the Route-Reflector.
Step 16	update-source <i>type/id</i> Example: <pre>switch(config-router) # update-source loopback0</pre>	Defines the interface for eBGP peering.
Step 17	address-family <i>l2vpn evpn</i> Example: <pre>switch(config-router) # address-family l2vpn evpn</pre>	Configures the L2VPN EVPN address family.
Step 18	send-community both Example: <pre>switch(config-router-af) # send-community both</pre>	Configures the community for BGP neighbors.
Step 19	import vpn unicast reoriginate Example: <pre>switch(config-router-af) # import vpn unicast reoriginate</pre>	Reoriginates the route with a new Route-Target. It can be extended to use an optional route-map.
Step 20	exit Example: <pre>switch(config-router-af) # exit</pre>	Exits command mode.


	Command or Action	Purpose
Step 21	neighbor <i>address remote-as number</i> Example: switch(config-router)# neighbor 10.51.131.131 remote-as 65013	Defines the eBGP neighbor IPv4 address and remote Autonomous-System (AS) number towards the P-Router.
Step 22	update-source <i>type/id</i> Example: switch(config-router)# update-source Ethernet1/1	Defines the interface for eBGP peering.
Step 23	address-family ipv4 labeled-unicast Example: switch(config-router)# address-family ipv4 labeled-unicast	Configures the address family for IPv4 labeled-unicast.
Step 24	send-community both Example: switch(config-router-af)# send-community both	Configures the community for BGP neighbors.
Step 25	exit Example: switch(config-router-af)# exit	Exits command mode.
Step 26	neighbor <i>address remote-as number</i> Example: switch(config-router)# neighbor 10.131.0.131 remote-as 65013	Defines the eBGP neighbor IPv4 address and remote Autonomous-System (AS) number.
Step 27	update-source <i>type/id</i> Example: switch(config-router)# update-source loopback0	Defines the interface for eBGP peering.
Step 28	ebgp-multihop <i>number</i> Example: switch(config-router)# ebgp-multihop 5	Specifies multihop TTL for the remote peer. The range of <i>number</i> is from 2 to 255.
Step 29	address-family vpnv4 unicast Example: switch(config-router)# address-family vpnv4 unicast	Configures the address family for VPNv4 or VPNv6.
Step 30	send-community both Example:	Configures the community for BGP neighbors.

	Command or Action	Purpose
	<code>switch(config-router-af)# send-community both</code>	
Step 31	import l2vpn evpn reoriginate Example: <code>switch(config-router-af)# import l2vpn evpn reoriginate</code>	Reoriginates the route with a new Route-Target. It can be extended to use an optional route-map.
Step 32	exit Example: <code>switch(config-router-af)# exit</code>	Exits command mode.

Example Configuration for Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

Scenario - 1 with DC to Core Network Domain Separation and IGP within MPLS-SR network.

Figure 3: Topology with DC to Core Network Domain Separation



The following is a sample CLI configuration that is required to import and reoriginate the routes from the VXLAN domain to the MPLS domain and in the reverse direction. The sample CLI configuration represents only the necessary configuration for the respective roles.

Border PE

```
hostname BL51-N9336FX2
install feature-set mpls

feature-set mpls

feature bgp
feature mpls l3vpn
feature mpls segment-routing
```

```
feature ospf
feature interface-vlan
feature vn-segment-vlan-based
feature nv overlay

nv overlay evpn

mpls label range 16000 23999 static 6000 8000

segment-routing
  mpls
    connected-prefix-sid-map
      address-family ipv4
        10.51.0.51/32 index 51

vlan 2000
  vn-segment 50000

vrf context VRF_A
  vni 50000
  rd auto
  address-family ipv4 unicast
    route-target both auto
    route-target both auto evpn
    route-target import 50000:50000
    route-target export 50000:50000
  address-family ipv6 unicast
    route-target both auto
    route-target both auto evpn
    route-target import 50000:50000
    route-target export 50000:50000

interface Vlan2000
  no shutdown
  vrf member VRF_A
  no ip redirects
  ip forward
  ipv6 address use-link-local-only
  no ipv6 redirects

interface nve1
  no shutdown
  host-reachability protocol bgp
  source-interface loopback1
  member vni 50000 associate-vrf

interface Ethernet1/1
  description TO_P-ROUTER
  ip address 10.51.131.51/24
  mpls ip forwarding
  no shutdown

interface Ethernet1/36
  description TO_SPINE
  ip address 10.95.51.51/24
  ip router ospf 10 area 0.0.0.0
  no shutdown

interface loopback0
  description ROUTER-ID & SR-LOOPBACK
  ip address 10.51.0.51/32
  ip router ospf UNDERLAY area 0.0.0.0

interface loopback1
```

Example Configuration for Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)

```

description NVE-LOOPBACK
ip address 10.51.1.51/32
ip router ospf UNDERLAY area 0.0.0.0

router ospf UNDERLAY
router-id 10.51.0.51

router bgp 65095
address-family ipv4 unicast
network 10.51.0.51/32
allocate-label all
!
neighbor 10.95.0.95
remote-as 65095
update-source loopback0
address-family l2vpn evpn
send-community
send-community extended
import vpn unicast reoriginate
!
neighbor 10.51.131.131
remote-as 65013
update-source Ethernet1/1
address-family ipv4 labeled-unicast
send-community
send-community extended
!
neighbor 10.131.0.131
remote-as 65013
update-source loopback0
ebgp-multihop 5
address-family vpv4 unicast
send-community
send-community extended
import l2vpn evpn reoriginate
address-family vpv6 unicast
send-community
send-community extended
import l2vpn evpn reoriginate
!
vrf VRF_A
address-family ipv4 unicast
redistribute direct route-map fabric-rmap-redirect-subnet

```

P-Router

```

hostname P131-N9336FX2
install feature-set mpls

feature-set mpls

feature bgp
feature isis
feature mpls l3vpn
feature mpls segment-routing

mpls label range 16000 23999 static 6000 8000

segment-routing
mpls
connected-prefix-sid-map
address-family ipv4
10.131.0.131/32 index 131

```

```
route-map RM_NH_UNCH permit 10
  set ip next-hop unchanged

interface Ethernet1/1
  description TO_BORDER-PE
  ip address 10.51.131.131/24
  ip router isis 10
  mpls ip forwarding
  no shutdown

interface Ethernet1/11
  description TO_PE
  ip address 10.52.131.131/24
  ip router isis 10
  mpls ip forwarding
  no shutdown

interface loopback0
  description ROUTER-ID & SR-LOOPBACK
  ip address 10.131.0.131/32
  ip router isis 10

router isis 10
  net 49.0000.0000.0131.00
  is-type level-2
  address-family ipv4 unicast
  segment-routing mpls

router bgp 65013
  event-history detail
  address-family ipv4 unicast
  allocate-label all
!
  neighbor 10.51.131.51
    remote-as 65095
    update-source Ethernet1/1
    address-family ipv4 labeled-unicast
      send-community
      send-community extended
!
  neighbor 10.51.0.51
    remote-as 65095
    update-source loopback0
    ebgp-multihop 5
    address-family vpnv4 unicast
      send-community
      send-community extended
    route-map RM_NH_UNCH out
    address-family vpnv6 unicast
      send-community
      send-community extended
    route-map RM_NH_UNCH out
!
  neighbor 10.52.131.52
    remote-as 65013
    update-source Ethernet1/11
    address-family ipv4 labeled-unicast
      send-community
      send-community extended
!
  neighbor 10.52.0.52
    remote-as 65013
    update-source loopback0
    address-family vpnv4 unicast
```

```

    send-community
    send-community extended
    route-reflector-client
    route-map RM_NH_UNCH out
address-family vpnv6 unicast
    send-community
    send-community extended
    route-reflector-client
    route-map RM_NH_UNCH out

```

Provider Edge (PE)

```

hostname L52-N93240FX2
install feature-set mpls

feature-set mpls

feature bgp
feature isis
feature mpls l3vpn
feature mpls segment-routing

mpls label range 16000 23999 static 6000 8000

segment-routing
mpls
    connected-prefix-sid-map
    address-family ipv4
        10.52.0.52/32 index 52

vrf context VRF_A
rd auto
address-family ipv4 unicast
    route-target import 50000:50000
    route-target export 50000:50000
address-family ipv6 unicast
    route-target import 50000:50000
    route-target export 50000:50000

interface Ethernet1/49
description TO_P-ROUTER
ip address 10.52.131.52/24
ip router isis 10
mpls ip forwarding
no shutdown

interface loopback0
description ROUTER-ID & SR-LOOPBACK
ip address 10.52.0.52/32
ip router isis 10

router isis 10
net 49.0000.0000.0052.00
is-type level-2
address-family ipv4 unicast
    segment-routing mpls


router bgp 65013
address-family ipv4 unicast
network 10.52.0.52/32
allocate-label all
!
neighbor 10.52.131.131
remote-as 65013
update-source Ethernet1/49

```

```
    address-family ipv4 labeled-unicast
      send-community
      send-community extended
!
neighbor 10.131.0.131
  remote-as 65013
  update-source loopback0
  address-family vpnv4 unicast
    send-community
    send-community extended
  address-family vpnv6 unicast
    send-community
    send-community extended
!
vrf VRF_A
  address-family ipv4 unicast
    redistribute direct route-map fabric-rmap-redirect-subnet
```

Scenario - 2 with DC to Core and within Core Network Domain Separation (eBGP within MPLS-SR network).

Figure 4: Multiple Administrative Domains within the Core network



The following is a sample CLI configuration that is required to import and reoriginate the routes from the VXLAN domain to the MPLS domain and in the reverse direction. The sample CLI configuration represents only the nodes that are different from Scenario #1, which are the P-Router and the Provider Edge (PE) roles. The Border PE remains the same for both scenarios.

P-Router

```
hostname P131-N9336FX2
install feature-set mpls

feature-set mpls

feature bgp
feature mpls l3vpn
feature mpls segment-routing
```



```
mpls label range 16000 23999 static 6000 8000

segment-routing
  mpls
    connected-prefix-sid-map
      address-family ipv4
        10.131.0.131/32 index 131

route-map RM_NH_UNCH permit 10
  set ip next-hop unchanged

interface Ethernet1/1
  description TO_BORDER-PE
  ip address 10.51.131.131/24
  mpls ip forwarding
  no shutdown

interface Ethernet1/11
  description TO_PE
  ip address 10.52.131.131/24
  mpls ip forwarding
  no shutdown

interface loopback0
  description ROUTER-ID & SR-LOOPBACK
  ip address 10.131.0.131/32
  ip router isis 10

router bgp 65013
  event-history detail
  address-family ipv4 unicast
    network 10.131.0.131/32
    allocate-label all
  !
  address-family vpnv4 unicast
    retain route-target all
  address-family vpnv6 unicast
    retain route-target all
  !
  neighbor 10.51.131.51
    remote-as 65095
    update-source Ethernet1/1
    address-family ipv4 labeled-unicast
      send-community
      send-community extended
  !
  neighbor 10.51.0.51
    remote-as 65095
    update-source loopback0
    ebgp-multihop 5
    address-family vpnv4 unicast
      send-community
      send-community extended
    route-map RM_NH_UNCH out
    address-family vpnv6 unicast
      send-community
      send-community extended
    route-map RM_NH_UNCH out
  !
  neighbor 10.52.131.52
    remote-as 65003
    update-source Ethernet1/11
    address-family ipv4 labeled-unicast
```

```

        send-community
        send-community extended
    !
    neighbor 10.52.0.52
        remote-as 65003
        update-source loopback0
        ebgp-multihop 5
        address-family vpnv4 unicast
            send-community
            send-community extended
            route-map RM_NH_UNCH out
        address-family vpnv6 unicast
            send-community
            send-community extended
            route-map RM_NH_UNCH out

```

Provider Edge (PE)

```

hostname L52-N93240FX2
install feature-set mpls

feature-set mpls

feature bgp
feature mpls l3vpn
feature mpls segment-routing

mpls label range 16000 23999 static 6000 8000

segment-routing
    mpls
        connected-prefix-sid-map
            address-family ipv4
                10.52.0.52/32 index 52

vrf context VRF_A
    rd auto
    address-family ipv4 unicast
        route-target import 50000:50000
        route-target export 50000:50000
    address-family ipv6 unicast
        route-target import 50000:50000
        route-target export 50000:50000

interface Ethernet1/49
    description TO_P-ROUTER
    ip address 10.52.131.52/24
    mpls ip forwarding
    no shutdown

interface loopback0
    description ROUTER-ID & SR-LOOPBACK
    ip address 10.52.0.52/32
    ip router isis 10

router bgp 65003
    address-family ipv4 unicast
        network 10.52.0.52/32
        allocate-label all
    !
    neighbor 10.52.131.131
        remote-as 65013
        update-source Ethernet1/49
        address-family ipv4 labeled-unicast
            send-community

```

```
        send-community extended
!
neighbor 10.131.0.131
  remote-as 65013
  update-source loopback0
  ebgp-multihop 5
  address-family vpnv4 unicast
    send-community
    send-community extended
  address-family vpnv6 unicast
    send-community
    send-community extended
!
vrf VRF_A
  address-family ipv4 unicast
    redistribute direct route-map fabric-rmap-redist-subnet
```

Example Configuration for Configuring Seamless Integration of EVPN with L3VPN (MPLS SR)