

Auto Configuration

The auto configuration contains the following tables:

- [Organization, page -10](#)
- [Partition, page -10](#)
- [Network, page -10](#)
- [Profile, page -11](#)
- [Mandatory Field Class table, page -12](#)

The following are the auto-configuration REST APIs:

- [List Organizations, page -15](#)
- [Create an Organization, page -16](#)
- [Get an Organization, page -17](#)
- [Update an Organization, page -18](#)
- [Delete an Organization, page -19](#)
- [List Partitions, page -20](#)
- [Create a Partition, page -21](#)
- [Get a Partition, page -22](#)
- [Update a Partition, page -23](#)
- [Delete a Partition, page -24](#)
- [List Networks, page -25](#)
- [Create a Network, page -26](#)
- [Get a Network, page -27](#)
- [Update a Network, page -28](#)
- [Delete a Network, page -29](#)
- [Create a Auto Configuration profile, page -33](#)
- [Delete a Auto Configuration profile, page -36](#)
- [Get Auto Config Settings, page -30](#)
- [Update Auto Config Settings, page -31](#)
- [List Auto Configuration Profiles, page -32](#)
- [Create a Auto Configuration profile, page -33](#)
- [Get a Auto Configuration profile, page -34](#)
- [Update a Auto Configuration profile, page -35](#)
- [Delete a Auto Configuration profile, page -36](#)

Organization

Attributes	Type	Require
organizationName	String	Mandatory
description	String	Optional
orchestrationSource	String	Optional

Partition

Attributes	Type	Require
partitionName	String	Mandatory
partitionSegmentId	String	Mandatory
organizationName	String	Mandatory
vrfProfileName	String	Mandatory
description	String	Optional
serviceNodeIpAddress	String	Optional
dnsServer	String	Optional
secondaryDNSServer	String	Optional
vrfName	String	Optional
dciId	String	Optional
configArg	String	Optional

Network

Attributes	Type	Require
organizationName	String	Mandatory
networkRole	String	Mandatory
networkName	String	Mandatory
segmentId	String	Mandatory
vlanId	String	Mandatory
mobilityDomainId	String	Mandatory
profileName	String	Mandatory
partitionName	String	Mandatory
dvsId	String	Optional
staticIpStart	String	Optional
gateway	String	Optional
netmaskLength	String	Optional
gatewayIpv6Address	String	Optional
prefixLength	String	Optional
secondaryGateway	String	Optional

Attributes	Type	Require
staticIpEnd	String	Optional
vSwitchControllerNetworkId	String	Optional
description	String	Optional
vSwitchControllerId	String	Optional
configArg	String	Optional
dhcpScope	subnet	Optional
	gateway	Optional
	ipRange	Optional
vrfName	String	Optional

Profile

Attributes	Type	Require
forwardingMode	String	Mandatory
profileName	String	Mandatory
configCommands	String	Mandatory
description	String	Optional
profileType	String	Mandatory
profileSubType	String	Mandatory

Mandatory Field Class table

ConfigDeliveryTask

Attributes	Type	Required	Constants, Formats
description	String	Mandatory	
timeout	Number	Mandatory	
scheduledTimeStr	String	Mandatory	Format: dd/MM/yyyy HH:mm:ss
configDeliveryTaskRollbackSetting	String	Mandatory	Possible values: <ul style="list-style-type: none"> Rollback on Device and Stop Delivery on Other Devices Rollback on Device and Continue Delivery on Other Devices Rollback on All Devices Stop Delivery on Error Stop Delivery on All Devices on Error Continue on Error
configDeliveryTaskDeliveryOrderSetting	String	Optional	Possible values: <ul style="list-style-type: none"> sequential parallel
configTemplateRef	ConfigTemplate	Mandatory	
configDeliveryTaskDeviceDetailsCollection	ConfigDeliveryTaskDeviceDetails[]	Mandatory	
isCopyRunToStartTask	Boolean	Optional	
username	String	Mandatory	
password	String	Mandatory	

ConfigTemplate

Attributes	Type	Required
name	String	Mandatory
instanceClassId	Number	Optional

ConfigDeliveryTaskDeviceDetails

Attributes	Type	Required
ipAddress	String	Mandatory
paramValues	Array	Mandatory

Status

The following table details the API Response code, status and, the HTTPS methods.

Status Code	Status	API's HTTPS Method or HTTPS Method
200	OK	GET OK POST PUT DELETE
202 ¹	Accepted	POST PUT DELETE
400	Bad Request	GET POST PUT DELETE
401	Unauthorized	GET POST PUT DELETE
403	Forbidden	GET POST PUT DELETE
404	Not Found	GET POST PUT DELETE

Status Code	Status	API's HTTPS Method or HTTPS Method
405	Method Not Allowed	GET POST PUT DELETE
500	Internal Server Error	GET POST PUT DELETE

1. Status Code 202 is returned only if the operation is **Un-committed**. Status code 200 is returned otherwise.

List Organizations

Resource Name /auto-config/organizations

Description Displays a list of Organizations.

https Method GET

URL https://dcnm-ip/rest/auto-config/organizations
https://dcnm-ip/rest/auto-config/organizations?detail=true

Parameter

Parameter	Type	Description

Return Value Format: JSON
Type: Object

Attribute Name	Type	Description
Organizations	A	By default, a list of organization names is displayed. If “detail=true”, then a list of Organization objects is displayed.

Create an Organization

Resource Name /auto-config/organizations

Description Enables you to create a new organization.

https Method POST

URL https://dcnm-ip/rest/auto-config/organizations

Parameter

Parameter	Type	Description
Organization	O	Organization object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
Organization-name	S	New organization name

Get an Organization

Resource Name /auto-config/organizations/organization-name

Description Enables you to get an organization.

https Method GET

URL https://dcnm-ip/rest/auto-config/organizations/organization-name

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
Organization	O	Organization object

Update an Organization

Resource Name /auto-config/organizations/organization-name

Description Enables you to update an organization.

https Method PUT

URL https://dcnm-ip/rest/auto-config/organizations/organization-name

Parameter

Parameter	Type	Description
Organization	O	Organization object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description

Delete an Organization

Resource Name /auto-config/organizations/organization-name

Description Enables you to delete a organization.

https Method DELETE

URL https://dcnm-ip/rest/auto-config/organizations/organization-name

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description

List Partitions

Resource Name /auto-config/organizations/organization-name/partitions

Description Displays a list of partitions.

https Method GET

URL <https://dcnm-ip/rest/auto-config/organizations/organization1/partitions>
<https://dcnm-ip/rest/auto-config/organizations/organization1/partitions?detail=true>

Parameter

Parameter	Type	Description

Return Value Format: JSON
Type: Object

Attribute Name	Type	Description
Partitions	A	By default, a list of partition names is displayed. If “detail=true”, then a list of partition objects is displayed.

Create a Partition

Resource Name /auto-config/organizations/organization-name/partitions

Description Enables you to create a new partition.

https Method POST

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions

Parameter

Parameter	Type	Description
Partition-object	O	Partition object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
partition-name	S	Partition name

Get a Partition

Resource Name /auto-config/organizations/organization-name/partitions/partition-name

Description Enables you to get a partition.

https Method GET

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
Partition	O	Partition object

Update a Partition

Resource Name /auto-config/organizations/organization-name/partitions/partition-name

Description Update a partition.

https Method PUT

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name

Parameter

Parameter	Type	Description
Partition	O	Partition object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description

Delete a Partition

Resource Name /auto-config/organizations/organization-name/partitions/partition-name

Description Delete a partition.

https Method DELETE

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description

List Networks

Resource Name /auto-config/organizations/organization-name/partitions/partition-name/networks

Description List of networks.

https Method GET

URL <https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks>
<https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks?detail=true>

Parameter

Parameter	Type	Description

Return Value Format: JSON
Type: Object

Attribute Name	Type	Description
Networks	A	By default, a list of segment IDs for 12 segments, a list of VLAN IDs, and Mobility Domain IDs for the VLAN Mobility Domain is displayed. If “detail=true”, then list of network objects is displayed

Create a Network

Resource Name /auto-config/organizations/organization-name/partitions/partition-name/networks

Description Create a new network.

https Method POST

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks

Parameter

Parameter	Type	Description
Network	O	Network object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
SegmentID or VLANID + MobilityDomainID	S	Segment ID for 12 segments or VLAN ID and Mobility Domain ID for VLAN Mobility Domain is displayed.

Get a Network

Resource Name /auto-config/organizations/organization-name/partitions/partition-name/networks/{network-id}

Description Get a network.

https Method GET

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/segment/20010
 https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/vlan/10/mobility-domain/mydomain

Parameter

Parameter	Type	Description

Return Value Format: JSON
 Type: Object

Attribute Name	Type	Description
Network	O	Network object

Update a Network

Resource Name /auto-config/organizations/organization-name/partitions/partition-name/networks/{network-id}

Description Update a network.

https Method PUT

URL <https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/segment/20010>
<https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/vlan/10/mobility-domain/mydomain>

Parameter

Parameter	Type	Description
Network	O	Network object

Return Value Format: JSON
Type: Object

Attribute Name	Type	Description

Delete a Network

Resource Name /auto-config/organizations/organization-name/partitions/partition-name/networks/{network-id}

Description Delete a network.

https Method DELETE

URL https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/segment/20010
 https://dcnm-ip/rest/auto-config/organizations/organization-name/partitions/partition-name/networks/vlan/10/mobility-domain/mydomain

Parameter

Parameter	Type	Description

Return Value Format: JSON
 Type: Object

Attribute Name	Type	Description

Get Auto Config Settings

Resource Name /auto-config/settings

Description Get auto config settings.

https Method GET

URL https://dcnm-ip/rest/auto-config/settings

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
Auto-config-settings	O	<p>The following auto config settings objects are displayed: ldapServer, ldapUserName, ldapPassWord, segmentIdRange, partitionIdRange, useLocalDhcp, dhcpPrimarySubnet, enableAmqpNotification, amqpServer, amqpPort, amqpVirtualHost, amqpUserName, amqpPassWord, amqpExchangeName, xmppServer, xmppUserName, xmppPassWord, xmppGroup, xmppResponseTimeout, xmppSearch, vrfName</p> <p>The following attributes are applicable for HA set-up: ldapPeerServer, ldapPeerUserName, ldapPeerPassWord.</p>

Update Auto Config Settings

Resource Name /auto-config/settings

Description Update auto config settings.

https Method PUT

URL https://dcnm-ip/rest/auto-config/settings

Parameter

Parameter	Type	Description
Auto-config-settings	O	<p>The following auto config settings object are displayed: ldapServer, ldapUserName, ldapPassWord, segmentIdRange, partitionIdRange, useLocalDhcp, dhcpPrimarySubnet, enableAmqpNotification, amqpServer, amqpPort, amqpVirtualHost, amqpUserName, amqpPassWord, amqpExchangeName, xmppServer, xmppUserName, xmppPassWord, xmppGroup, xmppResponseTimeout, xmppSearch, vrfName</p> <p>The following attributes are applicable for HA set-up: ldapPeerServer, ldapPeerUserName, ldapPeerPassWord.</p>

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description

List Auto Configuration Profiles

Resource Name /rest/auto-config/profiles

Description List of profiles

https Method GET

URL https://dcnm-ip/rest/auto-config/profiles

Parameter

Parameter	Type	Description

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
profiles	A	By default, a list of profile Names, profile Types and profile SubTypes are displayed. If "detail=true", a list of profile objects is displayed.

Create a Auto Configuration profile

Resource Name /rest/auto-config/profiles/

Description Create a new profile.

https Method POST

URL https://dcnm-ip/rest/auto-config/profiles/

Parameter

Parameter	Type	Description
profile	O	Profile object

Return Value Format: JSON

Type: Object

Attribute Name	Type	Description
ProfileName	S	Profile name

Get a Auto Configuration profile

Resource Name

```

/rest/auto-config/profiles/{profile-name}
/rest/auto-config/profiles/{profile-name}/type/IPVLAN
/rest/auto-config/profiles/{profile-name}/type/FPBD

```

Description

If profile Type has not been provided then response will return default FPVLAN profile.
 If profile Type is IPVLAN then response will return IPVLAN profile.
 If profile Type is FPBD then response will return FPBD profile.

https Method GET

URL

```

https://dcnm-ip/rest/auto-config/profiles/{profile-name}
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/IPVLAN
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/FPBD

```

Parameter

Parameter	Type	Description

Return Value

Format: JSON
 Type: Object

Attribute Name	Type	Description
profile	O	Profile object

Update a Auto Configuration profile

Resource Name

```
/rest/auto-config/profiles/{profile-name}
/rest/auto-config/profiles/{profile-name}/type/IPVLAN
/rest/auto-config/profiles/{profile-name}/type/FPBD
```

Description

If profile Type has not been provided then update a default FPVLAN profile.
 If profile Type is IPVLAN then update an IPVLAN profile.
 If profile Type is FPBD then update a FPBD profile.

https Method PUT

URL

```
https://dcnm-ip/rest/auto-config/profiles/{profile-name}
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/IPVLAN
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/FPBD
```

Parameter

Parameter	Type	Description
profile	O	Profile object

Return Value

Format: JSON
 Type: Object

Attribute Name	Type	Description

Delete a Auto Configuration profile

Resource Name

```

/rest/auto-config/profiles/{profile-name}
/rest/auto-config/profiles/{profile-name}/type/IPVLAN
/rest/auto-config/profiles/{profile-name}/type/FPBD

```

Description

If profile Type has not been provided then delete a default FPVLAN profile.
 If profile Type is IPVLAN then delete an IPVLAN profile.
 If profile Type is FPBD then delete a FPBD profile.

https Method DELETE

URL

```

https://dcnm-ip/rest/auto-config/profiles/{profile-name}
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/IPVLAN
https://dcnm-ip/rest/auto-config/profiles/{profile-name}/type/FPBD

```

Parameter

Parameter	Type	Description

Return Value

Format: JSON
 Type: Object

Attribute Name	Type	Description