



Configuring PKI

This chapter describes the Public Key Infrastructure (PKI) support on the Cisco NX-OS device. PKI allows the device to obtain and use digital certificates for secure communication in the network and provides manageability and scalability for Secure Shell (SSH).

This chapter includes the following sections:

- [Information About PKI, page 1](#)
- [Licensing Requirements for PKI, page 5](#)
- [Guidelines and Limitations for PKI, page 5](#)
- [Default Settings for PKI, page 6](#)
- [Configuring CAs and Digital Certificates, page 6](#)
- [Verifying the PKI Configuration, page 23](#)
- [Configuration Examples for PKI, page 23](#)
- [Additional References for PKI, page 66](#)
- [Feature History for PKI, page 66](#)

Information About PKI

This section provides information about PKI.

CAs and Digital Certificates

Certificate authorities (CAs) manage certificate requests and issue certificates to participating entities such as hosts, network devices, or users. The CAs provide centralized key management for the participating entities.

Digital signatures, based on public key cryptography, digitally authenticate devices and individual users. In public key cryptography, such as the RSA encryption system, each device or user has a key pair that contains both a private key and a public key. The private key is kept secret and is known only to the owning device or user only. However, the public key is known to everybody. Anything encrypted with one of the keys can be decrypted with the other. A signature is formed when data is encrypted with a sender's private key. The receiver verifies the signature by decrypting the message with the sender's public key. This process relies on

the receiver having a copy of the sender's public key and knowing with a high degree of certainty that it really does belong to the sender and not to someone pretending to be the sender.

Digital certificates link the digital signature to the sender. A digital certificate contains information to identify a user or device, such as the name, serial number, company, department, or IP address. It also contains a copy of the entity's public key. The CA that signs the certificate is a third party that the receiver explicitly trusts to validate identities and to create digital certificates.

To validate the signature of the CA, the receiver must first know the CA's public key. Typically, this process is handled out of band or through an operation done at installation. For instance, most web browsers are configured with the public keys of several CAs by default.

Trust Model, Trust Points, and Identity CAs

The PKI trust model is hierarchical with multiple configurable trusted CAs. You can configure each participating device with a list of trusted CAs so that a peer certificate obtained during the security protocol exchanges can be authenticated if it was issued by one of the locally trusted CAs. The Cisco NX-OS software locally stores the self-signed root certificate of the trusted CA (or certificate chain for a subordinate CA). The process of securely obtaining a trusted CA's root certificate (or the entire chain in the case of a subordinate CA) and storing it locally is called *CA authentication*.

The information about a trusted CA that you have configured is called the *trust point* and the CA itself is called a *trust point CA*. This information consists of a CA certificate (or certificate chain in case of a subordinate CA) and certificate revocation checking information.

The Cisco NX-OS device can also enroll with a trust point to obtain an identity certificate to associate with a key pair. This trust point is called an *identity CA*.

RSA Key Pairs and Identity Certificates

You can obtain an identity certificate by generating one or more RSA key pairs and associating each RSA key pair with a trust point CA where the Cisco NX-OS device intends to enroll. The Cisco NX-OS device needs only one identity per CA, which consists of one key pair and one identity certificate per CA.

The Cisco NX-OS software allows you to generate RSA key pairs with a configurable key size (or modulus). The default key size is 512. You can also configure an RSA key-pair label. The default key label is the device fully qualified domain name (FQDN).

The following list summarizes the relationship between trust points, RSA key pairs, and identity certificates:

- A trust point corresponds to a specific CA that the Cisco NX-OS device trusts for peer certificate verification for any application (such as SSH).
- A Cisco NX-OS device can have many trust points and all applications on the device can trust a peer certificate issued by any of the trust point CAs.
- A trust point is not restricted to a specific application.
- A Cisco NX-OS device enrolls with the CA that corresponds to the trust point to obtain an identity certificate. You can enroll your device with multiple trust points which means that you can obtain a separate identity certificate from each trust point. The identity certificates are used by applications depending upon the purposes specified in the certificate by the issuing CA. The purpose of a certificate is stored in the certificate as a certificate extension.
- When enrolling with a trust point, you must specify an RSA key pair to be certified. This key pair must be generated and associated to the trust point before generating the enrollment request. The association

between the trust point, key pair, and identity certificate is valid until it is explicitly removed by deleting the certificate, key pair, or trust point.

- The subject name in the identity certificate is the fully qualified domain name for the Cisco NX-OS device.
- You can generate one or more RSA key pairs on a device and each can be associated to one or more trust points. But no more than one key pair can be associated to a trust point, which means only one identity certificate is allowed from a CA.
- If the Cisco NX-OS device obtains multiple identity certificates (each from a distinct CA), the certificate that an application selects to use in a security protocol exchange with a peer is application specific.
- You do not need to designate one or more trust points for an application. Any application can use any certificate issued by any trust point as long as the certificate purpose satisfies the application requirements.
- You do not need more than one identity certificate from a trust point or more than one key pair to be associated to a trust point. A CA certifies a given identity (or name) only once and does not issue multiple certificates with the same name. If you need more than one identity certificate for a CA and if the CA allows multiple certificates with the same names, you must define another trust point for the same CA, associate another key pair to it, and have it certified.

Multiple Trusted CA Support

The Cisco NX-OS device can trust multiple CAs by configuring multiple trust points and associating each with a distinct CA. With multiple trusted CAs, you do not have to enroll a device with the specific CA that issued the certificate to a peer. Instead, you can configure the device with multiple trusted CAs that the peer trusts. The Cisco NX-OS device can then use a configured trusted CA to verify certificates received from a peer that were not issued by the same CA defined in the identity of the peer device.

PKI Enrollment Support

Enrollment is the process of obtaining an identity certificate for the device that is used for applications like SSH. It occurs between the device that requests the certificate and the certificate authority.

The Cisco NX-OS device performs the following steps when performing the PKI enrollment process:

- Generates an RSA private and public key pair on the device.
- Generates a certificate request in standard format and forwards it to the CA.

**Note**

The CA administrator may be required to manually approve the enrollment request at the CA server, when the request is received by the CA.

- Receives the issued certificate back from the CA, signed with the CA's private key.
- Writes the certificate into a nonvolatile storage area on the device (bootflash).

Manual Enrollment Using Cut-and-Paste

The Cisco NX-OS software supports certificate retrieval and enrollment using manual cut-and-paste. Cut-and-paste enrollment means that you must cut and paste the certificate requests and resulting certificates between the device and the CA.

You must perform the following steps when using cut and paste in the manual enrollment process:

- Create an enrollment certificate request, which the Cisco NX-OS device displays in base64-encoded text form.
- Cut and paste the encoded certificate request text in an e-mail or in a web form and send it to the CA.
- Receive the issued certificate (in base64-encoded text form) from the CA in an e-mail or in a web browser download.
- Cut and paste the issued certificate to the device using the certificate import facility.

Multiple RSA Key Pair and Identity CA Support

Multiple identity CAs enable the device to enroll with more than one trust point, which results in multiple identity certificates, each from a distinct CA. With this feature, the Cisco NX-OS device can participate in SSH and other applications with many peers using certificates issued by CAs that are acceptable to those peers.

The multiple RSA key-pair feature allows the device to maintain a distinct key pair for each CA with which it is enrolled. It can match policy requirements for each CA without conflicting with the requirements specified by the other CAs, such as the key length. The device can generate multiple RSA key pairs and associate each key pair with a distinct trust point. Thereafter, when enrolling with a trust point, the associated key pair is used to construct the certificate request.

Peer Certificate Verification

The PKI support on a Cisco NX-OS device can verify peer certificates. The Cisco NX-OS software verifies certificates received from peers during security exchanges for applications, such as SSH. The applications verify the validity of the peer certificates. The Cisco NX-OS software performs the following steps when verifying peer certificates:

- Verifies that the peer certificate is issued by one of the locally trusted CAs.
- Verifies that the peer certificate is valid (not expired) with respect to current time.
- Verifies that the peer certificate is not yet revoked by the issuing CA.

For revocation checking, the Cisco NX-OS software supports the certificate revocation list (CRL). A trust point CA can use this method to verify that the peer certificate has not been revoked.

Certificate Revocation Checking

The Cisco NX-OS software can check the revocation status of CA certificates. The applications can use the revocation checking mechanisms in the order that you specify. The choices are CRL, none, or a combination of these methods.

CRL Support

The CAs maintain certificate revocation lists (CRLs) to provide information about certificates revoked prior to their expiration dates. The CAs publish the CRLs in a repository and provide the download public URL in all issued certificates. A client verifying a peer's certificate can obtain the latest CRL from the issuing CA and use it to determine if the certificate has been revoked. A client can cache the CRLs of some or all of its trusted CAs locally and use them later if necessary until the CRLs expire.

The Cisco NX-OS software allows the manual configuration of predownloaded CRLs for the trust points, and then caches them in the device bootflash (cert-store). During the verification of a peer certificate, the Cisco NX-OS software checks the CRL from the issuing CA only if the CRL has already been cached locally and the revocation checking is configured to use the CRL. Otherwise, the Cisco NX-OS software does not perform CRL checking and considers the certificate to be not revoked unless you have configured other revocation checking methods.

Import and Export Support for Certificates and Associated Key Pairs

As part of the CA authentication and enrollment process, the subordinate CA certificate (or certificate chain) and identity certificates can be imported in standard PEM (base64) format.

The complete identity information in a trust point can be exported to a file in the password-protected PKCS#12 standard format. It can be later imported to the same device (for example, after a system crash) or to a replacement device. The information in a PKCS#12 file consists of the RSA key pair, the identity certificate, and the CA certificate (or chain).

Virtualization Support for PKI

The configuration and operation of the PKI feature is local to the virtual device context (VDC). For more information on VDCs, see the [Cisco Nexus 7000 Series NX-OS Virtual Device Context Configuration Guide, Release 4.2](#).

Licensing Requirements for PKI

The following table shows the licensing requirements for this feature:

Product	License Requirement
Cisco NX-OS	The PKI feature requires no license. Any feature not included in a license package is bundled with the Cisco NX-OS system images and is provided at no extra charge to you. For an explanation of the Cisco NX-OS licensing scheme, see the <i>Cisco Nexus 7000 Series NX-OS Licensing Guide, Release 4.2</i> .

Guidelines and Limitations for PKI

PKI has the following configuration guidelines and limitations:

- The maximum number of key pairs you can configure on a Cisco NX-OS device is 16.
- The maximum number of trust points you can declare on a Cisco NX-OS device is 16.
- The maximum number of identify certificates you can configure on a Cisco NX-OS device is 16.
- The maximum number of certificates in a CA certificate chain is 10.
- The maximum number of trust points you can authenticate to a specific CA is 10.
- Configuration rollbacks do not support the PKI configuration.
- The Cisco NX-OS software does not support OSCP.

**Note**

If you are familiar with the Cisco IOS CLI, be aware that the Cisco NX-OS commands for this feature might differ from the Cisco IOS commands that you would use.

Default Settings for PKI

This table lists the default settings for PKI parameters.

Table 1: Default PKI Parameters

Parameters	Default
Trust point	None
RSA key pair	None
RSA key-pair label	Device FQDN
RSA key-pair modulus	512
RSA key-pair exportable	Enabled
Revocation check method	CRL

Configuring CAs and Digital Certificates

This section describes the tasks that you must perform to allow CAs and digital certificates on your Cisco NX-OS device to interoperate.

Configuring the Hostname and IP Domain Name

You must configure the hostname and IP domain name of the device if you have not yet configured them because the Cisco NX-OS software uses the fully qualified domain name (FQDN) of the device as the subject in the identity certificate. Also, the Cisco NX-OS software uses the device FQDN as a default key label when

you do not specify a label during key-pair generation. For example, a certificate named DeviceA.example.com is based on a device hostname of DeviceA and a device IP domain name of example.com.

**Caution**

Changing the hostname or IP domain name after generating the certificate can invalidate the certificate.

SUMMARY STEPS

1. **configure terminal**
2. **hostname** *hostname*
3. **ip domain-name** *name* [**use-vrf** *vrf-name*]
4. **exit**
5. (Optional) **show hosts**
6. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	hostname <i>hostname</i> Example: <pre>switch(config)# hostname DeviceA</pre>	Configures the hostname of the device.
Step 3	ip domain-name <i>name</i> [use-vrf <i>vrf-name</i>] Example: <pre>DeviceA(config)# ip domain-name example.com</pre>	Configures the IP domain name of the device. If you do not specify a VRF name, the command uses the default VRF.
Step 4	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 5	show hosts Example: <pre>switch# show hosts</pre>	(Optional) Displays the IP domain name.
Step 6	copy running-config startup-config Example: <pre>switch# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Generating an RSA Key Pair

You can generate an RSA key pairs to sign and/or encrypt and decrypt the security payload during security protocol exchanges for applications. You must generate the RSA key pair before you can obtain a certificate for your device.

SUMMARY STEPS

1. **configure terminal**
2. **crypto key generate rsa** [*label label-string*] [*exportable*] [*modulus size*]
3. **exit**
4. (Optional) **show crypto key mypubkey rsa**
5. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto key generate rsa [<i>label label-string</i>] [<i>exportable</i>] [<i>modulus size</i>] Example: <pre>switch(config)# crypto key generate rsa exportable</pre>	<p>Generates an RSA key pair. The maximum number of key pairs on a device is 16.</p> <p>The label string is alphanumeric, case sensitive, and has a maximum length of 64 characters. The default label string is the hostname and the FQDN separated by a period character (.).</p> <p>Valid modulus values are 512, 768, 1024, 1536, and 2048. The default modulus size is 512.</p> <p>Note The security policy on the Cisco NX-OS device and on the CA (where enrollment is planned) should be considered when deciding the appropriate key modulus.</p> <p>By default, the key pair is not exportable. Only exportable key pairs can be exported in the PKCS#12 format.</p> <p>Caution You cannot change the exportability of a key pair.</p>
Step 3	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 4	show crypto key mypubkey rsa Example: <pre>switch# show crypto key mypubkey rsa</pre>	(Optional) Displays the generated key.

	Command or Action	Purpose
Step 5	copy running-config startup-config Example: <pre>switch# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Creating a Trust Point CA Association

You must associate the Cisco NX-OS device with a trust point CA.

Before You Begin

Generate the RSA key pair.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca trustpoint** *name*
3. **enrollment terminal**
4. **rsa***keypair label*
5. **exit**
6. (Optional) **show crypto ca trustpoints**
7. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca trustpoint <i>name</i> Example: <pre>switch(config)# crypto ca trustpoint admin-ca switch(config-trustpoint)#</pre>	Declares a trust point CA that the device should trust and enters trust point configuration mode. Note The maximum number of trust points that you can configure on a device is 16.
Step 3	enrollment terminal Example: <pre>switch(config-trustpoint)# enrollment terminal</pre>	Enables manual cut-and-paste certificate enrollment. The default is enabled. Note The Cisco NX-OS software supports only the manual cut-and-paste method for certificate enrollment.

	Command or Action	Purpose
Step 4	rsa keypair <i>label</i> Example: switch(config-trustpoint)# rsakeypair SwitchA	Specifies the label of the RSA key pair to associate to this trust point for enrollment. Note You can specify only one RSA key pair per CA.
Step 5	exit Example: switch(config-trustpoint)# exit switch(config)#	Exits trust point configuration mode.
Step 6	show crypto ca trustpoints Example: switch(config)# show crypto ca trustpoints	(Optional) Displays trust point information.
Step 7	copy running-config startup-config Example: switch(config)# copy running-config startup-config	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Generating an RSA Key Pair, page 8](#)

Authenticating the CA

The configuration process of trusting a CA is complete only when the CA is authenticated to the Cisco NX-OS device. You must authenticate your Cisco NX-OS device to the CA by obtaining the self-signed certificate of the CA in PEM format, which contains the public key of the CA. Because the certificate of the CA is self-signed (the CA signs its own certificate) the public key of the CA should be manually authenticated by contacting the CA administrator to compare the fingerprint of the CA certificate.



Note

The CA that you are authenticating is not a self-signed CA when it is a subordinate CA to another CA, which itself may be a subordinate to yet another CA, and so on, finally ending in a self-signed CA. This type of CA certificate is called the *CA certificate chain* of the CA being authenticated. In this case, you must input the full list of the CA certificates of all the CAs in the certification chain during the CA authentication. The maximum number of certificates in a CA certificate chain is 10.

Before You Begin

Create an association with the CA.

Obtain the CA certificate or CA certificate chain.

SUMMARY STEPS

1. configure terminal
2. crypto ca authenticate *name*
3. exit
4. (Optional) show crypto ca trustpoints
5. (Optional) copy running-config startup-config

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca authenticate <i>name</i> Example: <pre>switch(config)# crypto ca authenticate admin-ca input (cut & paste) CA certificate (chain) in PEM format; end the input with a line containing only END OF INPUT : -----BEGIN CERTIFICATE----- MIIC4jCCAoygAwIBAgIQBWDSiay0GZRPSRI1jK0ZeJANBgkqhkiG9w0BAQUFADCB kDEgMB4GCSqGSIb3DQEJARYRYW1hbmRrZUBjaXNjb20xMzAwCzAJBgNVBAYTAkIO MRIwEAYDVQQIEw1LYXJuYXRha2ExEjAQBgNVBACTCUJhbmdbG9yZTEOMAwGA1UE ChMFQ21lZy28xZARBgNVBASTCm5ldHN0b3JhZ2UxEjAQBgNVBAMTCUFwYXJuYSBD QTAEFw0wNTA1MDMyMjQ2MzdaFw0wNzA1MDMyMjU1MTdaMIGQMSAwHgYJKoZIhvcN AQkBFhFhbWVufuZGt1QGNpc2NvLmNvbTELMakGA1UEBhMCSU4xEjAQBgNVBAGTCUth cm5hdGFrYTESMBAGA1UEBxMJQmFuZ2Fsb3JlMQ4wDAYDVQQKEwVdaXNjbzETMBEG A1UECzMkbnV0c3RvcnFnZTESMBAGA1UEAxMjQXBhcm5hIENBMFwwDQYJKoZIhvcN AQEBBQADSwAwSAJBAMW/7b3+DXJPANBsIHHZluNccNM87ypyzwuoSNZXOMperXXI OzyBAgiXT2ASFuUOWQ1iDM8rO/41jf8RxyYKvysCAwEAAaOBvzCBvDALBgNVHQ8E BAMCAcYwDwYDVR0TAQH/BAUwAwEB/zAdBgNVHQ4EFgQUJyJyRoMbrCNMRU2OyRhQ GgsWbHEwawYDVR0fBGQwYjAuOCyGKoYoaHR0cDovL3NzZS0wOC9DZXJ0RW5yb2xs L0FwYXJuYXUyMENBLmNybDAwOC6gLIYqZmlsZTovL1xccc3N1LTA4XENlcnRFbnJv bGxcQXBhcm5hJTlIwQ0EuY3J3SMBAGCSsGAQQBgjcVAQQDAgEAMA0GCSqGSIb3DQEB BQUAA0EAHv6UQ+8nE399Tww+KaGr0g0NIJaNgLh0AFcT0rEyuyt/WYGPzksF9Ea NBG7E0oN66zex0EOEfG1Vs6mXp1//w== -----END CERTIFICATE----- END OF INPUT Fingerprint(s): MD5 Fingerprint=65:84:9A:27:D5:71:03:33:9C:12:23:92:38:6F:78:12 Do you accept this certificate? [yes/no]: yes</pre>	<p>Prompts you to cut and paste the certificate of the CA. Use the same name that you used when declaring the CA.</p> <p>The maximum number of trust points that you can authenticate to a specific CA is 10.</p> <p>Note For subordinate CA authentication, the Cisco NX-OS software requires the full chain of CA certificates ending in a self-signed CA because the CA chain is needed for certificate verification as well as for PKCS#12 format export.</p>
Step 3	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 4	show crypto ca trustpoints Example: <pre>switch# show crypto ca trustpoints</pre>	<p>(Optional)</p> <p>Displays the trust point CA information.</p>

	Command or Action	Purpose
Step 5	copy running-config startup-config Example: switch# copy running-config startup-config	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Creating a Trust Point CA Association, page 9](#)

Configuring Certificate Revocation Checking Methods

During security exchanges with a client (for example, an SSH user), the Cisco NX-OS device performs the certificate verification of the peer certificate sent by the client. The verification process may involve certificate revocation status checking.

You can configure the device to check the CRL downloaded from the CA. Downloading the CRL and checking locally does not generate traffic in your network. However, certificates can be revoked between downloads and your device would not be aware of the revocation.

Before You Begin

Authenticate the CA.

Ensure that you have configured the CRL if you want to use CRL checking.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca trustpoint *name***
3. **revocation-check {crl [none] | none}**
4. **exit**
5. (Optional) **show crypto ca trustpoints**
6. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: switch# configure terminal switch(config)#	Enters global configuration mode.
Step 2	crypto ca trustpoint <i>name</i> Example: switch(config)# crypto ca trustpoint admin-ca switch(config-trustpoint)#	Specifies a trust point CA and enters trust point configuration mode.

	Command or Action	Purpose
Step 3	revocation-check {crl [none] none} Example: switch(config-trustpoint) # revocation-check none	Configures the certificate revocation checking methods. The default method is crl . The Cisco NX-OS software uses the certificate revocation methods in the order that you specify.
Step 4	exit Example: switch(config-trustpoint) # exit switch(config) #	Exits trust point configuration mode.
Step 5	show crypto ca trustpoints Example: switch(config) # show crypto ca trustpoints	(Optional) Displays the trust point CA information.
Step 6	copy running-config startup-config Example: switch(config) # copy running-config startup-config	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Authenticating the CA, page 10](#)
- [Configuring a CRL, page 19](#)

Generating Certificate Requests

You must generate a request to obtain identity certificates from the associated trust point CA for each of your device's RSA key pairs. You must then cut and paste the displayed request into an e-mail or in a website form for the CA.

Before You Begin

Create an association with the CA.

Obtain the CA certificate or CA certificate chain.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca enroll** *name*
3. **exit**
4. (Optional) **show crypto ca certificates**
5. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca enroll <i>name</i> Example: <pre>switch(config)# crypto ca enroll admin-ca Create the certificate request .. Create a challenge password. You will need to verbally provide this password to the CA Administrator in order to revoke your certificate. For security reasons your password will not be saved in the configuration. Please make a note of it. Password:nbv123 The subject name in the certificate will be: DeviceA.cisco.com Include the switch serial number in the subject name? [yes/no]: no Include an IP address in the subject name [yes/no]: yes ip address:172.22.31.162 The certificate request will be displayed... -----BEGIN CERTIFICATE REQUEST----- MIIBQzCCARQCAQAwHDEaMBGGA1UEAxMRVmVnYXMtMS5jaXNjb20wgZ8wDQYJ KoZlHvcNAQEBAQADgY0AMIGJAoGBAL8Y1UAJ2NC7jUJ1DVA5MqNIgJ2kt8r14lKY 0JC6ManNy4qxk8VeMXZSiLJ4JgTzKWdxbLDkTTysnjuCXGvjb+wj0hEhv/y51T9y P2NJJ8ornqShrvFZgC7ysN/PyMwKcgzhbVpj+rargZvHtGJ91XTq4WoVksCzXv8S VqyH0vEvAgMBAAGGTzAVBgqhkiG9w0BCQcxCBMGBmJ2MTIzMDYGCsGSIb3DQEJ DjEpMCCwJQYDVR0RAQH/BBswGYIRVmVnYXMtMS5jaXNjb20wDQYJ KoZlHvcNAQEBAQADgYEAkT60KER6Qo8nj0sDXZVHSfJZh6K6JtDz3Gkd99G1FWgt PftrNcWUE/pw6HayfQl2T3ecgNwel2d15133YBF2bktExiI6U188nTOjglXMjja8 8a23bNDpNsM8rklwA6hWkrVL8NUZEFJxqbjfngPNTZacJCUS6ZqKCMetbKytUx0= -----END CERTIFICATE REQUEST-----</pre>	Generates a certificate request for an authenticated CA. Note You must remember the challenge password. It is not saved with the configuration. You must enter this password if your certificate needs to be revoked.
Step 3	exit Example: <pre>switch(config-trustpoint)# exit switch(config)#</pre>	Exits trust point configuration mode.
Step 4	show crypto ca certificates Example: <pre>switch(config)# show crypto ca certificates</pre>	(Optional) Displays the CA certificates.
Step 5	copy running-config startup-config Example: <pre>switch(config)# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Creating a Trust Point CA Association, page 9](#)

Installing Identity Certificates

You can receive the identity certificate from the CA by e-mail or through a web browser in base64 encoded text form. You must install the identity certificate from the CA by cutting and pasting the encoded text.

Before You Begin

Create an association with the CA.

Obtain the CA certificate or CA certificate chain.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca import *name* certificate**
3. **exit**
4. (Optional) **show crypto ca certificates**
5. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca import <i>name</i> certificate Example: <pre>switch(config)# crypto ca import admin-ca certificate input (cut & paste) certificate in PEM format: -----BEGIN CERTIFICATE----- MIIEADCCA6ggAwIBAgIKCj00oQAAAAAAdDANBgkqhkiG9w0BAQUFADCBkDEgMB4G CSqGSIB3DQEJARYRYWlhbmRrZUBjaXNjb5y5jb20xCzAJBgNVBAYTAk1OMRIwEAYD VQOIIEw1LYXJuYXRha2ExEjAQBGNVBACtCUJhbmdbG9yZTEOMAwGA1UEChMFQ2l2 Y28xEzARBGNVBASATCm5ldHN0b3JhZ2UxEjAQBGNVBAMTCUFwYXJuYSBDQTAEFw0w NTEuMTIwMzAyNDBaFw0wNjExMTIwMzEyNDBaMBwxGjAYBgNVBAMTEVZlZ2FzLWTEu Y2l2Y28uY29tMIGfMA0GCSqGSIB3DQEBAQUAA4GNADCBiQKBgQC/GNVACdjQu41C dQ1WkjkjSICdpLfK5eJSmNCQujGpzcKsZPFxjF2UoiyeCYE8y1ncWYw5E08rJ47 glxr42/sI9IRIb/8udU/cj9jSSfKK56koa7xWYA8rDfz8jMCnIM4WlaY/q2q4Gb x7RifdV06uFqFZEgsl7/Elash9LxLwIDAQABo4ICEzCCAg8wJQYDVR0RAQH/BBsw GYIRVmVnYXMTMS5jaXNjb5y5jb22HBKwWH6IwHQYDVR0OBBYEFKCLi+2sspWEfgrR bhWmlVyo9jngMIHMBGnVHSMGgcQwgcGAFCCo8kaDG6wjTEVNjskYUBoLFmxxoYGW pIGTMIGQMSAwHgYJKoZIhvcNAQkBFhFhbWFuZGt1QGNpc2NvLmNvbTELMakGA1UE BhMCSU4xEjAQBGNVBAGTCUthcm5hdGFrYTESMBAGA1UEBxMJQmFuZ2Fsb3JlMQ4w DAYDVQQKEwVDaXNjbzETMBEGA1UECzMKBmV0c3RvcnF2ZTESMBAGA1UEAxMjQXBh cm5hIENBghAFYNKJrLQ2lE9JEiWMrRl6MGsGA1UdHwRkMGiWlQAsocGKGGh0dHA6 Ly9zc2UtdGdvQ2VydEVucm9sbC9BcGFybmElmJBDQS5jcmwwMKAuoCYGKmZpbGU6 Ly9cXHNzZS0wOFx0ZDZlJ0R5yb2xsXEFwYXJuYXUyMENBLmNybDcBbigYIKwYBBQUH AQEEfjB8MDsGCCsGAQUFBzAChi9odHRwOi8vc3NlLTA4L0NlcnRFbnJvbGwvc3Nl LTA4X0FwYXJuYXUyMENBLmNydDA9BggrBgEFBQcwAoYxZmlsZTovL1xcc3NlLTA4 XENlcnRFbnJvbGwvc3NlLTA4X0FwYXJuYXUyMENBLmNydDANBgkqhkiG9w0BAQUF AANBADbGBGsbe7GNLh9xeOTWBNbm24U69ZSuDDcOcUZUUTgrpnTqVpPyejtsyflw E36cIZu4WsExREqxbTk8ycx7V5o= -----END CERTIFICATE-----</pre>	Prompts you to cut and paste the identity certificate for the CA named admin-ca. The maximum number of identify certificates that you can configure on a device is 16.

	Command or Action	Purpose
Step 3	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 4	show crypto ca certificates Example: <pre>switch# show crypto ca certificates</pre>	(Optional) Displays the CA certificates.
Step 5	copy running-config startup-config Example: <pre>switch# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Creating a Trust Point CA Association, page 9](#)

Ensuring Trust Point Configurations Persist Across Reboots

You can ensure that the trustpoint configuration persists across Cisco NX-OS device reboots.

The trust point configuration is a normal Cisco NX-OS device configuration that persists across system reboots only if you copy it explicitly to the startup configuration. The certificates, key pairs, and CRL associated with a trust point are automatically persistent if you have already copied the trust point configuration in the startup configuration. Conversely, if the trust point configuration is not copied to the startup configuration, the certificates, key pairs, and CRL associated with it are not persistent since they require the corresponding trust point configuration after a reboot. Always copy the running configuration to the startup configuration to ensure that the configured certificates, key pairs, and CRLs are persistent. Also, save the running configuration after deleting a certificate or key pair to ensure that the deletions permanent.

The certificates and CRL associated with a trust point automatically become persistent when imported (that is, without explicitly copying to the startup configuration) if the specific trust point is already saved in startup configuration.

We recommend that you create a password-protected backup of the identity certificates and save it to an external server.

**Note**

Copying the configuration to an external server does include the certificates and key pairs.

Related Topics

- [Exporting Identity Information in PKCS 12 Format, page 17](#)

Exporting Identity Information in PKCS 12 Format

You can export the identity certificate along with the RSA key pair and CA certificate (or the entire chain in the case of a subordinate CA) of a trust point to a PKCS#12 file for backup purposes. You can import the certificate and RSA key pair to recover from a system crash on your device or when you replace the supervisor modules.


Note

You can use only the `bootflash:filename` format when specifying the export URL.

Before You Begin

Authenticate the CA.

Install an identity certificate.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca export name pkcs12 bootflash:filename password**
3. **exit**
4. **copy bootflash:filename scheme://server/ [url /]filename**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca export name pkcs12 bootflash:filename password Example: <pre>switch(config)# crypto ca export admin-ca pkcs12 bootflash:adminid.p12 nbv123</pre>	Exports the identity certificate and associated key pair and CA certificates for a trust point CA. The password is alphanumeric, case sensitive, and has a maximum length of 128 characters.
Step 3	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 4	copy bootflash:filename scheme://server/ [url /]filename Example: <pre>switch# copy bootflash:adminid.p12 tftp:adminid.p12</pre>	<p>Copies the PKCS#12 format file to a remote server.</p> <p>For the <i>scheme</i> argument, you can enter tftp:, ftp:, scp:, or sftp:. The <i>server</i> argument is the address or name of the remote server, and the <i>url</i> argument is the path to the source file on the remote server.</p>

	Command or Action	Purpose
		The <i>server</i> , <i>url</i> , and <i>filename</i> arguments are case sensitive.

Related Topics

- [Generating an RSA Key Pair, page 8](#)
- [Authenticating the CA, page 10](#)
- [Installing Identity Certificates, page 15](#)

Importing Identity Information in PKCS 12 Format

You can import the certificate and RSA key pair to recover from a system crash on your device or when you replace the supervisor modules.



Note

You can use only the `bootflash:filename` format when specifying the import URL.

Before You Begin

Ensure that the trust point is empty by checking that no RSA key pair is associated with it and no CA is associated with the trust point using CA authentication.

SUMMARY STEPS

1. `copy scheme:// server/[url /]filename bootflash:filename`
2. `configure terminal`
3. `crypto ca import name pksc12 bootflash:filename`
4. `exit`
5. (Optional) `show crypto ca certificates`
6. (Optional) `copy running-config startup-config`

DETAILED STEPS

	Command or Action	Purpose
Step 1	copy <i>scheme:// server/[url /]filename bootflash:filename</i> Example: <pre>switch# copy tftp:adminid.p12 bootflash:adminid.p12</pre>	Copies the PKCS#12 format file from the remote server. For the <i>scheme</i> argument, you can enter tftp: , ftp: , scp: , or sftp: . The <i>server</i> argument is the address or name of the remote server, and the <i>url</i> argument is the path to the source file on the remote server. The <i>server</i> , <i>url</i> , and <i>filename</i> arguments are case sensitive.

	Command or Action	Purpose
Step 2	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 3	crypto ca import <i>name</i> pkcs12 bootflash:<i>filename</i> Example: <pre>switch(config)# crypto ca import admin-ca pkcs12 bootflash:adminid.p12 nbv123</pre>	Imports the identity certificate and associated key pair and CA certificates for trust point CA.
Step 4	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.
Step 5	show crypto ca certificates Example: <pre>switch# show crypto ca certificates</pre>	(Optional) Displays the CA certificates.
Step 6	copy running-config startup-config Example: <pre>switch# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Configuring a CRL

You can manually configure CRLs that you have downloaded from the trust points. The Cisco NX-OS software caches the CRLs in the device bootflash (cert-store). During the verification of a peer certificate, the Cisco NX-OS software checks the CRL from the issuing CA only if you have downloaded the CRL to the device and you have configured certificate revocation checking to use the CRL.

Before You Begin

Ensure that you have enabled certificate revocation checking.

SUMMARY STEPS

1. **copy *scheme:[//server/]url filename* bootflash:*filename***
2. **configure terminal**
3. **crypto ca *crl request name* bootflash:*filename***
4. **exit**
5. (Optional) **show crypto ca *crl name***
6. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	copy <i>scheme:[//server/[url /]]filename</i> bootflash:filename Example: switch# copy tftp:adminca.crl bootflash:adminca.crl	Downloads the CRL from a remote server. For the <i>scheme</i> argument, you can enter tftp: , ftp: , scp: , or sftp: . The <i>server</i> argument is the address or name of the remote server, and the <i>url</i> argument is the path to the source file on the remote server. The <i>server</i> , <i>url</i> , and <i>filename</i> arguments are case sensitive.
Step 2	configure terminal Example: switch# configure terminal switch(config)#	Enters global configuration mode.
Step 3	crypto ca crl request name bootflash:filename Example: switch(config)# crypto ca crl request admin-ca bootflash:adminca.crl	Configures or replaces the current CRL with the one specified in the file.
Step 4	exit Example: switch(config)# exit switch#	Exits configuration mode.
Step 5	show crypto ca crl name Example: switch# show crypto ca crl admin-ca	(Optional) Displays the CA CRL information.
Step 6	copy running-config startup-config Example: switch# copy running-config startup-config	(Optional) Copies the running configuration to the startup configuration.

Deleting Certificates from the CA Configuration

You can delete the identity certificates and CA certificates that are configured in a trust point. You must first delete the identity certificate, followed by the CA certificates. After deleting the identity certificate, you can disassociate the RSA key pair from a trust point. You must delete certificates to remove expired or revoked certificates, certificates that have compromised (or suspected to be compromised) key pairs, or CAs that are no longer trusted.

SUMMARY STEPS

1. **configure terminal**
2. **crypto ca trustpoint** *name*
3. **delete ca-certificate**
4. **delete certificate** [*force*]
5. **exit**
6. (Optional) **show crypto ca certificates** [*name*]
7. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto ca trustpoint <i>name</i> Example: <pre>switch(config)# crypto ca trustpoint admin-ca switch(config-trustpoint)#</pre>	Specifies a trust point CA and enters trust point configuration mode.
Step 3	delete ca-certificate Example: <pre>switch(config-trustpoint)# delete ca-certificate</pre>	Deletes the CA certificate or certificate chain.
Step 4	delete certificate [<i>force</i>] Example: <pre>switch(config-trustpoint)# delete certificate</pre>	Deletes the identity certificate. You must use the force option if the identity certificate you want to delete is the last certificate in a certificate chain or only identity certificate in the device. This requirement ensures that you do not mistakenly delete the last certificate in a certificate chain or only the identity certificate and leave the applications (such as SSH) without a certificate to use.
Step 5	exit Example: <pre>switch(config-trustpoint)# exit switch(config)#</pre>	Exits trust point configuration mode.
Step 6	show crypto ca certificates [<i>name</i>] Example: <pre>switch(config)# show crypto ca certificates admin-ca</pre>	(Optional) Displays the CA certificate information.

	Command or Action	Purpose
Step 7	copy running-config startup-config Example: <pre>switch(config)# copy running-config startup-config</pre>	(Optional) Copies the running configuration to the startup configuration.

Deleting RSA Key Pairs from a Cisco NX-OS Device

You can delete the RSA key pairs from a Cisco NX-OS device if you believe the RSA key pairs were compromised in some way and should no longer be used.



Note

After you delete RSA key pairs from a device, ask the CA administrator to revoke your device's certificates at the CA. You must supply the challenge password that you created when you originally requested the certificates.

SUMMARY STEPS

1. **configure terminal**
2. **crypto key zeroize rsa *label***
3. **exit**
4. (Optional) **show crypto key mypubkey rsa**
5. (Optional) **copy running-config startup-config**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: <pre>switch# configure terminal switch(config)#</pre>	Enters global configuration mode.
Step 2	crypto key zeroize rsa <i>label</i> Example: <pre>switch(config)# crypto key zeroize rsa MyKey</pre>	Deletes the RSA key pair.
Step 3	exit Example: <pre>switch(config)# exit switch#</pre>	Exits configuration mode.

	Command or Action	Purpose
Step 4	show crypto key mypubkey rsa Example: switch# show crypto key mypubkey rsa	(Optional) Displays the RSA key pair configuration.
Step 5	copy running-config startup-config Example: switch# copy running-config startup-config	(Optional) Copies the running configuration to the startup configuration.

Related Topics

- [Generating Certificate Requests, page 13](#)

Verifying the PKI Configuration

To display PKI configuration information, perform one of the following tasks:

Command	Purpose
show crypto key mypubkey rsa	Displays information about the RSA public keys generated on the Cisco NX-OS device.
show crypto ca certificates	Displays information about CA and identity certificates.
show crypto ca crt	Displays information about CA CRLs.
show crypto ca trustpoints	Displays information about CA trust points.

Configuration Examples for PKI

This section shows examples of the tasks that you can use to configure certificates and CRLs on Cisco NX-OS devices using a Microsoft Windows Certificate server.



Note

You can use any type of certificate server to generate digital certificates. You are not limited to using the Microsoft Windows Certificate server.

Configuring Certificates on a Cisco NX-OS Device

To configure certificates on a Cisco NX-OS device, follow these steps:

SUMMARY STEPS

1. Configure the device FQDN.
2. Configure the DNS domain name for the device.
3. Create a trust point.
4. Create an RSA key pair for the device.
5. Associate the RSA key pair to the trust point.
6. Download the CA certificate from the Microsoft Certificate Service web interface.
7. Authenticate the CA that you want to enroll to the trust point.
8. Generate a request certificate to use to enroll with a trust point.
9. Request an identity certificate from the Microsoft Certificate Service web interface.
10. Import the identity certificate.
11. Verify the certificate configuration.
12. Save the certificate configuration to the startup configuration.

DETAILED STEPS

Step 1

Configure the device FQDN.

```
switch# configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# hostname Device-1
Device-1(config)#
```

Step 2

Configure the DNS domain name for the device.

```
Device-1(config)# ip domain-name cisco.com
```

Step 3

Create a trust point.

```
Device-1(config)# crypto ca trustpoint myCA
Device-1(config-trustpoint)# exit
Device-1(config)# show crypto ca trustpoints
trustpoint: myCA; key:
revocation methods:  crl
```

Step 4

Create an RSA key pair for the device.

```
Device-1(config)# crypto key generate rsa label myKey exportable modulus 1024
Device-1(config)# show crypto key mypubkey rsa
key label: myKey
key size: 1024
exportable: yes
```

Step 5

Associate the RSA key pair to the trust point.

```
Device-1(config)# crypto ca trustpoint myCA
Device-1(config-trustpoint)# rsa keypair myKey
Device-1(config-trustpoint)# exit
Device-1(config)# show crypto ca trustpoints
trustpoint: myCA; key: myKey
```



```
revocation methods:  crt
```

Step 6 Download the CA certificate from the Microsoft Certificate Service web interface.

Step 7 Authenticate the CA that you want to enroll to the trust point.

```
Device-1(config)# crypto ca authenticate myCA
input (cut & paste) CA certificate (chain) in PEM format;
end the input with a line containing only END OF INPUT :
-----BEGIN CERTIFICATE-----
MIIC4jCCAoygAwIBAgIQBWDSiay0GZRPSRI1jK0ZeJANBgkqhkiG9w0BAQUFADCB
kDEgMB4GCSqGSIb3DQEJARYRYWlhbMRrZUBjaXNjb55jb20xCzAJBgNVBAYTAk1O
MRIWEAYDVQQIEWlLYXJuYXRha2ExEjAQBGNVBACTCUJhbmdbG9yZTEOMAwGA1UE
ChMFQ2l2Y28xEzARBGNVBAsTCm5ldHN0b3JhZ2UxEjAQBGNVBAMTCUFWYXJuYSBD
QTAEFw0wNTA1MDMyMjQ2MzdaFw0wNzA1MDMyMjU1MTdaMIGQMSAwHgYJKoZIhvcN
AQkBFhFhbWFWZGt1QGNpc2NvLmNvbTELMakGA1UEBhMCSU4xEjAQBGNVBAGTCUth
cm5hdGFrcyYTESMBAGA1UEBxMJQmFuZ2Fsb3JlMQ4wDAYDVQQKEwVdaXNjbzETMBEG
A1UECkxMKmV0c3RvcnFnZTESMBAGA1UEAxMJQXBhcm5hIENBMFwwDQYJKoZIhvcN
AQEBBQADSwAwSAJBAMW/7b3+DXJPANBsIHHZluNccNM87ypyzwuoSNZXOMpeRXXI
OzyBAGiXT2ASFuUowQ1iDM8rO/41jf8RxyYKvysCAwEAAaOBvzCBvDALBgNVHQ8E
BAMCAcYwDwYDVR0TAQH/BAUwAwEB/zAdBgNVHQ4EFgQUYjyYRoMbrCNMRU2OyRhQ
GgsWbHEwawYDVR0tFBGQwYjAuoCygKoYoAHR0cDovL3NzZS0wOC9DZXJ0RW5yb2xs
L0FwYXJuYXUyMENBLmNybDAwOC6gLIYqZmlsZTovL1xccc3N1LTA4XENlcnRfbnJv
bGxcQXBhcm5hJTIwQ0EuY3JsMBAGCSsGAQQBgjcVAQQDAgEAMA0GCSqGSIb3DQEB
BQUAA0EAHv6UQ+8nE399Tww+KaGr0g0NIJaQNgLh0AFcT0rEyuyt/WYGPzksF9Ea
NBG7E0oN66zex0EOEfG1Vs6mXp1//w==
-----END CERTIFICATE-----
END OF INPUT
Fingerprint(s): MD5 Fingerprint=65:84:9A:27:D5:71:03:33:9C:12:23:92:38:6F:78:12
Do you accept this certificate? [yes/no]:y

Device-1(config)# show crypto ca certificates
Trustpoint: myCA
CA certificate 0:
subject= /emailAddress=admin@yourcompany.com/C=IN/ST=Karnataka/
L=Bangalore/O=Yourcompany/OU=netstorage/CN=Aparna CA
issuer= /emailAddress=admin@yourcompany.com/C=IN/ST=Karnataka/
L=Bangalore/O=Yourcompany/OU=netstorage/CN=Aparna CA
serial=0560D289ACB419944F4912258CAD197A
notBefore=May 3 22:46:37 2005 GMT
notAfter=May 3 22:55:17 2007 GMT
MD5 Fingerprint=65:84:9A:27:D5:71:03:33:9C:12:23:92:38:6F:78:12
purposes: sslserver sslclient ike
```

Step 8 Generate a request certificate to use to enroll with a trust point.

```
Device-1(config)# crypto ca enroll myCA
Create the certificate request ..
Create a challenge password. You will need to verbally provide this
password to the CA Administrator in order to revoke your certificate.
For security reasons your password will not be saved in the configuration.
Please make a note of it.
Password: nbv123
The subject name in the certificate will be: Device-1.cisco.com
Include the switch serial number in the subject name? [yes/no]: no
Include an IP address in the subject name [yes/no]: yes
```

```
ip address: 10.10.1.1
The certificate request will be displayed...
-----BEGIN CERTIFICATE REQUEST-----
MIIBqzCCARQCAQAwHDEaMBGAlUEAxMRVmVnYXMTMS5jaXNjbY5jb20wgZ8wDQYJ
KoZIhvcNAQEBBQADgY0AMIGJAoGBAL8Y1UAJ2NC7jUJ1DVaSMqNIgJ2kt8r14lKY
0JC6ManNy4qxk8VeMXZSiLJ4JgTzKWdxBLDkTTysnjuCXGvjb+wj0hEhv/y51T9y
P2NJJ8ornqShrvFZgC7ysN/PyMwKcgzhbVpj+rargZvHtGJ91XTq4WoVkSCzXv8S
VqyH0vEvAgMBAAGgTzAVBgqhkiG9w0BCQcxCBMGBmJ2MTIzMDYGCsQGSIb3DQeJ
DjEpMCCwJQYDVORAAQH/BBswGYIRVmVnYXMTMS5jaXNjbY5jb22HBKwWH6IwDQYJ
KoZIhvcNAQEBBQADgYEAKT60KER6Qo8nj0sDXZVHSfJZh6K6JtDz3Gkd99G1FWgt
PftrNcWUE/pw6HayfQl2T3ecgNwel2d15133YBF2bktExiI6U188nTOjglXMjja8
8a23bNDpNsM8rk1wA6hWkrVL8NUZEFJxqbJfngPNTZacJCUS6ZqKCMetbKytUx0=
-----END CERTIFICATE REQUEST-----
```

Step 9 Request an identity certificate from the Microsoft Certificate Service web interface.

Step 10 Import the identity certificate.

```
Device-1(config)# crypto ca import myCA certificate
input (cut & paste) certificate in PEM format:
-----BEGIN CERTIFICATE-----
MIIEADCCA6qgAwIBAgIKCj00oQAAAAAADANBgkqhkiG9w0BAQUFADCBkDEgMB4G
CSqGSIb3DQEJARYRYW1hbmRrZUBjaXNjbY5jb20xCzAJBgNVBAYTAkOMRIWEAYD
VQQIEw1LYXJuYXRha2ExEjAQBGNVBACTCUJhbmhhdG9yZTEOMAwGA1UEChMFQ2l2
Y28xEzARBGNVBAsTCm5ldHN0b3JhZ2UxEjAQBGNVBAMTCUFwYXJuYSBDQTAEFw0w
NTEeMTIwMzAyNDBaFw0wNjExMTIwMzEyNDBaMBwxGjAYBgNVBAMTEVZlZ2FzLTEu
Y2l2Y28uY29tMIGfMA0GCSqGSIb3DQEBAQUAA4GNADCBiQKBgQC/GNVACdjQu41C
dQlWkKjKjSICdPlFK5eJSmNCQujGpzcKsZPFxjF2UoiyeCYE8ylncWyw5E08rJ47
glxr42/sI9IRIb/8udU/cj9jSSfKK56koa7xWYA8rDfz8jMCnIM4W1aY/q2q4Gb
x7RifdV06uFqFZEgS17/Elash9LxLwIDAQABo4ICEzCCAg8wJQYDVORAAQH/BBsw
GYIRVmVnYXMTMS5jaXNjbY5jb22HBKwWH6IwHQYDVROBBYEFKCLi+2sspWEfgrR
bhWm1Vyo9jngMIHMBGNVHSMGcQwgcGAFCco8kaDG6wjTEVNjskYUBoLFmxxoYGW
pIGTMIGQMSAwHgYJKoZIhvcNAQkBFhFhbWFWZGt1QGNpc2NvLmNvbTElMAkGA1UE
BhMCSU4xEjAQBGNVBAGTCUthcm5hdGFrYTESMBAGA1UEBxMJQmFuZ2Fsb3JlMQ4w
DAYDVQQKEwVDAxNjbzETMBEGA1UECxmKbmV0c3RvcnFnZTESMBAGA1UEAxMJQXBh
cm5hIENBghAFYnKJrLQZlE9JEiWMrRl6MGsGA1UdHwRkMGiWlQAsOCqGKGh0dHA6
Ly9zc2U2MDgvQ2VydEVucm9sbC9BcGFybmElMjBDBQ5jcmwWMAuoCyGKMGZpbGU6
Ly9cXHNzZS0wOFZDZXJ0RW5yb2xsXEFwYXJuYXUyMENBMLmNyBDBCBiYIKwYBBQUH
AQEEfjB8MDsGCCsGAQUFBzAChi9odHRwOi8vc3NlLTA4L0NlcnRfbnJvbGwvc3Nl
LTA4X0FwYXJuYXUyMENBMLmNyDA9BggrBgEFBQcwAoYxZmlsZTovL1xccc3NlLTA4
XENlcnRfbnJvbGwvc3NlLTA4X0FwYXJuYXUyMENBMLmNyDANBgkqhkiG9w0BAQUF
AANBADbGBGsbe7GNLh9xeOTWBNbm24U69ZSuDDcOcUZUUTgrpnTqVpPyejtsyflw
E36cIZu4WsExREqxbTk8ycx7V5o=
-----END CERTIFICATE-----
Device-1(config)# exit
Device-1#
```

Step 11 Verify the certificate configuration.

Step 12 Save the certificate configuration to the startup configuration.

Related Topics

- [Downloading a CA Certificate, page 27](#)


- [Requesting an Identity Certificate, page 35](#)

Downloading a CA Certificate


To download a CA certificate from the Microsoft Certificate Services web interface, follow these steps:

SUMMARY STEPS


1. From the Microsoft Certificate Services web interface, click **Retrieve the CA certificate or certificate revocation task** and click **Next**.




2. From the display list, choose the CA certificate file to download from the displayed list. Then click **Base 64 encoded** and click **Download CA certificate**.




3. Click **Open** in the File Download dialog box.




4. In the Certificate dialog box, click **Copy to File** and click **OK**.



- From the Certificate Export Wizard dialog box, choose the **Base-64 encoded X.509 (CER)** and click **Next**.




- In the File name: text box on the Certificate Export Wizard dialog box, enter the destination file name and click **Next**.
- In the Certificate Export Wizard dialog box, click **Finish**.
- Enter the Microsoft Windows **type** command to display the CA certificate stored in Base-64 (PEM) format.




DETAILED STEPS


-
- Step 1** From the Microsoft Certificate Services web interface, click **Retrieve the CA certificate or certificate revocation task** and click **Next**.



Step 2 From the display list, choose the CA certificate file to download from the displayed list. Then click **Base 64 encoded** and click **Download CA certificate**.




Step 3 Click **Open** in the File Download dialog box.




144759

Step 4 In the Certificate dialog box, click **Copy to File** and click **OK**.




144760

Step 5 From the Certificate Export Wizard dialog box, choose the **Base-64 encoded X.509 (CER)** and click **Next**.



- Step 6** In the File name: text box on the Certificate Export Wizard dialog box, enter the destination file name and click **Next**.
- Step 7** In the Certificate Export Wizard dialog box, click **Finish**.
- Step 8** Enter the Microsoft Windows **type** command to display the CA certificate stored in Base-64 (PEM) format.



Requesting an Identity Certificate

To request an identity certificate from a Microsoft Certificate server using a PKCS#12 certificate signing request (CSR), follow these steps:

SUMMARY STEPS

1. From the Microsoft Certificate Services web interface, click **Request a certificate** and click **Next**.

Microsoft Certificate Services -- Apama CA [Home](#)

Welcome

You use this web site to request a certificate for your web browser, e-mail client, or other secure program. Once you acquire a certificate, you will be able to securely identify yourself to other people over the web, sign your e-mail messages, encrypt your e-mail messages, and more depending upon the type of certificate you request.

Select a task:

- ☐ Retrieve the CA certificate or certificate revocation list
- ☒ Request a certificate
- ☐ Check on a pending certificate

[Next >](#)

144765

2. Click **Advanced request** and click **Next**.

Microsoft Certificate Services -- Apama CA [Home](#)

Choose Request Type


Please select the type of request you would like to make:

- ☐ User certificate request:
 - Web Browser Certificate
 - E-Mail Protection Certificate
- ☒ Advanced request


[Next >](#)

144766

5. Wait one or two days until the certificate is issued by the CA administrator.



6. Note that the CA administrator approves the certificate request.



7. From the Microsoft Certificate Services web interface, click **Check on a pending certificate** and click **Next**.

Microsoft Certificate Services -- Apama CA Home

Welcome

You use this web site to request a certificate for your web browser, e-mail client, or other secure program. Once you acquire a certificate, you will be able to securely identify yourself to other people over the web, sign your e-mail messages, encrypt your e-mail messages, and more depending upon the type of certificate you request.

Select a task:

- ☐ Retrieve the CA certificate or certificate revocation list
- ☐ Request a certificate
- ☒ Check on a pending certificate

Next >

144771

8. Choose the certificate request that you want to check and click **Next**.

Microsoft Certificate Services -- Apama CA Home

Check On A Pending Certificate Request


Please select the certificate request you want to check:

Saved-Request Certificate (12 November 2005 20:30:22)


Next >

144772


9. Click **Base 64 encoded** and click **Download CA certificate**.




10. In the File Download dialog box, click **Open**.



11. In the Certificate box, click **Details** tab and click **Copy to File...**. In the Certificate Export Dialog box, click **Base-64 encoded X.509 (.CER)**, and click **Next**.



12. In the File name: text box on the Certificate Export Wizard dialog box, enter the destination file name and click **Next**.



DETAILED STEPS

Step 1 From the Microsoft Certificate Services web interface, click **Request a certificate** and click **Next**.

Microsoft Certificate Services -- Apama CA Home

Welcome

You use this web site to request a certificate for your web browser, e-mail client, or other secure program. Once you acquire a certificate, you will be able to securely identify yourself to other people over the web, sign your e-mail messages, encrypt your e-mail messages, and more depending upon the type of certificate you request.

Select a task:

- ☐ Retrieve the CA certificate or certificate revocation list
- ☒ Request a certificate
- ☐ Check on a pending certificate

Next >

144765

Step 2 Click **Advanced request** and click **Next**.

Microsoft Certificate Services -- Apama CA Home

Choose Request Type

Please select the type of request you would like to make:

- ☐ User certificate request:
 - Web Browser Certificate
 - E-Mail Protection Certificate
- ☒ Advanced request

Next >

144766

Step 3 Click **Submit a certificate request using a base64 encoded PKCS#10 file or a renewal request using a base64 encoded PKCS#7 file** and click **Next**.

Microsoft Certificate Services -- Aparna CA Home

Advanced Certificate Requests

You can request a certificate for yourself, another user, or a computer using one of the following methods. Note that the policy of the certification authority (CA) will determine the certificates that you can obtain.

- ☐ Submit a certificate request to this CA using a form.
- ☒ Submit a certificate request using a base64 encoded PKCS #10 file or a renewal request using a base64 encoded PKCS #7 file.
- ☐ Request a certificate for a smart card on behalf of another user using the Smart Card Enrollment Station.
You must have an enrollment agent certificate to submit a request for another user.

Next >

Step 4 In the Saved Request text box, paste the base64 PKCS#10 certificate request and click **Next**. The certificate request is copied from the Cisco NX-OS device console.

Microsoft Certificate Services -- Aparna CA Home

Submit A Saved Request

Paste a base64 encoded PKCS #10 certificate request or PKCS #7 renewal request generated by an external application (such as a web server) into the request field to submit the request to the certification authority (CA).

Saved Request:

Base64 Encoded Certificate Request (PKCS #10 or #7):

```
VqyHOvEvAgMBAAGgTzAVBgkqhkiG9w0BCQsxCBMG
DjEpMCcwJQYDVORACQw/BBawGYIRVwVnYXN0MS5j
KozIhvcNAQEFBQADgTEAKT60KER6Qo8nj0sDXZVH
PfrNcWUE/pw6HayfQ12T3ecgNweL2d15133YBF2
8a23bNDpNsM8cklwA6hWkrVL8NUZEFJxqbjEngPN
-----END CERTIFICATE REQUEST-----
```


[Browse](#) for a file to insert.

Additional Attributes:


Attributes:

Submit >


Step 5 Wait one or two days until the certificate is issued by the CA administrator.




Step 6 Note that the CA administrator approves the certificate request.




Step 7 From the Microsoft Certificate Services web interface, click **Check on a pending certificate** and click **Next**.




Step 8 Choose the certificate request that you want to check and click **Next**.




Step 9 Click **Base 64 encoded** and click **Download CA certificate**.




Step 10 In the File Download dialog box, click **Open**.




Step 11 In the Certificate box, click **Details** tab and click **Copy to File...**. In the Certificate Export Dialog box, click **Base-64 encoded X.509 (.CER)**, and click **Next**.




Step 12 In the File name: text box on the Certificate Export Wizard dialog box, enter the destination file name and click **Next**.



Step 13 Click **Finish**.



Step 14 Enter the Microsoft Windows **type** command to display the identity certificate in base64-encoded format.



Related Topics


- [Generating Certificate Requests, page 13](#)
- [Configuring Certificates on a Cisco NX-OS Device, page 23](#)

Revoking a Certificate


To revoke a certificate using the Microsoft CA administrator program, follow these steps:

SUMMARY STEPS


1. From the Certification Authority tree, click **Issued Certificates** folder. From the list, right-click the certificate that you want to revoke.
2. Choose **All Tasks > Revoke Certificate**.



3. From the Reason code drop-down list, choose a reason for the revocation and click **Yes**.




4. Click the **Revoked Certificates** folder to list and verify the certificate revocation.




DETAILED STEPS

Step 1 From the Certification Authority tree, click **Issued Certificates** folder. From the list, right-click the certificate that you want to revoke.


Step 2 Choose **All Tasks > Revoke Certificate**.



Step 3 From the Reason code drop-down list, choose a reason for the revocation and click **Yes**.



Step 4 Click the **Revoked Certificates** folder to list and verify the certificate revocation.




Request ID	Requester Name	Binary Certificate	Serial Number	Certificate Effective Date
15	SSE-08\IUSR_SS...	-----BEGIN CERTI...	5dae53cd00000000000f	6/30/2005 3:27 AM
16	SSE-08\IUSR_SS...	-----BEGIN CERTI...	5db140d3000000000010	6/30/2005 3:30 AM
17	SSE-08\IUSR_SS...	-----BEGIN CERTI...	5e2d7c1b000000000011	6/30/2005 5:46 AM
18	SSE-08\IUSR_SS...	-----BEGIN CERTI...	16db4f8f000000000012	7/8/2005 3:21 AM
19	SSE-08\IUSR_SS...	-----BEGIN CERTI...	261c3924000000000013	7/14/2005 5:00 AM
20	SSE-08\IUSR_SS...	-----BEGIN CERTI...	262b5202000000000014	7/14/2005 5:16 AM
21	SSE-08\IUSR_SS...	-----BEGIN CERTI...	2634c7f2000000000015	7/14/2005 5:27 AM
22	SSE-08\IUSR_SS...	-----BEGIN CERTI...	2635b000000000000016	7/14/2005 5:28 AM
23	SSE-08\IUSR_SS...	-----BEGIN CERTI...	26485040000000000017	7/14/2005 5:48 AM
24	SSE-08\IUSR_SS...	-----BEGIN CERTI...	2a276357000000000018	7/14/2005 11:51 PM
25	SSE-08\IUSR_SS...	-----BEGIN CERTI...	3f88cbf7000000000019	7/19/2005 3:29 AM
26	SSE-08\IUSR_SS...	-----BEGIN CERTI...	6e4b5f5f00000000001a	7/28/2005 3:58 AM
27	SSE-08\IUSR_SS...	-----BEGIN CERTI...	725b89d800000000001b	7/28/2005 10:54 PM
28	SSE-08\IUSR_SS...	-----BEGIN CERTI...	735a887800000000001c	7/29/2005 3:33 AM
29	SSE-08\IUSR_SS...	-----BEGIN CERTI...	148511c700000000001d	8/3/2005 11:30 PM
30	SSE-08\IUSR_SS...	-----BEGIN CERTI...	14a7170100000000001e	8/4/2005 12:07 AM
31	SSE-08\IUSR_SS...	-----BEGIN CERTI...	14fc45b500000000001f	8/4/2005 1:40 AM
32	SSE-08\IUSR_SS...	-----BEGIN CERTI...	486ce80b000000000020	8/17/2005 3:58 AM
33	SSE-08\IUSR_SS...	-----BEGIN CERTI...	4ca4a3aa000000000021	8/17/2005 11:37 PM
47	SSE-08\IUSR_SS...	-----BEGIN CERTI...	1aa55c8e00000000002f	9/1/2005 11:36 PM
63	SSE-08\IUSR_SS...	-----BEGIN CERTI...	3f0845dd00000000003f	9/9/2005 1:11 AM
66	SSE-08\IUSR_SS...	-----BEGIN CERTI...	3f619b7e000000000042	9/9/2005 2:48 AM
82	SSE-08\IUSR_SS...	-----BEGIN CERTI...	6313c463000000000052	9/16/2005 1:09 AM
96	SSE-08\IUSR_SS...	-----BEGIN CERTI...	7c3861e3000000000060	9/20/2005 10:20 PM
97	SSE-08\IUSR_SS...	-----BEGIN CERTI...	7c6ee351000000000061	9/20/2005 11:20 PM
116	SSE-08\IUSR_SS...	-----BEGIN CERTI...	0a338ea1000000000074	11/12/2005 8:32 AM

Generating and Publishing the CRL


To generate and publish the CRL using the Microsoft CA administrator program, follow these steps:

SUMMARY STEPS

1. From the Certification Authority screen, choose **Action > All Tasks > Publish**.




2. In the Certificate Revocation List dialog box, click **Yes** to publish the latest CRL.




DETAILED STEPS

Step 1 From the Certification Authority screen, choose **Action > All Tasks > Publish**.



Step 2 In the Certificate Revocation List dialog box, click **Yes** to publish the latest CRL.




Downloading the CRL


To download the CRL from the Microsoft CA website, follow these steps:

SUMMARY STEPS


1. From the Microsoft Certificate Services web interface, click **Retrieve the CA certificate or certificate revocation list** and click **Next**.




2. Click **Download latest certificate revocation list**.



3. In the File Download dialog box, click **Save**.



4. In the Save As dialog box, enter the destination file name and click **Save**.




5. Enter the Microsoft Windows **type** command to display the CRL.


```
C:\WINNT\system32\cmd.exe
D:\testcerts>type aparnaCA.crl
-----BEGIN X509 CRL-----
MIIGBCCBa8CAQEWdQYJKoZIhucNAQEFBQAwwZAxIDAEBgkqhkiG9w0BCQEWewft
Y1W5ka2UAY2IzY28uY296MQswCQYDUQGEwJITjESMBAGA1UECBMJS2FybWFOYWhh
MRIwEAYDUQHHewIcYwV5NwYxcuUxDCFjAMBGBgUUAUUBUNpZ2NuMRMwEQYDUQGLwpu
RZkd3gyYUdIMRIwEAYDUQDQDEwIBGfYbmEGQ0EXDTA1MTEeMjA0MzYwNFQwXDTA1
MTEeOTIe2NTYwNFowggSxMBsCCmEbCaEAAAAAAAAIXDTA1MDgxNjIjxNTIjX0U0wGwIK
TNSGTGAaaaaaaaxcNMDUwODE2MjE1MjI5WjAbaGppM/CtCAAAAAAAAAEF00WNTA4MTYy
MTUwYnDFaMBsCCmXpnsIAAAAAAAAAUXDTA1MDgxNjIjxNTIjI1MlowGwIjKbM993Aaaaaaa
BhcNMDUwNjA4MDAxMjA0WjAbaGppwzE//AAAAAAAAHFw0WNTA4MTYyMTUwYnDFaMBsC
Ck2bEYRYaaaaaaXDTA1MDgxNjIjxNTMxNUowKQIKUggCMAaaaaaaCERNMDUwNjI3
MjA0MzE2WjAbaGppMCA1UdFQ0DCgECMCKCC1NjIjUyYVAAAAaaaxDTA1MDYyMzI2ZDcy
MlowDDAKBgNUHURUEawoBAjApGpTvrRc8AAAAAAALFw0WNTA3MDQwODABMDFAmaaw
GgYDUROUBANMKAAQYwGwIKUR56zgaAAAAAADBgNMDUwODE2MjE1MzE1WjAbaGppdFP0Uu
AAAAAANFw0WNTA2MjJkYU9jA3MjUwAAawGgYDUROUBAMKAQEwGwIKXkz3EwAAAAaa
DhcNMDUwNzE0MDA4ZmZlU2VjAbaGppdr1PNAaaaaaaPFw0WNTA4MTYyYmTUzMTUwYnDFa
C12xNMDUwNzE0MDA4ZmZlU2VjAbaGppdMjE1MjI5WjAbaGppKQIKX1I8GwAAAAAaERcNMDUwNzE2
MjE1MjA0MzE2WjAbaGppMCA1UdFQ0DCgEFMBsCCbbtI48AAAAaaABIXDTA1MDgxNjIjxNTMx
NUowGwIKUjhw5JAAAAaaaxcNMDUwODE2MjE1MjI5WjAbaGppKXDI1CAAAAAaaAFw0W
NTA3MTQwMDMzMTBaMBsCCiCY0x//IAAAAAABUXDTA1MDcxNDAAWmZl0NUowGwIKUjJjWw
AAAAAANFhcNMDUwNzE0MDA4ZmZlU2VjAbaGppSFBAAAAaaaxFw0WNTA3MTQwMDMzMT
MjA0MzE2WjAbaGppMCA1UdFQ0DCgEFMBsCCionY1CAAAAAaaBqXDTA1MDgxNjIjxNTMxNUow
GwIKP4jL9wAAAAaaGRcNMDUwODE2MjE1MjI5WjAbaGppuS19FAAAAAaaAFw0WNTA4MTYyYmTUz
MTUwYnDFaMBsCCnJh
idgAAAAaaBxDTA1MDgxNjIjxNTMxNUowGwIKc1qIeAAAAaaAHxcNMDUwODE2MjE1
MzE1WjAbaGpouHRRHAAAAaaAFw0WNTA4MTYyYmTUzMTUwYnDFaMBsCCShNfWEAAAAaaB4X
DTA1MDgxNjIjxNTMxNUowGwIKFPpXfTQAAAAaaHxcNMDUwODE3MTgzMDQyWjAbaGppI
b0GLAAAAaaAFw0WNTA4MTcxODMwNDNaMBsCCkyko6oAAAAaaCEXDTA1MDgxNzE4
MzA0M1AAWwGwIKGqUcJgAAAAaaALxcNMDUwOTA1MTcxNzE2WjAbaGp0/CEXdaAAAAaa/
Fw0WNTA5MDgyMDI0MzJaMBsCCj9hm34AAAAaaEIXDTA1MDkxODIjXNDAB0FowGwIK
YjPEYwAAAAaaUhcNMDUwOTESMTczNzE4WjAbaGpp8OGHjAAAAaaBfGw0WNTA5TjA3
NzUwYnDFaMBsCCcnux4I1EAAAAaaAGEXDTA1MDkyMDE4NTIjZmFowGwIKCj00QAAAAaa
dBCNMDUwNTIeYMDQzNDQyYU9jA1MDMwHwYDUROjBBGwFoAUjY3jRoMhCNRU2OyRhQ
GgsWbHwEwEAYJKwYBBAAGCNxUBBAMCAQAwDQYJKoZIhucNAQEFBQA0DQQAly91DCrhi
HoCUbm9NgwzYjJjEjgeU168CuaaFP3rkM8YyZYpu1c32R/Uu06a5xgrAC/SbsEa
nxpJt5xYJndy
-----END X509 CRL-----
D:\testcerts>
```

DETAILED STEPS


Step 1 From the Microsoft Certificate Services web interface, click **Retrieve the CA certificate or certificate revocation list** and click **Next**.



Step 2 Click **Download latest certificate revocation list**.




Step 3 In the File Download dialog box, click **Save**.



144786

Step 4 In the Save As dialog box, enter the destination file name and click **Save**.



144787

Step 5 Enter the Microsoft Windows **type** command to display the CRL.

```

C:\WINNT\system32\cmd.exe
D:\testcerts>type aparnaCA.crl
-----BEGIN X509 CRL-----
MIIgBTCCBa8CAQEFwDQYJKoZIhvcNAQEFBQAwZANIDAEBgqhkiG9w0BCQFEWEMFt
VW5ka2UAY2l2Y28uY29tMQswCQYDUQGEwJITjESMBAQIUECBMJS2FybmF0YVht
MRIwEAYDUQGEw1CYW5nYVxvcmUxDjAMBGNUBAOTBUNpc2NvMRMwEQYDUQGLEWpu
ZXRxZdG9yYWdlMRIwEAYDUQGEw1BcGFybmEgQ0EXDIA1MTExMjA0MzYwNFoXDTA1
MTExOTE2NTYwNFowggSxMBsCCmEhCaEAAAAAAAAI XDTA1MDgxNjI xNTI xOUowGwIK
TN5GTgAAAAAAAAxcNMDUwODE2MjE1MjI5WjAbaGpM/CtCAAAAAAAAAEFw0wNTA4MTYy
MTUyNDFAmBsCCmXpnsIAAAAAAAAAXDTA1MDgxNjI xNTI1M1owGwIKbM993AAAAAAAA
BhcNMDUwNjA4MDAxMjA0WjAbaGpwezE//AAAAAAAAHFw0wNTA4MTYyMTUzMTUaMBsC
Ck2bERYAAAAAAAAgXDTA1MDgxNjI xNTMxNUowKQIKUggCAAAAAAAAAACRcNMDUwNjI3
MjM0NzA2WjAMMAoGA1UdFQDDCgECMCKCC1NjYUAAAAAAAAoXDTA1MDYyNzIzNDcy
M1owDDAKBgNVHREUaWBoBAjAbaGpTvrRc8AAAAAAAAALFw0wNTA3MDQxODA0MDFaMAww
CgYDUR0UBAMKAQYwGwIKUR56zgAAAAAAAAADBcNMDUwODE2MjE1MzE1WjAbaGpdpP9Uu
AAAAAAAAANFw0wNTA2MjkyMjA3MjUaMAwwCgYDUR0UBAMKAQEFw0wIKXat3EwAAAAA
DhcNMDUwNzE0MDA2MzU2WjAbaGpdpLpNAAAAAAAAAFw0wNTA4MTYyMTUzMTUaMBsC
C12xQNMAAAAAAAAABAxDTA1MDgxNjI xNTMxNUowKQIKXii8GwAAAAAAERcNMDUwNzA2
MjE1MjEwWjAMMAoGA1UdFQDDCgEFMBsCCbbI48AAAAAAAABI XDTA1MDgxNjI xNTMx
NUowGwIKJhw5JAAAAAAAAEXcNMDUwODE2MjE1MzE1WjAbaGpMk1I CAAAAAAAAAUFw0w
NTA3MTQwMDMzMjBaMBsCCiY0x/I AAAAAAAAABUXDTA1MDcxNDAwMzI0NUowGwIKJjWw
AAAAAAAAAFhcNMDUwNzE0MDA2MTUxWjAbaGpMFBAAAAAAAAAXFw0wNTA3MTQwMDM5
MjUaMBsCCionY1cAAAAAAAABgXDTA1MDgxNjI xNTMxNUowGwIKP4jL9wAAAAAAGRcN
MDUwODE2MjE1MzE1WjAbaGpM19fAAAAAAAAaFw0wNTA4MTYyMTUzMTUaMBsCCnJb
idgAAAAAAAABsXDTA1MDgxNjI xNTMxNUowGwIKc1qIeAAAAAAAAHBcNMDUwODE2MjE1
MzE1WjAbaGpUhhRHAAAAAAAAAdFw0wNTA4MTYyMTUzMTUaMBsCCbSnFEAAAAAAAAAB4X
DTA1MDgxNjI xNTMxNUowGwIKFPxFtQAAAAAAAAHxcNMDUwODE3MTgzMDQyWjAbaGpI
bOgLAAAAAAAAAgFw0wNTA4MTcxODMwNDNaMBsCCkuko6oAAAAAAAACEXDTA1MDgxNzE4
MzA0M1owGwIKGgUcJgAAAAAAAAALxcNMDUwOTA1MTcwNzA2WjAbaGpO/CEXAAAAAAAA/
Fw0wNTA5MDgyMDI0MzJaMBsCCj9hm34AAAAAAAAEIXDTA1MDkwODI xNDA00FowGwIK
YxPEYwAAAAAAAAUhcNMDUwOTE5MTcxNzE4WjAbaGp8OGHjAAAAAAAABgFw0wNTA5MjAx
NzUyZAMBsCCnxu41EAAAAAAAAGEXDTA1MDkyMDE4NTIzMfFowGwIKCj00oQAAAAAAAA
dBeNMDUwMTExMDQzNDQyWgA1MDMwHwYDUR0jBBgwFoAuJyJyRoMbrCNMRU2OyRhQ
GgsWbHEwEAYJKoYBBAQCNxUBBAMCAQAwDQYJKoZIhvcNAQEFBQAQDQALy91DCRhi
HoCUbn9NqWzYjJjEjjeU168CuaacFP3rkM8YyZYpu1c32R/UvU6a5SxgrAC/SbsEa
nxpJt5xYJNdY
-----END X509 CRL-----
D:\testcerts>

```

Related Topics

- [Configuring Certificate Revocation Checking Methods, page 12](#)

Importing the CRL

To import the CRL to the trust point corresponding to the CA, follow these steps:

SUMMARY STEPS

1. Copy the CRL file to the Cisco NX-OS device bootflash.
2. Configure the CRL.
3. Display the contents of the CRL.

DETAILED STEPS

Step 1 Copy the CRL file to the Cisco NX-OS device bootflash.

Example:

```
Device-1# copy tftp:aparnaCA.crl bootflash:aparnaCA.crl
```

Step 2 Configure the CRL.**Example:**

```
Device-1# configure terminal
Device-1(config)# crypto ca crl request myCA bootflash:aparnaCA.crl
Device-1(config)#
```

Step 3 Display the contents of the CRL.**Example:**

```
Device-1(config)# show crypto ca crl myCA
Trustpoint: myCA
CRL:
Certificate Revocation List (CRL):
  Version 2 (0x1)
  Signature Algorithm: sha1WithRSAEncryption
  Issuer: /emailAddress=admin@yourcompany.com/C=IN/ST=Karnatak
Yourcompany/OU=netstorage/CN=Aparna CA
  Last Update: Nov 12 04:36:04 2005 GMT
  Next Update: Nov 19 16:56:04 2005 GMT
  CRL extensions:
    X509v3 Authority Key Identifier:
      keyid:27:28:F2:46:83:1B:AC:23:4C:45:4D:8E:C9:18:50:1
      1.3.6.1.4.1.311.21.1:
        ...
  Revoked Certificates:
    Serial Number: 611B09A1000000000002
      Revocation Date: Aug 16 21:52:19 2005 GMT
    Serial Number: 4CDE464E000000000003
      Revocation Date: Aug 16 21:52:29 2005 GMT
    Serial Number: 4CFC2B42000000000004
      Revocation Date: Aug 16 21:52:41 2005 GMT
    Serial Number: 6C699EC2000000000005
      Revocation Date: Aug 16 21:52:52 2005 GMT
    Serial Number: 6CCF7DDC000000000006
      Revocation Date: Jun 8 00:12:04 2005 GMT
    Serial Number: 70CC4FFF000000000007
      Revocation Date: Aug 16 21:53:15 2005 GMT
    Serial Number: 4D9B1116000000000008
      Revocation Date: Aug 16 21:53:15 2005 GMT
    Serial Number: 52A80230000000000009
      Revocation Date: Jun 27 23:47:06 2005 GMT
      CRL entry extensions:
        X509v3 CRL Reason Code:
          CA Compromise
    Serial Number: 5349AD4600000000000A
      Revocation Date: Jun 27 23:47:22 2005 GMT
      CRL entry extensions:
        X509v3 CRL Reason Code:
          CA Compromise
    Serial Number: 53BD173C00000000000B
      Revocation Date: Jul 4 18:04:01 2005 GMT
      CRL entry extensions:
        X509v3 CRL Reason Code:
          Certificate Hold
    Serial Number: 591E7ACE00000000000C
      Revocation Date: Aug 16 21:53:15 2005 GMT
    Serial Number: 5D3FD52E00000000000D
      Revocation Date: Jun 29 22:07:25 2005 GMT
```



```

CRL entry extensions:
  X509v3 CRL Reason Code:
    Key Compromise
Serial Number: 5DAB771300000000000E
  Revocation Date: Jul 14 00:33:56 2005 GMT
Serial Number: 5DAE53CD00000000000F
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 5DB140D30000000000010
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 5E2D7C1B0000000000011
  Revocation Date: Jul 6 21:12:10 2005 GMT
CRL entry extensions:
  X509v3 CRL Reason Code:
    Cessation Of Operation
Serial Number: 16DB4F8F0000000000012
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 261C39240000000000013
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 262B52020000000000014
  Revocation Date: Jul 14 00:33:10 2005 GMT
Serial Number: 2634C7F20000000000015
  Revocation Date: Jul 14 00:32:45 2005 GMT
Serial Number: 2635B0000000000000016
  Revocation Date: Jul 14 00:31:51 2005 GMT
Serial Number: 264850400000000000017
  Revocation Date: Jul 14 00:32:25 2005 GMT
Serial Number: 2A2763570000000000018
Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 3F88CBF70000000000019
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 6E4B5F5F000000000001A
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 725B89D8000000000001B
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 735A8878000000000001C
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 148511C7000000000001D
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 14A71701000000000001E
  Revocation Date: Aug 16 21:53:15 2005 GMT
Serial Number: 14FC45B5000000000001F
  Revocation Date: Aug 17 18:30:42 2005 GMT
Serial Number: 486CE80B0000000000020
  Revocation Date: Aug 17 18:30:43 2005 GMT
Serial Number: 4CA4A3AA0000000000021
  Revocation Date: Aug 17 18:30:43 2005 GMT
Serial Number: 1AA55C8E000000000002F
  Revocation Date: Sep 5 17:07:06 2005 GMT
Serial Number: 3F0845DD000000000003F
  Revocation Date: Sep 8 20:24:32 2005 GMT
Serial Number: 3F619B7E0000000000042
  Revocation Date: Sep 8 21:40:48 2005 GMT
Serial Number: 6313C4630000000000052
  Revocation Date: Sep 19 17:37:18 2005 GMT
Serial Number: 7C3861E30000000000060
  Revocation Date: Sep 20 17:52:56 2005 GMT
Serial Number: 7C6EE3510000000000061
  Revocation Date: Sep 20 18:52:30 2005 GMT
Serial Number: 0A338EA10000000000074  <-- Revoked identity certificate
  Revocation Date: Nov 12 04:34:42 2005 GMT
Signature Algorithm: sha1WithRSAEncryption
0b:cb:dd:43:0a:b8:62:1e:80:95:06:6f:4d:ab:0c:d8:8e:32:
44:8e:a7:94:97:af:02:b9:a6:9c:14:fd:eb:90:cf:18:c9:96:
29:bb:57:37:d9:1f:d5:bd:4e:9a:4b:18:2b:00:2f:d2:6e:c1:
1a:9f:1a:49:b7:9c:58:24:d7:72

```

Note The identity certificate for the device that was revoked (serial number 0A338EA10000000000074) is listed at the end.

Additional References for PKI

This section includes additional information related to implementing PKI.

Related Documents for PKI

Related Topic	Document Title
Cisco NX-OS Licensing	<i>Cisco Nexus 7000 Series NX-OS Licensing Guide, Release 4.2</i>
Command reference	Cisco Nexus 7000 Series NX-OS Security Command Reference, Release 4.2
VRF configuration	Cisco Nexus 7000 Series NX-OS Unicast Routing Configuration Guide, Release 4.2

Standards for PKI

Standards	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	—

Feature History for PKI

This table lists the release history for this feature.

Table 2: Feature History for PKI

Feature Name	Releases	Feature Information	
PKI	4.1(2)	This feature was introduced.	