



## CHAPTER 7

# Unset Commands

---

Revised: July 22, 2009, OL-19335-01

This chapter contains the following **unset** commands:

- [unset upgrade audio](#)
- [unset upgrade auxiliary-ctrl](#)
- [unset upgrade camera](#)
- [unset upgrade display](#)
- [unset upgrade firmware](#)
- [unset upgrade graphic-driver](#)
- [unset upgrade graphic-icons](#)

# unset upgrade audio

## unset upgrade audio

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.4.0	This command was introduced.

**Usage Guidelines** Use this command to clear a forced upgrade of the audio peripheral. You can see if a peripheral is set for a forced upgrade by running the [show upgrade detail](#) command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the [set upgrade](#) commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade audio
```

Unsetting forced audio upgrade

Related Commands	Command	Descriptions
	<a href="#">show upgrade</a>	Shows details of an upgrade.

# unset upgrade auxiliary-ctrl

## unset upgrade auxiliary-ctrl

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.4.0	This command was introduced.

**Usage Guidelines** Use this command to clear a forced upgrade of the auxiliary-ctrl peripheral. You can see if a peripheral is set for a forced upgrade by running the [show upgrade detail](#) command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the [set upgrade](#) commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade auxiliary-ctrl
```

Unsetting forced auxiliary-ctrl upgrade

Related Commands	Command	Descriptions
	<a href="#">show upgrade</a>	Shows details of an upgrade.

# unset upgrade camera

## unset upgrade camera

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.2	This command was introduced.

**Usage Guidelines** Use this command to clear a forced upgrade of the camera peripheral. You can see if a peripheral is set for a forced upgrade by running the [show upgrade detail](#) command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the [set upgrade](#) commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade camera
```

Unsetting forced camera upgrade

Related Commands	Command	Descriptions
	<a href="#">show upgrade</a>	Shows details of an upgrade.

# unset upgrade display

## unset upgrade display

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.2	This command was introduced.

**Usage Guidelines** Use this command to clear a forced upgrade of the display peripheral. You can see if a peripheral is set for a forced upgrade by running the [show upgrade detail](#) command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the [set upgrade](#) commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade display

Unsetting forced display upgrade
```

Related Commands	Command	Descriptions
	<a href="#">show upgrade</a>	Shows details of an upgrade.

# unset upgrade firmware

## unset upgrade firmware

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.2	This command was introduced.

**Usage Guidelines** Use this command to clear a forced upgrade of the firmware peripheral. You can see if a peripheral is set for a forced upgrade by running the [show upgrade detail](#) command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the [set upgrade](#) commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade firmware
```

Unsetting forced firmware upgrade

Related Commands	Command	Descriptions
	<a href="#">show upgrade</a>	Shows details of an upgrade.

# unset upgrade graphic-driver

**unset upgrade graphic-driver**

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.2	This command was introduced as <b>unset upgrade disp-driver-2</b> .
	1.4.0	The command, <b>unset upgrade disp-driver-2</b> , was replaced by <b>unset upgrade graphic-driver</b> .

**Usage Guidelines** Use this command to clear a forced upgrade of the graphic driver. You can see if a peripheral is set for a forced upgrade by running the **show upgrade detail** command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the **set upgrade** commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade graphic-driver

Unsetting forced graphic driver upgrade
```

Related Commands	Command	Descriptions
	<b>show upgrade</b>	Shows details of an upgrade.

# unset upgrade graphic-icons

## unset upgrade graphic-icons

**Syntax Description** This command has no arguments or keywords.

**Command Default** No default behavior or values.

**Command Modes** Admin  
Command privilege level: 3

Command History	Release	Modifications
	1.2	This command was introduced as <b>unset upgrade disp-driver-1</b> .
	1.4.0	The command, <b>unset upgrade disp-driver-1</b> , was replaced with <b>unset upgrade graphic-icons</b> .

**Usage Guidelines** Use this command to clear a forced upgrade of the of the graphic icons. You can see if a peripheral is set for a forced upgrade by running the **show upgrade detail** command. Each peripheral marked for a forced upgrade will be followed by an “F” in the output. You can mark a peripheral by using the **set upgrade** commands. See [Set Commands](#).

**Examples**

```
admin:unset upgrade graphic-icons
```

Unsetting forced graphic icons upgrade

Related Commands	Command	Descriptions
	<b>show upgrade</b>	Shows details of an upgrade.