



Licenses

Revised: March 2015

- [Procedures, page 3-1](#)
- [Reference, page 3-3](#)



Note

Although visible in the Cisco DMM user interface, Release 5.5 and 5.6 software does not support Cisco Digital Signs, Cisco Digital Media Players (DMPs), Cisco Cast, Cisco Digital Media Designer, or the Cisco Digital Media Player Device Manager.

Procedures

Features of Cisco DMS are licensed and activated separately. Until you obtain and install license keys, their corresponding features are hidden from all users—including you, the administrator.

See these sections to manage your Cisco DMS license keys:

- [Request License Keys, page 3-1](#)
- [Install License Keys, page 3-2](#)
- [View Installed Licenses, page 3-3](#)
- [Check the Dashboard Gauge for Licenses, page 3-3](#)

Request License Keys

Features of Cisco DMS are sold and licensed separately. After you purchase the right to use a feature, you must request and install a unique license key. Your key activates the feature on your server.

Procedure

- Step 1** Start DMS-Admin.
- Step 2** Choose **Licenses > Request Licenses**.

Step 3 Enter all requested values in the Request Licenses form.

DMM Appliance Serial Number:	2UX001015C
Version:	5.3.0
Company Name:	<input type="text" value="Amalgamated Examples, LLC"/>
Department:	<input type="text" value="Sprockets"/>
Contact:	<input type="text" value="Missy Laneous"/>
When entering the Cisco Sales Order Number for your DMS system, use numerals only. A valid sales order number contains exactly 8 numerals, e.g. 28876739	
Cisco Sales Order Number *:	<input type="text" value="28876739"/>
Issuer Remarks:	<input type="text"/>
Features to License:	<input checked="" type="checkbox"/> Show and Share <input checked="" type="checkbox"/> Digital Signage <input checked="" type="checkbox"/> Cast <input checked="" type="checkbox"/> Clustering <input checked="" type="checkbox"/> Show and Share Live Events
This email will be the recipient of the License file. Your email address will not be used for any other purpose other than communications regarding your licensing of DMS.	
Your Email *:	<input type="text" value="misc@example.com"/>
<input checked="" type="radio"/> Export, and save a local copy of the generated request (Later, email that file to dms-softwarekeys@cisco.com with the subject DMM License Request) <input type="radio"/> Send your request now, automatically. (Your DMM appliance must have a working internet connection and SMTP enabled.)	
Cisco will send your license keys to you via the email address you entered above, usually within 24 hours. When you receive your license keys, return to the Licenses tab and then click Install/Upgrade Licenses . From there, you can activate your newly licensed features.	

Step 4 Choose a method to send your license request as an email message to dms-softwarekeys@cisco.com.

- Export your request to a file that you can email later.
- Send your request immediately, assuming that your DMM server is configured to enable SMTP.

Step 5 After you receive a license key file from Cisco, save a local copy of the file.



Note Make sure that your local copy does not include any spaces in its filename. (CSCtj60727)

Install License Keys

Procedure

- Step 1** Start DMS-Admin.
- Step 2** Choose **Licenses > Install/Upgrade Licenses**.
- Step 3** Click **Browse** or **Choose File**, depending on your installed browser.
- Step 4** Find and click the license file where you saved it.
- Step 5** Click **Open**.
- Step 6** Click **Install License**.
- Step 7** Repeat these steps until all of your licenses are installed.
Features that you licensed are now activated.

View Installed Licenses

Before You Begin

Install license keys.

Procedure

- Step 1** Start DMS-Admin.
- Step 2** Choose **Licenses > View Licenses**.
-

Check the Dashboard Gauge for Licenses

Before You Begin

Install license keys.

Procedure

- Step 1** Start DMS-Admin.
- Step 2** Choose **Administration > Dashboard**.
- Step 3** Check the License Features gauge for the activated license features and any restrictions.
-

Reference

- [Base Licenses for Cisco DMS Appliances and Endpoints](#), page 3-4
- [Optional Module Licenses](#), page 3-5

Base Licenses for Cisco DMS Appliances and Endpoints

There is a base license included at no additional cost with the purchase of any Cisco DMS appliance or endpoint. These licenses are unit-specific and perpetual. There are no non-support fees and you are not obligated to purchase other licenses.

DMM appliance

With a DMM appliance base license, you can:

- Install feature licenses for components of Cisco DMS¹.
- Gain access to features after you license them.
- Create user accounts and user groups for components of Cisco DMS¹.
- Configure a user authentication framework for use throughout Cisco DMS¹.
- Configure event notifications and alarms for components of Cisco DMS¹.
- Check processes remotely.
- Monitor and restart servers remotely¹.

Show and Share appliance

With a *Show and Share* appliance base license (**and a DMM appliance**), you can set up a *Show and Share* site.

- Authors: **5**
- Viewers: *Unlimited*
- Category managers: *Unlimited*
- Featured video managers: *Unlimited*
- Video reviewers/publishers: *Unlimited*

DMP endpoint

With a DMP endpoint base license, you can set up the DMP itself² from its embedded device manager, DMPDM.

1. Including *Show and Share*, if you have and use it.
2. Managed in isolation, without involving DMM or any other DMPs.

Optional Module Licenses


Note

To obtain and activate any license for any component of Cisco DMS, you must have a DMM appliance.

Module or Pack		Part Number ¹	Description
Show and Share Author License Packs	10 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-10 • <i>DV-AUTHOR-FL-10=</i> 	Author licenses are cumulative. For example, the base license for <i>Show and Share</i> includes 5 authors — so, if you purchase and install a 10-author pack, your <i>Show and Share</i> will support as many as 15 authors.
	50 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-50 • <i>DV-AUTHOR-FL-50=</i> 	
	500 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-500 • <i>DV-AUTHOR-FL-500=</i> 	
	1,000 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-1000 • <i>DV-AUTHOR-FL-1000=</i> 	
	10,000 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-10000 • <i>DV-AUTHOR-FL-10000=</i> 	
	25,000 authors	<ul style="list-style-type: none"> • DV-AUTHOR-FL-25000 • <i>DV-AUTHOR-FL-25000=</i> 	
Show and Share Features	Live Event Module	<ul style="list-style-type: none"> • DMM-LEM52-K9 • <i>DMM-LEM52-K9=</i> 	Activates <i>Show and Share</i> abilities to host and produce managed, live webcasts—including audience polling, moderated Q&A, audio, video, and synchronized slides.
DMS-Admin Features	SNMP Notifications	<ul style="list-style-type: none"> • DMM-SNMP52-K9 • <i>DMM-SNMP52-K9=</i> 	Activates support for SNMP interaction with network monitoring applications. Also activates support for event notifications and alerts.
DMM Features	Digital Signs Module	<ul style="list-style-type: none"> • DMM-SIGNSM52-K9 • <i>DMM-SIGNSM52-K9=</i> 	Activates DMM baseline features to centrally manage and operate a digital signage network with Cisco DMPs.
	Cast Module	<ul style="list-style-type: none"> • DMM-CAST52-K9 • <i>DMM-CAST52-K9=</i> 	Activates DMM abilities to deliver on-demand video and live broadcast TV channels over IP networks to DMPs and their attached presentation systems.
Centralized DMP Management	1 DMP	<ul style="list-style-type: none"> • DMP-FL-1 • <i>DMP-FL-1=</i> 	To centrally manage DMPs from DMM, you must combine a Digital Signs Module license with at least one DMP feature license.
	10 DMPs	<ul style="list-style-type: none"> • DMP-FL-10 • <i>DMP-FL-10=</i> 	DMP feature licenses are cumulative. If you are already licensed to manage 500 DMPs before you install an additional 50-unit license, your DMM installation will support managing as many as 550 DMPs.
	50 DMPs	<ul style="list-style-type: none"> • DMP-FL-50 • <i>DMP-FL-50=</i> 	
	500 DMPs	<ul style="list-style-type: none"> • DMP-FL-500 • <i>DMP-FL-500=</i> 	
	1,000 DMPs	<ul style="list-style-type: none"> • DMP-FL-1000 • <i>DMP-FL-1000=</i> 	

1. During your initial order, use part numbers that omit the = character. Only later, when you want to extend what you ordered initially, should you use part numbers that end with =.

