



# CHAPTER 70

## Deleting Trust Element Configuration

---

Use this procedure to delete Trust Element from the Cisco Unified Communications Manager database.

### Before You Begin

1. Create a text file that lists the Element Name for the Trust Element that you want to delete:
2. Upload the custom files to the Cisco Unified Communications Manager server first node. See [“Uploading a File” section on page 2-3.](#)

To delete Trust Element that are listed in a custom file, use the following procedure.



---

**Note** Do not use the insert transaction files that are created with bat.xlt for the delete transaction. Instead, you must create a custom file with details of the Trust Element records that need to be deleted. Use only this file for the delete transaction. In this custom delete file, you do not need a header, and you can enter values for name, description, and so on.

---

### Procedure

---

- Step 1** Choose **Bulk Administration > Intercompany Media Services > Trust Element > Delete Trust Element.**

The Delete Trust Element Configuration window displays.

- Step 2** From the Delete Trust Element where Name in custom file drop-down list box, choose the filename of the custom file for this delete.

- Step 3** Click **Find.**

- Step 4** The Trust Element matching your search criteria displays.

- Step 5** Click **Submit** to create a job to delete the Trust Element.

Use the Job Scheduler option in the Bulk Administration main menu to schedule and/or activate this job. For more information on jobs, see the [Chapter 82, “Scheduling Jobs.”](#)

For information on log files, see [“BAT Log Files” section on page 83-3.](#)

---

### Additional Topics

See the [“Related Topics” section on page 70-2.](#)

## Related Topics

- [Inserting Trust Element Configuration, page 69-1](#)
- [Uploading a File, page 2-3](#)
- [Scheduling Jobs, page 82-1](#)
- [BAT Log Files, page 83-3](#)