



Release Notes for Cisco Unified SIP Proxy Release 1.1.3

First Published: May 21, 2009
Last Revised: December 12, 2011
OL-19828-01

This document describes the new features, system requirements, and caveats for Cisco Unified SIP Proxy 1.1.3. Use this document in conjunction with the documents listed in the [“Related Documentation”](#) section on page 6.

Contents

- [Introduction, page 1](#)
- [System Requirements, page 2](#)
- [Installation Notes, page 3](#)
- [Limitations and Restrictions, page 3](#)
- [Related Documentation, page 6](#)
- [Obtaining Documentation and Submitting a Service Request, page 6](#)

Introduction

Cisco Unified SIP Proxy is designed to help connect and manage SIP networks. The Cisco Unified SIP Proxy module is designed to be an integrated solution in Cisco 3800 Series Integrated Services Routers (Cisco ISRs). The module provides multiple features including SIP trunk aggregation, name resolution, routing, scalability, and high availability.



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

© 2009 Cisco Systems, Inc. All rights reserved.

System Requirements

- [Hardware Supported, page 2](#)
- [Software Compatibility, page 2](#)
- [Determining the Software Version, page 2](#)

Hardware Supported

The Cisco Unified SIP Proxy module runs on the NME-522 module. The part number of the Cisco Unified SIP Proxy module is NME-CUSP-522-K9. The module has 2 GB of RAM and 160 GB HDD. This module installs only on the Cisco 3825 or 3845 ISRs.

Software Compatibility

The Cisco Unified SIP Proxy module requires Cisco IOS Release 12.4(22)T or a later release on the Cisco ISR with k9 feature set.

Determining the Software Version

Procedure

- Step 1** Open a Telnet session.
- Step 2** Telnet to the router by entering **telnet ip-address**.
- Step 3** Enter the user ID and password of the router.
- Step 4** Enter the following command to enter the command environment:
- ```
enable
<router password>
service-module service-engine slot/port session
```
- Step 5** Enter the following command to display the Cisco Unified SIP Proxy software version:
- ```
show software versions
```
- Step 6** Enter the following command to enter Cisco Unified SIP Proxy execution mode:
- ```
culp
```
- Step 7** Enter the following command to display the Cisco Unified SIP Proxy software license:
- ```
show license
```
-

For information about IOS open source licensing, see the Notices section in the About Cisco IOS Release Notes at: http://www.cisco.com/en/US/docs/ios/12_4/12_4x/12_4xy15/ReleaseNote.html#wp398419

New Features and Enhancements

This section contains new features or enhancements added in this release.

- Cisco Unified SIP Proxy uses Netconf to perform IOS configuration validation at startup. Netconf over SSH is the only supported mechanism. Support for Netconf over BEEP has been removed. See configuration examples and tech notes for details at http://cisco.com/en/US/docs/voice_ip_comm/cusp/re11_1_3/configuration/guide/cuspgd113.html
- New configuration commands have been added to configure IP routes to facilitate support for multiple network interfaces. See the command reference for details at http://cisco.com/en/US/docs/voice_ip_comm/cusp/re11_1_3/command/reference/cuspcmdref_book.html

Installation Notes

The software is already loaded at the factory, and you can install it using the command:

```
software install clean url ftp://x.x.x/cusp-k9.nme.x.x.pkg
```

There are three software files, all of which you should save to the FTP directory. You need to load the .pkg file, the other files are downloaded automatically. See [Table 1](#).

Table 1 **Software Files**

| Name | Size |
|--------------------------------|--------|
| cusp-k9.nme.x.x.pkg | 100 KB |
| cusp-full-k9.nme.x.x.prt1 | 87 MB |
| cusp-installer-k9.nme.x.x.prt1 | 128 KB |

Limitations and Restrictions

Changing Licenses Requires Backing Up Your Configuration

Whenever you change the license for Cisco Unified SIP Proxy Release 1.1.3, the system restores the software to its factory default settings, thereby deleting your system's configuration data.

Therefore, if you need to change the license, you must first back up your configuration. After you change the license, you must restore the configuration. Otherwise, you will lose all of your system's configuration data.



Caution

You must back up your system's configuration data before changing the license or you will lose all of your system's configuration data.

Cryptographic Features

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer, and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute, or use encryption. Importers, exporters, distributors,

and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at: <http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>.

If you require further assistance, send an email to export@cisco.com.

Voice and Router Coresidency Restrictions

Voice and router functions may co-reside in the same router with Cisco Unified SIP Proxy with two exceptions:

- Cisco Unified SIP Proxy may not co-reside in the same router when Cisco Unified Communications Manager Express (Cisco Unified CME) or Cisco Unified Survivable Remote Site Telephony (Cisco Unified SRST) are configured for SCCP phones.
- Cisco Unified SIP Proxy may not co-reside in the same router with time division multiplex (TDM) gateways or configuration of H.323 dial peers (including Cisco Unified Border Element).

Cisco Unified CME, Cisco Unified SRST, and Cisco Unified Border Element configured for SIP may co-reside in the same router.

Caveats

- [Open Caveats, page 4](#)
- [Resolved Caveats, page 6](#)

These caveats describe unexpected behavior in Cisco Unified SIP Proxy software releases. Severity 1 caveats are the most serious caveats. Severity 2 caveats are less serious. Severity 3 caveats are moderate caveats, and only selected severity 3 caveats are included in the caveats document.



Note

If you have an account on Cisco.com, you can use Bug Toolkit to find caveats of any severity. The Bug Toolkit is at: http://www.cisco.com/cgi-bin/Support/Bugtool/launch_bugtool.pl

Open Caveats

| CDETS | Description |
|------------|--|
| CSCsw97690 | <p>Symptom There are two symptoms of this bug. The first is that pinging of all elements (TCP/TLS/UDP) will be delayed. Therefore, their status may not be accurately reflected by the show server-group status command. The second is that committing a configuration can cause the CLI to hang for several minutes.</p> <p>Conditions Invalid or down TCP elements are listed in server-group status.</p> <p>Workaround Only use UDP or TLS elements in server-group configurations.</p> |

| CDETS | Description |
|------------|--|
| CSCsx10996 | <p>Symptom Cisco Unified SIP Proxy DNS SRV based call routing does not work after rebooting Cisco Unified SIP Proxy.</p> <p>Workaround There are two workarounds. The first is to toggle off, then on the sip dns-srv command. The second is to configure route tables with server-group based routing.</p> |
| CSCsx18654 | <p>Symptom When multiple IPs are configured on Cisco Unified SIP Proxy, SIP messages source from wrong source ip.</p> <p>Conditions Cisco Unified SIP Proxy is configured with multiple IP interfaces.</p> |
| CSCsx38761 | <p>Symptom When trying to make a call to the SRV defined device, Cisco Unified SIP Proxy cannot establish a connection and issues a 502 message to the calling device.</p> <p>Conditions This problem only occurs if the network is of type NAT.</p> <p>Workaround Use a different network type, standard, for example.</p> |
| CSCsx48124 | <p>Symptom The maddr parameter in the request-uri is not handled properly.</p> <p>Conditions Cisco Unified SIP Proxy fails to remove the maddr parameter if it is pointing to Cisco Unified SIP Proxy on incoming requests. Cisco Unified SIP Proxy fails to forward the message based on the maddr address on outgoing requests.</p> |
| CSCsx62364 | <p>Symptom Invites from the Avaya PBX are rejected with a 404 “no matching algorithm found” message.</p> <p>Conditions An Avaya PBX is used.</p> <p>Workaround Use a different model PBX.</p> |
| CSCsx65522 | <p>Symptom Normalization on user portion of request-uri fails, NullPointerException is thrown during normalization operation. (This can be seen by looking at the trace.log file.)</p> <p>Conditions The user portion of the request-uri is empty.</p> <p>Workaround Normalize the entire request-uri to add/update the user portion.</p> |

| CDETS | Description |
|------------|--|
| CSCsw43287 | <p>Symptom When using the show configuration active page command, if you issue a q to exit the configuration from displaying any more pages, you are removed from the Cisco Unified SIP Proxy mode and returned to the module level exec mode of the CLI.</p> <p>Conditions Only occurs for show commands within Cisco Unified SIP Proxy mode.</p> <p>Workaround Avoid using q or ctrl-c. If you do, type cusp to get back into Cisco Unified SIP Proxy mode. To get into configure mode, type configure.</p> |
| CSCsy80883 | <p>Symptom In some scenarios, when Cisco Unified SIP Proxy fails to successfully route the message based on the first SRV record (destination is unavailable), it is not trying the next record in the list even when one exists.</p> <p>Conditions Only when routing is configured to use SRV and failover is done based on SRV records.</p> <p>Workaround Use server groups instead of SRV for failover and load balancing.</p> |

Resolved Caveats

| CDETS | Description |
|------------|--|
| CSCsx65091 | <p>Symptom CLI access to Cisco Unified SIP Proxy goes to unresponsive mode when executing show trace log command.</p> |
| CSCsu48446 | <p>Symptom When attempting to boot after doing a clean install, a message displays: corrupted bzImage detected The boot then stops.</p> |

Related Documentation

For Cisco Unified SIP Proxy documentation and configuration white papers, see http://cisco.com/en/US/products/ps10140/tsd_products_support_model_home.html

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

CCDE, CCENT, Cisco Eos, Cisco HealthPresence, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0812R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2011, Cisco Systems, Inc. All rights reserved.

