



## Configuring Route Groups

---

- [Viewing a List of Route Groups and Corresponding Elements](#)
- [Adding a Route Group](#)
- [Viewing and Deleting Route Group Elements](#)
- [Adding and Editing Route Group Elements](#)
- [Editing a Route Group](#)

## Viewing a List of Route Groups and Corresponding Elements

### Procedure

---

- Step 1** Choose **Configure > Route Groups**.
- The system displays the Route Groups page, which contains the fields described in [Table 9](#).
- Step 2** There can be multiple elements in a route group. To see the elements associated with this route group, click [click here](#).
- The system displays the Route Group ‘<name of route group>’ page, containing the fields described in [Table 10](#).
- Step 3** To delete a route group, do the following:
- a. Check the check box next to the name of the route group to delete.
  - b. Click **Remove**.
  - c. In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
- Step 4** To revert any changes you have made back to the state they were in at the time of the last commit, do the following:
- a. Check the check box next to the name of the route group that has the changes to revert back to.
  - b. Click **Revert**.
  - c. In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
-

### About Route Groups

A route group allows you to designate the order in which gateways and trunks are selected. It allows you to prioritize a list of gateways and ports for outgoing trunk selection.

For example, if you use two long-distance carriers, you could add a route group so that long-distance calls to the less expensive carrier are given priority. Calls only route to the more expensive carrier if the first trunk is unavailable.

You can add, update, or delete route groups from the Route Group page. You can also add, update, or delete elements.

### Route Group Fields

Table 9 lists the fields on the Route Groups page.

**Table 9**      **Route Group Parameters**

Parameter	Description
State	Can be one of the following: <ul style="list-style-type: none"> <li>• New—New record. Will be added to the active configuration when it is committed.</li> <li>• Modified—Modified record. Will become the active configuration when it is committed.</li> <li>• Deleted—Deleted record. Will be removed from the active configuration when it is committed.</li> <li>• Active—Active record and active configuration.</li> </ul>
Name	Name of this route group.
Elements	Elements that belong to this route group.
Time Of Day Routing	Specifies if this route group allows for time policy-based routing. Can be either true or false. The default value is false.
Weight Based Routing	Specifies if this route group allows for weight-based routing. Can be either true or false. The default value is false.

### Element Fields

Table 10 lists the fields on the Route Group '<name of route group>' page when the Elements tab is highlighted.

**Table 10**      **Route Group Element Parameters**

Parameter	Description
State	Can be one of the following: <ul style="list-style-type: none"> <li>• New—New record. Will be added to the active configuration when it is committed.</li> <li>• Modified—Modified record. Will become the active configuration when it is committed.</li> <li>• Deleted—Deleted record. Will be removed from the active configuration when it is committed.</li> <li>• Active—Active record and active configuration.</li> </ul>
<b>Target Destination</b>	
Host/Server Group	Specifies the interface host name or IP address of the route group element.
Port	Specifies the port used by the route group element. Valid values are from 1024 to 65535. The default is 5060.
Transport	Specifies the transport type of the route group element. Can be one of the following: <ul style="list-style-type: none"> <li>• none (default)</li> <li>• UDP</li> <li>• TCP</li> <li>• TLS</li> </ul>
<b>Next Hop</b>	
SIP URI	The URI of the next hop.
<b>Options</b>	
Network	The name of the network to which this route group is associated.
Q-Value	(Optional) Specifies a real number that specifies the priority of the route group element with respect to others in the route group. Valid values are from 0.0 to 1.0. The default value is 1.0.
Weight	(Optional) Specifies the percentage assigned to the IP element in the route group if implementing weight-based routing. The valid range is from 0 to 100. The default weight is 0.
Time Policy	Specifies the time policy if time-based routing is being used.
Failover Response Codes	The response code(s) that indicates the next-hop server is unable to process the request. The valid values are numbers between 400 and 599.  To add multiple failover response codes, separate the individual codes by a comma and indicate ranges with a dash. Commas and dashes must be followed by a space.

**Related Topics**

- [Managing the System Configuration](#)
- Back to the [Configuring Route Groups](#) menu page

## Adding a Route Group

**Procedure**

---

- Step 1** Choose **Configure > Route Groups**.  
The system displays the Route Groups page.
- Step 2** Click **Add**.  
The system displays the Route Group (New) page.
- Step 3** Enter a name for this route group. If you will enable time-of-day routing or weight-based routing, check those check boxes.
- Step 4** Click **Add**.  
The system displays the Route Groups page, with the new route group listed in the table.
- Step 5** In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
- 

**Related Topics**

- [Managing the System Configuration](#)
- Back to the [Configuring Route Groups](#) menu page

## Viewing and Deleting Route Group Elements

**Procedure**

---

- Step 1** Choose **Configure > Route Groups**.  
The system displays the Route Groups page.
- Step 2** On the line of the route group that has the element to delete, under the title Elements, click **click here**.  
The system displays the Route Group '<name of route group>' page with the Elements tab highlighted.
- Step 3** To delete a route group element, do the following:
- a. Check the check box next to the name of the element.
  - b. Click **Remove**.
  - c. In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.

- Step 4** To revert any changes you have made back to the state they were in at the time of the last commit, do the following:
- Check the check box next to the name of the route group element that has the changes to revert back to.
  - Click **Revert**.
  - In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
- 

#### Related Topics

- [Managing the System Configuration](#)
- Back to the [Configuring Route Groups](#) menu page

## Adding and Editing Route Group Elements

### Procedure

---

- Step 1** Choose **Configure > Route Groups**.
- The system displays the Route Groups page.
- Step 2** Under Elements, click **click here** on the line for the route group for which you want to add an element. The system displays the Route Group '<name of route group>' page with the Elements tab highlighted.
- Step 3** To add an element, do the following:
- Click **Add**. The system displays the Route Group '<name of route group>' Element (New) page.
  - Choose whether this element will use a target destination or next hop.
  - Enter information about the element as described in [Table 10](#).
  - Click **Add**.
- Step 4** To edit an element, do the following:
- Click the underlined Host/Server Group of the element. The system displays the Route Group '<name of route group>' Element page.
  - Make changes to the information about the element as described in [Table 10](#).
  - Click **Update**.
- Step 5** In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
- 

#### Related Topics

- [Managing the System Configuration](#)
- Back to the [Configuring Route Groups](#) menu page

# Editing a Route Group

## Procedure

---

- Step 1** Choose **Configure > Route Groups**.
- The system displays the Route Groups page.
- Step 2** Click the underlined name of the route group to edit.
- The system displays the Route Group ‘<name of route group>’ page with the Group Settings tab highlighted.
- Step 3** You can change if this route group will enable time-of-day routing or weight-based routing.
- Step 4** Click **Update**.
- Step 5** To edit the elements of the route group, follow the procedure in [Adding and Editing Route Group Elements](#).
- Step 6** In the Cisco Unified SIP Proxy header, click **Commit Candidate Configuration** to commit this change.
- 

## Related Topics

- [Managing the System Configuration](#)
- Back to the [Configuring Route Groups](#) menu page