



Configuring Groups

- [Viewing a List of Groups](#)
- [Adding a New User Group](#)
- [Subscribing Members or Owners to a Group](#)
- [Unsubscribing Members and Owners from a Group](#)
- [Displaying or Modifying Group Parameters](#)
- [Viewing Owners and Members of a Group](#)
- [Modifying Group Ownership and Membership in Other Groups](#)
- [Deleting a Group](#)
- [Finding a Group](#)
- [About Capabilities](#)

Viewing a List of Groups

Procedure

Step 1 Choose **Configure > Groups**.

The system displays the Configure Groups page, containing the following fields:

- Group ID
- Display Name
- Primary Extension
- Privileges

Step 2 To see a different number of groups on each page, choose another number from the drop-down box on the top right and click **Go**. You can choose to see 10, 25, 50, 100, or all groups.

Step 3 To move to another page, use the left and right arrow buttons on the bottom right, or enter another page number and press **Enter**.

Step 4 To sort groups, click any of the headers.

Group Fields

[Table 27](#) lists the fields on the page.

Table 27 **Group Parameters**

Parameter	Description
Group ID	Alphanumeric user identifier.
Full name	Long name of the group as it should appear on telephone displays.
Description	Description of the group. The word “group” is automatically added to the Group ID entry.
Primary Extension	Primary extension of the group’s general-delivery mailbox.
Primary E.164 Number	Associates a full telephone number and area code with this group.
Fax Number	Associates a fax number with this group.

Related Topics

Back to the [Configuring Groups](#) menu page

Adding a New User Group

Configuring one or more groups is optional. Many businesses find that having a mailbox for a group, called a general-delivery mailbox, is very convenient. Members of a group can retrieve voice messages left in the general-delivery mailbox. For example, a Customer Service mailbox could be configured to receive messages from customers, and anyone assigned to a Customer Service group could retrieve the messages. Members of the general-delivery mailbox can be individual users or other groups. Individual users also have their individual mailboxes, and groups that are members of another group have their own mailboxes.

Before You Begin

Determine the primary extension to be assigned to the group. Ensure that this extension is active.

Procedure

-
- Step 1** Choose **Configure > Groups**.
- The system displays the Configure Groups page.
- Step 2** Click **Add**.
- The system displays the Add a New Group page.
- Step 3** Enter information into the fields shown below:
- Group ID
 - Full name
 - Description—The word “group” is automatically added to the Group ID entry. You can add more text to this description.
 - Primary Extension for the group’s general-delivery mailbox
 - Primary E.164 Number

- Fax Number

Step 4 Check the check box next to the capabilities for this group to have. See [About Capabilities](#).

Step 5 Click **Add**.

The system displays the Configure Groups page, with the new group in the table.

Related Topics

Back to the [Configuring Groups](#) menu page

Subscribing Members or Owners to a Group

When you add members to a group, each member has access to the voice messages that are stored in that group's mailbox.

A group owner has control of the group's mailbox but cannot access the group's messages. To access messages, the group owner must also be a member of the group.

Procedure

Step 1 Choose **Configure > Groups**.

The system displays the Configure Groups page.

Step 2 Click the underlined name of the group to which you are adding new members or owners.

The system displays the Group Profile page for that group.

Step 3 Click the **Owners/Members** tab.

The system displays all owners and members of the group.

Step 4 To add a new member, click **Subscribe Member**. To add a new owner, click **Subscribe Owner**.

The system displays the Find page.

Step 5 Under type, select either users or groups. Enter the user ID or group ID, name or description, or the extension of the person or group to add to this group.

Step 6 Click **Find**.

The system displays all users or groups that meet the search criteria.

Step 7 Do one of the following:

- Add one or more member or owner to the group by checking the check box next to each selected member's or owner's name and clicking **Select Rows**. The system displays the Group page with the new member or owner added.
- Look for other people to add by clicking **Back to Find** without checking a check box next to any name. The system displays the Find page. Return to [Step 5](#) and continue.

Step 8 To add more members or owners to the group, repeat [Step 4](#) through [Step 7](#).

Related Topics

Back to the [Configuring Groups](#) menu page

Unsubscribing Members and Owners from a Group

Restriction

Only group owners can delete members and owners.

Procedure

- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Click the underlined name of the group to manage.
The system displays the Group Profile page for this group.
- Step 3** Click the **Owners/Members** tab.
The system displays all owners and members of the group.
- Step 4** Check the check box next to the name of each member or owner who you want to unsubscribe from this group.
- Step 5** Click **Unsubscribe**.
The system displays the Group Members page with the members or owners removed.
-

Related Topics

Back to the [Configuring Groups](#) menu page

Displaying or Modifying Group Parameters

Procedure

- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Click the underlined name of the group to view or modify.
The system displays the Group Profile page for this group, with the following fields:
- Group ID
 - Full name
 - Description
 - Primary Extension
 - Primary E.164 number
 - Fax Number
 - Capabilities. See [About Capabilities](#) for information about capabilities.
- Step 3** To edit these fields, enter the new information and click **Apply**.
-

Related Topics

Back to the [Configuring Groups](#) menu page

Viewing Owners and Members of a Group

Procedure

-
- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Click the underlined name of the group to view.
The system displays the Group Profile page for that group.
- Step 3** Click the **Owners/Members** tab to see the users who are owners or members of this group.
The system displays the Owners/Members page.
- Step 4** Click any column heading to sort by that subject.
-

Related Topics

Back to the [Configuring Groups](#) menu page

Modifying Group Ownership and Membership in Other Groups

A group has its own set of members, but a group can also be assigned as a member or an owner of one or more other groups. If a group is assigned as an owner of another group, any individual member of the owner group has privileges as an owner of the owned group. For example, if the Administrator group is added as an owner of the Technical Support group, any individual member of the Administrator group can add, modify, or delete members of the Technical Support group. Additionally, individual users that do not belong to another group can be added as owners of the Technical Support group.

Procedure

-
- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Click the name of the group whose membership you want to modify.
The system displays the Group Profile page for that group.
- Step 3** Click the **Owner/Member of Groups** tab.
The system displays the Owner/Member of Groups page.
- Step 4** To see a different number of groups on each page, on the top right, choose another number from the drop-down box and click **Go**. You can choose to see 10, 25, 50, 100, or 500 groups.
- Step 5** To move to another page, use the left and right arrow buttons on the bottom right, or enter another page number and press **Enter**.
- Step 6** To sort groups, click any of the headers.

- Step 7** To designate your group as an owner of another group, click **Subscribe as owner**. To subscribe your group as a member of another group, click **Subscribe as member**.
The system displays the Find page.
- Step 8** Enter the group ID, description, or extension of the groups to find.
- Step 9** Click **Find**.
The system displays all the groups that meet the search criteria.
- Step 10** To select one or more groups, check the check box next to each group's name and click **Select Rows**.
The system adds the new groups to the list of groups on the Owner/Member of Groups page.
-

Related Topics

Back to the [Configuring Groups](#) menu page

Deleting a Group

Deleting a group also deletes the group's mailbox but it does not delete the members of the group.

Procedure

-
- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Check the check box next to the name of the group to delete.
- Step 3** Click **Delete**.
- Step 4** At the prompt, click **OK** to delete the group.
-

Related Topics

Back to the [Configuring Groups](#) menu page

Finding a Group

Use this procedure to search for a group.

Procedure

-
- Step 1** Choose **Configure > Groups**.
The system displays the Configure Groups page.
- Step 2** Click **Find**. The following fields appear in the Find Groups window:
- Group ID
 - Description

- Extension—Extension for the group's general-delivery mailbox.

Step 3 Enter the search criteria in one or more fields and click **Find**.

The system displays the Configure Groups page with the results of your search.

Related Topics

Back to the [Configuring Groups](#) menu page

About Capabilities

You can assign capabilities to groups.

Cisco Unified SIP Proxy has three capabilities:

- pfsread—Allows users to read from the public file system (PFS).
- pfsreadwrite—Allows users to read from and write to the PFS.
- superuser—Gives administrator privileges to users in this group.

Related Topics

Back to the [Configuring Groups](#) menu page

