



Cisco Unified Contact Center Enterprise Developer Reference, Release 15.0(1)

First Published: 2025-11-21

Last Modified: 2025-12-10

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 1994–2026 Cisco Systems, Inc. All rights reserved.



CHAPTER 1

Working with Unified CCE APIs

- [Change History](#), on page 1
- [API Operations](#), on page 2
- [Cross-Origin Resources Sharing for CCE](#), on page 3
- [Access](#), on page 5
- [Usage and Behavior](#), on page 7
- [Error Responses](#), on page 8
- [Pagination](#), on page 9
- [Shared Parameters](#), on page 10
- [Permissions](#), on page 10
- [Synchronous vs. Asynchronous Writes](#), on page 11
- [Search](#), on page 12
- [Sort](#), on page 13
- [Contact Center AI Features](#), on page 13

Change History

This table lists changes made to this guide. Most recent changes appear at the top.

New APIs

Updated APIs

See	Updated	Date
Agent API	Add ciPerson details	October 2025
Agent API	Added a note related to API access for supervisors and administrators.	February 2025
Agent Team API		

API Operations

There are five API operations, and they are invoked by HTTP methods.

Responses are provided using HTTP headers and HTTP body containing XML. For information on XML, see [XML, on page 8](#).

create

The create operation uses the HTTP POST method to make one new item and return the URL of that item in the HTTP location header. That URL can then be used to perform the get, update, and delete operations. An XML body containing the parameters and values for the new item must be specified.

delete

The delete operation uses the HTTP DELETE method to delete one item. The item may be marked for deletion or permanently deleted depending on the item type.

To delete more than one item at a time, refer to the Operation API.

You cannot delete **BuiltIn** items (those automatically created by the system, such as the **BuiltIn** bucket interval), items referenced in scripts, or items referenced by other items.

get

The get operation uses the HTTP GET method to retrieve one item. For example, to return one bucket interval record, perform the get operation using the URL:

```
https://<server>/unifiedconfig/config/bucketinterval/<id> .
```



Note In all Unified CCE API URLs or examples, replace `<server>` with the Fully Qualified Domain Name (FQDN) of your Admin Workstation.

list

The list operation uses the HTTP GET method to retrieve a list of items. For example, to retrieve a list of bucket intervals, perform the list operation using the URL:

```
https://<server>/unifiedconfig/config/bucketinterval. See also Permissions, on page 10, Pagination, on page 9, Search, on page 12, and Sort, on page 13.
```

Query parameters:

- **Summary list:** Some APIs have parameters that include a large amount of data when returned, such as collections of references. Use this query parameter to reduce the number of parameters returned for each item in the list. For example, in the Skill Group API, if skill groups contain a large number of agents, a large amount of data may be returned. Use this query option to return the basic skill group data along with the number of agents having the skill. Append the query parameter `summary=true` to the URL for the API; for example,

```
https://<server>/unifiedconfig/config/skillgroup?summary=true.
```

update

The update operation uses the HTTP PUT method to modify one item. An XML body containing the parameters and values to update must be specified. For example, to update the name of a bucket interval, perform the update operation on the URL

`https://<server>/unifiedconfig/config/bucketinterval/(id)` with the following body:

```
<bucketInterval>
  <name>newName</name>
  <changeStamp>0</changeStamp>
</bucketInterval>
```

Cross-Origin Resources Sharing for CCE

Cross-Origin Resource Sharing (CORS) for Cisco Contact Center Enterprise (CCE) allows web applications running on different origins (domains, protocols, or ports) to securely access CCE APIs.

CORS enables the server to dynamically return appropriate CORS headers based on defined configurations, ensuring secure and controlled browser-based access to the APIs.

Enabling CORS for CCE

To enable CORS configuration from Windows Registry, do the following:

1. Launch the **Registry Editor** on the required Administrator and Data Server(s).

2. Navigate to the following path:

```
Computer\HKEY_LOCAL_MACHINE\SOFTWARE\Cisco Systems, Inc.\ICM\WEB\WebConfig
```

3. Right-click the **WebConfig** and select **New > Key** to create **CORS** key.

4. Create the **enabled** string value:

- a. Right-click the CORS folder and select **New > String Value** to create new string value and provide string value as **enabled**.
- b. Right-click the **enabled** string value.
The **Edit String** dialog box appears.
- c. In the **Value data** field, enter **true**.
- d. Click **OK**.

5. Create the **Access-Control-Allow-Origin** string value:

- a. Right-click the CORS folder and select **New > String Value** to create new string value and provide string value as **Access-Control-Allow-Origin**.
- b. Right-click the **Access-Control-Allow-Origin** string value.
The **Edit String** dialog box appears.
- c. In the **Value data** field, enter a valid origin URL.
- d. Click **OK**.



- Note**
- The origin value must be valid URL. To specify multiple origins, separate each entry with a comma.
 - CORS configuration updates do not require a service restart, as changes take effect within one minute.

CORS Header Configuration - Required String Values

String Value	Description	Value data
enabled	Enables CORS when set to true	True
Access-Control-Allow-Origin	<p>Specifies the allowed origin(s).</p> <p>Maximum string length of the Value data field must be less than 4000 characters.</p> <p>Ensure wildcard (*) is not present the Value data field in the Edit String dialog box.</p> <p>The Value data field cannot be empty.</p>	<p>https://<domain:port></p> <p>For example, https://domain.com:8000,https://domain.com:8001</p>

CORS Header Configuration - Optional String Values

The following table as the default values configured for the CORS. You can create the required string value to edit the CORS configuration by providing custom values as per requirement.

String Value	Description	Default Value
Access-Control-Allow-Methods	Specifies the HTTP methods permitted for cross-origin requests	GET, POST, PUT, DELETE, OPTIONS
Access-Control-Max-Age	Defines the duration (in seconds) that preflight request results are cached	3600 (seconds)
Access-Control-Allow-Credentials	Indicates whether credentials are included in cross-origin requests	true
Access-Control-Request-Headers	Specifies the headers allowed in cross-origin requests	CONTENT-TYPE, AUTHORIZATION

Disabling CORS

CORS is disabled by default. If the CORS registry key does not exist, CORS remains inactive. The following conditions also result in CORS being disabled:

String Value	Value Data
enabled	false Note: Set as 'false' to void all other settings.

Access

Administrator Access

Administrator access to Unified CCE Administration APIs and items is defined by the role for which the administrator is responsible.

The following API is not available for administrators:

- Agent Teams API

The following APIs allow update with restrictions:

- Agent Call API
 - When updating an agent, administrators can only change the following parameters:
 - skillGroups
 - defaultSkillGroup
 - skillGroupsAdded
 - skillGroupsRemoved
 - agentAttributes
 - agentAttributesAdded
 - agentAttributesRemoved
 - password
- [Skill Group API, on page 141](#)
 - When updating a skill group, administrators can only change the following parameters:
 - agents
 - agentsAdded
 - agentsRemoved

Supervisor Access

The following APIs are read only:

- Agent Teams API

- Supervisors can only see teams that are on their peripheral.

- [Precision Queue API, on page 121](#)

The following APIs allow update with restrictions:

- [Attribute API, on page 35](#)

- When updating an attribute, supervisors can only modify the collection of agentAttributes by adding, removing, or changing the value of agents who are on their teams.

- Agent Call API

:

- Supervisors can only see and update agents who are on their teams.
- When updating an agent, supervisors can only change the following parameters:

- skillGroups
- defaultSkillGroup
- skillGroupsAdded
- skillGroupsRemoved
- agentAttributes
- agentAttributesAdded
- agentAttributesRemoved
- password

- The Operation API can also be used to perform updates on agents.

- [Skill Group API, on page 141](#):

- Supervisors can only see and update skill groups that are on their peripheral.
- When updating a skill group, supervisors can only modify the collections of agents by adding or removing agents who are on their teams.

Agent Access

Agents have no access to the Unified CCE Administration APIs.

Authentication

To authenticate:

- Administrators must provide a fully qualified user name (for example, user@cisco.com) and password.
- Supervisors must provide their agent username and password.

Usage and Behavior

Duplicate Parameters

If a parameter is duplicated, the final value that is specified will be used by the API.

Read-Only Fields

Read-only parameters are ignored on create and update operations.

References

References are a type of parameter that provide a way to connect one item to another item, defining the relationship between them.

For example, to define which team an agent belongs to, the agent contains a reference to a team. When performing list or get operations, the reference contains the refURL of the item and the name. For example:

```
<agent>
  <team>
    <refURL>/unifiedconfig/team/5000</refURL>
    <name>NameOfTeam</name>
  </team>
  ...
</agent>
```

For items that do not have a name parameter, other parameters such as firstName and lastName are included.

```
<agent>
  <refURL>/unifiedconfig/config/agent/5000</refURL>
  <firstName>Jane</firstName>
  <lastName>Doe</lastName>
  <userName>username</userName>
  <agentId>8007</agentId>
  <canRemove>true</canRemove>
</agent>
```

When doing create or update, only the refURL parameter is required. Additional parameters are ignored. For example:

```
<agent>
  <team>
    <refURL>/unifiedconfig/team/5000</refURL>
  </team>
  ...
</agent>
```

Items can also contain a collection of references. For example, if an agent belongs to multiple skill groups, the skillGroups parameter contains a reference to each associated skill group:

```
<agent>
  <skillGroups>
    <skillGroup>
      <refURL>/unifiedconfig/config/skillgroup/5001</refURL>
      <name>FirstSkill</name>
    </skillGroup>
    <skillGroup>
      <refURL>/unifiedconfig/config/skillgroup/5005</refURL>
      <name>AnotherSkill</name>
    </skillGroup>
  </skillGroups>
</agent>
```

```

    </skillGroups>
    ...
</agent>

```

XML

XML is case sensitive. When XML data is sent to the server, the tag names must match. <Name> and <name> are two different XML elements.

Error Responses

Operations that fail return an HTTP status code ([HTTP 1.1 Status Codes](#)) indicating if there was a client error or server error. The body of the response contains a collection of API error items to provide additional information about the failure.

Parameters

- **errorType**: Indicates the type of error. This is the primary identifier for the problem and can be used to map the type to a user readable string. For example, if your application receives an error with the errorType of `invalidInput.fieldRequired`, then you could display "This field is a required field; it cannot be left blank" to the user.
- **errorData**: The name of the parameter that had the error.
- **errorMessage**: Extra information about the error that is intended for the developer. This information is typically a sentence or other string. It is not localized, so it should not be shown to the user.
- **errorDetail**: Some errors contain additional detail parameters that are included in the `errorDetail` parameter.
 - If the error type is `invalidInput.outOfRange`, then `errorDetail` includes the following parameters:
 - **min**: The minimum value allowed.
 - **max**: The maximum value allowed.
 - If you attempt to delete an item that is in use by other items, the `errorType` is `referenceViolation.api` and the `errorDetail` includes the following parameters:
 - **referenceType**: The type of item that references the item you tried to delete.
 - **references**: A collection of references, referencing the item you tried to delete, including the name and `refURL` of each referencing item.
 - **totalCount**: The total number of items referencing the item you attempted to delete.
 - **totalShown**: The total number of items included in the references collection.

Example Error Response

The following error is returned when attempting to create a call type with a negative value for the `serviceLevelThreshold` parameter:

```

<apiErrors>
  <apiError>
    <errorData>serviceLevelThreshold</errorData>
    <errorDetail>
      <min>1</min>
      <max>2147483647</max>
    </errorDetail>
    <errorMessage>This field must contain a value from 1 to 2147483647</errorMessage>
    <errorType>invalidInput.outOfRange</errorType>
  </apiError>
</apiErrors>

```

```
</apiError>
</apiErrors>
```

Pagination

Pagination allows you to limit the number of items returned by the list operation and provides information on how to get other pages.

Query Parameters

- `startIndex`: Specifies the index of the item at which to start. Zero-based: 0 is the first item.
- `resultsPerPage`: Specifies the number of items to retrieve. Minimum: 1. Default: 25. Maximum: 100.

Returned Parameters

- `totalResults`: Total number of items.
- `resultsPerPage`: Number of items requested per page.
- `startIndex`: The index of the first item returned. If you request a `startIndex` that is greater than total items, a full last page is returned.
- `nextPage`: The URL to get the next page. This parameter is not returned if you are on the last page.
- `prevPage`: The URL to get the previous page. This parameter is not returned if you are on the first page.
- `firstPage`: The URL to get the first page.
- `lastPage`: The URL to get the last page.
- `searchTerm`: The value specified in the search query parameter. See [Search, on page 12](#).
- `sortTerm`: The value specified in the sort query parameters. See [Sort, on page 13](#).



Note Query parameters for search and sort are included in the URL.

Example Response

```
<pageInfo>
  <resultsPerPage>2</resultsPerPage>
  <startIndex>0</startIndex>
  <totalResults>10</totalResults>
  <firstPage> http://<server>/bucketIntervals/?resultsPerPage=2</firstPage>
  <lastPage> http://<server>/bucketIntervals/?startIndex=8&resultsPerPage=2</lastPage>

  <prevPage/>
  <nextPage> http://<server>/bucketIntervals/?startIndex=2&resultsPerPage=2</nextPage>
</pageInfo>

<bucketIntervals>
  <bucketInterval/>
  <bucketInterval/>
</bucketIntervals>
```

Shared Parameters

changeStamp

- The version of the item. Initially set during a create ([create, on page 2](#)) operation.
- A changeStamp is a required parameter for the body of a PUT ([update, on page 3](#)) operation for items. If you do not provide a changeStamp, the update fails. This mechanism is in place so that two clients cannot edit the record at the same time.
- If the update is successful, the changeStamp is incremented.

description

- A description for this item.
- Optional parameter.
- No restriction of characters; OEM locale supported characters are allowed. For information on how to configure your system to support built-in character sets, see the latest version of the document *Cisco Unified Contact Center Enterprise Installation and Upgrade Guide* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-installation-guides-list.html>.
- Maximum length of 255 characters.

name

- Required parameter.
- Maximum length of 32 characters allowed.
- Valid characters are period (.), underscore (_), and alphanumeric. The first character must be alphanumeric.
- Does not allow internationalized characters.

refURL

- The identifier for an item.
- Read-only parameter.

Permissions

Permissions information is included in list responses to indicate the write operations that the user is allowed to perform. If the API does not support any write operations, then permissions information is not returned.

Parameters

- canCreate: Indicates whether a create operation is allowed. Values are true/false. If the create operation is not supported by the API, then this parameter is not returned.

- `canUpdate`: Indicates whether an update operation is allowed. Values are true/false. If the update operation is not supported by the API, then this parameter is not returned.
- `canDelete`: Indicates whether a delete operation is allowed. Values are true/false. If the delete operation is not supported by the API, then this parameter is not returned.
- `role`: Type of role of the user performing the request. Values are administrator/supervisor.

Example Get Response

```
<permissionInfo>
  <canCreate>false</canCreate>
  <canUpdate>true</canUpdate>
  <canDelete>false</canDelete>
  <role>Administrator</role>
</permissionInfo>
```

Synchronous vs. Asynchronous Writes

Synchronous API calls are blocking calls that do not return until either the change has been completed or there has been an error. For asynchronous calls, the response to the API call is returned immediately with a polling URL while the request continues to be processed. In heavier load conditions, it can be more efficient to submit multiple async calls and periodically check the status than to wait for each call to complete before submitting the next one.

The following examples describe how to use the asynchronous feature to create a call type.

Performing Asynchronous Operations

The create, update, and delete operations can be performed asynchronously by including the query parameter `async=true`. The request is accepted if the operation is valid and the number of outstanding requests does not exceed the capacity. If the request is accepted, the response includes the following items:

- The response code is HTTP 202, indicating that the request has been accepted for processing.
- The location header specifies a URL that can be polled to receive updated information on the progress of the request.
- The response includes a body. See the next section **Asynchronous result parameters**.

Asynchronous Result Parameters

- `progress`: Indicates the current state of the request. Values include the following states:
 - `IN_QUEUE`: The request passed validation and capacity checks and was put in the queue.
 - `IN_PROGRESS`: The request is being processed.

Polling the Asynchronous Request Status

Use the URL from the location header of an asynchronous operation request to get updated status. Responses of this request are:

- If the request has not completed yet, the response contains the HTTP 202 response code, a location header with polling URL, and a response body.
- If the request has completed, the response is identical to the responses of synchronous operations, including the following:

- For a successful create, the response code is HTTP 201 and the location header has the URL of the created item.
 - For a successful update or delete, the response code will be HTTP 200.
 - For an unsuccessful update, a body will provide information about the failure.
- If the request has been in queue for over 30 seconds, then it is removed and an error indicates that the request timed out.

Search

The list operation can be modified to return data you are looking for by applying the search query parameter.

Default Search Parameters

Typically, the name and description fields are searched when specifying a search string. Refer to each API section for the default search parameters permitted. For example, a query parameter of `q=abc` causes the list operation to return only entries with a name or description containing **abc**. The search value for default parameters has the following behaviors and restrictions:

Values:

- Are case-insensitive.
- Can be contained anywhere in the parameter value.
- Can match any of the default parameters.
- Cannot include SQL wildcards. They are not supported.
- Must be URL encoded. For example, **&** must be converted to **%26** so that it is not treated as a separator for additional query parameters.



Note The default search is a case-insensitive substring search on multiple columns and hence may take a longer time to respond, depending on the number of records and columns to search for.

Advanced Search

Advanced search parameters allow specific parameters to be searched. Refer to each API section for the advanced search parameters permitted. Advanced search parameters can be combined with a default search value. For example, applying the search query parameter of `q=abc routingType:1` to a dialed number list operation returns results where the routingType is set to one, and one of the default search parameters contains **abc**. Advanced search also has the following restrictions:

- Search terms must be separated by a space.
- Search terms can be specified in any order.

Sort

A sort query parameter can be used to specify the order of the results in a list response.

The query parameter is **sort=<parameterName>** order, where:

- **parameterName**: The name of the parameter that you want to sort on. This is case sensitive, so it must match the parameter in the API exactly.
- **order**: Specifies the order of the sort. Values are as follows:
 - **asc**: Perform an ascending sort. This is the default if no order is specified.
 - **desc**: Perform a descending sort.

Example

For example, to find all the CallTypes whose name or description contains *supervisor*, sorted in ascending order by *name*:

```
https://<server>/unifiedconfig/config/calltype?q=supervisor&sort=name
```

Contact Center AI Features

You can enable Contact Center AI feature(s) for an agent.

The type of Contact Center AI features and supported values are `Transcript`, `VAVTranscript`, and `Transcript`.

The following table has the list of all the Contact Center AI features:

Table 2: Contact Center AI Features and agentservices type

agentservices type	CCAI Feature
VAVTranscript	Virtual agent transcript
Transcript	Call transcript



CHAPTER 2

Active Directory Domain API

- [Active Directory Domain API, on page 15](#)

Active Directory Domain API

Use the Active Directory Domain API to list the active directory domains currently defined in your call center environment. It is read-only, and does not require authentication.

URL

`https://<server>/unifiedconfig/config/activedirectorydomain`

Operations

- [list](#): Retrieves a list of active directory domains.

Parameters

- `name`: The name of the domain.
- `systemDomain`: Indicates if the system is a member of this domain. Values are true/false.

Example List Response

```
<results>
  <activeDirectoryDomains>
    <activeDirectoryDomain>
      <name>boston.com</name>
      <systemDomain>>true</systemDomain>
    </activeDirectoryDomain>
    <activeDirectoryDomain>
      <name>cisco.com</name>
      <systemDomain>>false</systemDomain>
    </activeDirectoryDomain>
  </activeDirectoryDomains>
</results>
```




CHAPTER 3

Administrator API

- [Administrator API, on page 17](#)

Administrator API

An administrator is an Active Directory user who has been provided access to the system.

Use the Administrator API to list the administrators currently defined in the database, define new administrators, and view, edit, and delete existing administrators.

URL

`https://<server>/unifiedconfig/config/administrator`

Operations

- **create**: Creates one administrator.
- **delete**: Permanently deletes one administrator.
- **get**: Returns one administrator, using the URL
`https://<server>/unifiedconfig/config/administrator/<id>`.
- **list**: Retrieves a list of administrators.
- **update**: Updates one administrator.

Parameters

- **refURL**: The refURL of the administrator. See [Shared Parameters, on page 10](#).
- **changeStamp**: See [Shared Parameters, on page 10](#).
- **description**: See [Shared Parameters, on page 10](#).
- **userName**: Required. The unique username of an existing Active Directory account. Maximum length of 64 characters.
- **domainName**: The domain for this administrator. If blank, system uses the default domain name. Maximum length of 64 characters.

- **customer:** A reference to a customer, including the refURL.
- **readOnly:** Required. Specifies whether the administrator has read-only access to the APIs and tools. Values are true/false.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • userName • domainName • description 	<ul style="list-style-type: none"> • userName • domainName • description

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```
<administrator>
  <changeStamp>0</changeStamp>
  <domainName>domain</domainName>
  <userName>user1</userName>
  <readOnly>>false</readOnly>
  <customer>
    <refURL>/unifiedconfig/config/customer/(id)</refURL>
  </customer>
</administrator>
```



CHAPTER 4

Agent API

- [Agent API, on page 19](#)

Agent API

Agents respond to contacts from customers. Use the Agent API to view and edit the currently defined agents in the database.



Note Access to this API is different for supervisors and administrators. For more information, see [Access](#).

URL

`https://<server>/unifiedconfig/config/agent`

Operations

- **create:** Creates an agent.
- **delete:** Marks one agent for deletion, but does not permanently delete the agent.
- **get:** Returns one agent, using the URL
`https://<server>/unifiedconfig/config/agent/<id>`.
- **list:** Retrieves a list of agents.
 - **Query parameters:**
 - **selectedAttribute:** Use this query parameter to augment the returned agent parameters with an extra parameter called `selectedAttribute`. This parameter indicates if the agent belongs to the attribute with the ID specified in this query parameter. For example, to find out which agents belong to the specified attribute, add `selectedAttribute=5000`.



Note Using `selectedAttribute` automatically sets the summary list query parameter to `true`.

- `selectedSkillGroup`: Use this query parameter to augment the returned agent parameters with an extra parameter called `selectedSkillGroup`. This parameter indicates if the agent belongs to the skill group with the ID specified in this query parameter. For example, to find out which agents belong to the specified skill group, add `selectedSkillGroup=5001`.
- `ignoreRole`: Use this query parameter to allow a supervisor to see a list of all agents in the system, including agents the supervisor does not supervise. For example, to see all agents, add `ignoreRole=true`.
- Summary list: See [list, on page 2](#).
- `update`: Updates one agent.



Note

- API access is provided to users who have **Configuration** access (but not **Setup** access) assigned on the **User List** page. Additionally, the **Agent Explorer** must be enabled in the **Feature Control Set List** page.
- In Unified CCE, the `ConfigGroup` role is required for full CRUD access to the following configuration APIs:
 - Agent API
 - Agent Team API
 - Skill Group API

Users without the `ConfigGroup` role may have limited read or update access depending on the API and the deployment configuration.

Parameters

- `refURL`: The refURL for the agent. See [Shared Parameters, on page 10](#).
- `agentId`: The unique peripheral number. Maximum length of 11 characters allowed. The default is an autogenerated 7-digit number.
- `changeStamp`: See [Shared Parameters, on page 10](#).
- `description`: See [Shared Parameters, on page 10](#).
- `agentStateTrace`: Indicates if agent state tracing is turned on for the agent. True or false.
- `agentDeskSettings`: A reference to the agent's `agentDeskSettings`, including the refURL and name. See [References, on page 7](#).
- `peripheral`: Required for Create API only but not-required for Update API. Includes the following parameters:
 - `id`: A mandatory field for Create API only. Peripheral's ID under which the new agent exists. This value is not allowed to be changed or updated.
- `department`: Ignored for Create and Update APIs.

- name: The agent's enterprise name. It is autogenerated if not explicitly set. This name can be updated.
- person: Required. Includes the following parameters:
 - firstName: Agent's first name. Maximum of 32 characters. International characters are allowed.
 - lastName: Agent's last name. Maximum of 32 characters. International characters are allowed.
 - userName: Agent's username. Maximum of 32 alphanumeric characters.
 - password: Agent's password. Maximum of 256 ASCII characters. The password is case-sensitive. Password can be used when creating or updating, but is not returned.
 - changeStamp: Mandatory for any person Update action.
 - emailAddress: The email address of the person. It can be updated.
 - description: Optional. Person's description. It can be updated.
 - department: Ignored for Create, Update, and Read APIs.
- supervisor: Required. Indicates whether the agent is marked as supervisor. True or false.
- agentAttributes: A collection of agent attribute ([Attribute API, on page 35](#)) references for this agent, including the refURL, and read-only parameters name, dataType, and description for each associated attribute. Also includes the attributeValue parameter which indicates the value (true or false or 1-10), and description of the attribute for this agent. See [References, on page 7](#).
- agentAttributesAdded: A collection of agent attribute references ([Attribute API, on page 35](#)) to be added to the agent, including the agent refURL and the attributeValue of each attribute. If the attributeValue is not specified, it is assigned the default value. Agents that already have this attribute are updated with the specified attributeValue. This parameter is update only, and cannot be used with the agentAttributes parameter. This parameter can be used with the agentAttributesRemoved parameter. See [References, on page 7](#).
- agentAttributesRemoved: A collection of agent attribute references ([Attribute API, on page 35](#)) to be removed from the agent, including the refURL of each attribute. This parameter is update only, and cannot be used with the agentAttributes parameter. This parameter can be used with the agentAttributesAdded parameter. See [References, on page 7](#).
- selectedAttribute: Indicates if the agent has the specified attribute. Returned only when using the selectedAttribute query parameter. True or false.
- skillGroups: A collection of skill group references for this agent ([Skill Group API, on page 141](#)), including the refURL and name of each associated skill group. See [References, on page 7](#).
- skillGroupsAdded: A collection of skill group references to be added to the agent, including the refURL of each skill group to be added. This parameter is update only, and cannot be used with the skillGroups parameter. This parameter can be used with the skillGroupsRemoved parameter. See [References, on page 7](#).
- skillGroupsRemoved: A collection of skill group references to be removed from the agent, including the refURL of each skill group to be removed. This parameter is update only, and cannot be used with the skillGroups parameter. This parameter can be used with the skillGroupsAdded parameter. See [References, on page 7](#).
- defaultSkillGroup: A reference to a skill group, including the refURL and name. Identifies the default skill group associated with this agent. See [References, on page 7](#).

- **selectedSkillGroup**: Indicates if the agent has the specified skill group. Returned only when using the `selectedSkillGroup` query parameter. True or false.
- **agentServicesEnabled** - A collection of CCAI features enabled for an agent.
 - **agentService**: The type of Contact Center AI features. Supported values are `VAVTranscript`, `Transcript`, `.`

For more information about the list of available AI features, see the [Contact Center AI Features](#) topic in this guide.
- **agentTeam**: A reference to the agent's team (Agent Team API), including the `refURL` and name. See [References, on page 7](#).
- **supervisorTeams**: If this agent has supervisor access, this collection of references is for this supervisor's teams, including the `refURL` and name of each supervised team. See [References, on page 7](#).

Search and Sort Values

The following table shows the parameters that are searchable and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • <code>agentId</code> • <code>description</code> • <code>person.firstName</code> • <code>person.lastName</code> • <code>person.userName</code> 	<ul style="list-style-type: none"> • <code>agentId</code> • <code>description</code> • <code>supervisor</code> • <code>agentStateTrace</code> • <code>person.firstName</code> • <code>person.lastName</code> • <code>person.userName</code> • <code>person.loginEnabled</code> • <code>peripheral.name</code>

See [Search, on page 12](#) and [Sort, on page 13](#).

Advanced search parameters

- **supervisor: (true/false)** Find agents that are (or are *not*) supervisors.
 - **q=supervisor:true** Returns all agents who are supervisors.
 - **q=supervisor:false** Returns all agents who are *not* supervisors.
- **attributes: (attr1 & attr2 & attr3, ...)** find *all* agents that have *all* the specified attributes. Up to 10 attributes can be specified. The attribute names are fully matched.
- **skillgroups: (skill1 & skill2 & skill3,...)** find *all* agents that have *all* the specified skillgroups. Up to 10 skillgroups can be specified. The skill group names are fully matched.

- **team:** (**team1|team2|team3, ...**) find *all* agents who belong to *any* of the specified teams. Up to ten team names can be specified. The team name is fully matched.
- **include:** (**ID1 & ID2 & ID3, ...**) find *all* specified agents even if they do not meet other search criteria. Each ID is fully matched. Obtain this ID from the refURL. For example, 5017 is the ID in the following refURL `<refURL>/unifiedconfig/config/agent/5017</refURL>`.
- **exclude:** (**ID1 & ID2 & ID3, ...**) exclude *all* specified agents from the results even if they meet all other search criteria. Each ID is fully matched. Obtain this ID from the refURL. For example, 5017 is the ID in the following refURL `<refURL>/unifiedconfig/config/agent/5017</refURL>`.

Agent-Person Mapping

There are the following allowed Agent-Person relation:

- many-to-one: when agents are mapped to different peripherals;

From the Peripheral resource perspective, there is the following allowed Peripheral-Agent-Person relation:

- one-many-one: which means that a Person resource is not allowed to have more than one Agents for a specific Peripheral;

Example of Agent-Person Mapping requests:

Create a new Agent resource:

- by mapping it to a non existing Person resource

```
<agent>
  <peripheral>
    <id>5000</id>
  </peripheral>
  <person>
    <firstName>SVFN1</firstName>
    <lastName>SVLN1</lastName>
    <loginEnabled>true</loginEnabled>
    <ssoEnabled>false</ssoEnabled>
    <userName>SVLoginName1</userName>
  </person>
  ...
</agent>
```

- by mapping it to an existing Person resource without updating Person fields

```
<agent>
  <peripheral>
    <id>5000</id>
  </peripheral>
  <person>
    <refURL>/unifiedconfig/config/person/14915</refURL>
  </person>
  ...
</agent>
```

- by mapping it to an existing Person resource and by updating some Person fields

```
<agent>
  <changeStamp>8</changeStamp>
  <person>
    <refURL>/unifiedconfig/config/person/14915</refURL>
    <firstName>SVFN1</firstName>
    <lastName>SVLN1</lastName>
```

```

        <loginEnabled>true</loginEnabled>
        <ssoEnabled>>false</ssoEnabled>
        <userName>SVLoginName1</userName>
    </person>
    ...
</agent>

```

Example Get Response

```

<agent>
  <department>
    <refURL>/unifiedconfig/config/department/5001</refURL>
    <name>debit_card</name>
  </department>
  <changeStamp>2877</changeStamp>
  <refURL>/unifiedconfig/config/agent/5017</refURL>
  <agentId>8006</agentId>
  <agentServicesEnabled>

    <agentService>Transcript</agentService>
    <agentService>VAVTranscript</agentService>
    <agentService>VATransferSummaries</agentService>
    <agentService>RealTimeAssist</agentService>
    <agentService>WrapUpSummaries</agentService>
  </agentServicesEnabled>

  <agentStateTrace>>false</agentStateTrace>
  <description>an agent</description>
  <person>
    <refURL>/unifiedconfig/config/person/14915</refURL>
    <firstName>Agent2</firstName>
    <lastName>Agent2</lastName>
    <loginEnabled>true</loginEnabled>
    <userName>Agent2@xyz.com</userName>
    <password>mypassword</password>
    <ssoEnabled>>false</ssoEnabled>
    <ecePerson>true</ecePerson>
    <emailAddress>agent@xyz.com</emailAddress>
    <screenName>agentScreenName</screenName>
  </person>
  <agentDeskSettings>
    <name>test2</name>
    <refURL>/unifiedconfig/config/agentdesksetting/5434</refURL>
  </agentDeskSettings>
  11.6 PCCCE multi PG support<datacenter>
    <name>Berlin</name>
    <refURL>/unifiedconfig/config/datacenter/5000</refURL>
  </datacenter>
  <supervisor>true</supervisor>
  <agentAttributes>
    <agentAttribute>
      <attribute>
        <refURL>/unifiedconfig/config/attribute/5004</refURL>
        <name>Sales</name>
        <dataType>4</dataType>
        <description>Sales proficiency</description>
      </attribute>
      <attributeValue>8</attributeValue>
      <description>postgraduate certification</description>
    </agentAttribute>
  </agentAttributes>
  <skillGroups>

```

```
        <skillGroup>
          <refURL>/unifiedconfig/config/skillgroup/5229</refURL>
          <name>Support</name>
        </skillGroup>
      </skillGroups>

      <defaultSkillGroup>
        <refURL>/unifiedconfig/config/skillgroup/5229</refURL>
        <name>Support</name>
      </defaultSkillGroup>

      <agentTeam>
        <refURL>/unifiedconfig/config/agentteam/5003</refURL>
        <name>theTeam</name>
      </agentTeam>
      <supervisorTeams>
        <supervisorTeam>
          <refURL>/unifiedconfig/config/agentteam/5003</refURL>
          <name>theTeam</name>
        </supervisorTeam>
        <supervisorTeam>
          <refURL>/unifiedconfig/config/agentteam/5006</refURL>
          <name>theBTeam</name>
        </supervisorTeam>
      </supervisorTeams>
    </agent>
```




CHAPTER 5

Agent Config Summary API

- [Agent Config Summary API, on page 27](#)

Agent Config Summary API

Agent Config Summary API provides a report of number of Agents that are configured with AI features.

URL

`https://<server>/unifiedconfig/config/contactcenterai/configsummary/agent`

Operations

- **GET:** Returns Agent AI configuration summary

Example Get Response

```
<agentConfigSummary>
  <totalAgents>982</totalAgents>
  <agentsWithFeatures>70</agentsWithFeatures>
  <featureList>
    <agentCountByFeature>
      <agentCount>68</agentCount>
      <featureId>1</featureId>
    </agentCountByFeature>
    <agentCountByFeature>
      <agentCount>4</agentCount>
      <featureId>2</featureId>
    </agentCountByFeature>
    <agentCountByFeature>
      <agentCount>4</agentCount>
      <featureId>3</featureId>
    </agentCountByFeature>
    <agentCountByFeature>
      <agentCount>1</agentCount>
      <featureId>4</featureId>
    </agentCountByFeature>
  </featureList>
</agentConfigSummary>
```




CHAPTER 6

Agent Security API

- [Agent Security API](#), on page 29

Agent Security API

Use the Agent Security API to get and update the status of global switch for generating advanced agent password hashing, and also to clear older agent password hashes from the system.

This API is available for administrators only, applicable for all the deployments, and is not supported in SSO modes.

URL

`https://unifiedconfig/config/agentsecurity`

Operations

- **get:** Returns the secure global switch value.

`https://unifiedconfig/config/agentsecurity?details=true`

- **update:** Updates the secure global switch status and clears the older agent password from the system.

Parameters

`enforceAdvancedHashing: true` means, global switch will be enabled and removes older Agent passwords, `false` means global switch will be disabled.

Example Get Response

```
<agentSecurity>
  <enforceAdvancedHashing>true</enforceAdvancedHashing>
  <agentsWithoutAdvancedHashing>10</agentsWithoutAdvancedHashing>
</agentSecurity>
```

Example Update Request

```
<agentSecurity>
  <changeStamp>277</changeStamp>
```

```
<enforceAdvancedHashing>true</enforceAdvancedHashing>  
</agentSecurity>
```



CHAPTER 7

Agent Team API

- [Agent Team API](#), on page 31

Agent Team API

You can associate a set of agents to a team with a specific supervisor. The supervisor can run reports on that team and receive Supervisor Assist requests from its members.

You can use the Agent Team API to list and view the agent teams currently defined in the database.



Note Access to this API is different for supervisors and administrators. For more information, see [Access](#).

URL

`https://<server>/unifiedconfig/config/agentteam`

Operations

- **get:** Returns one agent team, using the URL
`https://<server>/unifiedconfig/config/agentteam/<id>`.
- **list:** Retrieves a list of agent teams.
 - **Query parameters:**
 - Summary list: See [list](#).
- **create:** Creates a agentTeam using the url: `https://<ip_address>/unifiedconfig/config/agentteam`
- **update:** Updates a agentTeam using the url:
`https://<ip_address>/unifiedconfig/config/agentteam/<agentTeamID>`
- **delete:** Deletes a agentTeam using the url:
`https://<ip_address>/unifiedconfig/config/agentteam/<agentTeamID>`

Parameters

- peripheral: Required for Create API only. Fully ignored for Update API. Includes the following parameters:
 - id: a mandatory field for Create API only. This value is not allowed to be changed/updated.
- primarySupervisor: Added, which will be mapped to supervisorId.
- refURL: The refURL of the agent team.
- name: The name of the agent team. Maximum length of 32 characters allowed.
- description: Description for agent team. See [Shared Parameters, on page 10](#). Maximum length of 255 characters.
- dialedNumber: A reference to an internal dialed number (Dialed Number API) for the agent team, including the refURL and dialed number string.
- agents: A collection of agent (Agent Call API) references, including the refURL, first name, last name, username, and agent ID for each agent on the team.
- agentCount: Read-only field. Number of agents on the team.
- supervisors: A collection of supervisor (Agent Call API) references, including the refURL, first name, last name, username, and agent ID for each supervisor who supervises this team.
- supervisorCount: Read-only field. Number of supervisors who supervise this team.

Search and Sort Values

Sorting fields can be set to ascending (asc) or descending (desc) order.

The following table shows the parameters that are searchable and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description

See [Search](#) and [Sort](#).

Example Get Response

```
<agentTeam>
  <refURL>/unifiedconfig/config/agentteam/5000</refURL>
  <changeStamp>1</changeStamp>
  <agentCount>10</agentCount>
  <name>1000.AT</name>
  <peripheral>
    <id>5000</id>
    <name>PG1_CCM1</name>
  </peripheral>
  <peripheralId>5000</peripheralId>
  <supervisorCount>1</supervisorCount>
  <agents>
    <agent>
      <refURL>/unifiedconfig/config/agent/(id_1)</refURL>
      <firstName>John</firstName>
```

```
        <lastName>Smith</lastName>
        <userName>username</userName>
        <agentId>8006</agentId>
    </agent>
    <agent>
        <refURL>/unifiedconfig/config/agent/(id_2)</refURL>
        <firstName>Jane</firstName>
        <lastName>Doe</lastName>
        <userName>username</userName>
        <agentId>8007</agentId>
    </agent>
</agents>
<primarySupervisor>
    <refURL>/unifiedconfig/config/agent/27001</refURL>
    <agentId>8010572</agentId>
    <firstName>8010572</firstName>
    <lastName>8010572</lastName>
    <userName>8010572@stooges.icm</userName>
</primarySupervisor>
<supervisors>
    <supervisor>
        <refURL>/unifiedconfig/config/agent/27001</refURL>
        <agentId>8010572</agentId>
        <firstName>8010572</firstName>
        <lastName>8010572</lastName>
        <userName>8010572@stooges.icm</userName>
    </supervisor>
</supervisors>
</agentTeam>
```




CHAPTER 8

Attribute API

- [Attribute API, on page 35](#)

Attribute API

Attributes identify a call routing requirement, such as language, location, or agent expertise. You can create two types of attributes: boolean or proficiency. For example, you can create a Boston attribute that specifies that the agent assigned to this attribute must be located in Boston. Then, if a precision queue requires an agent who lives in Boston, then an agent with the attributes Boston = True is a good match. When you create a proficiency attribute, you assign a proficiency level to the agent.

Use the Attribute API to list the attributes currently defined in the database, define new attributes, and view, edit, and delete existing attributes.

URL

`https://<server>/unifiedconfig/config/attribute`

Operations

- **create:** Creates an attribute.
- **delete:** Marks one attribute and associated Agent attribute values for deletion, but does not permanently delete them.
- **get:** Returns one attribute, using the URL
`https://<server>/unifiedconfig/config/attribute/<id>`.
- **list:** Retrieves a list of attributes.



Note List operation is not supported if number of configured agents are more than 24k.

• Query parameters:

- **selectedAgentCount:** Use this query parameter to augment attribute information about multiple agents. The selectedAgentCount parameter shows the number of specified agents associated with this attribute. For example, to find out how many of agents 5000, 5001, 5002, and 5003 in the list have this associated attribute, add `selectedAgentCount=5000,5001,5002,5003`.



Note Using `selectedAgentCount` automatically sets the summary list query parameter to **true**.

- Summary list: See [list](#), on page 2.

- **update**: Updates one attribute.

- **Query Parameters:**

- **removeNonMatchingDepartmentalRefs**: Use this query parameter to remove all agent attributes from an attribute when they no longer belong to the department id specified in the query parameter or the global department. For example, to remove all agent attributes that do not belong to department 5000 or the global department, add `removeNonMatchingDepartmentalRefs=5000`. If this parameter is not specified, the agent attributes must belong to the attribute's department or the global department.

Parameters

- **refURL**: The refURL of the attribute. See [Shared Parameters](#), on page 10.
- **name**: The name of the attribute. See [Shared Parameters](#), on page 10.
- **changeStamp**: See [Shared Parameters](#), on page 10.
- **description**: See [Shared Parameters](#), on page 10.
- **dataType**: The data type of the attribute. Values are:
 - 3: Boolean.
 - 4: Proficiency.
- **defaultValue**: Used to specify the default value for the attribute when assigned to an agent, if no explicit value is provided. Values are:
 - Boolean: `true\false`.
 - Proficiency: 1-10.
- **agentAttributes**: A collection of agent attribute references for this attribute, including the description, refURL, and read-only parameters `agentId`, `userName`, `firstName`, and `lastName`. Also includes the `attributeValue` parameter which indicates the value (`true/false` or 1-10) of the attribute for this agent. See [References](#), on page 7.
- **agentAttributesAdded**: A collection of agent attribute references ([Attribute API](#), on page 35) to be added to the attribute, including the agent refURL and the `attributeValue` of each agent. If the `attributeValue` is not specified, it is assigned the default value. Agents that already have this attribute are updated with the specified `attributeValue`. This parameter is update only, and cannot be used in conjunction with the `agentAttributes` parameter. This parameter can be used with the `agentAttributesRemoved` parameter. See [References](#), on page 7.

- **agentAttributesRemoved**: A collection of agent attribute references ([Attribute API, on page 35](#)) to be removed from the attribute, including the refURL of each agent. This parameter is update only, and cannot be used in conjunction with the agentAttributes parameter. This parameter can be used with the agentAttributesAdded parameter. See [References, on page 7](#).
- **agentCount**: Read-only field. Number of agents associated with the attribute.
- **selectedAgentCount**: Read-only field. Indicates the number of specified agents associated with this attribute. Returned only when using the selectedAgentCount query parameter.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • dataType • defaultValue • description

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```
<attribute>
  <refURL>/unifiedconfig/config/attribute/5002</refURL>
  <changeStamp>0</changeStamp>
  <dataType>4</dataType>
  <defaultValue>1</defaultValue>
  <description>test</description>
  <name>AttributeA</name>
</attribute>
```




CHAPTER 9

Bucket Interval API

- [Bucket Interval API, on page 39](#)

Bucket Interval API

Configure bucket intervals to report how many calls are handled or abandoned during specific, incremental time slots. Each bucket interval has a maximum of nine configurable time slots, called Upper Bounds. Upper Bounds are ranges measured in seconds to segment and capture call-handling activity. You can run reports that show calls answered and calls abandoned for these intervals.

Use the Bucket Intervals API to add new bucket intervals, edit the name of an existing bucket interval, get a list of all of the configured bucket intervals, and delete existing bucket intervals.

URL

```
https://<server>/unifiedconfig/config/bucketinterval
```

Operations

- **create**: Creates one bucket interval.
- **delete**: Deletes one bucket interval from the database.
- **get**: Returns one bucket interval, using the URL
`https://<server>/unifiedconfig/config/bucketinterval/<id>`.
- **list**: Retrieves a list of bucket intervals.
- **update**: Updates the name of one bucket interval.

Parameters

- **refURL**: The refURL of the bucket interval. See [Shared Parameters, on page 10](#).
- **name**: The name of the bucket interval. See [Shared Parameters, on page 10](#).
- **changeStamp**: See [Shared Parameters, on page 10](#).
- **upperBound1**: Required. The first Bucket Interval value, in seconds. Must be greater than 0. This parameter cannot be updated.

- upperBound2 to upperBound 9: Optional. The next Bucket Interval values, in seconds. Each must be greater than the previous upperBound field or be left blank (if blank, all remaining upperBound fields must also be blank). These parameters cannot be updated.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name 	<ul style="list-style-type: none"> • name (default) • upperBound 1-9

See [Search](#), on page 12 and [Sort](#), on page 13.

Example Get Response

```
<bucketInterval>
  <refURL>/unified/config/bucketInterval/(id)</refURL>
  <name>test</name>

  <upperBound1>10</upperBound1>
  <upperBound2>20</upperBound2>
  <upperBound3>30</upperBound3>
  <upperBound4>40</upperBound4>
  <upperBound5>50</upperBound5>
  <upperBound6>60</upperBound6>
  <upperBound7>70</upperBound7>
  <upperBound8>80</upperBound8>
  <upperBound9>90</upperBound9>
  <changeStamp>0</changeStamp>
</bucketInterval>
```



CHAPTER 10

Bulk Job API

- [Bulk Job API, on page 41](#)

Bulk Job API

Use the Bulk Job API to list the bulk jobs currently defined in the database, define new bulk jobs, and view or delete records of existing bulk jobs.



Note Avoid performing a bulk job transaction during a maintenance window.



Note Limit the bulk job import to 1000 records at any given instance.

URL

`https://<server>/unifiedconfig/config/bulkjob`

Operations

- **create**: Creates one bulk job.
 - You can update the existing agent and supervisor usernames to SSO usernames using the **ssomigration** jobType.
- **delete**: Permanently deletes one bulk job.
- **get**: Returns one bulk job using the URL
`https://<server>/unifiedconfig/config/bulkjob/<id>`.
- **get** (template): Returns a sample CSV template for the given bulk job type. The response contains the CSV template as a file attachment. The form of the request is
`https://<server>/unifiedconfig/config/bulkjob/templates/<jobType>`, where `<jobType>` can be one of the following:
 - `dialednumber`

- agent
- calltype
- skillgroup
- inventory (for lab mode inventory)
- CVP file transfer
- ssomigration:

Returns the Cisco IdS ssomigration CSV template as a file attachment. The template includes the first 12,000 agent and supervisor accounts that are not enabled for Cisco IdS SSO.

If the database contains more than 12,000 non-SSO users, get the first 12,000 and update their credentials for Cisco IdS SSO. Then get the next 12,000 users and update their credentials for Cisco IdS SSO. Repeat until there are no more agents to migrate.

Non-SSO users can be filtered by peripheralId, agentTeamId, or both.

To filter by peripheralId, use the following URL:

`https://<server>/unifiedconfig/config/bulkjob/templates/ssomigration?&peripheralId:<peripheralId>`

To filter by agentTeamId, use the following URL:

`https://<server>/unifiedconfig/config/bulkjob/templates/ssomigration?&agentTeamId:<agentTeamId>`

To filter by both peripheralId and agentTeamId, use the following URL:

`https://<server>/unifiedconfig/config/bulkjob/templates/ssomigration?&peripheralId:<peripheralId>&agentTeamId:<agentTeamId>`

- aiFeatures_association

The sample CSV template returns the list of agents and the associated Contact Center AI feature types.

- [list](#): Retrieves a list of bulk jobs.

Parameters

- refURL: The refURL of the bulk job. See [Shared Parameters, on page 10](#).
- description: See [Shared Parameters, on page 10](#).
- fileContent: The content of the bulk CSV file. The size of the file must not exceed 3MB. For information about the CSV file data, see *Manage Bulk Jobs* section in the *Administration Guide for Cisco Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-maintenance-guides-list.html>.
- createDateTime: The time the bulk job was submitted. It indicates the time in milliseconds elapsed from the zero epoch value of January 1, 1970, 00:00:00 GMT. Read-only.
- jobHostName: The Windows computer name of the AW that initiated the bulk job. Read-only.
- startDateTime: The time the bulk job began to run. Read-only.
- endDateTime: The time the bulk job completed or failed. Read-only.
- jobState: The current state of the job. Read-only.

- 1: Queued
 - 2: Processing
 - 3: Succeeded
 - 4: Failed
 - 5: Cancelled
 - 6: Partially succeeded
- description: See [Shared Parameters, on page 10](#).
 - logFile: A URL to download the log file for the bulk job. Read-only.
 - csvFile: A URL to download the CSV file that was originally uploaded in the fileContent parameter. Read-only.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • description 	<ul style="list-style-type: none"> • description • jobType • jobState • jobHostName • createDateTime • startDateTime • endDateTime

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Create Request

For more information about the list of available AI features, see the [Contact Center AI Features](#) topic in this guide.

Example Get Response

Example response for a SSO migration create job that completed successfully:

```
<bulkJob>
  <changeStamp>2</changeStamp>
  <refURL>/unifiedconfig/config/bulkjob/(id)</refURL>
  <jobHostName>CCE_AW</jobHostName>
  <createDateTime>1461785074000</createDateTime>
  <startDateTime>1461785074000</startDateTime>
  <endDateTime>1461785074000</endDateTime>
  <jobState>3</jobState>
  <jobType>5</jobType>
```

```
<description>sso migration bulk job</description>
<logFile>
  <refURL>/unifiedconfig/config/bulkjob/(id)/log</refURL>
</logFile>
<csvFile>
  <refURL>/unifiedconfig/config/bulkjob/(id)/csv</refURL>
</csvFile>
</bulkJob>
```



CHAPTER 11

Business Hours API

- [Business Hours API](#), on page 45
- [Business Hour Status Reason API](#), on page 48
- [Time Zone API](#), on page 49

Business Hours API

Use this API to list the currently defined business hours, define new business hours, and view, edit, and delete the existing business hours.

URL

`https://<server>/unifiedconfig/config/businesshour`

Operations

- **create**: Creates one business hour.
- **get**: Returns one business hour using the URL
`https://<server>/unifiedconfig/config/businesshour/<id>`
- **get(template)**: Returns a sample CSV template for Special Hours and Holidays, which is provided by the API, using the URL
`https://<server>/unifiedconfig/config/businesshour/specialdayschedule/template`.
The response contains the CSV template as a file attachment.
- **list**: Retrieves a list of business hours.
- **update**: Updates one business hour.
- **delete**: Permanently deletes one business hour.

Parameters

- **changeStamp**: See [Shared Parameters](#), on page 10.
- **refURL**: The refURL of the business hour. See [Shared Parameters](#), on page 10.
- **name**: The name of the business hour. See [Shared Parameters](#), on page 10.

- description: See [Shared Parameters, on page 10](#).
- type: Required. The type of the business hour.
 - 0: 24x7
 - 1: Custom
- configuredStatus: The configured status of the business hour.
 - status: Required.
 - 0: Calendar Schedule
 - 1: Force Close
 - 2: Force Open
 - statusReason: Required if the status is Force Open or Force Close.
- runTimeStatus: The run time status of the business hour. Available only in Get. It cannot be set or updated.
- timezone: Required. The time zone of the business hour.
- weekDaySchedules: The list of schedules on weekdays of business. Required only when business hour type is Custom.
 - dayOfWeek: Required.
 - 0: Sunday
 - 1: Monday
 - 2: Tuesday
 - 3: Wednesday
 - 4: Thursday
 - 5: Friday
 - 6: Saturday
 - startTime: Required. Format HH:MM
 - endTime: Required. Format HH:MM
- specialDaySchedules: The list of schedules on special days of business.
 - date: Required. Format: DD-MM-YYYY
 - startTime: Required, if the status is Open. Format: HH:MM
 - endTime: Required, if the status is Open. Format: HH:MM
 - description: Optional. Maximum of 255 characters.
 - status: Required.
 - 0: Closed

- 1: Open
- statusReason: Required. The refURL to existing status reason.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name • runTimeStatus • runTimeStatusReason • type • timezone.displayName

See [Search](#), on page 12 and [Sort](#), on page 13.

Example Get Response

```
<businessHour>
  <refURL>/unifiedconfig/config/businesshour/1000</refURL>
  <changeStamp>0</changeStamp>
  <runTimeStatus>2</runTimeStatus>
  <runTimeStatusReason>closed</runTimeStatusReason>
  <name>credit_card</name>
  <type>1</type>
  <description>Business Line of Credit</description>
  <timezone>
    <refURL>/unifiedconfig/config/timezone/3001</refURL>
    <displayName>(UTC-05:00) Eastern Time (US & Canada)</displayName>
  </timezone>
  <configuredStatus>
    <status>1</status>
    <statusReason>
      <refURL>/unifiedconfig/config/businesshourstatusreason/5000</refURL>
      <reasonText>Emergency</reasonText>
    </statusReason>
  </configuredStatus>
  <specialDaySchedules>
    <specialDaySchedule>
      <refURL>/unifiedconfig/config/businesshour/1000/specialdayschedule/2001</refURL>

      <changeStamp>0</changeStamp>
      <date>04-02-2019</date>
      <startTime>03:26</startTime>
      <endTime>04:16</endTime>
      <description>Thanksgiving Day</description>
      <status>1</status>
      <statusReason>
        <refURL>/unifiedconfig/config/businesshourstatusreason/5000</refURL>
        <reasonText>Emergency</reasonText>
      </statusReason>
    </specialDaySchedule>
  </specialDaySchedules>
  <weekDaySchedules>
```

```

    <weekDaySchedule>
      <refURL>/unifiedconfig/config/businesshour/1000/weekdayschedule/1001</refURL>
      <changeStamp>0</changeStamp>
      <dayOfWeek>1</dayOfWeek>
      <startTime>06:20</startTime>
      <endTime>07:22</endTime>
    </weekDaySchedule>
  </weekDaySchedules>
</businessHour>

```

Business Hour Status Reason API

Use this API to list the currently defined business hour status reasons, define new status reasons, and view, edit, and delete the existing status reasons.

URL

`https://<server>/unifiedconfig/config/businesshourstatusreason`

Operations

- **create**: Creates one business hour status reason.
- **get**: Returns one business hour status reason using the URL
`https://<server>/unifiedconfig/config/businesshourstatusreason/<id>`
- **list**: Retrieves a list of business hour status reasons.
- **update**: Updates one business hour status reason.
- **delete**: Permanently deletes one business hour status reason.

Parameters

- **category**: Optional. The category of the reason codes: User-defined or System-defined.
- **reasonCode**: Required. The unique status reason code for business hour. Range is 1001 to 65535.



Note Codes 1 to 1000 are reserved as system defined reason codes. The System-defined reason codes cannot be deleted.

- **reasonText**: Optional. The reason for the business schedule. Maximum of 255 characters.

Example Create Request

```

<businessHourStatusReason>
  <category>User-defined</category>
  <reasonCode>1234</reasonCode>
  <reasonText>Emergency</reasonText>
</businessHourStatusReason>

```

Example Get Response

```
<businessHourStatusReason>
  <refURL>/unifiedconfig/config/businesshourstatusreason/5000</refURL>
  <changeStamp>0</changeStamp>
  <category>User-defined</category>
  <reasonCode>2550</reasonCode>
  <reasonText>Open</reasonText>
</businessHourStatusReason>
```

Time Zone API

Use the Time Zone API to list all available time zones and to get time zone information for a specified zone. Time zone information is stored in the registry of the Windows operating system.



Important Microsoft periodically releases cumulative time zone updates. These updates include worldwide changes to time zone names, bias (the amount of time in minutes that a time zone is offset from Coordinated Universal Time (UTC)), and observance of daylight saving time. These patches update the information in the Windows registry. When these updates are available, apply them to all virtual machines in the deployment that are running a Microsoft Windows operating system.

Use this API with the Business Hours API to set the default time zone for a business hour.

This API is read-only.

URL

`https://<server>/unifiedconfig/config/timezone/v2`

Operations

- **list:** Retrieves a list of available time zones. The list is sorted by UTC offset from the International Date Line from west to east.
- **get:** Returns information for a specific time zone using the URL `https://<server>/unifiedconfig/config/timezone/v2/<id>`.

Response Parameters

- **name:** The name of the time zone.
- **displayName:** Specific bias and location information about the time zone, such as the offset from UTC and one or more places located within the time zone.
Example: “(UTC-05:00) Eastern Time (US & Canada)”
- **changeStamp:** See [Shared Parameters, on page 10](#).

Example Get Response

```
<timezone>
  <refURL>/unifiedconfig/config/timezone/v2/5000</refURL>
  <changeStamp>0</changeStamp>
```

```
<displayName>(UTC-05:00) Eastern Time (US & Canada)</displayName>  
<name>UTC</name>  
</timezone>
```



CHAPTER 12

Call Type API

- [Call Type API, on page 51](#)

Call Type API

Call types categorize calls. Based on call type, the system maps a dialed number to a routing script that ultimately sends the call to the appropriate destination.

Use the Call Type API to list the call types currently defined in the database, define new call types, and view, edit, or delete records of existing call types.

URL

`https://<server>/unifiedconfig/config/calltype`

Operations

- **get:** Returns one call type, using the URL
`https://<server>/unifiedconfig/config/calltype/<id>`.
- **list:** Retrieves a list of call types.
- **update:** Updates one call type.

Parameters

- **refURL:** The refURL of the call type. See [Shared Parameters, on page 10](#).
- **name:** The name of the call type. See [Shared Parameters, on page 10](#).
- **changeStamp:** See [Shared Parameters, on page 10](#).
- **description:** See [Shared Parameters, on page 10](#).
- **ccaiConfigID:** Identifier for the Contact Center AI (CCAI) configuration saved in the Control Hub. Used to map the call type with the CCAI configuration. This parameter is available for administrators only when Cloud Connect is added in the inventory.
- **id:** The database id of the call type. Read-only field. Used in scripting.

- `serviceLevelThreshold`: Maximum time in seconds that a caller should wait before being connected with an agent. Leave blank to use the system default.
- `serviceLevelType`: This value indicates how the system calculates the service level.
 - blank: Use the system default.
 - 1: Ignore Abandoned Calls.
 - 2: Abandoned Calls have Negative Impact.
 - 3: Abandoned Calls have Positive Impact.
- `bucketInterval`: A reference to the bucket interval ([Bucket Interval API, on page 39](#)), including the `refURL` and name.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description • id 	<ul style="list-style-type: none"> • name (default) • description • id • serviceLevelThreshold • serviceLevelType

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```

<callType>
<department>
<refURL>/unifiedconfig/config/department/5001</refURL>
<name>Sales</name>
</department>
<refURL>/unifiedconfig/config/calltype/ (id) </refURL>
<name>test</name>
<description>test call type</description>
<id>5002</id>

<ccaiConfigID>Serviceconfig</ccaiConfigID>
<serviceLevelThreshold>10</serviceLevelThreshold>
<serviceLevelType>1</serviceLevelType>
<changeStamp>0</changeStamp>
<bucketInterval>
<refURL>/unifiedconfig/config/bucketinterval/ (id) </refURL>
<name>bucket1</name>
</bucketInterval>
<survey>
<questionnaireName>1d222cb3</questionnaireName>
OR <dispatchId>115097d3-ea65-432b-b90a-08aa7e5de361</dispatchId>
</survey>
</callType>

```



CHAPTER 13

Call Type Config Summary API

- [Call Type Config Summary API](#), on page 53

Call Type Config Summary API

Call Type Config Summary API provides a report of number of Call Types that are configured with AI features. If default CCAI configuration is already set, Call types that are not configured with any AI features are counted against the default configuration.

URL

`https://<server>/unifiedconfig/config/contactcenterai/configsummary/calltype`

Operations

- **GET:** Returns Call Type AI configuration summary

Example Get Response

```
<callTypeConfigSummary>
  <totalCallTypes>4269</totalCallTypes>
  <aiConfigList>
    <callTypeCountByAiConfig>
      <aiConfig>Webex CCAI Config</aiConfig>
      <callTypeCount>4266</callTypeCount>
    </callTypeCountByAiConfig>
    <callTypeCountByAiConfig>
      <aiConfig>GoogleConf2</aiConfig>
      <callTypeCount>2</callTypeCount>
    </callTypeCountByAiConfig>
    <callTypeCountByAiConfig>
      <aiConfig>GoogleConf1</aiConfig>
      <callTypeCount>1</callTypeCount>
    </callTypeCountByAiConfig>
  </aiConfigList>
  <aiConnectorList>
    <callTypeCountByAiConnector>
      <aiConnector>Google</aiConnector>
      <callTypeCount>3</callTypeCount>
    </callTypeCountByAiConnector>
    <callTypeCountByAiConnector>
      <aiConnector>Cisco</aiConnector>
```

```
        <callTypeCount>4266</callTypeCount>
      </callTypeCountByAiConnector>
    </aiConnectorList>
  </callTypeConfigSummary>
```



CHAPTER 14

Config Summary API

- [Config Summary API](#), on page 55

Config Summary API

Config Summary API provides a report of number of Agents and Call types that use AI features and configurations.

If default CCAI configuration is already set, Call types that are not configured with any AI features are counted against the default configuration.

•

URL

`https://<server>/unifiedconfig/config/contactcenterai/configsummary`

Operation

- **GET**: Returns both Agent and Call type AI configuration summaries.

Example Get Response

```
<aiConfigSummary>
  <agentConfigSummary>
    <totalAgents>982</totalAgents>
    <agentsWithFeatures>69</agentsWithFeatures>
    <featureList>
      <agentCountByFeature>
        <agentCount>67</agentCount>
        <featureId>1</featureId>
      </agentCountByFeature>
      <agentCountByFeature>
        <agentCount>4</agentCount>
        <featureId>2</featureId>
      </agentCountByFeature>
      <agentCountByFeature>
        <agentCount>4</agentCount>
        <featureId>3</featureId>
      </agentCountByFeature>
      <agentCountByFeature>
        <agentCount>1</agentCount>
```

```
        <featureId>4</featureId>
      </agentCountByFeature>
    </featureList>
  </agentConfigSummary>
<callTypeConfigSummary>
  <totalCallTypes>4269</totalCallTypes>
  <aiConfigList>
    <callTypeCountByAiConfig>
      <aiConfig>Webex CCAI Config</aiConfig>
      <callTypeCount>4266</callTypeCount>
    </callTypeCountByAiConfig>
    <callTypeCountByAiConfig>
      <aiConfig>GoogleConf2</aiConfig>
      <callTypeCount>1</callTypeCount>
    </callTypeCountByAiConfig>
    <callTypeCountByAiConfig>
      <aiConfig>GoogleConf1</aiConfig>
      <callTypeCount>1</callTypeCount>
    </callTypeCountByAiConfig>
  </aiConfigList>
  <aiConnectorList>
    <callTypeCountByAiConnector>
      <aiConnector>Google</aiConnector>
      <callTypeCount>2</callTypeCount>
    </callTypeCountByAiConnector>
    <callTypeCountByAiConnector>
      <aiConnector>Cisco</aiConnector>
      <callTypeCount>4266</callTypeCount>
    </callTypeCountByAiConnector>
  </aiConnectorList>
</callTypeConfigSummary>
</aiConfigSummary>
```



CHAPTER 15

Congestion Control API

- [Congestion Control API, on page 57](#)

Congestion Control API

Congestion control parameters determine how calls are treated by the system when too many calls are received at one time. Use the Congestion Control API to list or edit the current congestion control parameters in the database.

URL

`https://<server>/unifiedconfig/config/congestioncontrol`

Operations

- [get](#): Returns the congestion control parameters, using the URL `https://<server>/unifiedconfig/config/congestioncontrol`.
- [update](#): Updates the congestion control parameters.

Parameters

- `deploymentType`: The type of deployment.
- `congestionEnabled`: Indicates if congestion control is enabled. Value is true/false.
- `congestionTreatmentMode`: Mode to handle congestion. Values are:
 - 1: Dialed Number default label is used for call treatment.
 - 2: Treat call with Routing client default label.
 - 3: Treat call with System default label.
 - 4: Terminate with Dialog Fail/RouteEnd.
 - 5: Release message to the Routing client.
- `systemDefaultLabel`: Default label string to treat the calls subjected to congestion control. Only used if `congestionTreatmentMode` is set to 3 (Treat call with System default label).

- `cpsCapacity`: The maximum number of calls per second allowed.
- `cpsCapacityDefault`: The default value for the `cpsCapacity` parameter for the current deployment type. Read-only.

Example Get Response

```
<congestionControl>  
  <deploymentType>0</deploymentType>  
  <congestionTreatmentMode>1</congestionTreatmentMode>  
  <congestionEnabled>true</congestionEnabled>  
  <systemDefaultLabel></systemDefaultLabel>  
  <cpsCapacity>100</cpsCapacity>  
  <cpsCapacityDefault>150</cpsCapacityDefault>  
</congestionControl>
```



CHAPTER 16

Contact Center AI API

- [Global Config API, on page 59](#)
- [Config API, on page 60](#)

Global Config API

Use the Contact Center AI (CCAI) Global Config API to retrieve the global configuration for AI services. This API is available for administrators only when Cloud Connect is added in the inventory and is registered.

URL

Operations

- `get`: returns the global CCAI configuration.

`https://<server>/unifiedconfig/config/contactcenterai/globalconfig`

- `post`: syncs the default global configurations with the latest available from the control hub.

`https://<server>/unifiedconfig/config/contactcenterai/globalconfig/sync`

Parameters

- `name`: Configuration Name.
- `value`: Configuration Value.
- `status`: Indicates if the values are in sync with Control Hub.
- `lastSyncTime`: Time when config data was last synced with Control Hub

Example Get Response

```
<globalConfigDetail>
  <globalConfigs>
    <globalConfig>
      <name>CCAI.GlobalConfigId</name>
      <value>AXgB4em4bwWpdn7vJcLC</value>
    </globalConfig>
    <globalConfig>
      <name>CCAI.GlobalConfigName</name>
```

```

        <value>SS5T1</value>
      </globalConfig>
    </globalConfigs>
    <lastSyncTime>2021-03-05T16:07:43.497+05:30</lastSyncTime>
    <status>IN_SYNC</status>
  </globalConfigDetail>

```

Config API

This API is a proxy to Control Hub CMS service to fetch Contact Center AI configuration.

URL

`https://<server>/unifiedconfig/config/contactcenterai/config`

Operations

- **get**: Returns Contact Center AI config corresponding to `<id>` using the URL `https://<server>/unifiedconfig/config/contactcenterai/config/<id>`.
- **list**: Retrieves list of Contact Center AI configs.

Example Get Response

```

<ccaiconfig>
<conversationProfileId>sdfsd78bmplj89</conversationProfileId>
<defaultVirtualAgent>>false</defaultVirtualAgent>
<connectorId>XK123UIU6887787JLK</connectorId>
<defaultAnswers>>true</defaultAnswers>
<name>CCAIConfig2</name>
<description>Sample CCAI Config2</description>
<id>AXQlSeOzECsy_j49EVRz</id>
<type>Cisco</type>
<orgId>6d9069aa-76ce-45d6-a799-d38e60e92788</orgId>
</ccaiconfig>

```

Example List Response

```

<ccaiconfigs>
<ccaiconfig>
<conversationProfileId>sdfsd78bmplj89</conversationProfileId>
<defaultVirtualAgent>>false</defaultVirtualAgent>
<connectorId>XK123UIU6887787JLK</connectorId>
<defaultAnswers>>true</defaultAnswers>
<name>CCAIConfig2</name>
<description>Sample CCAI Config2</description>
<id>AXQlSeOzECsy_j49EVRz</id>
<type>Cisco</type>
<orgId>6d9069aa-76ce-45d6-a799-d38e60e92788</orgId>
</ccaiconfig>
<ccaiconfig>
<conversationProfileId>asdf8768mnnb89</conversationProfileId>
<defaultVirtualAgent>>true</defaultVirtualAgent>
<connectorId>XK123UIU6123567JLK</connectorId>
<defaultAnswers>>false</defaultAnswers>
<name>CCAIConfig3</name>
<description>Sample CCAI Config3</description>
<id>AXQlSjp5ECsy_j49EVSp3</id>

```

```
<type>Google</type>
<orgId>6d9069aa-76ce-45d6-a799-d38e60e92788</orgId>
</ccaiconfig>
<ccaiconfig>
  <conversationProfileId>qwewq556sad8asd</conversationProfileId>
  <defaultVirtualAgent>>false</defaultVirtualAgent>
  <connectorId>XK123UIU6778787JLK</connectorId>
  <defaultAnswers>>false</defaultAnswers>
  <name>CCAIConfig</name>
  <description>Sample CCAI Config</description>
  <id>AXQlSmksECsy_j49EVS</id>
  <type>Google</type>
  <orgId>6d9069aa-76ce-45d6-a799-d38e60e92788</orgId>
</ccaiconfig>
</ccaiconfigs>
```




CHAPTER 17

Cloud Connect Device Configuration

- [Cloud Connect Configuration, on page 63](#)

Cloud Connect Configuration

This is global API for *cloudconnector* (same configuration will be applicable for all the cloud connect present in the system).

The Cloud Connect API is applicable for the following deployments only:

- Unified CCE 2000 Agents.
- PCCE 2000 Agents and
- PCCE LabOnly

URL

`https://<server>/unifiedconfig/config/cloudconnectsettings`

Operations

• Get:

Gets the configuration information of the cloud

connect`https://<server>/unifiedconfig/config/cloudconnectsettings`

• Put:

Updates the proxy server and media type mapping to cloud connect.

`https://<server>/unifiedconfig/config/cloudconnectsettings`

with the following body.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?><CloudConnectSettings>
  <registrationStatus>Registered</registrationStatus>
  <dataGenerationEnabled>
    <changeStamp>310</changeStamp>
    <analyserIntegrated>true</analyserIntegrated>
  </dataGenerationEnabled>
  <dataSource>
    <sideA>
      <address>
```

```

        <refURL>/unifiedconfig/config/machineinventory/9939</refURL>
        <name>ABC</name>
    </address>
    <userName>Cisco</userName>
    <password>Cisco</password>
</sideA>
<sideB>
    <address>
        <refURL>/unifiedconfig/config/machineinventory/9940</refURL>
        <name>XYZ</name>
    </address>
    <userName>Cisco123</userName>
    <password>Cisco</password>
</sideB>
</dataSource>
<proxyAddress>http://10.10.10.10:80</proxyAddress>
<streamerEnabled>true</streamerEnabled>
<deploymentID>9de8bdfe-d513-4ab9-a021-2b729efa9c63</deploymentID>
<deploymentName>CloudConnectSettings</deploymentName>
<changeStamp>6</changeStamp>
</CloudConnectSettings>

```

Parameters

- **dataGenerationEnabled**: Enables data generation for Cloud Connect.
- **dataSourceAddress**: DataSource address for Cloud Connect.
- **dataSourceUserName**: DataSource user name for Cloud Connect.
- **dataSourcePassword**: DataSource password for Cloud Connect.
- **proxyAddress**: Proxy address or hostname for the Cloud Connect to connect to the Control Hub.
- **streamerEnabled**: Enables the data flow between Cloud Connect and Control Hub.

Example Get Response

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?><CloudConnectSettings>
  <registrationStatus>Registered</registrationStatus>
  <dataGenerationEnabled>
    <changeStamp>310</changeStamp>
    <analyserIntegrated>true</analyserIntegrated>
  </dataGenerationEnabled>
  <dataSource>
    <sideA>
      <address>
        <refURL>/unifiedconfig/config/machineinventory/9939</refURL>
        <name>ABC</name>
      </address>
      <userName>Cisco</userName>
    </sideA>
    <sideB>
      <address>
        <refURL>/unifiedconfig/config/machineinventory/9940</refURL>
        <name>XYZ</name>
      </address>
      <userName>Cisco123</userName>
    </sideB>
  </dataSource>
  <proxyAddress>http://10.10.10.10:80</proxyAddress>
  <streamerEnabled>true</streamerEnabled>

```

```
<deploymentID>9de8bdfe-d513-4ab9-a021-2b729efa9c63</deploymentID>  
<deploymentName>CloudConnectSettings</deploymentName>  
<changeStamp>6</changeStamp>  
</CloudConnectSettings>
```




CHAPTER 18

Deployment API

- [Deployment API, on page 67](#)

Deployment API

The Deployment API is used to view the deployment type of the installation. It is read-only, and does not require authentication. To change the deployment type, use the Deployment Type Info API.

URL

```
https://<server>/unifiedconfig/config/deployment
```

Parameters

- `deploymentType`: The type of deployment.
- `supervisorLoginAllowed`: Indicates whether the current deployment type allows supervisor login.

Operations

- `get`: Returns the deployment type of the installation using the URL `https://<server>/unifiedconfig/config/deployment`.

Example Get Response

```
<deployment>
  <deploymentType>7</deploymentType>
  <supervisorLoginAllowed>true</supervisorLoginAllowed>
</deployment>
```




CHAPTER 19

Deployment Type Info API

- [Deployment API, on page 69](#)

Deployment API

The Deployment API is used to view the deployment type of the installation. It is read-only, and does not require authentication. To change the deployment type, use the Deployment Type Info API.

URL

```
https://<server>/unifiedconfig/config/deployment
```

Parameters

- `deploymentType`: The type of deployment.
- `supervisorLoginAllowed`: Indicates whether the current deployment type allows supervisor login.

Operations

- `get`: Returns the deployment type of the installation using the URL `https://<server>/unifiedconfig/config/deployment`.

Example Get Response

```
<deployment>  
  <deploymentType>7</deploymentType>  
  <supervisorLoginAllowed>true</supervisorLoginAllowed>  
</deployment>
```




CHAPTER 20

ECC Payload API

- [ECC Payload API, on page 71](#)

ECC Payload API

You use expanded call variables to store values that are associated with a call. These variables are commonly called Expanded Call Context (ECC) variables. While you can define many more ECC variables in the system, you can pass a maximum of 2000 bytes of these variables at any time over any interface. To enable you to pass different ECC variables at different times, the solution has ECC payloads.

An ECC payload is a defined set of ECC variables. You can create ECC payloads to suit the necessary information for a given operation. You can include an ECC variable in multiple ECC payloads. The particular ECC variables in a given ECC payload are called its members.



Note

- ECC payload ID 1 is the default ECC payload. The API prevents the deletion of this ECC payload.
 - In solutions that only use the default ECC payload, the Logger does not create an ECC variable that exceeds the 2000-byte limit for an ECC payload or the 2500-byte CTI Message Size limit. The Logger does this because it automatically adds all ECC variables to the default ECC payload if that is the only ECC payload.

If you create another ECC payload, the Logger no longer checks the 2000-byte limit when creating ECC variables. The Logger creates the ECC variables without assigning them to an ECC payload. Assign the new ECC variable to an appropriate ECC payload yourself, either through the ECC Payload API or through the ECC Payload Tool.
 - For create and update operations, the ECC Payload API verifies that the members of the ECC payload do not exceed the 2000-byte limit.
-



Important

During upgrades, when the system first migrates your existing ECC variables to the Default payload, it does not check the CTI message size limit. The member names might exceed the extra 500 bytes that is allocated for ECC payloads to a CTI client. Manually check the **CTI Message Size** counter in the **Expanded Call Variable Payload List** tool to ensure that the Default payload does not exceed the limit. If the Default payload exceeds the limit, modify it to meet the limit.

URL

`https://<server>/unifiedconfig/config/eccpayload`

Operations

- **create**: Creates one ECC payload and stores it in the database.

- **Query Parameters**

- **name**: The name of the ECC payload (Required)
- **description**: A description of the ECC payload (Optional)
- **variables**: 0 or more ECC variables (Optional)



Note Specify each variable with the `ecc.refURL` of a valid, non-deleted ECC variable.



Note This API supports synchronous and asynchronous create operations.

- **delete**: Permanently deletes one ECC payload and all its members from the database.
- **get**: Returns one ECC payload from the database, using the URL `https://<server>/unifiedconfig/config/eccpayload/<id>`.
- **list**: Retrieves a list of ECC payloads.
- **update**: Updates one ECC payload in the database.
 - **Query Parameters**
 - **changeStamp**: The change stamp for the ECC payload record which the GET returns (Required)
 - **refURL**: The `refURL` of the ECC payload to update (Required)
 - **name**: The name of the ECC payload (Optional)
 - **description**: A description of the ECC payload (Optional)
 - **variables**: 0 or more ECC variables (Optional)



Note Specify each variable with the `ecc.refURL` of a valid, non-deleted ECC variable.

Parameters

- **refURL**: The refURL of the ECC payload. See [Shared Parameters, on page 10](#).
- **name**: The name of the ECC payload. See [Shared Parameters, on page 10](#).

- changeStamp: See [Shared Parameters, on page 10](#).
- description: See [Shared Parameters, on page 10](#).
- variables: The members of the ECC payload.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description

See [Search, on page 12](#) and [Sort, on page 13](#).



Note This API does not support advanced search parameters.

Example Get Response

```
<eccpayload>
  <refURL>/unifiedconfig/config/eccpayload/1</refURL>
  <changeStamp>18</changeStamp>
  <description>Initial default data.</description>
  <name>Default</name>
  <variables>
    <variable>
      <refURL>/unifiedconfig/config/expandedcallvariable/8</refURL>
      <name>POD.ID</name>
    </variable>
    <variable>
      <refURL>/unifiedconfig/config/expandedcallvariable/5009</refURL>
      <name>user.A1</name>
    </variable>
    <variable>
      <refURL>/unifiedconfig/config/expandedcallvariable/5010</refURL>
      <name>user.A2</name>
    </variable>
  </variables>
</eccpayload>
```




CHAPTER 21

Expanded Call Variable API

- [Expanded Call Variable API, on page 75](#)

Expanded Call Variable API

Calls carry data with them as they move through the system. This data, called expanded call variable data, is embedded with the call and is visible on the agent desktop.

Use the Expanded Call Variable API to view and list the expanded call variables currently defined in the database.

URL

`https://<server>/unifiedconfig/config/expandedcallvariable`

Operations

- **create**: Creates one expanded call variable.
- **delete**: Marks one expanded call variable for deletion, but does not permanently delete it.
- **get**: Returns one expanded call variable, using the URL
`https://<server>/unifiedconfig/config/expandedcallvariable/<id>`.
- **list**: Retrieves a list of expanded call variables.
- **update**: Updates one expanded call variable.

Parameters

- **refURL**: The refURL of the expanded call variable. See [Shared Parameters, on page 10](#).
- **name**: The name of the expanded call variable. See [Shared Parameters, on page 10](#).
- **changeStamp**: See [Shared Parameters, on page 10](#).
- **description**: See [Shared Parameters, on page 10](#).
- **maxLength**: The maximum length of the expanded call variable. The value is 1 to 210.



Note Cisco Provided POD.ID variable, **Maximum length** can be modified.

- **eccArray**: Indicates whether the expanded call variable is an array. Values are true/false.
- **maximumArraySize**: The maximum number of elements in the array is 1 to 255. Required if eccArray is true; must be blank or not specified if eccArray is false.
- **enabled**: Indicates whether the expanded call variable is enabled. Values are true/false.
- **persistent**: Specifies whether the expanded call variable is written to the historical database with each Termination Call Detail and Route Call Detail record. Values are true/false.
 - No persistent, enabled arrays are allowed.
 - The maximum number of persistent, scalar, enabled variables is 20.
- **ciscoProvided**: Indicates whether the expanded call variable is provided by Cisco. Values are true/false. Read-only.
- **bytesRequired**: The number of bytes required to store the expanded call variable in the system. Read-only. The size is calculated using the following formula:
 - If eccArray is false, the size is 5+Maximum Length.
 - If eccArray is true, the size is 5+(1+Maximum length)*Maximum Array size.
- **bytesRequiredInCtiServer**: The number of bytes required to send this variable to CTI Server. Read-only. The size is calculated using the following formula:
 - If eccArray is false, the size is Length of name+Maximum length+4.
 - If eccArray is true, the size is (Length of name+Maximum length+5)*Maximum array size.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description • maximumLength • maximumArraySize • eccArray • enabled • persistent • ciscoProvided

See [Search](#), on page 12 and [Sort](#), on page 13.

Example Get Response

```
<expandedCallVariable>
  <refURL>/unifiedconfig/config/expandedcallvariable/(id)</refURL>
  <name>test</name>
  <maxLength>9</maxLength>
  <maximumArraySize>10</maximumArraySize>
  <eccArray>true</eccArray>
  <enabled>true</enabled>
  <ciscoProvided>false</ciscoProvided>
  <description>test expanded call variable</description>
  <persistent>false</persistent>
  <changeStamp>0</changeStamp>
  <bytesRequired>105</bytesRequired>
  <bytesRequiredInCtiServer>180</bytesRequiredInCtiServer>
</expandedCallVariable>
```




CHAPTER 22

General Setting API

- [General Setting API](#), on page 79

General Setting API

GeneralSetting API is introduced to include the session inactivity timeout field. Both GET and PUT are available in all supported deployments.

URL

`https://<server>/unifiedconfig/config/generalsetting`

Operations

- **get**: Returns the general settings configured in the system.
- **put**: To update any general setting applicable in the system.

Parameters

- **sessioninactivitytimeout**: Timeout after which user is logged out if the user is inactive

Example Get Request

```
<generalSettings>
  <loginSession>
    <sessionInactivityTimeout>
      30
    </sessionInactivityTimeout>
  </loginSession>
</generalSettings>
```

Example Put Request

```
<generalSettings>
  <loginSession>
    <sessionInactivityTimeout>
      60
    </sessionInactivityTimeout>
  </loginSession>
</generalSettings>
```




CHAPTER 23

GeneralSetting API with Agent Event Detail Extended support

- [General Setting API with Agent Event Detail Extended Support, on page 81](#)

General Setting API with Agent Event Detail Extended Support

You can enable the agent event details from the user instance, thus the value of the AED.AgentEventDetailExtended flag is set to yes on the t_Global_Configuration table. The agent event details can be obtained using the Agent Event Detail Extended API.

URL

`https://<server>/unifiedconfig/config/generalsetting`

Operations

- **GET:** Returns the value of AED.AgentEventDetailExtended set in the t_Global_Configuration table. The returned value is "true", if AED.AgentEventDetailExtended is set to "yes". Or else, it returns "false" if its value is set to "no" or if no record is found.
- **PUT:** Creates the AED.AgentEventDetailsExtended entry in the t_Global_Configuration table if no entry is found. If an entry is found, it would update the AED.AgentEventDetailsExtended flag value to "yes" or "no" based on whether the value for "agentEventDetailExtended" in the request body is "true" or "false".

Parameters

- **agentEventDetailExtended:** Indicates whether agent event details are enabled or not.
- **sessionInactivityTimeout:** Indicates the time interval for which a session can be inactive. You can change the session inactivity timer.
- **generalSettings:** You can now change both the session inactivity timer and also change the agentEventDetailExtended flag value.

Example Get Response

```
<generalSettings>
  <agentEventDetailExtended>true</agentEventDetailExtended>
  <loginSession>
    <sessionInactivityTimeout>30</sessionInactivityTimeout>
  </loginSession>
</generalSettings>
```

Example Put Response

```
{
  "agentEventDetailExtended": false
}
```



CHAPTER 24

Internet Script Editor API

- [Internet Script Editor API, on page 83](#)

Internet Script Editor API

The Internet Script Editor API indicates whether Internet Script Editor is enabled. If Internet Script Editor is enabled in Web Setup, the API displays the download link in the format `https://<server>/install/iScriptEditor.exe`.

URL

`/internetscripteditor`

Operations

- `get`: Returns whether Internet Script Editor is enabled and a download link.

Parameters

- `enabled`: Indicates whether Internet Script Editor is enabled in Web Setup. True or false.
- `downloadLink`: The download link for Internet Script Editor. This link appears only when the `enabled` parameter is true.

Example Get Response

```
<internetScriptEditor>
  <enabled>true</enabled>
  <downloadLink>https://10.10.10.207/install/iScriptEditor.exe</downloadLink>
</internetScriptEditor>
```




CHAPTER 25

Machine Inventory API

- [Machine Inventory API](#), on page 85

Machine Inventory API

This API returns the machines in the solution.

URL

`https://<server>/unifiedconfig/config/machineinventory`

Operations

- **create**: Creates a machine by updating the database. See the following table for restrictions per machine type.
- **delete**: Removes one machine.
- **get**: Returns one machine and all associated addresses and services based on the machine ID, using the URL `https://<server>/unifiedconfig/config/machineinventory/<id>`.
- **list**: Retrieves a list of all machines in the inventory. See the following table for more details.
- **update**: Updates one machine.

Type	Create / Update / Delete operations allowed	Number allowed
CCE_ROUTER	No	0/1 Side A 0/1 Side B
CCE_PG	No	0/150 Side A 0/150 Side B
LIVE_DATA	All	0/1 Side A 0/1 Side B
PRIMARY_AW	All	0/2 Primary

Type	Create / Update / Delete operations allowed	Number allowed
SECONDARY_AW	All	0/2 Secondary
CLOUD_CONNECTOR_PUB	All	0-1
CLOUD_CONNECTOR_SUB	No	0-1

Parameters

Machine parameters:

- refURL: The refURL of the machine. See [Shared Parameters, on page 10](#).
- name: External name of the machine. For example, the VM hostname. See [Shared Parameters, on page 10](#).
- changeStamp: See [Shared Parameters, on page 10](#).
- type: The type of machine.
- autogenerated: Indicates if the information was generated automatically.
- hostName: The hostname of the machine.
 - If you provide a hostname, a lookup is performed to find the FQDN for that host. If the FQDN is found, the hostName field is then set to that FQDN value and the Machine Address is set to the IP address corresponding to the hostname.
 - If you do not provide a hostname, a lookup is performed using the address field in the API request. If the FQDN is found, the hostName field is set to that FQDN value.
- networks: A collection of network parameters. See the Network Parameters section.

Network parameters:

- type: Must be public.
- address: The IP address. Must be valid hostname, IPv4, or IPv6 address.
- services: A collection of service parameters. See the Services Parameters section.

Services parameters:

- port: The port for this service.
- username: The username used to access the service. Username maximum is 128 characters.
- password: The password used to access the service. The password can be used when creating or updating, but is not returned.
- description: The description of the service. See [Shared Parameters, on page 10](#).
- pairing: Indicates if services on different machines are related. Related services have a matching value. For the service type PRINCIPAL_AW, the pairing value is "false" for all AWs.
- type: The service type. Values for type are as follows:

- LIVE_DATA_API: Connection information for the Live Data Rest API. Requires a username and password.
- LIVE_DATA_CASSANDRA: Connection information for the Live Data Cassandra database.
- LIVE_DATA_WEB_SOCKETS: Connection information for the Live Data Socket.IO service.
- TIP_PG: LiveData connection information for peripheral gateways.
- TIP_ROUTER: LiveData connection information for the router.
- TIP_PG_TOS: LiveData test-other-side connection information for peripheral gateways.
- TIP_ROUTER_TOS: LiveData test-other-side connection information for the router.
- ACTIVE_MQ: LiveData Active MQ connection information.
- STORM_DRPC: LiveData Storm DRPC connection information.
- AW_REST_API: Administration & Data Server (AW) Rest API
- CLOUD_CONNECT_CREDINITIALS: Credinitial information for Cloud Connect Services.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description • hostName

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Update Request

https://<server>/unifiedconfig/config/machineinventory

```
<machine>
  <name>myLiveDataMachine</name>
  <hostName>liveDataHostName</hostName>
  <type>LIVE_DATA</type>
  <networks>
    <network>
      <type>PUBLIC</type>
      <address>1.2.3.4</address>
      <services>
        <service>
          <type>ACTIVE_MQ</type>
          <port>61616</port>
          <pairing>1</pairing>
        </service>
        <service>
          <type>STORM_DRPC</type>
          <port>3772</port>
          <pairing>1</pairing>
        </service>
      </services>
    </network>
  </networks>
</machine>
```

```

    <service>
      <type>LIVE_DATA_WEB_SOCKETS</type>
      <port>12008</port>
      <pairing>1</pairing>
    </service>
    <service>
      <type>LIVE_DATA_API</type>
      <port>12005</port>
      <pairing>1</pairing>
      <userName>user</userName>
      <password>password</password>
    </service>
    <service>
      <type>LIVE_DATA_CASSANDRA</type>
      <port>12000</port>
      <pairing>1</pairing>
    </service>
  </services>
</network>
</networks>
</machine>

```

Example Get Response

https://<server>/unifiedconfig/config/machineinventory/<id>

```

<machine>
  <changeStamp>3</changeStamp>
  <refURL>/unifiedconfig/config/machineinventory/5000</refURL>
  <networks>
    <network>
      <address>1.2.3.4</address>
      <services>
        <service>
          <autoGenerated>true</autoGenerated>
          <pairing>0</pairing>
          <port>40034</port>
          <type>TIP_ROUTER</type>
        </service>
        <service>
          <autoGenerated>true</autoGenerated>
          <pairing>0</pairing>
          <port>40035</port>
          <type>TIP_ROUTER_TOS</type>
        </service>
      </services>
      <type>PUBLIC</type>
    </network>
  </networks>
  <autoGenerated>true</autoGenerated>
  <hostName>routerA</hostName>
  <type>CCE_ROUTER</type>
  <name>routerA</name>
</machine>

```



CHAPTER 26

Media Routing Domain API

- [Media Routing Domain API, on page 89](#)

Media Routing Domain API

A media routing domain is a collection of skill groups associated with a common media class. It is used to organize how requests for different media are routed.

Use the Media Routing Domain (MRD) API to list the MRDs currently defined in the database, define new MRDs, and view, edit, and delete existing MRDs.

The built-in Cisco_Voice MRD and legacyMultichannel MRDs are read-only; they cannot be created, updated, or deleted. You can perform all API operations on multichannel MRDs.

URL

```
https://<server>/unifiedconfig/config/mediaroutingdomain
```

Operations

- **create**: Creates an MRD.
- **delete**: Permanently deletes one MRD.
- **list**: Retrieves a list of MRDs.
- **get**: Returns one MRD using the URL
`https://<server>/unifiedconfig/config/mediaroutingdomain/<id>`.
- **update**: Updates one MRD.

Parameters

- **refURL**: The refURL of the MRD. See [Shared Parameters, on page 10](#).
- **name**: Name of the MRD. See [Shared Parameters, on page 10](#).
- **description**: See [Shared Parameters, on page 10](#).
- **id**: The database id of the MRD. Read-only field.

- **type**: The type of MRD. Values are as follows:
 - **voice**: Used only for the built-in Cisco_Voice MRD. These MRDs are read-only.
 - **legacyMultichannel**: Used for MRDS for the Enterprise Chat and Email application. These MRDs are read-only.
 - **multichannel**: (Default) Used for MRDs for Task Routing APIs.
- **taskLife**: If the connection goes down, the amount of time, in seconds, that the system waits before ending all tasks. Default is 1200.
- **taskStartTimeout**: The amount of time, in seconds, that the system waits between an agent being selected for a task and an agent being offered or beginning the task. When this time is reached, the system makes the agent Not Routable. Default is 30.
- **maxTaskDuration**: The maximum duration for a task, in seconds. Default is 28800.
- **serviceLevelThreshold**: Maximum time in seconds that a customer should wait before being connected with an agent. Default is 30.
- **interruptible**: Indicates if an agent can be interrupted by assigned tasks from another MRD. Values are true/false.
- **maxTasksInQueue**: The maximum number of tasks allowed to be queued at one time.
- **maxTimeInQueue**: The maximum amount of time, in seconds, a task can be queued.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description • id 	<ul style="list-style-type: none"> • name (default) • description • id • interruptible • maxTasksInQueue • maxTaskDuration • maxTimeInQueue • serviceLevelThreshold • taskLife • taskStartTimeout

See [Search](#), on page 12 and [Sort](#), on page 13.

Advanced search parameters

You can perform a nonVoiceOnly search on the Media Routing Domain API:

- **nonVoiceOnly**: Set this attribute to true in the search query parameter to make the API return only media routing domains other than the Cisco_Voice MRD. For example, **q=nonVoiceOnly:true**.

Example Get Response

```
<mediaRoutingDomains>
  <mediaRoutingDomain>
    <changeStamp>0</changeStamp>
    <refURL>/unifiedconfig/config/mediaroutingdomain/5001</refURL>
    <description>Media channel for routing Chat tasks</description>
    <id>5001</id>
    <type>multichannel</type>
    <interruptible>false</interruptible>
    <taskLife>1200</taskLife>
    <taskStartTimeout>30</taskStartTimeout>
    <maxTaskDuration>28800</maxTaskDuration>
    <maxTasksInQueue>1000</maxTasksInQueue>
    <maxTimeInQueue>1000</maxTimeInQueue>
    <name>Chat_Task_MRD</name>
    <serviceLevelThreshold>30</serviceLevelThreshold>
  </mediaRoutingDomain>
  <mediaRoutingDomain>
    <changeStamp>0</changeStamp>
    <refURL>/unifiedconfig/config/mediaroutingdomain/1</refURL>
    <description>Default Media Routing Domain for Cisco_Voice</description>
    <id>1</id>
    <type>voice</type>
    <interruptible>false</interruptible>
    <taskLife>1200</taskLife>
    <taskStartTimeout>30</taskStartTimeout>
    <maxTaskDuration>28800</maxTaskDuration>
    <name>Cisco_Voice</name>
    <serviceLevelThreshold>30</serviceLevelThreshold>
  </mediaRoutingDomain>
</mediaRoutingDomains>
```

Topic 2.1



CHAPTER 27

Operation API

- [Operation API, on page 93](#)

Operation API

Use the Operation API to save changes to several items of the same type in a single request. The following changes are allowed in an operation:

- delete: Multiple items of the same type. Any item that supports the delete operation can be deleted using the Operation API.
- Agent update: Update multiple agents (available for supervisors and administrators).

URL

```
https://<server>/unifiedconfig/config/operation
```

HTTP Method

Use HTTP POST to submit a request to the Operation API.

Parameters

- operationType: Indicates if the items specified in the refURLs should be updated or deleted. Values are update/delete.
- refURLs: A collection of refURL parameters indicating which items are included in the request. See [Shared Parameters, on page 10](#).
- changeset: Includes the parameters that are changed in an update operation. See Agent Call API.
 - skillGroupsAdded
 - skillGroupsRemoved
 - attributesAdded
 - attributesRemoved
 - agentServicesToEnable: Indicates the Contact Center AI services to be enabled for a set of agents.

- `agentService`: The type of Contact Center AI service. Supported values are `AgentAnswers` and `Transcript`.
- `agentServicesToDisable`: Indicates the Contact Center AI service to be disabled for a set of agents.
 - `agentService`: The type of Contact Center AI service. Supported values are `AgentAnswers` and `Transcript`.

Example Delete Request

```
<operation>
  <operationType>delete</operationType>
  <refURLs>
    <refURL>/unifiedconfig/config/calltype/5000</refURL>
    <refURL>/unifiedconfig/config/calltype/5001</refURL>
  </refURLs>
</operation>
```

Example Update Request

```
<operation>
  <operationType>update</operationType>
  <refURLs>
    <refURL>/unifiedconfig/config/agent/5000</refURL>
    <refURL>/unifiedconfig/config/agent/5001</refURL>
  </refURLs>
  <changeSet>
    <agent>

      <agentServicesToEnable>
        <agentService>AgentAnswers</agentService>
        ....
      </agentServicesToEnable>
      <agentServicesToDisable>
        <agentService>Transcript</agentService>
        ....
      </agentServicesToDisable>

      <skillGroupsAdded>
        <skillGroup>
          <refURL>/unifiedconfig/config/skillgroup/6000</refURL>
        </skillGroup>
      </skillGroupsAdded>
      <skillGroupsRemoved>
        <skillGroup>
          <refURL>/unifiedconfig/config/skillgroup/6001</refURL>
        </skillGroup>
      </skillGroupsRemoved>
    </agent>
  </changeSet>
</operation>
```

Response Parameters

- `status`: Indicates the state of the operation.
 - `success`: The operation succeeded for all items.
 - `partialSuccess`: The operation succeeded for some items, but other items had errors.

- failure: The operation failed for all items.
- apiErrors: Errors indicate which items had errors and the cause of the error.

Example Success Response

The following example shows the response when the delete operation is successful:

```
<operationsResult>
  <status>success</status>
</operationsResult>
```

Example Partial Success Message

The following example shows a partial success response for a request to delete several agents:

```
<operationsResult>
  <apiErrors>
    <apiError>
      <errorDetail xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance" xsi:type=
        "resourceErrorDetail">
        <refURL>agent/1</refURL>
        <apiErrors>
          <apiError>
            <errorMessage>The specified ID does not exist
              in the database.</errorMessage>
            <errorType>notFound.dbData</errorType>
          </apiError>
        </apiErrors>
      </errorDetail>
      <errorMessage>There were one or more errors processing the following
        request: delete agent/1</errorMessage>
      <errorType>operation.resourceErrors</errorType>
    </apiError>
    <apiError>
      <errorDetail xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance" xsi:type=
        "resourceErrorDetail">
        <refURL>agent/2</refURL>
        <apiErrors>
          <apiError>
            <errorMessage>The specified ID does not exist
              in the database.</errorMessage>
            <errorType>notFound.dbData</errorType>
          </apiError>
        </apiErrors>
      </errorDetail>
      <errorMessage>There were one or more errors processing the following
        request: delete agent/2</errorMessage>
      <errorType>operation.resourceErrors</errorType>
    </apiError>
  </apiErrors>
  <status>partialSuccess</status>
</operationsResult>
```

Example Failure Response

The following example shows a failure response for a request to delete a call type that does not exist:

```
<operationsResult>
  <status>failure</status>
  <apiErrors>
    <apiError>
```

```

<errorDetail xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance" xsi:type=
"resourceErrorDetail">
  <refURL>/unifiedconfig/config/calltype/9999</refURL>
  <apiErrors>
    <apiError>
      <errorMessage>The specified ID does not exist in the database.</errorMessage>
      <errorType>notFound.dbData</errorType>
    </apiError>
  </apiErrors>
</errorDetail>
<errorMessage>There were one or more errors processing the following request:
delete /unifiedconfig/config
/calltype/9999</errorMessage>
<errorType>operation.resourceErrors</errorType>
</apiError>
</apiErrors>
</operationsResult>

```

Request Limit

Maximum 100 items are allowed in a request:

Example Request Limit Response

```

<operationsResult>
<apiErrors>
  <apiError>
    <errorMessage>The number of resources provided (101) exceeds the maximum number allowed
(100).</errorMessage>
    <errorType>operation.tooManyResources</errorType>
  </apiError>
</apiErrors>
<status>failure</status>
</operationsResult>

```



CHAPTER 28

Outbound API

Outbound API allows you to use REST APIs to create, modify, and delete Outbound Option campaigns.

Outbound API provides a streamlined mechanism for creating campaigns with a single associated query rule and import rule. As such, if you use the API to create a campaign, that campaign is not available in the Outbound Campaign tool. If a campaign was created with the API, you must use the API to view, edit, or delete it. If a campaign was created with the Outbound Campaign tool, you must use the Outbound Campaign tool to view, edit, or delete it.

Administrative scripts are not required for Outbound Option campaigns created with the Outbound API. If an administrative script is provided, the information in the script overrides the information defined in the API.

Outbound API consists of the following APIs:

- **Outbound Campaign API:** Use this API to define new Outbound Option campaigns, and to view, edit, or delete existing campaigns.
 - **Campaign Status API:** Use this API to get the real-time status of running Outbound Option campaigns.
 - **Do Not Call API:** Use this API to set the Do Not Call (DNC) import rule configuration for Outbound Option. This prevents the dialer from dialing numbers on the DNC list.
 - **Import API:** Use this API to import customer contact information for an Outbound Option campaign.
 - **Personal Callback API:** Use this API to configure your Outbound Option campaign to handle personal callbacks. You can create personal callback records individually or in bulk. You can also update or delete personal callback records.
 - **Time Zone API:** Use this API to list all available time zones and to get information about a specified time zone.
-
- [Outbound Campaign API, on page 98](#)
 - [Campaign Status API, on page 105](#)
 - [Do Not Call API, on page 107](#)
 - [Import API, on page 109](#)
 - [Personal Callback API, on page 113](#)
 - [Time Zone API, on page 118](#)

Outbound Campaign API

An Outbound Campaign makes outgoing calls to customers for a specific purpose or task and delivers these calls to agents.

Use the Outbound Campaign API to define new outbound campaigns, and to view, edit, or delete existing outbound campaigns.



Note In the Role API, when you enable the CampaignStatus or CampaignContact subfeature in the accessList parameter for a custom role then the Outbound Campaign API is provided with Update Only Access instead of Full Access. With Update Only Access, you cannot create and delete a campaign using Outbound Campaign API.

URL

`https://<server>/unifiedconfig/config/campaign`

Operations

- **create**: Creates one campaign and stores it in the database.
- **delete**: Deletes one campaign from the database. The campaign is saved under **Configuration Manager > Miscellaneous Tools > Deleted Objects**.

You can only delete campaigns that were created using the API. You cannot use the API to delete campaigns that were created in the Outbound Option Campaign tool.

- **list**: Retrieves a list of campaigns from the database. Only campaigns that were created using the Outbound Option API are retrieved. Campaigns created using the Outbound Option Campaign tool do not appear in the list.
- **get**: Returns one campaign from the database using the URL
`https://<server>/unifiedconfig/config/campaign/<id>`.

You must specify the ID for a campaign that was created using the API. If you specify the ID for a campaign created using the Outbound Option Campaign tool, the request returns `CceDBDataNotFoundException`.

- **update**: Updates one campaign in the database using the URL
`https://<server>/unifiedconfig/config/campaign/<id>`.

You can only update campaigns that were created using the API. You cannot use the API to update campaigns that were created in the Outbound Option Campaign tool.

Parameters

- **name**: Required. The name of the campaign. See [Shared Parameters, on page 10](#).
- **department**: A reference to the campaign's department, including the refURL and name. See [References, on page 7](#).
- **description**: Optional description for the campaign. See [Shared Parameters, on page 10](#).

- **linesPerAgent:** The number of lines dedicated to each agent in the campaign. Range is 1 to 100. Default is 1.5. This parameter performs as follows in the Outbound Option dialing modes:
 - Preview mode: Ignored (always 1).
 - Progressive mode: Used as defined.
 - Predictive mode: Used as an initial value.
- **maximumLinesPerAgent:** The upper bound for the number of customers the dialer dials for a reserved agent when a campaign is running in predictive mode. Range is 1 to 100. Default is 2.
- **abandonEnabled:** True or false. Default is true.
- **abandonPercent:** When enabled (`abandonEnabled` is set to true), you can set the abandoned calls limit for the percentage of abandoned calls in the campaign. When disabled (`abandonEnabled` is set to false), the campaign dials without regard to the abandon limit. Range is 1 to 100. The granularity is to one 10th of a percent. Default is 3.
- **predictiveCorrectionPace:** A count of the number of live voice connections that must occur before the Dialer adjusts. Increasing this number results in less frequent adjustments based on larger sample size. Decreasing this number results in more frequent adjustments using a smaller sample size. Range is 10 to 5000. Default is 70.
- **predictiveGain:** The size of the adjustment to lines per agent each time an adjustment is made. Increasing this number results in larger lines per agent adjustments. Decreasing this number results in smaller lines per agent adjustments. Range is 0.1 to 3.0. Default is 1.
- **noAnswerRingLimit:** The number of times the software allows a dialed phone number to ring. Range is from 2 to 10. Default is 4.
- **maxAttempts:** The maximum number of attempts, including callbacks and retries. Range is from 1 to 100. Default is 3.
- **minimumCallDuration:** Minimum duration (in seconds) of an outbound call. If the outbound call is less than the specified value, Outbound Option considers the call to be customer abandoned and schedules the record for a retry. To disable this feature, set the parameter to 0. Range is 0 to 10. Default is 1.
- **noAnswerDelay:** The time (in minutes) that the software waits before calling back a no-answer call. Range is 1 to 99999. Default is 60.
- **busySignalDelay:** The time (in minutes) that the software waits before calling back a busy phone number. Range is 1 to 99999. Default is 60.
- **customerAbandonedDelay:** If a customer abandons a call, the time (in minutes) that the Dialer waits before calling the customer back. Range is 1 to 99999. Default is 30.
- **dialerAbandonedDelay:** If the Dialer abandons a call, the time (in minutes) that the Dialer waits before calling the customer back. Range is 1 to 99999. Default is 60.
- **answeringMachineDelay:** If an answering machine answers a call, the time (in minutes) that the Dialer waits before calling the customer back. Range is 1 to 99999. Default is 60.
- **customerNotHomeDelay:** If a customer is not home, the time (in minutes) that the Dialer waits before calling the customer back. Range is 1 to 99999. Default is 60.

- **personalizedCallbackEnabled**: If enabled, this parameter allows an agent to schedule a callback to a customer for a specific date and time. A personal callback connects the same agent who initiated the callback to the customer. True or false. Default is false.
- **rescheduleCallbackMode**: Determines how Outbound Option handles a personal callback if the agent is not available. Default is `useCampaignDN`. Options are as follows:
 - Use campaign DN
 - Same time next business day
 - Abandon
- **campaignPurposeType**: The type of campaign. Default is `agentCampaign`. The options are as follows:
 - **Agent Campaign**: This type of campaign uses an outbound mode that causes the Dialer to transfer every customer call associated with a specific skill group to an agent.
 - **IVR Campaign**: This type of campaign uses an outbound mode that causes the Dialer to transfer every customer call associated with a specific skill group to a service control-based IVR instead of an agent. This option allows a contact center to run unassisted outbound campaigns using prerecorded messages in the IVR.
- **ipAmdEnabled**: When enabled, directs the Dialer to perform a specific action if it detects an answering machine. True or false. Default is true.
- **amdTreatmentMode**: If enabled (`ipAmdEnabled` is set to true), when the Dialer detects an answering machine, it does one of the following:
 - Abandon call (default)
 - Transfer to agent
 - Transfer to IVR route point
 - Terminate tone detect
- **ipTerminatingBeepDetect**: When this parameter is set to true, the Dialer transfers the call after detecting the answering machine beep. True or false. Default is false.
- **timeZone**: Required. The refURL and display name for the selected time zone. The default time zone is UTC (Universal Coordinated Time). The display name is the text that may be displayed in a user interface and can be localized.



Note If time zone information changed due to periodic updates and the campaign's configured time zone is no longer valid, the following information is returned:

```
<timeZone>
  <refURL>/unifiedconfig/config/timezone/INVALID</refURL>
  <displayName>INVALID Time Zone</displayName>
</timeZone>
```

- **startTime**: The time the campaign starts dialing customer numbers. The format for this parameter is hours:minutes. Range is from 00:00 to 23:59. The default value is taken from the `Blended_Agent_Options` table column values for `DialStartHours` and `DialStartMinutes`.
- **endTime**: The time the campaign stops dialing customer numbers. The format for this parameter is hours:minutes. Range is from 00:00 to 23:59. The default value is taken from the `Blended_Agent_Options` table column values for `DialEndHours` and `DialEndMinutes`.
- **enabled**: Whether the dialer is available to call contacts. True or false. Default is false.
- **startDate**: The date that the campaign starts. The format is YYYY-MM-DD.
- **endDate**: The date that the campaign ends. The format is YYYY-MM-DD.
- **campaignPrefix**: Digits to prefix to each customer number dialed from this campaign. Maximum length of 15 digits.
- **dialingMode**: The dialing mode to use for the campaign skill groups. Valid values are as follows:
 - INBOUND
 - PREDICTIVEONLY
 - PREVIEWONLY
 - PROGRESSIVEONLY
 - PREVIEWDIRECTONLY
- **reservationPercentage**: The percentage of agents to reserve within the skill groups associated with the campaign. Range is from 0 to 100. Default is 100.
- **callProgressAnalysis**: A collection of parameters for Call Progress Analysis (CPA). Any combination of parameters within this collection can be set. If none of the parameters are provided and CPA is enabled for the campaign by default, CPA recording is set to false and default parameter values are set from the `Blended_Agent_Options` table.
 - **enabled**: When set to false, CPA for all calls made from this Dialer is disabled on a campaign-by-campaign basis, including voice detection, fax/modem detection, and answering machine detection. True or false. Default is true.
 - **record**: If enabled is set to true, you can specify this parameter. If you set it to true, the gateway provides a media stream and the Dialer records .wav files. True or false. Default is false.
 - **minSilencePeriod**: The minimum silence period (in milliseconds) required to classify a call as voice detected. If many answering machine calls are being passed through to agents as voice, then increasing this value accounts for longer pauses in answering machine greetings. Range is from 100 to 1000. Default is 608.
 - **analysisPeriod**: The number of milliseconds spent analyzing this call. If there is a short agent greeting on an answering machine, then a longer value categorizes that answering machine call as voice. If the call is to a business where the operator has a longer scripted greeting, a shorter value categorizes the long, live greeting as an answering machine call. Range is from 1000 to 10000. Default is 2500.
 - **minimumValidSpeech**: Minimum number of milliseconds of voice required to classify a call as voice detected. Range is 50 to 500. Default is 112.

- **maxTimeAnalysis**: The maximum number of milliseconds allowed for analysis before identifying a problem analysis as dead air/low volume. Range is 1000 to 10000. Default is 3000.
- **maxTermToneAnalysis**: The maximum number of milliseconds the dialer analyzes an answering machine voice message looking for a termination tone. If the message has an odd tone and the analysis does not recognize it, the call is not transferred or dropped until this timeout occurs. Range is 1000 to 60000. Default is 30000.
- **skillGroupInfos**: A collection of information about the skill groups associated with the campaign.
 - **skillGroupInfo**: A collection of information about one skill group.
 - **skillGroup**: The name and the refURL of the skill group assigned to the campaign.
 - **overflowAgents**: This parameter ensures that at least one extra agent is reserved before the dialer begins dialing for a Progressive campaign. If the parameter is set to 1, at least two agents must be reserved before the dialer begins dialing. Range is 0 to 100. Default is 0.
 - **dialedNumber**: The digits that are dialed to reserve an agent in the configured skill group. This parameter can contain letters, numbers, periods (.), and underscores (_) and can be up to ten characters in length.
 - **recordsToCache**: The minimum number of dialing numbers that each dialer caches for each of the Outbound Option skill groups. Range is 1 to 400. Default is 1.
 - **ivrPorts**: The total number of IVR ports allocated for the skill group. This parameter indicates how many ports are available for the dialer to transfer customer calls. Because this value indicates the total number of ports supported by the IVR for the current skill group, multiple skill groups can make transfer to IVR calls. One IVR can also be used to play different messages based on the route point where the contact is transferred. If multiple dialers are associated with the skill group, each dialer dials a fraction of the total number of ports. Default is 0.
 - **ivrRoutePoint**: If the campaign is a Transfer to IVR campaign or is configured to transfer AMD calls to an IVR, this parameter indicates the route point required to run the transfer to IVR routing script. This parameter must coincide with a route point configured on Unified Communications Manager and be assigned to a PGUser. Contacts are transferred to the route point, which points to a routing script. The script transfers the call to an IVR. Maximum length of 32 characters.
 - **abandonedRoutePoint**: If the campaign is a Transfer to IVR campaign or is configured to transfer AMD calls to an IVR, this number allows the dialer to play a message to calls about to be disconnected because no agents are available. This number must coincide with a route point configured on Unified Communications Manager and be assigned to the agent PG's CTI application (for example, PGUser). Contacts are transferred to this route point, which points to a routing script. The script transfers the call to an IVR. Maximum length of ten characters.
- **skillGroupInfosAdded**: A collection of skill group references to be added to the campaign, including the skill group refURL. This parameter is update only. This parameter can be used with the **skillGroupInfosRemoved** parameter. See [References, on page 7](#).
- **skillGroupInfosRemoved**: A collection of skill group references to be removed from the campaign, including the skill group refURL of each skill group. This parameter is update only. This parameter can be used with the **skillGroupInfosAdded** parameter. See [References, on page 7](#).

Search and Sort Parameters

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description

See [Search](#), on page 12 and [Sort](#), on page 13.

Disable All Campaigns (Emergency Stop)

The Outbound Campaign API provides a method to immediately disable all outbound campaigns that are currently enabled. To disable all of the campaigns, perform a PUT on the following URL:

`https://<server>/unifiedconfig/config/campaign/disable`

This request retrieves a list of all campaigns created using the Outbound Campaign API that are currently enabled and sets the enabled parameter to false. The Campaign Manager stops sending out records to the Dialer for these campaigns. All active records in the Dialer's memory are removed.

Example Get Response

```
<campaign>
<department>
  <refURL>/unifiedconfig/config/department/5001</refURL>
  <name>Sales</name>
</department>
<changeStamp>48</changeStamp>
<refURL>/unifiedconfig/config/campaign/5168</refURL>
<import>
  <refURL>/unifiedconfig/config/import/5000</refURL>
</import>
<abandonEnabled>true</abandonEnabled>
<abandonPercent>3.0</abandonPercent>
<amdTreatmentMode>abandonCall</amdTreatmentMode>
<campaignPrefix>978</campaignPrefix>
<campaignPurposeType>agentCampaign</campaignPurposeType>
<dialingMode>PREVIEWONLY</dialingMode>
<enabled>true</enabled>
<endDate>2016-01-15</endDate>
<endTime>17:00</endTime>
<ipAMDEnabled>true</ipAmdEnabled>
<ipTerminatingBeepDetect>>false</ipTerminatingBeepDetect>
<linesPerAgent>1.5</linesPerAgent>
<maxAttempts>3</maxAttempts>
<maximumLinesPerAgent>100.0</maximumLinesPerAgent>
<minimumCallDuration>1</minimumCallDuration>
<name>APIoct1</name>
<noAnswerRingLimit>4</noAnswerRingLimit>
<personalizedCallbackEnabled>>false</personalizedCallbackEnabled>
<predictiveCorrectionPace>70</predictiveCorrectionPace>
<predictiveGain>1.0</predictiveGain>
<rescheduleCallbackMode>useCampaignDN</rescheduleCallbackMode>
<reservationPercentage>100</reservationPercentage>
<retries>
  <answeringMachineDelay>60</answeringMachineDelay>
  <busySignalDelay>60</busySignalDelay>
```

```

        <customerAbandonedDelay>30</customerAbandonedDelay>
        <customerNotHomeDelay></customerNotHomeDelay>
        <dialerAbandonedDelay>60</dialerAbandonedDelay>
        <noAnswerDelay>60</noAnswerDelay>
    </retries>
    <skillGroupInfos>
    <skillGroupInfo>
        <ivrPorts>0</ivrPorts>
        <overflowAgents>0</overflowAgents>
        <recordsToCache>1</recordsToCache>
        <abandonedRoutePoint>12345</abandonedRoutePoint>
        <dialedNumber>123</dialedNumber>
        <ivrRoutePoint>91234</ivrRoutePoint>
        <skillGroup>
            <refURL>/unifiedconfig/config/skillgroup/5004</refURL>
            <name>errorDetailsRouteScript</name>
        </skillGroup>
    </skillGroupInfo>
    </skillGroupInfos>
    <startDate>2016-01-14</startDate>
    <startTime>09:00</startTime>
    <timeZone>
        <displayName>(UTC-05:00) Eastern Time (US & Canada)</displayName>
        <refURL>/unifiedconfig/config/timezone/Eastern%20Standard%20Time</refURL>
    </timeZone>
    <callProgressAnalysis>
        <enabled>true</enabled>
        <record>false</record>
        <minSilencePeriod>608</minSilencePeriod>
        <analysisPeriod>2500</analysisPeriod>
        <minimumValidSpeech>112</minimumValidSpeech>
        <maxTimeAnalysis>3000</maxTimeAnalysis>
        <maxTermToneAnalysis>30000</maxTermToneAnalysis>
    </callProgressAnalysis>
</campaign>

```

Example Create Request

```

<campaign>
<department>
    <refURL>/unifiedconfig/config/department/5001</refURL>
    <name>Sales</name>
</department>
<name>APIOct1</name>
<description>APIOct1</description>
<dialingMode>PREVIEWONLY</dialingMode>
<skillGroupInfos>
    <skillGroupInfo>
        <ivrPorts>0</ivrPorts>
        <overflowAgents>0</overflowAgents>
        <recordsToCache>1</recordsToCache>
        <skillGroup>
            <refURL>/unifiedconfig/config/skillgroup/5001</refURL>
            <name>sgcampaign</name>
        </skillGroup>
    </skillGroupInfo>
</skillGroupInfos>
<timeZone>
    <refURL>/unifiedconfig/config/timezone/UTC</refURL>
</timeZone>
<callProgressAnalysis>
    <enabled>true</enabled>

```

```
<record>false</record>
<minSilencePeriod>608</minSilencePeriod>
<analysisPeriod>2500</analysisPeriod>
<minimumValidSpeech>112</minimumValidSpeech>
<maxTimeAnalysis>3000</maxTimeAnalysis>
<maxTermToneAnalysis>30000</maxTermToneAnalysis>
</callProgressAnalysis>
</campaign>
```

Campaign Status API

Use the Campaign Status API to get the real-time status of running Outbound Option campaigns.

URL

`https://<server>/unifiedconfig/config/campaign/<campaign-id>/runtimestats`



Note You must specify the ID for a campaign that was created using the Outbound Campaign API (see [Outbound Campaign API, on page 98](#)). If you specify the ID for a campaign created using the Outbound Option Campaign tool, the request returns `CceDBDataNotFoundException`.

Operations

- `get`: Returns the runtime status of a campaign.

Response Parameters

- `abandonDetectCount`: The number of calls abandoned by the dialer.
- `abandonToIvrCount`: The number of calls that were abandoned by the dialer and transferred to IVR.
- `agentClosedCount`: The number of preview and callback calls that were closed by the agent.
- `agentRejectedCount`: The number of preview and callback calls that were rejected by the agent.
- `answeringMachineCount`: The number of calls that detected an answering machine.
- `attemptedCount`: Summary total of the number of calls attempted.
- `busyCount`: The number of calls that detected a busy signal.
- `callBackCount`: The number of callback contacts.
- `cancelledDetectCount`: The number of calls where the dialer canceled a ringing customer call.
- `closedCount`: The number of contacts closed for any reason other than reaching a live customer.
- `customerAbandonDetectCount`: The number of calls where the customer hung up immediately after picking up the phone.
- `customerNotHomeCount`: The number of contacts where the party who answered the phone was not the customer.

- **dateTime:** The date and time when this data was updated last. The format is yyyy-MM-ddTHH:mm:ss (for example, 2016-03-13T04:50:31).
- **faxDetectCount:** The number of calls that detected a fax machine.
- **networkAnsMachineCount:** The number of calls that detected a network answering machine.
- **noAnswerDetectCount:** The number of calls that were not answered.
- **noDialToneDetectCount:** The number of calls that did not detect a dial tone.
- **noRingBackDetectCount:** The number of calls that did not detect a ring back.
- **personalCallbackCount:** The number of callback contacts scheduled.
- **sitToneDetectCount:** The number of calls that detected a special information tone (SIT).
- **talkTimeCount:** The total number of seconds that agents spent talking on the phone since midnight.
- **totalCount:** The total number of records available to dial for the current campaign.
- **totalVoiceCount:** The number of live customers that have been reached for this campaign since the last time the imported dialing list was overwritten.
- **voiceCount:** The number of calls for the day that ended in successful customer contact.
- **wrapupTimeCount:** The number of seconds that agents spent in wrap-up mode since midnight.
- **wrongNumberCount:** The number of contacts where the party who answered the phone indicated that the customer did not live there.

Example Get Response

```
<runtimeStatus>
  <abandonDetectCount>0</abandonDetectCount>
  <abandonToIvrCount>0</abandonToIvrCount>
  <agentClosedCount>0</agentClosedCount>
  <agentRejectedCount>0</agentRejectedCount>
  <answeringMachineCount>0</answeringMachineCount>
  <attemptedCount>1</attemptedCount>
  <busyCount>0</busyCount>
  <callBackCount>0</callBackCount>
  <cancelledDetectCount>0</cancelledDetectCount>
  <closedCount>0</closedCount>
  <customerAbandonDetectCount>0</customerAbandonDetectCount>
  <customerNotHomeCount>0</customerNotHomeCount>
  <dateTime>2016-01-15T13:43:00</dateTime>
  <faxDetectCount>0</faxDetectCount>
  <networkAnsMachineCount>0</networkAnsMachineCount>
  <noAnswerDetectCount>0</noAnswerDetectCount>
  <noDialToneDetectCount>0</noDialToneDetectCount>
  <noRingBackDetectCount>0</noRingBackDetectCount>
  <personalCallbackCount>0</personalCallbackCount>
  <sitToneDetectCount>0</sitToneDetectCount>
  <talkTimeCount>1</talkTimeCount>
  <totalCount>0</totalCount>
  <totalVoiceCount>1</totalVoiceCount>
  <voiceCount>1</voiceCount>
  <wrapupTimeCount>0</wrapupTimeCount>
  <wrongNumberCount>0</wrongNumberCount>
</runtimeStatus>
```

Do Not Call API

Use the Do Not Call API to set the Do Not Call (DNC) import rule configuration for Outbound Option so that the campaign dialer doesn't dial the numbers in the DNC list.

The DNC import is automatically scheduled to start when the file is available. After the import is complete, the file is RENAMED or DELETED based on the boolean value for the renameFileAfterImport field.

URL

`https://<server>/unifiedconfig/config/dnc`

Operations

- **create**: Sets the configuration in the database. Returns the refURL if the configuration is set.
- **delete**: Deletes the specific DNC configuration using the URL `https://<server>/unifiedconfig/config/dnc/<id>`. This does not delete the DNC import file that is present at the location of the filePath.
- **list**: Retrieves a list available DNC import rules.
- **get**: Returns the DNC import configuration from the database using the URL `https://<server>/unifiedconfig/config/dnc/<id>`.
- **update**: Updates the specific DNC import configuration with the new values using the URL `https://<server>/unifiedconfig/config/dnc/<id>`.

Parameters

- **name**: Name of the DNC import. See [Shared Parameters, on page 10](#).
- **filePath**: Path to a file on the logger or accessible from the logger. Maximum length of 255 characters.
- **overwrite**: Whether the new DNC import overwrites the phone numbers from the previous DNC import. True or false. Default is false.
- **renameFileAfterImport**: Whether to delete the DNC import file after the import is complete. True or false. Default is true. If the parameter is set to true, the DNC file is renamed. If the parameter is set to false, the DNC import file is deleted.

Search and Sort Parameters

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name 	<ul style="list-style-type: none"> • name

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```
<dnc>
  <refURL>/unifiedconfig/config/dnc/unifiedconfig/config/dnc/5001</refURL>
  <name>dnc1</name>
  <filePath>\\CCE-ROGGER-A\C$\Users\boston\Desktop\dnc.txt</filePath>
  <overwrite>>false</overwrite>
  <renameFileAfterImport>>true</renameFileAfterImport>
</dnc>
```

Create Do Not Call List

When creating a Do_Not_Call list file, format it correctly using the following instructions.

Procedure

-
- Step 1** Using a text editor, create a text file that contains all the do-not-call phone numbers.
- Step 2** Enter a phone number for each Do Not Call entry on a new line.
- Step 3** Observe the following characteristics for each Do Not Call entry:
- Each phone number can be a maximum of 20 characters long.
 - The Do Not Call table can support up to 60 million entries, but note that the information is stored in memory in the Campaign Manager process.
 - Each Do Not Call entry uses 16 bytes of memory. So, 60 million entries requires approximately 1 GB of memory on the Logger Side A platform.
- Step 4** Save the text file to the local server.
-

The following is an example of a Do_Not_Call list:

```
2225554444
2225556666
2225559999
```

To add a customer to this list, import a Do Not Call list.

The Campaign Manager reads from the Do_Not_Call table. Dialing List entries are marked as Do Not Call entries only when the Campaign Manager fetches the Dialing List entry *and only when there is an exact, digit-for-digit match*. This allows Do Not Call imports to happen while a Campaign is running without rebuilding the Dialing List.



Note If the Dialing List includes a base number plus extension, this entry must match a Do Not Call entry for that same base number and same extension. The dialer will not dial the extension.

When the Campaign Manager starts it automatically imports from the DoNotCall.restore file that is stored in the <drive>\icm\<instance>\la\bin directory. When reading Do Not Call import files, the Campaign Manager

appends the data to the DoNotCall.restore file. This restore file allows recovery of Do Not Call records after the Campaign Manager stops unexpectedly or for planned maintenance, such as a Service Release installation.

The restore file can grow to approximately 1 GB if 60 million DNC records are imported, each having ten-digit numbers plus five-digit extensions. Sufficient disk space must be available on LoggerA to store the DoNotCall.restore file.



Note To clear the Do Not Call list, import a blank file with the Overwrite table option enabled.

Import API

Use the Import API to import customer contact information for an outbound campaign. You can import up to 10,000 records in one create request.



Note

- You can queue up to 30 requests. If the queue has 30 requests and you submit another request, the response is HTTP 503 Service Unavailable with the boundary error condition "Request processing queue is at capacity."

If you receive this error, wait until a few requests are processed and submit the next request when the queue has less than 30 requests.

If a particular integration is doing multiple small inserts per second for a campaign and this error appears, it is more efficient to batch up the records into larger imports.

- Avoid performing a bulk job transaction during a maintenance window.
 - Only administrators can use the Import API. For this reason, Import API user roles are authorized with the Active Directory, and the local cache is updated every 30 minutes (the interval cannot be modified).
-

URL

```
https://<server>/unifiedconfig/config/campaign/<id>/import
```



Note You must specify the ID for a campaign that was created using the Outbound Campaign API. If you specify the ID for a campaign created using the Outbound Option Campaign tool, the request returns CceDBDataNotFoundException.

Operations

- **create**: Imports customer contacts for a specific campaign.
- **delete**: Deletes the imported contacts for a specific campaign.



Note The delete operation deletes all imported contacts for the campaign. You cannot delete an individual record.

- **get** (template): Returns a sample CSV template for contacts, which is provided by the API, using the URL `https://<server>/unifiedconfig/config/campaign/import/template`. The response contains the CSV template as a file attachment.
- **get**: Retrieves the details of a single import record using the URL `https://<server>/unifiedconfig/config/campaign/<campaignId>/import/<id>`. The `<id>` is the ID of the imported contact.
- **list**: Retrieves a list of all imported contacts for the campaign.
 - **Query parameters**
 - Summary list: See [list, on page 2](#).

Parameters

Response Parameters for get:

- **accountNumber**: The customer's account number.
- **callsMade**: The number of calls made.
- **callStatus**: The call status of the last call placed for this record. Possible values include the following:
 - active (A)
 - callbackRequested (B)
 - closed (C)
 - agentRejected (J)
 - maxAttemptsReached (M)
 - pending (P)
 - retry (R)
 - personalCallbackRequested (S)
 - unknown (U)

For more information about these values, see the *CallStatusZone Values* section of the *Outbound Option Guide for Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-user-guide-list.html>.

- **callResultOverall**: The call result from the last call placed for this record.
- **firstName**: The customer's first name.
- **lastName**: The customer's last name.
- **importDate**: The date and time that the record was imported.

- phone01 through phone10: A collection of information about the customer's phones. Each phone contains the following parameters:

- number: The phone number.
- callResult: The call result from the last call placed for this phone number.

For more information about possible callResult values, see the CallResult Codes and Values section of the *Outbound Option Guide for Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-user-guide-list.html>.

- dstObserved: Whether DST is observed for this phone's location. True or false.
- gmtOffset: The number of minutes that the customer's time zone is offset from GMT. When you create import records, you can optionally provide a TimeZoneBias. The TimeZoneBias parameter represents the way information about time zones is stored in the Windows registry. You can use the following formula to convert TimeZoneBias to gmtOffset:

```
if timeZoneBias is positive:
    gmtOffset = 1440 - timeZoneBias (where 1440 is the number of minutes in 24
hours)
else if timeZoneBias is negative:
    gmtOffset = -1 * timeZoneBias
else if timeZoneBias is 0
    gmtOffset = timeZoneBias
```

Parameters for create:

- fileContent: Required. Comma-separated or pipe-separated list of data embedded within a CDATA section.
- overwriteData: True or false. If set to true, the existing import data in the database is overwritten by the new import data. If set to false, the new import data is appended to the existing data. Default is false.



Note You cannot modify or remove existing fields or append a new field to existing data.

- delimiter: Comma (,) or pipe (|). Default is comma (,).
- header fields: The following header fields are allowed:
 - AccountNumber: Can contain any characters, including internationalized characters, except the delimiter specified in the input XML. Maximum length of 30 bytes.
 - FirstName: Can contain any characters, including internationalized characters, except the delimiter specified in the input XML. Maximum length of 50 characters.
 - LastName: Can contain any characters, including internationalized characters, except the delimiter specified in the input XML. Maximum length of 50 characters.
 - Phone01 through Phone10: Can contain digits 0-9, pound sign (#), and asterisk (*). Maximum length of 20 bytes. At least one Phone field is required.
 - TimeZoneBias: Specifies the offset of the customer's time zone from UTC in minutes. Integer. Range is from -780 to 720 (-13 to 12 hours from UTC).

- DstObserved: Specifies whether DST is observed for the customer's location. True or false. Default is false.



Note If the TimeZoneBias parameter is provided but the DstObserved parameter is not, DstObserved is set to false. If the DstObserved parameter is provided but not TimeZoneBias, a validation error is returned.

If TimeZoneBias is not provided, time zone and Daylight Saving Time information is assigned by matching phone numbers to region prefix strings. If a phone number for a contact does not match a configured region prefix, the default time zone for the campaign is used.

If a customer record contains multiple phone numbers, the value for TimeZoneBias and DstObserved are applied to all of that customer's phone numbers.

You can use the Time Zone API to look up the values for TimeZoneBias and DstObserved for the target time zone. For more information, see [Time Zone API, on page 118](#).

Search and Sort

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • accountNumber • firstName • lastName 	<ul style="list-style-type: none"> • accountNumber (default) • firstName • lastName

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```
<importContact>
  <refURL>/unifiedconfig/config/campaign/5000/import/1</refURL>
  <accountNumber>4019</accountNumber>
  <callsMade>1</callsMade>
  <callStatus>pending</callStatus>
  <callResultOverall>0</callResultOverall>
  <firstName>Mir</firstName>
  <lastName>Ali</lastName>
  <importDate>2016-03-28T01:09:40</importDate>
  <phone01>
    <callResult>0</callResult>
    <dstObserved>true</dstObserved>
    <gmtOffset>720</gmtOffset>
    <number>9789360001</number>
  </phone01>
  <phone02>
    <callResult>0</callResult>
    <dstObserved>true</dstObserved>
    <gmtOffset>720</gmtOffset>
</importContact>
```

```

        <number>9789360002</number>
    </phone02>
    <phone03>...</phone03>
    <phone04>...</phone04>
    <phone05>...</phone05>
    <phone06>...</phone06>
    <phone07>...</phone07>
    <phone08>...</phone08>
    <phone09>...</phone09>
    <phone10>
        <callResult>0</callResult>
        <dstObserved>true</dstObserved>
        <gmtOffset>330</gmtOffset>
        <number>9789360010</number>
    </phone10>
</importContact>

```

Example Create Request

```

<import>
  <fileContent>
    <![CDATA[
      AccountNumber,FirstName,LastName,Phone01,Phone02,TimeZoneBias,DstObserved
      6782,Henry,Martin,2225554444,2225556262,720,false
      3456,Michele,Smith,2225559999,2225551234,540,true
      4569,Walker,Evans,2225552000,2225557890,-600,true
    ]]>
  </fileContent>
  <delimiter>,</delimiter>
</import>

```

Personal Callback API

Use the Personal Callback API to configure your Outbound Option campaign to handle personal callbacks. The Personal Callback feature allows an agent to schedule a callback to a customer for a specific date and time.

URL

<https://<server>/unifiedconfig/config/personalcallback>

Operations

- **create**: Creates a single PersonalCallback record and stores it in the BA database.
- **create** (bulk): Creates PersonalCallback records in bulk and stores them in the BA database using the URL <https://<server>/unifiedconfig/config/personalcallback/import>.
- **delete**: Deletes one or more PersonalCallback records from the PersonalCallback list using the URL <https://<server>/unifiedconfig/config/personalcallback/<id>>.
- **get** (template): Retrieves a sample CSV template for contacts, which is provided by the API, using the URL <https://<server>/unifiedconfig/config/personalcallback/template>.
- **get** (record): Retrieves one PersonalCallback record from the database using the URL <https://<server>/unifiedconfig/config/personalcallback/<id>>.

- **list**: Retrieves a list of PersonalCallback records from the database.
 - **Query parameters:**
 - agentId
 - accountNumber
 - firstName
 - lastName
- **update**: Updates one PersonalCallback record in the database using the URL `https://<server>/unifiedconfig/config/personalcallback/<id>`.

Parameters

Parameters for create (single record), get, and update operations:

- **campaign**: A reference to a specific campaign, including the refURL and campaign ID.
- **agent**: A reference to a specific agent, including the refURL and agent ID.
- **campaignId**: Read only. The ID for the campaign.
- **peripheralId**: Read only. ID for the peripheral on which the agent would be available.
- **agentId**: Read only. ID of the agent to whom to connect the call.
- **campaignDn**: The Dialed Number (DN) to use if the original agent is not available.
- **phone**: Required. The phone number to call back. Can contain digits 0 to 9, pound sign (3), and asterisk (*). Maximum length of 20 bytes.
- **accountNumber**: The customer's account number. Internationalized characters are allowed. Maximum length of 30 bytes.
- **maxAttempts**: Required. The maximum number of times to attempt a call (decrements at each attempt). An attempt is the Dialer's attempt to reserve the agent and call the customer. Because the Dialer places multiple customer call attempts (such as busy, no answer), individual call attempts are not tracked here; only the result at the end of the callback time range. After this parameter is set to 0, no more attempts are made. Must be a positive integer value.
- **callbackDateTime**: Required. The time to attempt the customer callback is normalized to the logger GMT zone. For example, the Campaign Manager is in Boston and the customer is in California. The customer wants to be called back at 3 p.m. The time in this column is 6 p.m. The format for this parameter is yyyy-MM-ddTHH:mm:ss (for example, 2016-03-13T04:50:31).

The following rules apply to the callbackDateTime parameter:

- The callbackDateTime that is used is local to the time zone of the Logger. You need to consider this if the client machine on which you are using this API is in a different time zone than the Logger machine.
- The setting of the callbackDateTime by this API reads the CallbackDateTimeLimit in the registry. For more information, see the Registry Settings section of the *Outbound Option Guide for Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-user-guide-list.html>.

- The Campaign Manager uses the `CallbackDateTimeLimit` registry value to select Personal Callback records to queue to the Dialer.
 - The default `CallbackDateTimeLimit` in the registry is 15 minutes. For create and update operations, you cannot set the `callbackDateTime` to 15 minutes or more before the current time. For example, if it is currently 4:00, you cannot set the `callbackDateTime` to 3:30.
 - For update operations, the new `callbackDateTime` value can only be set if the current `callbackDateTime` is 15 minutes or more after the current Logger time. For example, if the current Logger time is 4:00 and the current `callbackDateTime` is 4:30, the new `callbackDateTime` can be set to 4:10. However, if the current `callbackDateTime` is 4:10, it cannot be set to 4:00.
- `callStatus`: The status of the personal callback. Possible values include the following:
 - active (A)
 - `callbackRequested` (B)
 - closed (C)
 - `agentRejected` (J)
 - `maxAttemptsReached` (M)
 - pending (P)
 - retry (R)
 - `personalCallbackRequested` (S)
 - unknown (U)
 - `agentNotAvailable` (X)

For more information about these values, see the `CallStatusZone Values` section of the *Outbound Option Guide for Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-user-guide-list.html>.

- `callResult`: Read only. Corresponds to the `CallResult` value in the `Dialer_Detail` table.
For more information about possible `callResult` values, see the `CallResult Codes and Values` section of the *Outbound Option Guide for Unified Contact Center Enterprise* at <https://www.cisco.com/c/en/us/support/customer-collaboration/unified-contact-center-enterprise/products-user-guide-list.html>.
- `lastName`: The customer's last name. Internationalized characters are allowed. Maximum length of 50 characters.
- `firstName`: The customer's first name. Internationalized characters are allowed. Maximum length of 50 characters.

Bulk parameters:

- `fileContent`: Comma-separated or pipe-separated list of data embedded within a CDATA section.
- `overwriteData`: True or false. If set to true, the existing personal callback data in the database is overwritten by the new personal callback data. If set to false, the new personal callback data is appended to the existing data. Default is false.



Note You cannot modify or remove existing fields or append a new field to existing data.

If overwriteData is set to true, any agent scheduled personal callback records are also overwritten.



Note Avoid performing a bulk job transaction during a maintenance window.

- delimiter: Comma (,) or pipe (|). Default is comma (,).

Bulk fileContent parameters:



Note The descriptions for these parameters are the same as the descriptions for the parameters for create (single record), get, and update operations. Only the case is different.

- CampaignId (must be a valid campaign ID in the database)
- AgentSkillTargetId (must be a valid SkillTargetID in the database)
- CampaignDn
- Phone
- AccountNumber
- MaxAttempts
- CallbackDateTime
- LastName
- FirstName

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • agentId • accountNumber • firstName • lastName 	<ul style="list-style-type: none"> • agentId • accountNumber • firstName • lastName

See [Search](#), on page 12 and [Sort](#), on page 13.

Advanced search parameters

There are several advanced searches you can perform on the Personal Callback API, including agentId, accountNumber, firstName, and lastName. All search terms are case-insensitive.

- **agentId:<ID>** finds all personal callback records where the agent ID contains a specified ID. For example, **agentId:123** returns all records where the agent ID contains the string "123".
- **lastName:<name>** finds all personal callback records where the last name contains the specified name. For example, **lastName:smith** returns all records where the last name includes "smith".
- **firstName:<name>** finds all personal callback records where the firstName contains the specified name. For example, **firstName:John** returns all records where the first name includes "john".
- **accountNumber:<number>** finds all personal callback records where the accountNumber contains the specified number. For example, **accountNumber:456** returns all records where the account number includes "456".

Example Create Request (Single Record)

```
<personalCallback>
  <campaign>
    <refURL>/unifiedconfig/config/campaign/5000</refURL>
  </campaign>
  <agent>
    <refURL>/unifiedconfig/config/agent/5050</refURL>
  </agent>
  <campaignDn>222222</campaignDn>
  <phone>999333</phone>
  <accountNumber>23334343334</accountNumber>
  <maxAttempts>1</maxAttempts>
  <callbackDateTime>2016-01-15T11:37:00</callbackDateTime>
  <callStatus>pending</callStatus>
  <lastName>Kumar</lastName>
  <firstName>Akshaya</firstName>
</personalCallback>
```

Example Create Request (Bulk)

```
<personalCallback>
  <fileContent>
    <![CDATA[
      AccountNumber,FirstName,LastName,Phone,AgentSkillTargetId,CampaignId,CampaignDn,
      CallbackDateTime,MaxAttempts
      6782,Henry,Martin,2225554444,1004,5000,2222222221,2016-01-25T05:12:00,1
      3444,Thomas,Edison,2225554555,1004,5000,2222222222,2016-01-25T05:23:00,1
      5444,Tom,Hilfiger,2225554666,1004,5000,2222222223,2016-01-25T05:37:00,1
    ]]>
  </fileContent>
</personalCallback>
```

Example Get (Record) Response

```
<personalCallback>
  <changeStamp>48</changeStamp>
  <refURL>/unifiedconfig/config/campaign/personalcallback/2</refURL>
  <campaign>
    <refURL>/unifiedconfig/config/campaign/5000</refURL>
  </campaign>
  <agent>
```

```

    <refURL>/unifiedconfig/config/agent/5050</refURL>
  </agent>
  <campaignId>5000</campaignId>
  <peripheralId>5000</peripheralId>
  <agentId>1001</agentId>
  <campaignDn>222222</campaignDn>
  <phone>999333</phone>
  <accountNumber>23334343334</accountNumber>
  <maxAttempts>1</maxAttempts>
  <callbackDateTime>2016-01-15T11:37:00</callbackDateTime>
  <callStatus>pending</callStatus>
  <callResult>0</callResult>
  <lastName>Kumar</lastName>
  <firstName>Akshaya</firstName>
</personalCallback>

```

Time Zone API

Use the Time Zone API to list all available time zones and to get time zone information for a specified zone. Time zone information is stored in the registry of the Windows operating system.



Important Microsoft periodically releases cumulative time zone updates. These updates include worldwide changes to time zone names, bias (the amount of time in minutes that a time zone is offset from Coordinated Universal Time (UTC)), and observance of daylight saving time. These patches update the information in the Windows registry. When these updates are available, apply them to all virtual machines in the deployment that are running a Microsoft Windows operating system.

Use this API with the Outbound Campaign API to set the default time zone for an Outbound Option campaign. An Outbound Option campaign uses the time zone when the location of the customer number being dialed is unknown.

This API is read-only.

URL

`https://<server>/unifiedconfig/config/timezone`

Operations

- **list**: Retrieves a list of available time zones. The list is sorted by UTC offset from the International Date Line from west to east.
- **get**: Returns information for a specific time zone using the URL `https://<server>/unifiedconfig/config/timezone/<id>`, where `<id>` is the URL-encoded version of the name parameter.

Response Parameters

- **name**: The name of the time zone.
- **displayName**: Specific bias and location information about the time zone, such as the offset from UTC and one or more places located within the time zone.

Example: “(UTC+5:30) Chennai, Kolkata, Mumbai, New Delhi”

- **stdName:** The time zone name during standard time.

Example: Malay Peninsula Standard Time

- **dstName:** The time zone name during daylight saving time.

Example: Malay Peninsula Daylight Time

- **dstObserved:** Indicates whether daylight saving time is observed for the time zone. True or false.
- **bias:** The current bias for local time translation on the server (in minutes). That is, the number of minutes to add to the local time to yield UTC.

Example Get Response

```
<timeZone>
  <refURL>
    /unifiedconfig/config/timezone/Pacific%20Standard%20Time%20%28Mexico%29
  </refURL>
  <name>Pacific Standard Time (Mexico)</name>
  <displayName>(UTC-08:00) Baja California</displayName>
  <stdName>Pacific Standard Time (Mexico)</stdName>
  <dstName>Pacific Daylight Time (Mexico)</dstName>
  <dstObserved>true</dstObserved>
  <bias>480</bias>
</timeZone>
```




CHAPTER 29

Precision Queue API

- [Precision Queue API, on page 121](#)

Precision Queue API

Precision queues help direct incoming callers to appropriate agents, as they match specific agent attributes with caller requirements. If a precision queue requires an agent who lives in Boston and who speaks fluent Spanish, then an agent with the attributes **Boston = True** and **Spanish = True** is a good match.

Use the Precision Queue API to list the precision queues currently defined in the database, define new precision queues, and view, edit, and delete existing precision queues.

URL

`https://<server>/unifiedconfig/config/precisionqueue`

Operations

- **create**: Creates one precision queue.
- **delete**: Marks one precision queue for deletion, but does not permanently delete it. Deleting a precision queue that is referenced dynamically in a script is allowed. No new calls are queued against it, but the precision queue remains operational until calls are no longer in the queue.
- **get**: Returns one precision queue, using the URL
`https://<server>/unifiedconfig/config/precisionqueue/<id>`.

- **Query parameters:**

- **agentcount**: Use this query parameter to have the agent count parameter included in the response; for example, `agentcount=true`.
- **attributes**: Use this query parameter to have the attribute parameter included in the response; for example, `attributes=true`.
- **skillgroups**: Use this query parameter to augment the returned precision queue attributes with an id listing of all skillgroups that are associated with the precision queue; for example, `skillgroups=true`.

- **list**: Retrieves a list of precision queues. Query parameters described above for the get operation are also allowed for list.
- **update**: Updates one precision queue.

Parameters

Precision queue parameters:

- **refURL**: The refURL of the precision queue. See [Shared Parameters, on page 10](#).
- **name**: The name of the precision queue. See [Shared Parameters, on page 10](#).
- **changeStamp**: See [Shared Parameters, on page 10](#).
- **description**: See [Shared Parameters, on page 10](#).
- **bucketInterval**: A reference to a bucket interval ([Bucket Interval API, on page 39](#)), including the refURL and name. See [References, on page 7](#).
- **agentCount**: Returns agent count for the precision queue. Returned only when using the agentcount query parameter.
- **agentOrdering**: Determines the order in which agents receive calls from this queue.
 - 1: LAA (Agent availability time)
 - 2: Most skilled agent
 - 3: Least skilled agent
- **callOrdering**: Determines the order of calls in this precision queue.
 - 1: Top priority in queue. This is the default value.
- **id**: The database id of the precision queue. Read-only field. Used in scripting.
- **attributes**: A collection of attribute names (attribute1, attribute2, and so on) indicating all attributes used in this precision queue. Returned only when the query parameter attributes=true.
- **serviceLevelThreshold**: Maximum time in seconds that a caller should wait before being connected with an agent.
- **serviceLevelType**: This value indicates how the system calculates the service level.
 - 1: Ignore abandoned calls.
 - 2: Abandoned call has negative impact.
 - 3: Abandoned call has positive impact.
- **skillgroups**: A collection of skill groups associated with this precision queue, including the id of each skill group. Returned only when the query parameter skillgroups=true.
- **steps**: Required. A collection of steps for this precision queue. You can have 1-10 steps. Returned only for get operation. See the Step parameters below.

Step parameters:

- **waitTime:** Time in seconds to wait before proceeding to the next step.
- **considerIf:** A Consider If expression which must be met to run a particular step. Items used in the expression are case sensitive. You cannot add an expression to the last step.
- **terms:** Required. A collection of terms for this step. Each step can have 1-10 terms. See the Term parameters below.

Term parameters:

- **attribute:** A reference to the attribute ([Attribute API, on page 35](#)), including the refURL, name, description, and dataType. Multiple unique attributes can be used across all terms in a precision queue.
- **parenCount:** Denotes a parenthesis before or after this term. A value of 1 means a parenthesis before the current term, and a value of -1 means a parenthesis after the current term. The sum of all parenCount for all terms in a step must be equal to zero, meaning that all parenthesis in the expression are matched. For example, a step to check for agents that have (sales > 7 or expertSales = true) and english = true requires 3 terms with the parenCount set to 1 on the first term, -1 on the second term, and 0 on the last term.
- **termRelation:** Indicates the relationship of this term to the preceding term, using the following values:
 - 0: None. Valid only on the first term in a step.
 - 1: AND
 - 2: OR
- **attributeRelation:** Indicates what kind of comparison is done on the attribute, using the following values:
 - 1: Equal
 - 2: Not equal
 - 3: Less than
 - 4: Less than or equal
 - 5: Greater than
 - 6: Greater than or equal
- **value1:** The value that the attribute is tested against. For boolean attributes, this value must be true/false. For proficiency attributes, this value must be 1-10.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description

See [Search, on page 12](#) and [Sort, on page 13](#).

Example Get Response

```

<precisionQueue>
  <changeStamp>4</changeStamp>
  <refURL>/unifiedconfig/config/precisionqueue/5002</refURL>
  <agentOrdering>1</agentOrdering>
  <bucketInterval>
    <refURL>/unifiedconfig/config/bucketinterval/1</refURL>
    <name>Default_Bucket_Intervals</name>
  </bucketInterval>
  <description>This is a practice precision queue</description>
  <name>Practice_Queue</name>
  <serviceLevelThreshold>3</serviceLevelThreshold>
  <serviceLevelType>1</serviceLevelType>
  <steps>
    <step>
      <terms>
        <term>
          <attribute>
            <refURL>/unifiedconfig/config/attribute/5698</refURL>
            <name>test</name>
            <dataType>4</dataType>
          </attribute>
          <attributeRelation>5</attributeRelation>
          <parenCount>0</parenCount>
          <termRelation>0</termRelation>
          <value1>2</value1>
        </term>
      </terms>
      <waitTime>0</waitTime>
    </step>
    <step>
      <terms>
        <term>
          <attribute>
            <refURL>/unifiedconfig/config/attribute/5698</refURL>
            <name>test</name>
            <dataType>4</dataType>
          </attribute>
          <attributeRelation>3</attributeRelation>
          <parenCount>0</parenCount>
          <termRelation>0</termRelation>
          <value1>2</value1>
        </term>
      </terms>
      <waitTime>-1</waitTime>
    </step>
  </steps>
</precisionQueue>

```



CHAPTER 30

Peripheral API

- [Peripheral API](#), on page 125

Peripheral API

URL

`https://<server>/unifiedconfig/config/peripheral`

Operations

- **get**: Returns a single peripheral.

- **Search Parameter:**

q : `excludeClientType` or `includeClientType` (e.g. `excludeClientType:(13&30)`):

- Returns peripherals using the search for a specific client type (e.g. `clientType=47`) - `https://<IP address>/unifiedconfig/config/peripheral?q=includeClientType:(47)`
- Returns peripherals using search except a specific client type (e.g. `clientType=!13`) - `https://<IP address>/unifiedconfig/config/peripheral?q=excludeClientType:(13)`
- Returns peripherals using search except a specific set of client types (e.g. `clientType=!13,!30`) - `https://<IP address>/unifiedconfig/config/peripheral?q=excludeClientType:(13%2630)`
- Returns peripherals using search for a specific set of client types (e.g. `clientType=13,47`) - `https://<IP address>/unifiedconfig/config/peripheral?q=includeClientType:(13%2647)`

Search parameter

Query parameters

- **q** : query parameter for search
- **sort** : `<fieldName>%20<asc/desc>`
- **startIndex** : Default 0
- **resultsPerPage** : Default 25



Note Access is provided to users who have the *ConfigGroup* API user role.

Parameters

Values

- Are case-insensitive.
- Can be contained anywhere in the parameter value.
- Can match any of the default parameters.
- Cannot include SQL wildcards. They are not supported.
- Must be URL encoded. For example, **&** must be converted to **%26** so that it is not treated as a separator for additional query parameters.

Search and Sort Values

Sorting fields can be set to ascending (asc) or descending (desc) order.

The following table shows the parameters that are searchable and the parameters that are sortable.

Search Parameter	Sort Parameter
name	values
description	
clientType (excludeClientType or includeClientType)	

See [Search](#) and [Sort](#).

Example Get Response

```

<peripherals>
  <peripheral>
    <refURL>/unifiedconfig/config/peripheral/5000</refURL>
    <changeStamp>125</changeStamp>
    <clientType>30</clientType>
    <defaultDeskSetting>
      <refURL>/unifiedconfig/config/agentdesksetting/5000</refURL>
      <name>Default</name>
    </defaultDeskSetting>
    <name>PG1_CC1</name>
    <peripheralGateway>
      <refURL>/unifiedconfig/config/peripheralgateway/5000</refURL>
      <name>PG1</name>
    </peripheralGateway>
    <peripheralName>PG1_CC1</peripheralName>
    <peripheralId>5000</peripheralId>
    <routingClient>
      <refURL>/unifiedconfig/config/routingclient/5000</refURL>
      <changeStamp>0</changeStamp>
      <clientType>30</clientType>
    </routingClient>
  </peripheral>
</peripherals>

```

```
<lateThreshold>500</lateThreshold>
<logicalController>
  <refURL>/unifiedconfig/config/peripheralgateway/5000</refURL>
  <name>PG1</name>
</logicalController>
<name>PG1_CCM1.RC</name>
<peripheral>
  <id>5000</id>
  <name>PG1_CCM1</name>
</peripheral>
<timeoutLimit>10</timeoutLimit>
<timeoutThreshold>1500</timeoutThreshold>
</routingClient>
<routingClientId>5000</routingClientId>
</peripheral>
</peripherals>
```




CHAPTER 31

Person API

- [Person API](#), on page 129

Person API

Use the Person API to list the persons currently defined in the database, define new persons, view, edit, and delete existing persons.

URL

`https://<server>/unifiedconfig/config/person/`

Operations

- **create**: Creates a person using the url: `https://<ip_address>/unifiedconfig/config/person`
- **delete**: Deletes a person using the url: `https://<ip_address>/unifiedconfig/config/person/<personID>`
- **get**: Returns a single person using the url: `https://<ip_address>/unifiedconfig/config/person/<personID>`
- **update**: Updates a person using the url: `https://<ip_address>/unifiedconfig/config/person/<personID>`.
- **list**: Retrieves a list of persons.
 - Query parameters:
 - **q** : Query parameter for search
 - **sort**
 - **startIndex** : Default 0
 - **resultsPerPage** : Default 25
 - **assignableForPeripheralId** : Short number, considers all Person resources which can be assigned to an Agent under the specified Peripheral.



Note API access is provided to users who have **Configuration** access (but not **Setup** access) assigned on the **User List** page. Additionally, the **Person List** must be enabled in the **Feature Control Set List** page.

Parameters

- refURL: The refURL for the Person
- digitalChannel: Whether the person is enabled for digital channel interaction. Email address is mandatory when digitalChannel is set to True. The valid values are True or False. The default is False.
- changeStamp: shared parameter
- description: shared parameter
- emailAddress: The email address of the Person.
- firstName: Person's first name. Maximum of 32 characters.
- lastName: Person's last name. Maximum of 32 characters.
- loginEnabled: Whether the Person can log in. True or False. The default is True.
- userName: Person's login name. Maximum of 255 characters. It cannot be empty.
- password: Person's password. If Cisco IdS SSO is enabled, the password cannot be set.

Search and Sort Values

Sorting fields can be set to ascending (asc) or descending (desc).

The following table shows the parameters that are searchable and the parameters that are sortable.

Search Parameter	Sort Parameter
firstName	firstName
lastName	lastName
loginName	loginName

See [Search](#) and [Sort](#).

Example Get Response

```
<person>
  <refURL>/unifiedconfig/config/person/5013</refURL>
  <digitalChannel>>false</digitalChannel>
  <emailAddress>person1@gmail.com</emailAddress>
  <firstName>person1</firstName>
  <lastName>person1</lastName>
  <loginEnabled>>true</loginEnabled>
  <ssoEnabled>>false</ssoEnabled>
  <changeStamp>0</changeStamp>
  <userName>person1@gmail.com</userName>
</person>
```



CHAPTER 32

Scan API

- [Scan API, on page 131](#)

Scan API

The Scan API enforces the validation of media routing configurations for the customer collaboration platform.

URL

`https://<server>/unifiedconfig/config/status/scan`

HTTP method

PUT: Invoke the PUT method to force a scan to start immediately.



CHAPTER 33

Single Sign-On Global State API

- [Single Sign-On Global State API, on page 133](#)

Single Sign-On Global State API

Use the Single Sign-On (SSO) Global State API to view or update the global status of SSO.

To retrieve the overall status of setting the SSO state or the status for a single component, see the [Single Sign-On Status API, on page 137](#).

URL

`https://<server>/unifiedconfig/config/sso/globalstate`

Operations

- **get**: Returns the current global state of SSO in the database.
- **update**: Updates the global state of SSO in the database.

Parameters

- **refURL**: The RefURL. See [Shared Parameters, on page 10](#).
- **changeStamp**: See [Shared Parameters, on page 10](#).
- **permissionInfo**: Information about permissions.
 - **canUpdate**: Whether ssoState can be updated. True or false.
 - **role**: The role of the user.
- **state**: Required for update. Valid values are NON_SSO (SSO is disabled for all users), SSO (SSO is enabled for all users), and HYBRID (mix of enabled and disabled).

Example Get Response

```
<ssoState>  
  <refURL>/ssostate</refURL>
```

```
<changeStamp>227</changeStamp>
<permissionInfo>
  <canUpdate>true</canUpdate>
  <role>Administrator</role>
</permissionInfo>
<state>SSO</state>
</ssoState>
```



CHAPTER 34

Single Sign-On Registration API

- [Single Sign-On Registration API](#) , on page 135

Single Sign-On Registration API

Use the Single Sign-On (SSO) Registration API to register SSO-compatible components with the Cisco Identity Service. These components include AW, Finesse, and Unified Intelligence Center machines.

To retrieve the overall registration status or the status for a single component, see the [Single Sign-On Status API](#), on page 137.

URL

```
https://<server>/unifiedconfig/config/sso/register
```

Operations

- **update**: Registers all SSO-compatible components in the Machine Inventory with the Cisco Identity Service, using the URL `https://<server>/unifiedconfig/config/sso/register`. (See Machine Inventory API)

Parameters

None



CHAPTER 35

Single Sign-On Status API

- [Single Sign-On Status API, on page 137](#)

Single Sign-On Status API

Use the Single Sign-On (SSO) Registration API to get the current status of registering components with the Cisco Identity Service (IdS) and setting SSO state on the SSO-compatible components. These components include AW, Finesse, and Unified Intelligence Center machines.

URL

```
https://<server>/unifiedconfig/config/sso/status
```

Operations

- **get** component status: Returns the status of registering a specific component with the Cisco IdS and setting SSO state, using the URL `https://<server>/unifiedconfig/config/sso/status/<id>`. The `<id>` is the `machine_id` of the component.
- **list**: Retrieves a list with the overall and individual component statuses of registering SSO-compatible components with the Cisco Identity Service and setting SSO state, using the URL `https://<server>/unifiedconfig/config/sso/status`.

Parameters

- `globalSsoState`: The current SSO state as set in the AW database. The values are `NON_SSO` (SSO is disabled for all users), `SSO` (SSO is enabled for all users), and `HYBRID` (mix of enabled and disabled).
- `registrationState`: The overall status of registering components with the Cisco IdS. Values are the following:
 - `SUCCEEDED`: All of the components were successfully registered.
 - `FAILED`: Registration failed on one or more components. Error detail is set on each failed component.
 - `PROCESSING`: Registration started and is not complete.
 - `NOT_STARTED`: Registration has not started.
- `modeState`: The overall status of registering components with the Cisco IdS. Values are the following:

- SUCCEEDED: The SSO state was successfully set on all of the components.
 - FAILED: The SSO state failed to be set on one or more components. Error detail is set on each failed component.
 - PROCESSING: The SSO state change has started and is not complete.
 - NOT_STARTED: The SSO state change has not started.
- idSConfigurationState: Whether the Cisco IdS has been configured and is in service.
 - STATE_NOT_CONFIGURED : The Cisco IdS is not been configured.
 - STATE_IN_SERVICE : The Cisco IdS is configured and is in service.
 - STATE_OUT_OF_SERVICE : The Cisco IdS is configured and is out of service.
 - STATE_PARTIAL_SERVICE: The Cisco IdS is configured and is partially in service.
 - STATE_UNREACHABLE: The Cisco IdS cannot be reached.
- hasIdsCredentials: Whether the Machine Inventory has the necessary IdS credentials to register components (see Machine Inventory API. Values are true or false. The default is false.
 - idsBaseUrl: The base URL for accessing the Identity Service.
 - ssoComponentStatuses: A collection of registration and SSO state status information for all of the individual components. Returned on a list operation.
 - ssoComponentStatus: Registration and SSO state status information for an individual component. Includes the following parameters:
 - registrationState: The status of registering the component with the IdS. See the values for this parameter above.
 - modeState: The status of setting the SSO state for the component. See the values for this parameter above.
 - refURL: The refURL for the component machine. See [Shared Parameters, on page 10](#).
 - name: The name of the component machine.

Example Get Response

Example URL: `https://<server>/unifiedconfig/config/sso/status/21`

```
<ssoComponentStatus>
  <registrationState>FAILED</registrationState>
  <modeState>NOT_STARTED</modeState>
  <refURL>/unifiedconfig/config/machineinventory/21</refURL>
  <name>FINESSE-A.boston.com</name>
</ssoComponentStatus>
```

Example List Response

```
<ssoStatus>
  <globalSsoState>HYBRID</globalSsoState>
  <registrationState>FAILED</registrationState>
```

```
<modeState>NOT_STARTED</modeState>
<idSConfigurationState>STATE_IN_SERVICE</idSConfigurationState>
<hasIdsCredentials>true</hasIdsCredentials>
<idsBaseUrl>https://<server>:<serverport></idsBaseUrl>
<ssoComponentStatuses>
  <ssoComponentStatus>
    <registrationState>FAILED</registrationState>
    <modeState>NOT_STARTED</modeState>
    <refURL>/unifiedconfig/config/machineinventory/21</refURL>
    <name>FINESSE-A.boston.com</name>
  </ssoComponentStatus>
  <ssoComponentStatus>
    <registrationState>FAILED</registrationState>
    <modeState>NOT_STARTED</modeState>
    <refURL>/unifiedconfig/config/machineinventory/22</refURL>
    <name>FINESSE-B.boston.com</name>
  </ssoComponentStatus>
  <ssoComponentStatus>
    <registrationState>FAILED</registrationState>
    <modeState>NOT_STARTED</modeState>
    <refURL>/unifiedconfig/config/machineinventory/23</refURL>
    <name>CUIC-A.boston.com</name>
  </ssoComponentStatus>
</ssoComponentStatuses>
</ssoStatus>
```




CHAPTER 36

Skill Group API

- [Skill Group API, on page 141](#)

Skill Group API

A skill group is a collection of agents who share a common set of competencies that equip them to handle the same types of requests. Some examples of skill groups are a collection of agents who speak a specific language or who can assist callers with billing questions.

Use the Skill Group API to list, view, or edit existing skill groups.



Note Access to this API is different for supervisors and administrators. For more information, see [Access, on page 5](#).

URL

`https://<server>/unifiedconfig/config/skillgroup`



Note `unifiedconfig api` does not support skill groups in System PGs

Operations

- **get:** Returns one skill group, using the URL `https://<server>/unifiedconfig/config/skillgroup/<id>`.
- **list:** Retrieves a list of skill groups.
 - **Query Parameters:**
 - **selectedAgentCount:** Use this query parameter to augment skill group information about multiple agents. The `selectedAgentCount` parameter shows the number of specified agents belonging to that skill group. For example, to find out how many of agents 5000, 5001, 5002, and 5003 belong to each of the skill groups in the list, add **`selectedAgentCount=5000,5001,5002,5003`**.



Note Using `selectedAgentCount` automatically sets the summary list query parameter to **true**.

- Summary list: See [list](#), on page 2.

- `update`: Updates one skill group.

Parameters

- `refURL`: The refURL of the skill group. See [Shared Parameters](#), on page 10.
- `name`: The name of the skill group. See [Shared Parameters](#), on page 10.
- `changeStamp`: See [Shared Parameters](#), on page 10.
- `description`: See [Shared Parameters](#), on page 10.
- `mediaRoutingDomain`: A reference to the media routing domain () including the name and refURL. See [References](#), on page 7.
 - Defaults to `Cisco_Voice MRD` if this parameter is not provided.
 - This reference cannot be updated.
- `agents`: A collection of agents assigned to the skill group (See [Agent Call API](#)). References also include `firstName`, `lastName`, `agentId`, and `agentTeam` (which includes the team name and refURL). See [References](#), on page 7.
 - `canRemove`: This parameter only appears for supervisors. It indicates whether or not the supervisor has permission to remove the agent from this skill group. The supervisor can remove the agent from the skill group if the agent belongs to a team of this supervisor.
- `agentsAdded`: A collection of agent references to be added to the skill group, including the refURL of each agent to be added. This parameter is update only, and cannot be used in conjunction with the `agents` parameter. This parameter can be used with the `agentsRemoved` parameter. See [References](#), on page 7.
- `agentsRemoved`: A collection of agent references to be removed from the skill group, including the refURL of each agent to be removed. This parameter is update only, and cannot be used in conjunction with the `agents` parameter. This parameter can be used with the `agentsAdded` parameter. See [References](#), on page 7.
- `agentCount`: Read-only parameter containing the number of agents having the skill.
- `selectedAgentCount`: Read-only field. Indicates the number of specified agents belonging to the skill group. Returned only when using the `selectedAgentCount` query parameter.
- `bucketInterval`: A reference to the bucket interval ([Bucket Interval API](#), on page 39). Includes the name and refURL. See [References](#), on page 7.
- `serviceLevelThreshold`: Maximum time in seconds that a caller should wait before being connected with an agent. Positive integers only, or blank.
- `serviceLevelType`: This value indicates how the system calculates the service level.

- 1: Ignore Abandoned Calls (default).
- 2: Abandoned Calls have Negative Impact.
- 3: Abandoned Calls have Positive Impact.

Search and Sort Values

The following table shows the parameters that are searched and the parameters that are sortable.

Search parameters	Sort parameters
<ul style="list-style-type: none"> • name • description 	<ul style="list-style-type: none"> • name (default) • description • serviceLevelThreshold • serviceLevelType • peripheralNumber • peripheral.name

See [Search, on page 12](#) and [Sort, on page 13](#).

For more information on search restrictions, see [Search, on page 12](#).

Example Get Response

```
<skillGroup>
  <refURL>/unifiedconfig/config/skillgroup/(id)</refURL>
  <name>test</name>
  <description>test skill group</description>
  <changeStamp>0</changeStamp>
  <peripheral>
    <id>5001</id>
    <name>CUCM_PG1</name>
  </peripheral>
  <mediaRoutingDomain>
    <name>Cisco_Voice</name>
    <refURL>/unifiedconfig/config/mediaroutingdomain/1</refURL>
  </mediaRoutingDomain>
  <bucketInterval>
    <name>bucketIntervalName</name>
    <refURL>/unifiedconfig/config/bucketinterval/1</refURL>
  </bucketInterval>
  <serviceLevelThreshold>20</serviceLevelThreshold>
  <serviceLevelType>1</serviceLevelType>
  <agents>
    <agent>
      <refURL>/unifiedconfig/config/agent/5000</refURL>
      <firstName>Jane</firstName>
      <lastName>Doe</lastName>
      <userName>username</userName>
      <agentId>8007</agentId>
      <canRemove>true</canRemove>
    </agent>
    <agent>
      <refURL>/unifiedconfig/config/agent/5001</refURL>
```

```
<firstName>John</firstName>
<lastName>Smith</lastName>
<userName>username2</userName>
<agentId>8008</agentId>
<agentTeam>
  <refURL>/unifiedconfig/config/agentteam/5000</refURL>
  <name>someTeam</name>
</agentTeam>
<canRemove>false</canRemove>
</agent>
<agent>...</agent>
<agent>...</agent>
</agents>
<agentCount>4</agentCount>
</skillGroup>
```



CHAPTER 37

Status API

- [Configuration Rules](#), on page 145
- [Operation Rules](#), on page 146

Configuration Rules

Unified CCE AW, Unified Intelligence Center, CUIC-LD-IdS, and Finesse Machines

These rules show the potential configuration errors and warnings for Unified CCE AW, Unified Intelligence Center, CUIC-LD-IdS, and Finesse machines.

Table 3: Unified CCE AW, Unified Intelligence Center, CUIC-LD-IdS, and Finesse Rules

Rule	Description
SSO_COMPONENT_STATUS_MATCHES_GLOBAL	The global SSO status must be the same as component SSO status.
SSO_VALID_IDS_REFERENCE	If single sign-on is enabled, this machine must be associated with a valid Cisco Identity Service.

Table 4: Unified CCE AW Rules

Rule	Description
TASK_ROUTING_APP_PATHS_EXIST	Each Peripheral Gateway with a Communications Manager PIM must have an associated Task Routing Application Path.

Customer Collaboration Platform Machines

These rules show the potential configuration errors and warnings for Customer Collaboration Platform machines.

Table 5: Customer Collaboration Platform Rules

Rule	Description
SOCIAL_MINER_MR_ENABLED	Multichannel routing must be enabled on Customer Collaboration Platform.

Cloud Connect Machines

These rules show the potential configuration errors and warnings for all of the machines, ESX hosts, and Gateways. Each section has a rule table that applies to all machines listed in that category, as well as a rule table for each type of machine in that category.

These rules show the potential configuration errors and warnings for Cloud Connect machines.

Table 6: Cloud Connect Rules

Rule	Description
CLOUD_CONNECT_STATUS	Shows the sync status of Cloud Connect Machine.

Operation Rules

Common Operation Rules

These rules show the potential operation errors and warnings for Unified CCE, Unified CM, Unified CVP, Gateways, Unified Intelligence Center, Finesse, and Enterprise Chat and Email. Each section has a rule table that applies to all machines listed in that category, as well as a rule table for each type of machine in that category.

These rules show the potential operation errors and warnings for the following machines:

- All Unified CCE components
- Unified Intelligence Center
- CUIC-LD-IdS
- Finesse
- Live Data
- Identity Service
- Customer Collaboration Platform

Table 7: Common Rules

Rule	Description
SERVER_CONNECTION	<p>The Diagnostic Portal, AXL, REST, or SOAP service on this machine must be in service. The status you see varies according to the product type, as follows:</p> <ul style="list-style-type: none"> • Unified CCE: The Cisco ICM Diagnostic Framework service on the Principal AW must be reachable on the network. • CUIC-LD-IdS: The SOAP service on the Publisher must be reachable on the network. • Finesse: The SOAP service on the Primary Finesse machine must be reachable on the network. • IdS: The REST service on the Primary Identity Server must be reachable on the network • Customer Collaboration Platform : The service must be reachable on the network.
SERVER_CREDENTIALS	<p>The inventory's credentials for the machine must be valid. The status you see varies according to the product type, as follows:</p> <ul style="list-style-type: none"> • Unified CCE: The Diagnostic Framework credentials entered for the Principal AW must be valid for all CCE components in the solution. • CUIC-LD-IdS: The Unified Intelligence Center Administration credentials entered for the Publisher must be valid • Finesse: The Finesse Administration credentials entered for the Primary Finesse machine must be valid. • IdS: The Identity Service Administration credentials entered for the Primary Identity Server must be valid • Customer Collaboration Platform : The service credentials must be valid. <p>Note This rule does not apply to a standalone Live Data machine.</p>

Cloud Connect Machines

These rules show the potential operational errors and warnings for Cloud Connector machines.

Table 8: Cloud Connect Rules

Rule	Description
CLOUD_CONNECTOR_TYPE	Cloud connect is either publisher or subscriber.

Rule	Description
CONTACT_CENTER_AI_CALL_TYPE_CONFIG_NOT_FOUND	Some of the Contact Center AI configurations that are associated with the call types are not available in the Control Hub.



INDEX

C

creating [108](#)
Do Not Call list [108](#)

D

Do Not Call list [108](#)
creating [108](#)

