



Configure Restriction Tables

- [Configure Restriction Table Parameters, on page 1](#)
- [Add a New Restriction Table, on page 1](#)
- [Add Call Patterns to a Restriction Table, on page 2](#)
- [Edit Restriction Table Entries, on page 2](#)
- [Delete Restriction Table Entries, on page 2](#)
- [Delete Restriction Tables, on page 3](#)

Configure Restriction Table Parameters

Use this procedure to configure restriction table parameters.

-
- Step 1** Choose **System > Restriction Tables**.
- Step 2** Choose the restriction table name from the drop-down list. If there is no name indicated in the list, proceed to [Add a New Restriction Table, on page 1](#).
- Step 3** Choose the minimum digits allowed. Range:1-30. Default:1.
- Step 4** Choose the maximum digits allowed. Range: 1-30. Default: 30.
- Step 5** Click **Apply** to save your settings.
-

Add a New Restriction Table

Use this procedure to add a new restriction table.

-
- Step 1** Choose **System > Restriction Tables**
- Step 2** Click **Add**.
- Step 3** Choose a name for your new restriction table by entering the name in the field.
- Step 4** Click **Add** to save your changes.
-

Add Call Patterns to a Restriction Table

If desired, add up to 10 dial strings in the Call Pattern list. For each dial string, you must configure a call pattern and specify whether numbers matching the pattern are allowed or disallowed. External and long distance access codes should be specified. Digits 0 to 9 and the following special characters are allowed:

- *—Match zero or more digits
- .—Match exactly one digit. Each “.” serves as a placeholder for one digit.
- 91555* (Allowed)
- 9011* (Not allowed)

Use this procedure to add call patterns to a restriction table.

-
- Step 1** Choose **System > Restriction Tables**.
- Step 2** In the Call Pattern window, enter the call pattern in the field. Valid patterns can include digits 0 to 9, asterisk (*), and dot (.). The * indicates a match of zero or more digits. Each dot serves as a placeholder for 1 digit.
- Step 3** Choose whether the call pattern is to be allowed in the restriction table by clicking **Yes** or **No**.
- Step 4** Click **Add** to save your settings.
- (Optional) To change the location of a dial string in the comparison sequence, click **Move Up** or **Move Down**. Notification numbers that the user configures are compared against dial strings in the order that the strings are listed in the Call Pattern box. See [Restriction Table Examples, on page 3](#) for more information.
- Step 5** Click **Yes** or **No** to allow or not allow the call pattern.
-

Edit Restriction Table Entries

Use this procedure to edit call pattern entries in a restriction table.

-
- Step 1** Choose **System > Restriction Tables**.
- Step 2** Select the call pattern from the drop-down list and click **Edit**.
- Step 3** In the pop-up window, choose whether the call pattern is to be allowed by clicking **Yes** or **No**.
- Step 4** Click **Apply** to save your settings.
-

Delete Restriction Table Entries

Use this procedure to delete call pattern entries in a restriction table.

-
- Step 1** Choose **System** > **Restriction Tables**.
- Step 2** Select the call pattern from the list and click the **Delete** button.
- Step 3** Click **Apply** to save your settings.
-

Delete Restriction Tables

Use this procedure to delete a restriction table.



Note Deleting a restriction table will cause unrestricted outgoing calls to be allowed by any features using that restriction table.

-
- Step 1** Choose **System** > **Restriction Tables**.
- Step 2** Select the restriction table from the **Restriction Table Name** drop-down list and click **Delete**. A warning message appears asking if you wish to continue.
- Step 3** Click **Yes** or **No** to complete the task.
-

Restriction Table Examples

To restrict international and long distance numbers:

-
- Step 1** Enter 9011* in the Call Pattern field, select **No**, and click **Add**.
- Step 2** Enter 91..... in the Call pattern field, select **No**, and click **Add**.
-

Disallow a Specific Area Code

To disallow a specific area code, except for one phone number within the area code:

-
- Step 1** Enter 9011* in the Call Pattern field, select **No**, and click **Add**.
- Step 2** Enter 915551212 in the Call Pattern field, select **Yes**, and click **Add**.
- Step 3** Enter 91555..... in the Call Pattern field, select **No**, and click **Add**.

The system would first check against the * string, which allows any digits. Therefore, the configuration of any notification number would be permitted, because the 91555* and 9011* strings would not be reached. Moving the * string down to the end of the list would permit any numbers except those that matched in the first two dial strings.
