



# Configuring the Cisco Unified Communications Manager System

---

Use this procedure to modify the Java Telephony API (JTAPI) provider (on Cisco Unified Communications Manager) information in Cisco Unity Express.



**Note**

Any changes to the JTAPI provider on Cisco Unified Communications Manager require a software reload of Cisco Unity Express. You must save your Cisco Unity Express configuration and reload for the changes to take effect.

---

Use this procedure to configure the Cisco Unified Communications Manager (CUCM).

---

- Step 1** Choose **Configure > Communications Manager**. The Configure CUCM window appears.
- Step 2** Enter the information in the following fields:
- Primary Communications Manager—IP address or hostname of the primary Cisco Unified Communications Manager system.
  - Secondary Communications Manager—IP address or hostname of the first alternate Cisco Unified Communications Manager system.
  - Tertiary Communications Manager—IP address or hostname of the second alternate Cisco Unified Communications Manager system.
  - Web User Name—Username to log in to the Cisco Unified Communications Manager system.
  - Web Password—Password to log in to the Cisco Unified Communications Manager system.
  - JTAPI user ID and password
- Step 3** Click **Apply** to save the information.
- Step 4** Click **Verify** to test the connection between Cisco Unified Communications Manager and Cisco Unity Express.
- Step 5** Click **Reload Unity Express** to reload the software after you make configuration changes.
-

