



Release Notes for Cisco Wireless Control System Navigator 1.0.91

June 29, 2007

These release notes describe open and resolved caveats for the Cisco Wireless Control System Navigator 1.0.91.

The Cisco Wireless Control System Navigator is hereafter referred to as *Cisco WCS Navigator*.

Contents

These release notes contain the following sections.

- [Introduction, page 2](#)
- [Cisco WCS Navigator Features, page 2](#)
- [Requirements for Cisco WCS Navigator, page 2](#)
- [Caveats, page 3](#)
- [Troubleshooting, page 4](#)
- [Related Documentation, page 4](#)
- [Obtaining Documentation, Obtaining Support, and Security Guidelines, page 4](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

© 2007 Cisco Systems, Inc. All rights reserved.

Introduction

Cisco WCS Navigator delivers an aggregated platform for enhanced scalability, manageability, and visibility of large-scale implementations of the Cisco Unified Wireless Network. This software-based solution gives network administrators easy access to information from multiple geographically diverse Cisco WCS management platforms. It supports partitioning of the unified wireless network at the management level.

Cisco WCS Navigator Features

The Cisco WCS Navigator provides:

- Management of multiple Cisco WCSs
 - Supports up to 20 Cisco WCS management platforms
 - Management of up to 15,000 Cisco Aironet lightweight access points from a single management console
- A unified view of the network
- Overview and multilevel monitoring of wireless networks
- The ability to run reports for all WCSs
- Network-wide searches
- A link to return to the Navigator when directed to a regional WCS from Navigator

Requirements for Cisco WCS Navigator

Hardware Requirements for Navigator

The following server hardware and software is required to support Cisco WCS Navigator for Windows or Linux.

- Standard Server
 - Supports up to 20 wireless control systems depending on the Navigator license.
 - Requires a 3.2 GHz Intel Dual Core processor with 4-GB RAM and 80-GB hard drive.
 - Requires 40-GB minimum of free disk space on your hard drive.

**Note**

The free disk space listed is a minimum requirement but may be different for your system depending on the number of backups.

**Note**

The screen resolution should be set to 1024 x 768 pixels for Navigator.

Supported Operating Systems

The following operating systems are supported:

- Windows 2003/SP1 and SR2 with all critical and security Windows updates installed.



Note SP2 is not supported at this time.

- Red Hat Linux Enterprise Server 4.0 or Advanced Server 4.0. Only 32-bit operating system installations are supported. 64-bit operating system installations are not supported.



Note

The Cisco WCS Navigator supports both Internet Explorer 6.0 and 7.0.

Caveats

Open Caveats

These caveats are open in Cisco WCS Navigator 1.0.91:

- CSCsi04593—There are problems with the graph on the Monitor -network summary.
Workaround: After a refresh, the graphs works fine.
- CSCsi04839—An irrelevant exception appears when searching for clients on Navigator.
Workaround: None at this time.
- CSCsi24635—When a WCS on Navigator becomes unreachable, a WCS alarm appears on the alarm dashboard. Clicking the alarm opens the Alarm Details page. Clicking the link to the events history produces an unknown exception.
Workaround: None at this time.
- CSCsi31663—Accessing the wireless control system pages from Navigator results in a prompt that http is not enabled and user must click in the designated link to access using https.
Workaround: Under **Configure > WCS** within the affected wireless control system, change the protocol to https.
- CSCsi35069—A user cannot access the wireless control system alarm details page in Navigator.
Workaround: None at this time.
- CSCsi35113—Deleting a configuration manager user on Navigator sometimes results in an unknown exception.
Workaround: None at this time.
- CSCsi35254—When a backup of Navigator is started directly from the server, there is no prompt to first stop the Navigator. This may cause the backup to run more slowly.
Workaround: To avoid this, stop Navigator prior to starting a backup.

- CSCsh55877—After installing navigator as a service, it has to be started manually by rebooting the server. The server does not start automatically. If installed as an application, the server must be started manually; a reboot is not required.

Workaround: None at this time.

Resolved Caveats

These caveats are resolved in Cisco WCS Navigator 1.0.91:

- CSCsh62013—When WCS Navigator cannot get the client count from WCS it waits three to five polling intervals before setting the client count to zero.

Troubleshooting

For the most up-to-date, detailed troubleshooting information, refer to the Cisco TAC website at the following location:

<http://www.cisco.com/tac>

Click **Technology Support**, select **Wireless** from the menu on the left, and click **Wireless LAN**.

Related Documentation

For information on the Cisco WCS Navigator, refer to the *Cisco Wireless Control System Navigator 1.0.83 Installation Guide*.

Obtaining Documentation, Obtaining Support, and Security Guidelines

For information on obtaining documentation, obtaining support, providing documentation feedback, security guidelines, and also recommended aliases and general Cisco documents, see the monthly What's New in Cisco Product Documentation, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

CCVP, the Cisco Logo, and the Cisco Square Bridge logo are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, BPX, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuick Study, LightStream, Linksys, MeetingPlace, MGX, Networking Academy, Network Registrar, *Packet*, PIX, ProConnect, RateMUX, ScriptShare, SlideCast, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0704R)