



# Crypto Vendor Policy Configuration Mode Commands

The Crypto Vendor Policy Configuration Mode can be used to assign priorities to vendors for cryptographic configurations. A maximum of 32 vendor policies can be configured.

**Command Modes** Exec > Global Configuration > Context Configuration > Crypto Vendor Policy Configuration

**configure** > **context** *context\_name* > **crypto vendor-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-crypto-vendor-policy) #
```



**Important** The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 1](#)
- [end, on page 2](#)
- [exit, on page 2](#)
- [precedence, on page 2](#)

## do show

Executes all **show** commands while in Configuration mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>do show</b>

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

end

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

## end

Exits the current configuration mode and returns to the Exec mode.

**Product**

All

**Privilege**

Security Administrator, Administrator

**Syntax Description****end****Usage Guidelines**

Use this command to return to the Exec mode.

## exit

Exits the current mode and returns to the parent configuration mode.

**Product**

All

**Privilege**

Security Administrator, Administrator

**Syntax Description****exit****Usage Guidelines**

Use this command to return to the parent configuration mode.

## precedence

Use this command to associate a vendor ID with a vendor template, and set precedence for it.

**Product**

ePDG

**Privilege**

Security Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > Crypto Vendor Policy Configuration

**configure** > **context** *context\_name* > **crypto vendor-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-crypto-vendor-policy)#
```

---

**Syntax Description**     **precedence** *precedence\_value* **vendor-id** *id* **vendor-template** *template\_name*

**no precedence** *precedence\_value*

**no**

Restores the configuration to its default value.

***precedence\_value***

*precedence\_value* must be an integer from 1 through 64.

**vendor-id** *id*

Specifies the vendor ID to match the vendor template.

*id* must be an alphanumeric string from 1 to 256 characters.

**vendor-template** *template\_name*

Specifies the vendor template to associate with the vendor ID.

*template\_name* must be an alphanumeric string from 1 to 127 characters.

---

**Usage Guidelines**

Use this command to associate a vendor ID with a vendor template, and set precedence for it. A maximum of 64 vendor templates can be associated with a vendor policy.

**Example**

The following command associate a vendor ID called **atl23** and associate it to a vendor template called **atlcryptpl** with the precedence value of **2** :

```
precedence 2 vendor-id atl23 vendor-template atlcryptpl
```

precedence