



BGP Address-Family (VPNv4/VPNv6) Configuration Mode Commands

The Border Gateway Protocol (BGP) Address-Family (VPNv4/VPNv6) Configuration Mode is used to configure the VPNv4 or VPNv6 address family information.

Command Modes

Exec > Global Configuration > Context Configuration > BGP Configuration > BGP Address-Family Configuration

configure > **context** *context_name* > **router bgp** *as_number* > **address-family** *address_family_type*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-bgp-af-v4)#
```



Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [end, on page 1](#)
- [exit, on page 2](#)
- [neighbor, on page 2](#)
- [timers bgp, on page 3](#)

end

Exits the current configuration mode and returns to the Exec mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

end

Usage Guidelines

Use this command to return to the Exec mode.

exit

Exits the current mode and returns to the parent configuration mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

exit

Usage Guidelines

Use this command to return to the parent configuration mode.

neighbor

Configures the VPNv4 or VPNv6 address family on BGP routers that interconnects to non-broadcast networks and enables the exchange of routing information with a peer router (neighbor).

Product

All

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration > Context Configuration > BGP Configuration > BGP Address-Family Configuration

configure > **context** *context_name* > **router bgp** *as_number* > **address-family** *address_family_type*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-bgp-af-v4) #
```

Syntax Description

```
[ no ] neighbor ip_address { activate | advertisement-interval interval_seconds
| send-community { both | extended | standard } }
```

no

Delete the specified parameter from the router configuration.

neighbor ip_address

Specifies the IP address of the peer router (neighbor) in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

activate

Enables the exchange of routing information with this neighbor.

advertisement-interval interval_seconds

Specifies the minimum interval in seconds between sending BGP routing updates as an integer from 0 through 600.

send-community { both | extended | standard }

Sends the community attributes to a peer router (neighbor).

both: Sends standard and extended community attributes.

extended: Sends extended community attributes.

standard: Sends standard community attributes.

Usage Guidelines

Use this command to enable the exchange of routing information with a peer router. The chassis supports a maximum of 64 peers per context.

Example

The following command enables the exchange of routing information with the neighbor at IP address *192.168.100.25*:

```
neighbor 192.168.100.25 activate
```

timers bgp

Enables or disables an aggressive minimum BGP route advertisement interval (MinRtAdvInterval) for ICSR configurations.

Product

All products that support ICSR

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration > Context Configuration > BGP Configuration > BGP Address-Family Configuration

configure > **context** *context_name* > **router bgp** *as_number* > **address-family** *address_family_type*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-bgp-af-v6)#
```

Syntax Description

[no] **timers bgp icshr-aggr-advertisement-interval** *seconds*

no

Disables this aggressive ICSR BGP advertisement interval.

seconds

Sets the number of seconds as an integer from 0 to 30. Default: 0.

Usage Guidelines

Use this command to configure an aggressive ICSR BGP advertisement interval (MinRtAdvInterval). The default value is 0. If set as 0, the aggressive advertisement interval is disabled.

The MinRtAdvInterval can be uniquely set for each address family.

After ICSR switchover, BGP will set the advertisement-interval for each AFI/SAFI (Address Family Identifier/Subsequent Address Family Identifier) supported by the peer to the configured value. BGP updates will be advertised to the peer based on this interval.

Example

The following command sets the MinRtAdvInterval for this address family to 1 second:

```
timers bgp icsr-aggr-advertisement-interval 1
```